

## IDENTIFICATION

Product Code: Maindec 08-D1GB-D

Product Name: PDP-8, 8I, 8S Extended Memory Control

Date Created: May 5, 1968

Maintainer: Diagnostics Group

## 1. Abstract

This program tests the Extended Memory Control logic for proper operation. It may be used with a PDP-8, 8I, or 8S equipped with a minimum of 4K of extended memory. The program exercises and tests the control IOT's; the ability to reference all fields from field 0; program interrupt and interrupt inhibit; auto-indexing in each field, and a special test for the PDP-8I which tests the presence of a false memory pulse when a non-existent memory field is referenced.

Errors encountered during running will result in a program halt. The halt locations are labeled, and the error may be identified by referencing the program listing or table of error halts.

## 2. Requirements

### 2.1 Equipment

A standard PDP-8, 8I or 8S equipped with an Extended Memory Control, and at least 4K of extended memory.

### 2.2 Storage

The program requires 1726(8) locations of code memory. The program must reside in memory field 0 only.

### 2.3 Preliminary Programs

All programs for a basic PDP-8, 8I or 8S must have been previously run successfully.

## 3. Loading Procedure

### 3.1 Method

The program must be loaded with the Binary loader.

- a. Turn off the Teletype reader.
- b. Set the SWITCH REGISTER to 7777.
- c. Press LOAD ADDRESS, and then START.
- d. Place the program tape in the reader and turn on the reader.
- e. When the program has been loaded, stop the computer, turn off the reader, and remove the tape.

#### 4. Starting Procedure

##### 4.1 Starting Addresses

The starting address is 0200(8).

##### 4.2 Control Switch Settings

SR 8 must be on a 1 if a PDP-8I is being used. Otherwise, on a 0 for a PDP-8 or 8S.

SR 9, 10 and 11 must contain an octal value equal to the number of EXTENDED memory fields available (1 to 7 octal). Note that field 0 is not to be included in this value.

##### 4.3 Operator Action

With the program in memory, set the SWITCH REGISTER to 0200 octal.

Press LOAD ADDRESS.

Set SR 8 to a 1 if a PDP-8I is being used. Otherwise, set SR 8 to a 0.

Place the octal number of EXTENDED memory fields available in SR 9, 10 and 11. This value may vary from 1 to 7 only.

Press START.

The program will run until an error is detected, or stopped by the operator.

The TTY bell is rung once after one complete pass of the program.

#### 5. Operating Procedure

See section 4.2

##### 5.2 Subroutine Abstracts

Refer to the program listing for descriptions of each test, and the method of testing.

##### 5.3 Operator Action

See section 4.3

6. Errors6.1 Error Halts and Description

Table of Error Halts

<u>C (MA)</u>	<u>Tag</u>	<u>Description</u>
<u>CDF and RDF Tests</u>		
206	E 1	CDF 0 or RDF failed.
217	E 2	CDF 7 or RDF failed.
234	E 3	CDF 1 or RDF failed.
245	E 4	CDF 2 or RDF failed.
262	E 5	CDF 3 or RDF failed.
273	E 6	CDF 4 or RDF failed.
310	E 7	CDF 5 or RDF failed.
321	E 8	CDF 6 or RDF failed.
<u>DF, IB and SF Tests</u>		
341	E 9	RIB or ION failed.
351	E 10	DF not cleared, or no interrupt.
360	E 11	RIB or SF failed. (DF 1)
410	E 12	DF not cleared, or no interrupt.
417	E 13	RIB or SF failed. (DF 2)
427	E 14	DF not cleared, or no interrupt.
436	E 15	RIB or SF failed. (DF 3)
452	E 16	DF not cleared, or no interrupt.
<del>462</del> 461	E 17	RIB or SF failed. (DF 4)

471	E 18	DF not cleared or no interrupt.
500	E 19	RIB or SF failed. (DF 5)
514	E 20	DF not cleared, or no interrupt.
523	E 21	RIB or SF failed. (DF 6)
533	E 22	DF not cleared, or no interrupt.
542	E 23	RIB or SF failed. (DF 7)

#### DCA I and TAD I Tests

653	E 24	DCA I or TAD I to an extended field failed. The DF indicators equal the current field under test. The AC contains the data as read from location 7000 of the extended field. The halt occurred due to the data read and the current data field not being equal. Each extended field should contain its field number in location 7000.
-----	------	---

#### CIF, IB and SF Tests

Program interrupt is enabled for these tests. A CIF is issued, followed by an ION and a JMP. The IF should always equal 0, because of the interrupt occurring after the JMP instruction. A HLT is in location 1 of each intended field in case the IF does get set. The TTY flag is used for interrupts.

710	E 25	No interrupt, or inhibit interrupt failed.
717	E 26	CIF 1. The IB or SF failed. The AC = C(IB).
733	E 27	No interrupt or inhibit interrupt failed.
742	E 28	CIF 2. The IB or SF failed. The AC = C(IB).
756	E 29	No interrupt or inhibit interrupt failed.
765	E 30	CIF 3. The IB or SF failed. The AC = C(IB).
1004	E <del>24</del> 31	No interrupt, or inhibit interrupt failed.
1013	E 32	CIF 4. The IB or SF failed. The AC = C(IB).

1027	E 33	No interrupt, or inhibit interrupt failed.
1036	E 34	CIF 5. The IB or SF failed. The AC = C(IB).
1052	E 35	No interrupt, or inhibit interrupt failed.
1061	E 36	CIF 6. The IB or SF failed. The AC = C(IB).
1075	E 37	No interrupt, or inhibit interrupt failed.
1104	E 38	CIF 7. The IB or SF failed. The AC = C(IB).

#### Interrupt Inhibit Test

A subroutine is placed in each extended field to ensure that program interrupt is inhibited after a CIF IOT, and is enabled after a JMP instruction. The routine is in one field at a time; the contents of all other extended fields will equal 0000. The routine is described on the program listing as the "Extended Field Test Routine," and is tagged EXFLD.

The test routine is entered at location 1174 in the extended field. This location contains a CIF XX IOT, where XX equals the extended field number. Location 1175 contains an ION IOT. Locations 1176 to 7776 contain all 0's. Location 7777 contains a JMP I 12. The routine, therefore, issues a CIF, ION, and JMP I 12 sequence. Program interrupt should be inhibited until after the JMP I 12 at location 7777. An error halt occurs in field 0 if an interrupt occurs between locations 1176 and 7777. Location 12 contains 1175 (E 40 in field 0), and will auto-index to 1176.

1175	E 40	CIF or interrupt failed. The DF and IF should equal an extended field.
1203	E 41	The DF was not cleared after the interrupt. All other functions worked properly.
1221	E 42	RMF or SF failed. The SF register should have saved the extended field number after interrupt. The AC = C(I.B.) after an RMF.
1235	E 43	All functions worked, but the PC did not equal location E 40 + 1 after the interrupt in the extended field failed. The AC = contents of location 0, field 0.
4	E 44	Location 4 in the extended field. The interrupt went to this field instead of field 0, or the JMP I 12 at location 7777 was not executed. Also,

make sure interrupt was enabled in location 1175 in the extended field.

10	E 45	Location 10 in the extended field. The JMP 1 12 at location 7777 was not executed, or interrupt failed.
<del>1422</del> 1420	E 45A	No program interrupt occurred. Press CONTINUE to <del>try</del> again. <del>try</del>
70000	-	Memory field 1 halt. An interrupt in field 0 was followed by a CIF 10 IOT, and then an RMF. The RMF should have restored the IB to field 0. The SF and IB were OR'd together, resulting in the IF being set to field 1, after the JMP instruction at location 1430. Restart from 1400 to repeat the test.

#### Auto-Index Test

The subroutine labeled "Auto-Index Test" on the listing is placed in each extended field. Auto-index registers 10 through 17 in each field are tested. All of memory not occupied by the subroutine is set to 0. The error halts tagged E 46 through E 53 will occur in the extended field if an auto-index register fails. The DF and IF indicators will display the current field being tested.

<del>1524</del> 1522	E 46	Index register 10 failed.
<del>1527</del> 1525	E 47	Index register 11 failed.
<del>1532</del> 1530	E 48	Index register 12 failed.
<del>1535</del> 1533	E 49	Index register 13 failed.
<del>1540</del> 1536	E 50	Index register 14 failed.
<del>1543</del> 1541	E 51	Index register 15 failed.
<del>1546</del> 1544	E 52	Index register 16 failed.
<del>1551</del> 1547	E 53	Index register 17 failed.

#### Non-Existent Memory Test

This is the last test performed, and is included for PDP-8I's only. The test makes sure that a false memory done pulse is generated when the DF is set to a non-existent memory field. If the PDP-8I being used is equipped with the maximum of 32 K of

code memory, the program automatically skips this test and restarts at location 200. SR 8 on a 0 will cause the program to always skip this test.

The test also makes certain that the correct data is deposited in the AC when a non-existent field is referenced. This data must always equal 0000 or 7777 octal, depending on the number of extended fields existing. For example, if the PDP-8I is equipped with fields 0, 1, 2 and 3, any reference with a TAD I to fields 4 through 7 should result with 7777 octal in the AC. If equipped with fields 0, 1 and 2, a TAD I to field 3 should result with 0000 octal in the AC, and referencing 4 through 7 will result with 7777 octal in the AC. In other words, referencing the lowest order non-existent field, when the total number available is odd, will result with 0000 in the AC. Referencing all other non-existent fields will result with 7777 in the AC. When the total number available is even, referencing any non-existent field will result with 7777 in the AC.

The only legal halts in this test, are at locations 1700 and 1725. If the computer halts at any other location, the false memory done pulse probably was not generated.

The false memory done pulse is not generated when a CIF to a non-existent field is attempted.

1700	E 54	All 0's should have been deposited in the AC, or an existing field was referenced. Make sure the proper value is in SR 9-11. The number of extended fields available must be in <u>SR 9-11</u> .
1725	E 57	All 1's should have been deposited in the AC, or an existing field was referenced. Make sure the proper value is in SR 9-11.

## 6.2 Error Recovery

Press CONTINUE to repeat the failing test. Place a NOP in the error halt location to loop on a failing test. Restart from 1400 after a halt at 7000 in field 1.

## 7. Restrictions

### 7.1 Starting Restrictions

None



7.2 Operating Restrictions

The number of extended memory fields available must be in SR 9-11 before starting from location 200.

8. Miscellaneous

8.1 Execution Time

Running time is dependent on the amount of extended memory for testing, and on whether the processor being used is a PDP-8, 8I or 8S. The TTY bell will ring once for each pass of the program.

9. Program Description

The program exercises all IOT's associated with the Extended Memory Control logic, plus the ability to reference extended fields from field 0, and vice-versa. Each test is looped 4096 times before initiating the next test. A switch option is provided to skip or execute a non-existent memory test for the PDP-8I.

The individual test routines and error halts are commented on the program listing as an aid to trouble-shooting. Section 6 contains a Table of Error Halts which also may be referenced.

10. Listing

```

/
/PDP-8, 8I EXTENDED MEMORY CONTROL TEST, PLACE NUMBER
/OE EXTENDED 4K FIELDS AVAILABLE IN SR9 TO 11, (UP TO 7)
/IF USING AN 8I, PLACE SR8 ON A 1, OTHERWISE LEAVE 0.
/START PROGRAM AT 200
/
/CONSTANTS
/
6201      CDF=6201
6202      CIF=6202
6214      RDF=6214
6224      RIF=6224
6244      RMF=6244
6234      RIB=6234
0001      *1
/
0001      5001      JMP 1
0002      0002      0002
0003      0003      0003
/
0020      *20
/
0020      5400      JMP10, JMP 1 0
0021      2000      ISZ0, ISZ 0
0022      1742      XTFLG, TFLG
0023      1734      XSTKS, NSTKS
0024      1112      XRMF, TRMF
0025      1321      XTRANS, TRANS
0026      1432      XAUTO, TAUTO
0027      0000      LOOP, 0
0030      0000      NDF, 0
0031      0000      STKS, 0
0032      0000      DAT, 0
0033      0000      NOSTAK, 0
0034      0000      NOFLD, 0
0035      1174      KE40M, E40-1
0036      1175      KE40, E40
0037      7402      KHLT, HLT
0040      6201      KCDF, 6201
0041      6202      KCIF, 6202
0042      0703      KCF1, CIF1-1
0043      1316      XFD, EXFD
0044      0001      K1, 1
0045      0007      K7, 7
0046      0010      K10, 10
0047      7777      K7777, 7777
0050      7000      K7000, 7000
0051      7707      K7707, 7707
0052      7767      K7767, 7767
0053      7757      K7757, 7757
0054      7747      K7747, 7747
0055      7737      K7737, 7737
0056      7727      K7727, 7727
0057      7717      K7717, 7717

```

0067	7776	K7776,	7776
0061	7775	K7775,	7775
0062	7774	K7774,	7774
0063	7773	K7773,	7773
0064	7772	K7772,	7772
0065	7771	K7771,	7771
0066	7770	K7770,	7770
0067	0071	POINT,	+2

0070	0071	K7S,	,+1
0071	7766	K7766,	7766
0072	7755		7755
0073	7744	K7744,	7744
0074	7733		7733
0075	7722		7722
0076	7711		7711
0077	7700		7700
0100	1171	XTOF,	STOF
0101	1172	XTOF1,	STOF+1
0102	1302	KXFLD,	EXFLD
0103	5402	KJMP,	JMP I 2
0104	1200	KPTR,	ENTER
0105	0020	K20,	20
0106	5507	JMP2,	JMP I KFLD0
0107	1427	KFLD0,	RTRN
0110	1422	KRTN,	E45A+2
0111	1400	XFIB,	SFIB

```

/TEST CDF AND RDF
/
0200
*200
/
0200 7200 BEGIN, CLA
0201 3027 DCA LOOP /LOOP COUNTER
/
0202 6201 DF0, CDF 00 /DF 0
0203 6214 RDF
0204 7450 SNA /SHOULD NOT SKIP
0205 5211 JMP DF7
0206 7402 E1, HLT /ERROR, CDF OR RDF FAILED
0207 7200 CLA
0210 5202 JMP DF0 /REPEAT
/
0211 1051 DF7, TAD K7707 /7707
0212 6271 CDF 70 /DF 7
0213 6214 RDF
0214 7040 CMA /AC = 0
0215 7450 SNA /SHOULD NOT SKIP
0216 5222 JMP OK1
0217 7402 E2, HLT /CDF OR RDF FAILED
0220 7200 CLA
0221 5211 JMP DF7
/
0222 2027 OK1, ISZ LOOP /CHECK DONE
0223 5202 JMP DF0
/
0224 7200 CLA
0225 3027 DCA LOOP /LOOP COUNTER
/
0226 1052 DF1, TAD K7767 /7767
0227 6211 CDF 10 /DF 10
0230 6214 RDF
0231 7040 CMA /AC=0
0232 7450 SNA
0233 5237 JMP DF2
0234 7402 E3, HLT /CDF1 OR RDF FAILED
0235 7200 CLA
0236 5226 JMP DF1
/
0237 1053 DF2, TAD K7757 /7757
0240 6221 CDF 20 /DF2
0241 6214 RDF
0242 7040 CMA /AC=0
0243 7450 SNA
0244 5250 JMP OK2

```

0245	7402	E4,	HLT	/CDF 2 OR RDF FAILED
0246	7200		CLA	
0247	5237		JMP DF2	
/				
0250	2027	OK2,	ISZ LOOP	/DONE IF SKIP
0251	5226		JMP DF1	
0252	7200		CLA	
0253	3027		DCA LOOP	
/				
0254	1054	DF3,	TAD K7747	/7747
0255	6231		CDF 30	/DF 3
0256	6214		RDF	
0257	7040		CMA	/AC=0
0260	7450		SNA	
0261	5265		JMP DF4	
0262	7402	E5,	HLT	/CDF 3 OR RDF FAILED
0263	7200		CLA	
0264	5254		JMP DF3	
/				
0265	1055	DF4,	TAD K7737	/7737
0266	6241		CDF 40	/DF 4
0267	6214		RDF	
0270	7040		CMA	/AC=0
0271	7450		SNA	
0272	5276		JMP OK3	
0273	7402	E6,	HLT	/CDF 4 OR RDF FAILED
0274	7200		CLA	
0275	5265		JMP DF4	
/				
0276	2027	OK3,	ISZ LOOP	/DONE IF SKIP
0277	5254		JMP DF3	
/				
0300	7200		CLA	
0301	3027		DCA LOOP	
/				
0302	1056	DF5,	TAD K7727	/7727
0303	6251		CDF 50	/DF5
0304	6214		RDF	
0305	7040		CMA	/AC=0
0306	7450		SNA	
0307	5313		JMP DF6	
0310	7402	E7,	HLT	/CDF 5 OR RDF FAILED,
0311	7200		CLA	
0312	5302		JMP DF5	
/				
0313	1057	DF6,	TAD K7717	/7717
0314	6261		CDF 60	/DF 6
0315	6214		RDF	
0316	7040		CMA	/AC=0
0317	7450		SNA	
0320	5324		JMP OK4	

0321	7402	E8,	HLT	/CDF 6 OR RDF FAILED
0322	7200		CLA	
0323	5313		JMP DF6	
/				
0324	2027	OK4,	ISZ LOOP	/DONE WHEN SKIP
0325	5302		JMP DF5	
/				
/NOW TEST INTERRUPT BUFFER (IB) BITS 9-11 WITH				
/RIB. PI IS ENABLED. TELEPRINTER FLAG IS				
/USED FOR INTERRUPT.				
/				
0326	6201		CDF 00	/DF0
0327	1020		TAD JMP10	/JMP 10=JMP I 0
0330	3001		DCA 1	/C(1)=JMP I 0
0331	3027		DCA LOOP	
0332	6041		TSF	/TEST TTY FLAG
0333	4422		JMS I XTFLG	/SET FLAG
/				
0334	6001	IR0,	ION	/ENABLE PI
0335	7200		CLA	
0336	6234		RIB	/READ SF
0337	7450		SNA	
0340	5343		JMP IB1	
0341	7402	E9,	HLT	/RIB FAILED
0342	5334		JMP IB0	
/				
0343	6211	IB1,	CDF 10	/DF 1
0344	6001		ION	
0345	7200		CLA	
0346	6214		RDF	/DF SHOULD BE 0 AFTER A PI
0347	7450		SNA	
0350	5353		JMP ,+3	
0351	7402	F10,	HLT	
0352	5343		JMP IB1	/DF NOT CLEARED, OR NO PI
/				
0353	1060		TAD K7776	
0354	6234		RIB	/READ SF
0355	7040		CMA	/AC=0
0356	7450		SNA	
0357	5362		JMP OK5	
0360	7402	E11,	HLT	/RIB OR SF FAILED
0361	5343		JMP IB1	
0362	2027	OK5,	ISZ LOOP	/DONE WHEN SKIP
0363	5334		JMP IB0	
0364	5765		JMP I ,+1	
0365	0400		IB2-2	

0400	0400	*400	CLA	
0401	7200		DCA LOOP	
0402	3027			
0402	6221	/		
0403	6001	1B2,	CDF 20	/DF 2
0404	7200		ION	
0405	6214		CLA	
0406	7450		RDF	/SHOULD BE 0 AFTER PI
0407	5212		SNA	
0410	7402	•	JMP ,+3	
0411	5202	E12,	HLT	/DF NOT CLEARED, OR NO PI
			JMP 1B2	
0412	1061	/		
0413	6234		TAD K7775	
0414	7040		RIB	/AC=7777
0415	7450		CMA	/=0
0416	5221		SNA	
0417	7402		JMP 1B3	
0420	5202	F13,	HLT	/RIB OR SF FAILED
			JMP 1B2	
0421	6231	/		
0422	6001	1B3,	CDF 30	/DF3
0423	7200		ION	
0424	6214		CLA	
0425	7450		RDF	/DF SHOULD BE CLEARED
0426	5231		SNA	
0427	7402		JMP ,+3	
0430	5221	F14,	HLT	/DF NOT CLEARED
			JMP 1B3	
0431	1062	/		
0432	6234		TAD K7774	
0433	7040		RIH	/AC=7777
0434	7450		CMA	/AC=0
0435	5240		SNA	
0436	7402		JMP 0K6	
0437	5221	F15,	HLT	/RIB OR SF FAILED
			JMP 1B3	
0440	2027	/		
0441	5202	0K6,	ISZ LOOP	/DONE IF SKIP
			JMP 1B2	
0442	7200	/		
0443	3027		CLA	
			DCA LOOP	
0444	6241	/		
0445	6001	1B4,	CDF 40	/DF 3
0446	7200		ION	
0447	6214		CLA	
0450	7450		RDF	/DF MWSV BE 000 AFTER A PI
0451	5254		SNA	/ERROR IF SKIP
			JMP ,+3	



0452	7402	E16,	HLT	/DF NOT 0 AFTER PI
0453	5244		JMP IB4	
/				
0454	1063		TAO K7773	/AC=7773
0455	6234		RIB	/AC=7777
0456	7040		CMA	/AC=0
0457	7450		SNA	
0460	5263		JMP IB5	
0461	7402	E17,	HLT	/RIB OR SF FAILED
0462	5244		JMP IB4	
/				
0463	6251	IB5,	CDF 50	/DF5
0464	6701		ION	
0465	7200		CLA	
0466	6214		RDF	/DF SHOULD=000
0467	7450		SNA	
0470	5273		JMP ,+3	
0471	7402	E18,	HLT	/DF NOT 0 AFTER PI
0472	5263		JMP IB5	
/				
0473	1064		TAO K7772	/AC= 7772
0474	6234		RIB	/ = 7777
0475	7040		CMA	/ = 0
0476	7450		SNA	
0477	5302		JMP OK7	
0500	7402	E19,	HLT	/RIB OR SF FAILED
0501	5263		JMP IB5	
/				
0502	2027	OK7,	ISZ LOOP	/DONE IF 0 AND SKIP
0503	5244		JMP IB4	
/				
0504	7200		CLA	
0505	3027		DCA LOOP	
/				
0506	6261	IB6,	CDF 60	/DF6
0507	6001		ION	
0510	7200		CLA	
0511	6214		RDF	/DF MUST=0 AFTER PI
0512	7450		SNA	
0513	5316		JMP ,+3	
0514	7402	E20,	HLT	/DF NOT 0 AFTER PI
0515	5306		JMP IB6	

0516	1065	/	TAD K7771	/,7771
0517	6234		RIB	/AC=7777
0520	7040		CMA	
0521	7450		SNA	
0522	5325		JMP 187	
0523	7402	E21,	HLT	/RIB OR SF FAILED
0524	5306		JMP 186	
/				
0525	6271	187,	CDE 70	/DF 7
0526	6001		ION	
0527	7200		CLA	
0530	6214		RDF	/DF MUST = 0 AFTER PI
0531	7450		SNA	
0532	5335		JMP ,+3	
0533	7402	E22,	HLT	/DF NOT 0
0534	5325		JMP 187	
/				
0535	1066		TAD K7770	
0536	6234		RIB	/AC=7777
0537	7040		CMA	
0540	7450		SNA	
0541	5344		JMP OK8	
0542	7402	E23,	HLT	/RIB OR SF FAILED
0543	5325		JMP 187	
/				
0544	2027	OK8,	ISZ LOOP	/DONE IF 0
0545	5306		JMP 186	
0546	5747		JMP I ,+1	/NEW PAGE
0547	0600		600	

0600.

\*600

/NOW TEST DCA I AND TAD I TO ALL STACKS. NUMBER OF  
/EXTENDED STACKS SHOULD BE IN SR9 TO 11. EACH STACK WILL  
/CONTAIN ITS DF# IN LOCATION 7000.  
/

0600	3027		DCA LOOP	
0601	4423	DCAI,	JMS I XSTKS	/READ SR 9-11
0602	7001		IAC	
0603	3030		DCA NDF	/DF NUMBER = 1 TO START
0604	1040		TAD KCDF	/6201
0605	1046		TAD K10	
0606	3207		DCA ,+1	/DF 001 TO START WITH
0607	6201	DFLD,	CDF 00	/WILL BE INCREMENTED
0610	1030		TAD NDF	/DF#
0611	3450		DCA I K7000	/PUT IN 7000 OF STACK
0612	2031		ISZ STKS	/ALL STACKS WHEN 0
0613	7410		SKP	
0614	5222		JMP TADI	/TEST TAD I
0615	1046		TAD K10	
0616	1207		TAD DFLD	/INCR. CDF 10T
0617	3207		DCA DFLD	
0620	2030		ISZ NDF	
0621	5207		JMP DFLD	/-
/				
0622	4423	TADI,	JMS I XSTKS	/SR9=11 AGAIN
0623	7001		IAC	
0624	3030		DCA NDF	/DF#=1 AGAIN
0625	1040		TAD KCDF	/6201
0626	1046		TAD K10	
0627	3230		DCA ,+1	
0630	6201	TFLD,	CDF 00	
0631	1450		TAD I K7000	/AC=DF CONTENTS NOW
0632	3032		DCA DAT	/SAVE TEMP
0633	1032		TAD DAT	
0634	7041		CIA	/2'S COMP
0635	1030		TAD NDF	/BETTER BE EQUAL
0636	7640		SZA CLA	
0637	5252		JMP E24-1	/ERROR PATH
0640	2031		ISZ STKS	/ALL WHEN 0
0641	5245		JMP ,+4	
0642	2027		ISZ LOOP	/DONE WHEN 0
0643	5201		JMP DCAI	
0644	5256		JMP IBSF	/NEXT TEST
0645	1046		TAD K10	
0646	1230		VAD VFLD	/CDF 10V + 10
0647	3230		DCA TFLD	
0650	2030		ISZ NDF	
0651	5230		JMP TFLD	
/				
0652	1032		TAD DAT	/DATA AS READ
0653	7402	E24,	HLT	/AC=DATA READ. DF INDICATORS
				/EQUAL FIELD WHERE GOT DATA.
				/BOTH SHOULD BE EQUAL
0654	7220		CLA	

4/30/68 13:24,36

PAGE 9-1

0655 5230

JMP TFLD

/  
 / ON TEST CIF WITH PROGRAM INTERRUPT ENABLED, THE  
 / I.F. SHOULD ALWAYS = 00 SINCE A JMP OR JMS IS EX-  
 / ECUTED AFTER THE CIF IOT. THE SF REGISTER IS  
 / TESTED WITH THE RIB IOT AFTER THE INTERRUPT,  
 / IF THE I.F. IS SET A HLT WILL OCCUR AT LOC. 1  
 / IN THE EXTENDED FIELD.  
 / A HLT WILL OCCUR AFTER THE ION IOT  
 / IF NO INTERRUPT OCCURS, PRESS CONT. TO REPEAT.

/  
 / SKIP LOGS. 1, 2 TO = 152 0, AND  
 / 1 1 1, RESPECTIVELY.

0656	6201	LDI 00	/SET DF TO 000.
0657	1021	LAD ISZ0	/ISZ 0
0658	3021	LCA 1	
0661	1022	LAD JMRI0	/JMR 1 0
0662	3022	LCA 2	

/  
 / IF A HLT IN LOC. 1 OF ALL EXTENDED FIELDS.

0663	4023	JMS I XSIAS	
0664	1043	LAD KCOF	
0665	1046	LAD K10	
0666	3067	LCA ,+1	
0667	6011	LDI 10	/FIELD 1 TO START WITH
0670	1 07	LAD KHI 1	/KHLT = 7402
0671	3444	LCA I K1	
0672	2031	ISZ STKS	/ALL FIELDS WHEN SKIP
0673	7410	KRP	
0674	5277	JMP ,+3	
0675	1067	LAD HLTS	
0676	5260	JMP HLTS-1	

/  
 / CIF TESTS

0677	6201	LDI 00	
0678	6041	VSE	
0701	4422	JMS I XTEP	/SET TTY FLAG
0702	3027	LCA LOOP	
0703	4423	JMS I XSTKS	/READ SR 9-11
0704	6212	LDI 10	/FIELD 1
0705	6011	ION	
0706	7000	LOP	
0707	5010	JMP ,+1	
0710	7402	HLT	/ERROR, NO PI OR INHIBIT PI
0711	6234	RIB	/RETURN HERE FROM LOC.3
0712	1062	LAD K7760	
0713	7040	SMA	
0714	7650	SNA CLA	/OK IF NO SKIP
0715	5322	JMP SKF1	
0716	6234	RIB	
0717	7402	HLT	/I.F. OR S.F. FAILED, C(AC)=C(IB)

4/30/68 13:24,37

PAGE 10-1

0720 7200  
0721 5304

CLA  
JMP CIF1

/REPEAT

```

/
0722 2031      OKF1,  ISZ STKS          /ALL FIELDS IF 0
0723 5327      JMP CIF2
0724 2027      ISZ LOOP          /ALL DONE IF 0
0725 5303      JMP CIF1-1
0726 5424      JMP I XRMF      /TEST RMF
/
0727 6222      CIF2,  CIF 22      /FIELD 2
0730 6001      ION
0731 7020      NOP
0732 5335      JMP ,+1
0733 7402      E27,  HLT          /NO PI OR INHIBIT PI
0734 6234      RIR          /RETURN FROM LOC.3
0735 1053      TAD K7757
0736 7040      CMA
0737 7650      SNA CLA          /ERROR IF SKIP
0740 5345      JMP OKF2
0741 6234      RIR
0742 7402      E28,  HLT          /IR OR SF FAILED, C(AC)=C(18)
0743 7200      CLA
0744 5327      JMP CIF2
/
0745 2031      OKF2,  ISZ STKS          /ALL FIELDS IF 0
0746 5352      JMP CIF3
0747 2027      ISZ LOOP          /ALL DONE IF 0
0748 5303      JMP CIF1-1
0751 5424      JMP I XRMF      /TEST RMF
/
0752 6232      CIF3,  CIF 30      /FIELD 3
0753 6001      ION
0754 7020      NOP
0755 5356      JMP ,+1
0756 7402      E29,  HLT          /NO PI OR INHIBIT PI
0757 6234      RIR          /RETURN FROM LOC.3
0760 1054      TAD K7747
0761 7040      CMA
0762 7650      SNA CLA          /ERROR IF SKIP
0763 5370      JMP OKF3
0764 6234      RIR
0765 7402      E30,  HLT          /SF OR IR FAILED, C(AC)=C(18)
0766 7200      CLA
0767 5352      JMP CIF3
/
0770 2031      OKF3,  ISZ STKS          /ALL FIELDS IF 0
0771 5775      JMP I ,+4
0772 2027      ISZ LOOP          /ALL DONE IF 0
0773 5303      JMP CIF1-1
0774 5424      JMP I XRMF      /TEST RMF
0775 1000      CIF4
/

```

## /PDP-8,81 EXT, MEM, CONTROLL TEST-TAPE 2

1000	6242	CIF4,	CIF 40	/FIELD 4
1001	6001		ION	
1002	7000		NOP	
1003	5204		JMP ,+1	
1004	7402	E31,	HLT	/NO PI OR INHIBIT PI
1005	6234		RIB	/JMP TO HERE FROM LOC, 3
1006	1055		TAD K7737	
1007	7040		CMA	
1010	7650		SNA CLA	/AC MUSV BE 0
1011	5216		JMP OKF4	
1012	6234		RIB	
1013	7402	E32,	HLT	/IB OR SF FAILED, C(AC)=C(IB)
1014	7200		CLA	
1015	5200		JMP CIF4	
		/		
1016	2031	OKF4,	ISZ STKS	/ALL FIELDS IF 0
1017	5223		JMP CIF5	
1020	2027		ISZ LOOP	/ALL DONE IF 0
1021	5442		JMP I KCF1	
1022	5312		JMP TRMF	/TEST RMF
		/		
1023	6252	CIF5,	CIF 50	/FIELD 5
1024	6001		ION	
1025	7000		NOP	
1026	5227		JMP ,+1	
1027	7402	E33,	HLT	/NO PI OR INHIBIT PI
1030	6234		RIB	/JMP HERE FROM LOC, 3
1031	1056		TAD K7727	
1032	7040		CMA	
1033	7650		SNA CLA	/ERROR IF SKIP
1034	5241		JMP OKF5	
1035	6234		RIB	
1036	7402	E34,	HLT	/IB OR SF FAILED, C(AC)=C(IB)
1037	7200		CLA	
1040	5223		JMP CIF5	
		/		
1041	2031	OKF5,	ISZ STKS	/DONE WHEN SKIP
1042	5246		JMP CIF6	
1043	2027		ISZ LOOP	/512 VIMES IF SKIP
1044	5442		JMP I KCF1	
1045	5312		JMP TRMF	/TEST RMF
		/		
1046	6262	CIF6,	CIF 60	/FIELD 6
1047	6001		ION	
1050	7000		NOP	
1051	5252		JMP ,+1	
1052	7402	E35,	HLT	/NO PI OR INHIBIT PI
1053	6234		RIB	/JMP HERE FROM LOC, 3
1054	1057		TAD K7717	
1055	7040		CMA	
1056	7650		SNA CLA	/TO SKIP IS TO ERROR



4/30/68 13:24,39

PAGE 12-1

1057 5264  
1760 6234

JMP OKF6  
R18

1061	7402	E36,	HLT	/IB OR SF FAILED, C(AC)=C(IB)
1062	7200		CLA	
1063	5246		JMP CIF6	
/				
1064	2031	OKF6,	ISZ STKS	/SEE IF ALL FIELDS
1065	5271		JMP CIF7	
1066	2027		ISZ LOOP	/ALL DONE WHEN SKIP
1067	5442		JMP I KCF1	
1070	5312		JMP TRMF	/TEST RMF
/				
1071	6272	CIF7,	CIF 70	/FIELD 7
1072	6001		ION	
1073	7000		NOP	
1074	5275		JMP ,+1	
1075	7402	E37,	HLT	/NO PI OR INHIBIT PI
1076	6234		RIB	/RETURN HERE FROM LOC,3
1077	1051		TAD K7707	
1100	7040		CMA	
1101	7650		SNA CLA	/ERROR IF SKIP
1102	5307		JMP OKF7	
1103	6234		RIB	
1104	7402	E38,	HLT	/IB OR SF FAILED, C(AC)=C(IB)
1105	7200		CLA	
1106	5271		JMP CIF7	
/				
1107	2027	OKF7,	ISZ LOOP	/DONE IF SKIP
1110	5442		JMP I KCF1	
1111	5312		JMP TRMF	/TEST RMF

```

/
/TEST INTERRUPT INHIRT
/FROM EACH FIELD, REFER TO HEADING TITLED "EXTENDED
/FIELD TEST ROUTINE", THIS ROUTINE IS PLACED IN
/EACH TESTED FIELD AT THE ADDRESSES SPECIFIED, THE
/INDICATED ERROR HALTS WILL BE IN THE EXTENDED
/FIELD. PRESS CONT, TO RECOVER, ONLY 1 FIELD WILL
/CONTAIN THE ROUTINE AT ANY ONE TIME, OTHER FIELDS
/WILL CONTAIN ALL 0'S. THE ROUTINE IS REPLACED WITH
/HALTS AFTER COMPLETION, THE PORTIONS OF THE FIELD
/WHICH DO NOT CONTAIN THE ROUTINE ARE SET TO 0000
/BEFOREHAND.
/
/

```

```

/SETUP FIELDS TO TEST, POINTERS, ETC.,
/

```

```

1112 4423
1113 1040
1114 3322
1115 1322
1116 1046
1117 3322
1120 7040
1121 3010
1122 6201
1123 3410
1124 1010
1125 7040
1126 7640
1127 5323
1130 2031
1131 5315

```

```

TRMF,    JMS I XSTKS    /READ SR9-11
          TAD KCDF      /6201
          DCA ,+6
          TAD ,+5
          TAD K10
          DCA ,+3
          CMA
          DCA 10
          CDF 00
          DCA I 10
          TAD 10        /PLACE 0'S IN EACH FIELD FROM
                        /LOC, 0 TO 7777,
          CMA
          SZA CLA
          JMP , -4
          ISZ STKS
          JMP TRMF+3

```

/  
 /NOW PUT A HLT IN EACH FIELD IN THE SAME  
 /LOCATION AS E40, BELOW.  
 /

1132	4423	JMS I XSTKS	/READ SR 9-11
1133	1040	TAD KCDF	
1134	1046	VAD K10	
1135	3336	DCA ,+1	
1136	6201	CHDF, CDF 00	
1137	1036	TAD KE40	/KE40 = ADDRESS OF E40.
1140	3027	DCA LOOP	/SAVE TEMPORARILY
1141	1037	TAD KHLT	/KHLT = 7402 (HLT)
1142	3427	DCA I LOOP	
1143	2031	ISZ STKS	/DONE ALL STACKS WHEN SKIP
1144	7410	SKP	
1145	5350	JMP ,+3	
1146	1336	TAD CHDF	
1147	5334	JMP CHDF-2	
/			
1150	6201	CDF 00	
1151	6041	STDF, TSF	/CHECK TTY FLAG
1152	4422	JMS I XTFLG	/GO SET IT
1153	1051	TAD K7707	
1154	3027	DCA LOOP	
1155	1067	TAD POINT	
1156	3070	DCA K7S	/POINTER FOR K7700 TO K7766
1157	4423	JMS I XSTKS	/READ SR 9-11
1160	1040	TAD KCDF	/6201
1161	1046	TAD K10	/10
1162	3371	DCA STDF	
1163	1041	TAD KCIF	/6202
1164	1046	TAD K10	/10
1165	3372	DCA STDF+1	
1166	1372	TAD STDF+1	
1167	3443	DCA I XFD	
1170	4425	JMS I XRANS	/PUT TEST ROUTINE INTO FIELD X
/			
1171	6211	STDF, CDF 10	/FIELD 1 TO START WITH
1172	6212	CIF 10	
1173	5374	JMP ,+1	/SHOULD ENTER EXTENDED FIELD
			/AFTER THIS JMP, HLT IF NOT
1174	7000	NOP	
1175	7402	E40, HLT	/ERROR, PI FAILED
			/C(AC) = C(1.B.)
1176	5371	JMP STDF	/REPEAT SAME TEST.
/			

```

1200
1200 6214
1201 7450
1202 5206
1203 7402
1204 7200
1205 5500
1206 6212
1207 6244
1210 6234
1211 6202
1212 6201
1213 1470
1214 7040
1215 7650
1216 5226
1217 6244
1220 6234
1221 7402
1222 7200
1223 6201
1224 6202
1225 5500
1226 1036
1227 7001
1230 7041
1231 1000
1232 7650
1233 5240
1234 1000
1235 7402
1236 7200
1237 5500
1240 2031
1241 5246
1242 2027
1243 5645
1244 5511
1245 1155

/ENTER HERE AFTER PI FROM EXTENDED BANK
*1200
/
ENTER, RDF /DF SHOULD BE 000
SNA /ERROR IF SKIP
JMP ,+4 /CHECK C(SF)
E41, HLT /AC=C(DF)
CLA
JMP I XTDF /REPEAT TEST
CIF 10 /SET I,B. TO FIELD 1
RMF /I,B. NOW EQUAL TO SF
RIB /READ IB
CIF 00
CDF 00
TAD I K7S
CMA
SNA CLA /ERROR IF SKIP
JMP CKPC
RMF
RIB
E42, HLT /ERROR RMF AND PI WORKED, BUT
/I,B. NOT CORRECT AFTER RMF.
/AC=C(IB)
CLA
CDF 00
CIF 00
JMP I XTDF /BACKUP A PAGE AND REPEAT
/
CKPC, TAD KE40 /KE40=ADDRESS OF E40
IAC /MAKE E40+1
CIA
TAD 0 /COMPARE TO C(0)
SNA CLA /SHOULD NOT SKIP
JMP ,+5 /ALL OK SETUP FOR NEXT FIELD
TAD 0
E43, HLT /ERROR, ALL WORKED, BUT
/C(PC) WAS NOT=TO E40+1
/AFTER PI IN EXTENDED
/FIELD, C(AC)=C(0),F0,
/CHECK FOR PI NOT INHIBITED,
/OR AUTO-INDEX REG,
/12 FAILING IN THE EXTENDED FIELD.
CLA
JMP I XTDF /BACKUP AND REPEAT
/
/SETUP FOR NEXT FIELD
/
ISZ STKS /DONE ALL IF SKIP
JMP ,+5
ISZ LOOP /DONE LOOPING IF SKIP
JMP I ,+2 /REPEAT ALL AGAIN
JMP I XFIB /EXIT TO NEXT TEST
STRMF+4 /BACK TO LAST PAGE

```

/
   
/SET LAST TESTED FIELD TO ALL 0'S AND PUT A
   
/HIT IN RESPECTIVE ADDRESS OF E40
   
/

1246	7240	CLA CMA	
1247	3010	DCA 10	
1250	1500	TAD I XTDF	/CDF X0 AT STDF
1251	3252	DCA ,+1	
1252	6211	CDF 10	/F1 TO START WITH
1253	3410	DCA I 10	
1254	1010	TAD 10	
1255	7040	CMA	
1256	7640	SZA CLA	/CLEAR IF SKIP
1257	5253	JMP ,-4	
1260	6201	CDF 00	
1261	1500	TAD I XTDF	/CDF X0 AT STDF
1262	3263	DCA ,+1	
1263	6211	CDF 10	
1264	1037	TAD KHLT	/=7402 (HLT)
1265	3436	DCA I KE40	/KE40=ADDRESS OF E40
1266	6201	CDF 00	/RESTORE DF

/
   
/INCREMENT CDF AND CIF 10T'S AT STDF, STDF+1
   
/TO NEXT FIELD,
   
/

1267	1500	TAD I XTDF	/CDF X0 AT STDF
1270	1046	VAD K10	
1271	3500	DCA I XTDF	
1272	1501	TAD I XTDF1	/CIF X0 AT STDF
1273	1046	TAD K10	
1274	3501	DCA I XTDF1	
1275	1501	TAD I XTDF1	
1276	3316	DCA EXFD	
1277	2070	ISZ K7S	
1300	4321	JMS TRANS	/PUT ROUTINE IN NEW FIELD
1301	5500	JMP I XTDF	/TEST NEW FIELD

## /EXTENDED FIELD TEST ROUTINE

/THE FOLLOWING INSTRUCTIONS ARE PLACED IN  
 /EACH EXTENDED FIELD TESTED, THE NUMBERS IN THE  
 /COMMENTS FIELD CORRESPOND TO THE  
 /MEMORY LOCATIONS IN THE TESTED FIELD. LOCATIONS  
 /0 THRU 11 ARE USED FOR AN ERROR ROUTINE  
 /IN CASE FIELD 0 IS NOT ENTERED AFTER AN  
 /INTERRUPT, THE EXTENDED FIELD SHOULD BE  
 /ENTERED AT LOCATION E40-1 WHICH CORRESPONDS  
 /TO E40-1 IN FIELD 0.

/EXTENDED FIELD INSTRUCTIONS:

1302 0000  
 1303 1000  
 1304 7450

EXFLD. 0 /0  
 TAD 0 /1  
 SNA /IF LOC. 0 NOT =0 PI DIDN'T  
 /ENTER FIELD 0  
 JMP ,+5 /3  
 E44, HLT /4, INTERRUPTED TO THIS FIELD  
 /INSTEAD OF FIELD 0. C(AC)=C(0)  
 /WHICH SHOULD BE E40+1  
 /IF NOT, CHECK LOC, 7777, IT  
 /MUST = 5412 (JMP I 12).

1307 7200  
 1310 3000  
 1311 5420  
 1312 7402

CLA /5  
 DCA 0 /6  
 JMP I 20 /7, C(20) =E40  
 E45, HLT /10, THE JMP I 12 AT LOC,  
 /7777 WAS NOT EXECUTED,  
 /OR INTERRUPT FAILED, IF  
 /NO INTERRUPT, LOCATION 12  
 /NOW CONTAINS 0 INSTEAD  
 /OF ADDRESS E40,  
 JMP , -4 /11, REPEAT IN THIS FIELD  
 E40 /12, AUTO-INDEXS TO E40+1  
 /IN F 0 IF THE JMP I 12  
 /WORKS.

/LOCS. 13 TO 17 ARE ALL 0'S

1315 1175

E40 /20, EQUALS E40 IN F0,

/LOCS. 21 TO E40-2 ARE ALL 0'S

1316 6212  
 1317 6001

EXFD. CIF 10 /FIELD 1 TO START WITH  
 ION /LOC. E40, SEE SYMBOL TABLE  
 /FOR E40.

/LOCS. E40+1 TO 7776 ARE ALL 0'S

1320 5412

JMP I 12 /7777, PI SHOULD OCCUR,  
 /AFTER THIS INSTRUCTION,  
 /TO FIELD 0.

```

/ROUTINE TO TRANSFER TEST ROUTINE TO PROPER FIELD
/
1321 0000 TRANS, 0
1322 1103 TAD KJMP /KJMP=JMP I 2
1323 3001 DCA 1 /IN FIELD 0
1324 1104 TAD KNTR /KNTR = LOC, ENTER
1325 3002 DCA 2 /OF FIELD 0
1326 1102 TAD KXFLD /KXFLD = LOC, EXFLD
1327 3010 DCA 10
1330 3011 DCA 11
1331 1071 TAD K7766 /1-10 DECIMAL
1332 3000 DCA 0 /SAVE
1333 1500 TAD I XTDF /CDF X0 IN STDF
1334 3337 DCA ,+3
1335 6201 CDF 00
1336 1410 TAD I 10
1337 6211 TRFLD, CDF 10 /F1 TO START WITH
1340 3411 DCA I 11 /PUT IN EXTENDED FIELD
1341 2000 ISZ 0 /DONE LOCS 1 TO 12 IF SKIP
1342 5335 JMP ,+5
1343 1337 TAD TRFLD
1344 3347 DCA ,+3
1345 6201 CDF 00
1346 1410 TAD I 10
1347 6211 CDF 10
1350 3505 DCA I K20 /PUT E40 IN LOC. 20
1351 6201 CDF 00
1352 1337 TAD TRFLD
1353 3355 DCA ,+2
1354 1410 TAD I 10
1355 6211 CDF 10
1356 3435 DCA I KE40M /PUT CIF X0 IN E40-1
1357 6201 CDF 00
1360 1337 TAD TRFLD
1361 3363 DCA ,+2
1362 1410 TAD I 10
1363 6211 CDF 10
1364 3436 DCA I KE40 /ION TO LOC, E40
1365 6201 CDF 00
1366 1337 TAD TRFLD
1367 3371 DCA ,+2
1370 1410 TAD I 10
1371 6211 CDF 10
1372 3447 DCA I K777 /PUT JMP I 12 IN 7777
1373 6201 CDF 00
1374 5721 JMP I TRANS /EXIT

```



1400

```

*1400
/
/TEST SF WITH AN RMF IOT, AN INTERRUPT IN FIELD 0 IS CREATED, AFTER
/WHICH, THE DF AND IR REGISTERS ARE SET TO FIELD 1.
/THE SF SHOULD CONTAIN FIELD 0, THE TEST
/THEN MAKES SURE THE IR IS CLEARED, THEN SET BY ISSUING AN RMF,
/FOLLOWED BY A JMP I K7000, IF THE IR IS CLEARED, THE JMP GOES TO 7000 IN FIELD 0.
/IF THE IR AND SF ARE INCLUSIVE OR'D, THE JMP GOES TO 7000 IN FIELD 1, AND
/IF A HALT OCCURS THERE, RESTART FROM 1400 AFTER AN ERROR, THE TEST IS LOOPEO
/512 TIMES,
/
1403 6041 SFIB, TSF /SEE IF FLAG IS SET.
1404 4422 JMS I XTFLG /SET IT
1405 1450 TAD K7000 /7000
1406 3027 DCA LOOP
1407 6211 CDF 10 /DF=FIELD 1
1408 1037 TAD KHLT /HLT
1409 3450 DCA I K7000 /7000, FIELD 1=HLT
1410 6201 CDF 00 /DF=0
1411 1106 TAD JMP2 /JMP2=JMP I KFLD0
1412 3450 DCA I K7000 /7000, FIELD 0=JMP I KFLD0
/ KFLD0=LOC, RTN
/ KJMP=JMP I 2
1413 1103 TAD KJMP
1414 3001 DCA 1
1415 1110 TAD KRTN /KRTN=LOC, E45A+2
1416 3002 DCA 2
/
/ BEGIN TEST
/
1417 6001 IOV /ENABLE PI
1418 7000 NOP
1419 7002 E45A, HLT /ERROR NO PI
1420 1200 JMP SFIB /REPEAT TEST
/
/ RETURN HERE AFTER PI
/
1421 7000 CLA
1422 6211 CDF 10 /DF=FIELD1
1423 6212 CDF 10 /IR=FIELD1
1424 6244 RMF /IR SHOULD=FIELD0
1425 5450 JMP I K7000 /IF SHOULD=FIELD0
/
RTN, ISZ LOOP /WORKED OK
1427 2027 JMP E45A-2 /LOOP
1428 5216 JMP TAD10 /DONE, GO TO NEXT TEST
1429 5232

```

```

/
/
/TEST ALL AUTO-INDEX REGISTERS IN EACH EXTENDED FIELD.
/IDENTICAL TEST ROUTINES ARE PERFORMED FROM EACH FIELD.
/AND ERROR HALTS OCCUR IN THE FIELD CURRENTLY RUNNING
/THE ROUTINE, PRESS CONT. TO RESUME TESTING. EACH
/FIELD CONTAINS ALL M'S EXCEPT FOR THE AREA OCCUPIED
/ BY THE TEST ROUTINE. FIELD 0 IS RE-ENTERED
/ AFTER EACH TEST, AND THE NEXT SEQUENTIAL FIELD
/ IS THEN ENTERED. REFER TO THE HEADING "AUTO-
/ INDEX TEST" FOR THE SEQUENCE OF OPERATIONS.
/
1432 6201      TAD TO,   CDF 00
1433 1751      TAD K7707
1434 3027      DCA LOOP           /LOOP COUNTER
1435 4423      JMS I XSTKS       /READ SR 9-11
1436 1040      TAD KCDF         /6201
1437 3246      DCA DFN
1438 1246      TAD DFN
1439 1246      TAD K10          /INCREMENT OF
1440 3246      DCA DFN
/
/ CLEAR ONE FIELD TO 0
/
1443 7040      CHA
1444 3010      DCA 10
1445 3000      DCA 0           /USE LOC. 0 FOR A COUNTER
1446 6211      DFN,   CDF 10    /FIELD 1 TO START WITH
1447 3410      DCA I 10
1448 2000      ISZ 0
1449 5247      JMP .-2
1450 6201      CDF 00
/
/ NOW PUT TEST ROUTINE IN THE EXTENDED FIELD
/
1453 1316      TAD DOAUTO       /1ST LOC. OF ROUTINE MINUS 1
1454 3010      DCA 10           /SOURCE
1455 1073      TAD K7744        /-28 DECIMAL
1456 3000      DCA 0           /USE LOC. 0 AS COUNTER
1457 1316      TAD DOAUTO
1458 3011      DCA 11          /DESTINATION
1459 1246      TAD DFN         /CDF X0
1460 3265      DCA .+3
1461 6201      MOVE,   CDF 00
1462 1410      TAD I 10
1463 6211      CDF 10         /FIELD 1 TO START
1464 3411      DCA I 11
1465 2000      ISZ 0          /MOVE WHEN SKIP
1466 5263      JMP MOVE

```

```

/
/ NOW SET AUTO-I REGS 10 TO 17 TO 7777,
/
1471 1066      TAD K7770      /-8 DECIMAL
1472 3000      DCA 0
1473 1045      TAD K7      /7
1474 3010      DCA 10
1475 7040      CMA      /7777
1476 3410      DCA I 10
1477 2000      ISZ 0      /10 TO 17 = 7777 WHEN SKIP
1500 5275      JMP , -3
1501 7040      CMA
1502 3447      DCA I K7777  /PUT 7777 IN LOC. 7777 OF EXTENDED FIELD
1503 6214      RUF      /READ D.F.
1504 1041      TAD KCIF      /6202
1505 3306      DCA , +1
1506 6212      CIF 10      /FIELD 1 TO START
1507 4715      JMS I FILDX  /ENTER EXTENDED FIELD
                               /515 OCTAL LOCS, BEFORE THE
                               /TAD I 10 INSTRUCTION,
                               /THIS IS A TEST OF THE
                               /DEFER BIT, 500 US DELAY
/
/ ENTER FIELD 0 FROM EXTENDED FIELD HERE,
/
1510 2031      GOTO, ISZ STKS  /DONE ALL WHEN SKIP
1511 5240      JMP NEWUF      /SETUP FOR NEXT
1512 2027      ISZ LOOP      /ALL DONE IF SKIP
1513 5235      JMP NEWOF_3    /REPEAT ALL
1514 5353      JMP CSR8      /CHECK SR 8
/
1515 1001      FILDX, DOAUTO-515

```

```

/
/      AUTO-INDEX TEST
/
/ THE ROUTINE WILL BE PLACED IN THE SAME RESPECTIVE
/ LOCATIONS IN EACH EXTENDED FIELD. ANY ERROR
/ HALT WILL OCCUR IN THE EXTENDED FIELD. PRESS
/ CONTINUE TO PROCEED WITH TESTING. THE INDEX
/ REGISTERS 10 TO 17 INITIALLY CONTAIN 7777, AND
/ ARE AUTO-INDEXED TO 0000 BY A TAD I INSTRUCTION.
/ A HALT OCCURS IF THE REG. IS NOT INCREMENTED TO 0.
/ THE TAD I WOULD HAVE THEN REFERENCED LOC. 7777,
/ WHICH CONTAINS 7777.
/

1516 1516      DD AUTO, .      / THIS LOC. IS NOT MOVED TO
                                / THE EXTENDED FIELD.

1517 7200      CLA
1520 1410      TAD I 10
1521 7440      SZA
1522 7402      E46, HLT      / ERROR, INDEX REG. 10 FAILED
1523 1411      TAD I 11
1524 7440      SZA
1525 7402      E47, HLT      / INDEX REG. 11 FAILED
1526 1412      TAD I 12
1527 7440      SZA
1530 7402      E48, HLT      / 12 FAILED
1531 1413      TAD I 13
1532 7440      SZA
1533 7402      E49, HLT      / 13 FAILED
1534 1414      TAD I 14
1535 7440      SZA
1536 7402      E50, HLT      / 14 FAILED
1537 1415      TAD I 15
1540 7440      SZA
1541 7402      E51, HLT      / 15 FAILED
1542 1416      TAD I 16
1543 7440      SZA
1544 7402      E52, HLT      / 16 FAILED
1545 1417      TAD I 17
1546 7440      SZA
1547 7402      E53, HLT      / 17 FAILED
1550 6201      CDF 00      / SET DF TO FIELD 0
1551 6202      CIF 00      / SET I.B. TO FIELD 0
1552 5310      JMP GOTO0    / EXIT TO FIELD 0

/ END OF TEST ROUTINE
/
/

```

/CHECK SR 8. IF AN 81 IS BEING USED SR 8 MUST BE  
/ON A 1. OTHERWISE, 0.

/

1553 7604  
1554 0246  
1555 7640  
1556 5766  
1557 0007  
1560 1357  
1561 6046  
1562 6041  
1563 5362  
1564 5765

CSR8, LAS  
AND K10  
SZA CLA  
JMP I XMEM /NEXT TEST  
AND 7  
BELL, TAD .-1  
ILS /RING BELL  
TSF  
JMP .-1  
JMP I XBGN /START OVER AT 200

/

1565 0200  
1566 1600

XBGN, BEGIN  
XMEM, NOMEM

```

/
*1600
/
/REFERENCE ALL 4K FIELDS NOT PRESENT, IF 32K
/IS PRESENT, THE TEST IS BY-PASSED, AND PROGRAM IS
/RESTARTED AT 200, EACH FIELD NOT PRESENT IS
/REFERENCED BY THE PROGRAM WITH JMP, DCA AND TAD.
//THE PROGRAM MUST CONTINUE IN SEQUENCE/ THE TTY
/BELL WILL SIGNAL A SUCCESSFUL TEST, AND THE PRO-
/GRAM IS THEN RESTARTED AT 200.
/
1600 7200      NOREM,   CLA
1601 1066      TAD K7770
1602 3027      DCA LOOP      /TEST LOOP COUNTER
1603 7604      LAS          /READ SR9=11
1604 0045      AND K7
1605 7041      CIA
1606 1045      TAD K7        /SUBTRACT MAX, POSSIBLE
1607 7450      SNA
1608 5652      JMP I XBELL    /32K PRESENT, CAN'T TEST
1609 3033      DCA NOSTAK     /SAVE NO, MISSING
1610 3651      DCA I XELL     /CLEAR THE TLS IOT AT
                               /BELL+1 TO PROHIBIT
                               /FALSE INDICATION, TLS
                               /IS RESTORED LATER WRONG
                               /ENTRY FROM NON-EXISTENT
                               /MEMORY MAY CAUSE A
                               /HANG-UP AT BELL+2 AND +3.
                               /# OF FIELDS PRESENT
1613 7604      LAS
1614 0045      AND K7
1615 7001      IAC          /+1 TO GET 1ST MISSING
1616 7100      CLL
1617 7006      RTL          /POSITION TO AC 6-8,
1618 7004      RAL
1619 3034      DCA NOFLD      /1ST MISSING
1620 1033      TAD NOSTAK     /# STACKS NOT HERE
1621 7041      CIA
1622 3033      DCA NOSTAK     /USED AS COUNTER
1623 7041
1624 3033

```

1625 1040  
1626 1034  
1627 3262  
1630 1040  
1631 1034  
1632 3307

TAD KCDF /601  
TAD NOFLD /MISSING STACK  
DCA CDF0S  
TAD KCDF  
TAD NOFLD  
DCA CDF1S

/  
/NOW SEE IF AN ODD OR EVEN NUMRER IS MISSING  
/

1633 1033  
1634 7041  
1635 7010  
1636 7620

TAD NOSTAK  
CIA  
RAR  
SNL CLA

/L=1, FIRST READ 0'S, THEN ALWAYS  
/ALL 1'S

1637 5257  
1640 4261  
1641 2033  
1642 5254  
1643 2027  
1644 5650  
1645 1253  
1646 3651  
1647 5650

CNSTK,

JMP POS+3  
JMS ALL0  
ISZ NOSTAK  
JMP POS  
ISZ LOOP  
JMP I XNOM  
TAD TTR  
DCA I XBELL  
JMP I XBELL

/L=0, ALWAYS READ ALL 1'S  
/READ ALL 0 FROM 1ST  
/DONE ALL MISSING IF SKIP  
/READ ALL 1'S FROM HERE ON  
/DONE LOOPING IF SKIP  
/REPEAT

/RESTORE TLS  
/RING BELL

1650 1633  
1651 1561  
1652 1560  
1653 6046

/XNOM, NOMEM+3  
XBELL, BELL+1  
XBELL, BELL  
TTR, TLS  
/

1654 1307  
1655 1046  
1656 3307  
1657 4306  
1660 5241

POS, TAD CDF1S  
TAD K10  
DCA CDF1S  
JMS ALL1  
JMP CNSTK

/DF PLUS 1

/READ ALL 1'S  
/CHECK DONE

```

/
/ROUTINE TO READ ALL 0'S.
/
1661 0000      ALL0, 0
1662 6201      CDF0S, CDF 00      /SET DF TO 1ST MISSING
1663 7240      CLA CMA
1664 3010      DCA 10      /10 AND 11 USED FOR ADDRESS
1665 7040      CMA
1666 3011      DCA 11
1667 3002      DCA 2      /USE AS COUNTER
1670 7040      CMA
1671 3410      DCA I 10      /WRITE 1'S INTO NON-EXIS-
                                /TENT FIELD,
1672 2002      ISZ 2
1673 5270      JMP , -3
1674 1411      TAD I 11      /READ NON-EXIST. FIELD
1675 7650      SNA CLA      /SHOULD = 0000
1676 5301      JMP , +3
1677 1011      TAD 11
1700 7402      E54, HLT      /ERROR, AN EXISTING FIELD
                                /WAS REFERENCED, C(AC)=
                                /ADDRESS REFERENCED
1701 2002      ISZ 2
1702 5274      JMP E54-4      /READ NEXV
/
1703 6201      001E0, CDF 00
1704 6202      CIF 00
1705 5661      JMP I ALL0      /EXIT
/

```



/ROUTINE TO READ ALL 1'S

```

/
1706 0000      ALL1, 0
1707 6201      CDF1S, CDF 00      /SET DF TO MISSING FIELD
1710 7240      CLA CMA
1711 3010      DCA 10      /10 AND 11 USED FOR ADDRESSING
1712 7040      CMA

1713 3011      DCA 11
1714 3002      DCA 2      /USED AS COUNTER
1715 3410      DCA I 10      /WRITE 0'S
1716 2022      ISZ 2
1717 5315      JMP , -2
1720 1411      TAD I 11      /READ 1'S FROM NO MEMORY
1721 7040      CMA
1722 7450      SNA
1723 5327      JMP .+4
1724 7040      CMA
1725 7402      E57, HLT      /7777 NOT READ, C(AC)= DATA
                                /READ, C(11)= ADDRESS,

1726 7200      CLA
1727 2002      ISZ 2
1730 5320      JMP E57-5
1731 6201      CDF 00
1732 6202      CIF 00
1733 5706      JMP I ALL1      /EXIT
/

```

```

1734 0000
1735 7604
1736 0045
1737 7041
1740 3031
1741 5734

/READ SR9-11
/
NSTKS, 0
      LAS
      AND K7
      CIA
      DCA STKS
      JMP I NSTKS
/
/SET TTY FLAG
/
1742 0000
1743 7200
1744 0015
1745 1344
1746 6046
1747 6041
1750 5347
1751 7200
1752 5742

TFLG, 0
      CLA
      AND 15
      TAD ,-1
      TLS
      TSF
      JMP ,-1
      CLA
      JMP I TFLG      /EXIT
/
$

```

THERE ARE NO ERRORS

## SYMBOL TABLE

ALLO	1661
ALLO	1706
REGIN	0200
RELL	1560
COF	6201
COFUS	1662
COFIS	1707
CHOF	1136
CIF	6202
CIF1	0704
CIF2	0727
CIF3	0752
CIF4	1000
CIF5	1023
CIF6	1046
CIF7	1071
CKAC	1226
CNSTK	1641
CSRA	1553
DAT	0032
DCAI	0601
DFLO	0607
DF0	1446
DF0	0202
DF1	0226
DF2	0237
DF3	0254
DF4	0265
DF5	0302
DF6	0313
DF7	0211
D, AUTO	1516
DONE0	1703
ENTER	1200
EXFD	1316
EXFLD	1302
E1	0206
E10	0351
E11	0360
E12	0410
E13	0417
E14	0427
E15	0436
E16	0452
E17	0461
E18	0471
E19	0500
E2	0217
E20	0514
E21	0523
E22	0533
E23	0542
E24	0653

## SYMBOL TABLE

E25	0710
E26	0717
E27	0733
E28	0742
E29	0756
E3	0234
E30	0765
E31	1004
E32	1013
E33	1027
E34	1036
E35	1052
E36	1061
E37	1075
E38	1104
E4	0245
E40	1175
E41	1203
E42	1221
E43	1235
E44	1306
E45	1312
E45A	1420
E46	1522
E47	1525
E48	1530
E49	1533
E5	0262
E50	1536
E51	1541
E52	1544
E53	1547
E54	1700
E57	1725
E6	0273
E7	0310
E8	0321
E9	0341
FILDX	1515
GOTO2	1512
HNTS	2667
I0SF	0656
I02	2334
I01	2343
I02	2422
I03	0421
I04	2444
I05	0463
I06	0506
I07	2525
ISZ0	0021
JMPI2	2222
JMP2	2126

## SYMBOL TABLE

KCDF	0040
KCF1	0042
KCIF	0041
KE42	2236
KE40M	0035
KFLD0	0107
KHIT	0037
KJMP	0103
KNTR	0104
KRTN	0110
KXFLD	0102
K1	0044
K10	0046
K20	0105
K7	0045
K7S	0070
K7000	0050
K7707	0051
K7717	0057
K7727	0056
K7737	0055
K7744	0073
K7747	0054
K7757	0053
K7766	0071
K7767	0052
K7770	0066
K7771	0065
K7772	0064
K7773	0063
K7774	0062
K7775	0061
K7776	0060
K7777	0047
LOOP	0027
MOVE	1463
NDF	0030
NEWDF	1440
NOFLD	0034
NOMEM	1600
NOSTAK	0033
NSTKS	1734
OKF1	0722
OKF2	0745
OKF3	0770
OKF4	1016
OKF5	1041
OKF6	1064
OKF7	1107
OK1	0222
OK2	0250
OK3	0276
OK4	0324

## SYMBOL TABLE

OK5	1362
OK6	0440
OK7	0502
OK8	0544
POINT	0067
PUS	1654
RDF	6214
RIR	6234
RIF	6224
RMF	6244
RTRN	1427
SFT3	1400
STDF	1171
STKS	0031
STRMF	1151
TADI	0622
TAUTO	1432
TFLD	0630
TFLG	1742
TRANS	1321
TRELD	1337
TRMF	1112
TIR	1653
XAUTO	0026
XBELL	1652
XBGV	1565
XELL	1651
XFD	0043
XFIB	0111
XMFM	1566
XNDM	1650
XTRANS	0025
XRMF	0024
XSTKS	0023
XTDF	0100
XTDF1	0101
XTFLG	0022

## SYMBOL TABLE

JMP1	0020
ISZM	0021
XTFLG	0022
XSTKS	0023
XRM	0024
XTRANS	0025
XAHIL	0026
LOOP	0027
NDF	0030
STKS	0031
DAT	0032
NOSTAK	0033
NOFLD	0034
KE40M	0035
KE41	0036
KHLI	0037
KCDF	0040
KCFE	0041
KCF1	0042
XFD	0043
K1	0044
K7	0045
K10	0046
K7777	0047
K7778	0050
K7787	0051
K7767	0052
K7757	0053
K7747	0054
K7737	0055
K7727	0056
K7717	0057
K7776	0060
K7775	0061
K7774	0062
K7773	0063
K7772	0064
K7771	0065
K7770	0066
POINT	0067
K7S	0070
K7766	0071
K7744	0073
XTDF	0100
XTDF1	0101
KXFLD	0102
KJMP	0103
KNTR	0104
K20	0105
JMP2	0106
KFLD0	0107
KRTN	0110
XFIS	0111

## SYMBOL TABLE

REGIA	0200
DF0	0202
F1	0206
DF7	0211
E2	0217
OK1	0222
DF1	0226
F3	0234
DF2	0237
E4	0245
OK2	0250
DF3	0254
E5	0262
DF4	0265
E6	0273
OK3	0276
DF5	0302
E7	0310
DF6	0313
E8	0321
OK4	0324
IB0	0334
E9	0341
IB1	0343
F10	0351
E11	0360
OK5	0362
IB2	0402
E12	0410
E13	0417
IB3	0421
E14	0427
E15	0436
OK6	0440
IB4	0444
E16	0452
E17	0461
IB5	0463
E18	0471
E19	0500
OK7	0502
IB6	0506
E20	0514
E21	0523
IB7	0525
E22	0533
E23	0542
OK8	0544
DCAI	0601
DFLD	0607
TADI	0622
TFLD	0630
E24	0653



## SYMBOL TABLE

IBSF	0656
HLTS	0667
CIF1	0704
E25	0710
E26	0717
OKF1	0722
CIF2	0727
E27	0733
E28	0742
OKF2	0745
CIF3	0752
E29	0756
E30	0765
OKF3	0770
CIF4	1000
E31	1004
E32	1013
OKF4	1016
CIF5	1023
E33	1027
E34	1036
OKF5	1041
CIF6	1046
E35	1052
E36	1061
OKF6	1064
CIF7	1071
E37	1075
E38	1104
OKF7	1107
TRMF	1112
CHDF	1136
STRMF	1151
STDF	1171
E40	1175
ENTER	1200
E41	1203
E42	1221
CKPC	1226
E43	1235
EXFLD	1302
E44	1306
E45	1312
EXFD	1316
TRANS	1321
TRFLD	1337
SFIB	1400
E45A	1420
RTRN	1427
TAUTO	1432
NEWDF	1440
DFN	1446
MOVE	1463

## SYMBOL TABLE

GOTO	1510
FILDX	1515
DOAUTO	1516
E46	1522
E47	1525
E48	1530
E49	1533
E50	1536
E51	1541
E52	1544
E53	1547
OSP8	1553
RELL	1560
XBCN	1565
XMFM	1566
NOMEM	1600
CNSTK	1641
XNOM	1650
XELL	1651
XBELL	1652
TTR	1653
POS	1654
ALL0	1661
CDFMS	1662
E54	1700
DONE0	1703
ALL1	1706
CDF1S	1707
E57	1725
NSTKS	1734
TFLG	1742
CDF	6201
CIF	6202
RDF	6214
RIF	6224
RIR	6234
RMF	6244