

DH11

DH11 SINGLE LINE DATA  
CZDHFC0

AH-FG25C-MC

1 OF 1 OCT 1985

COPYRIGHT© 1972-85

digital

MADE IN USA



.REM !

IDENTIFICATION  
-----

PRODUCT CODE: AC-8464C-MC  
PRODUCT NAME: CZDHFCO DH11 SINGLE LINE DATA TEST  
DATE: JUNE 1985  
MAINTAINER: NAC SOFTWARE ENGINEERING  
AUTHOR: MICHAEL DAVIS

THE INFORMATION IN THIS DOCUMENT IS SUBJECT TO CHANGE WITHOUT  
NOTICE AND SHOULD NOT BE CONSTRUED AS A COMMITMENT BY DIGITAL  
EQUIPMENT CORPORATION. DIGITAL EQUIPMENT CORPORATION ASSUMES  
NO RESPONSIBILITY FOR ANY ERRORS THAT MAY APPEAR IN THIS  
DOCUMENT.

NO RESPONSIBILITY FOR THE USE OR RELIABILITY OF SOFTWARE ON  
EQUIPMENT THAT IS NOT SUPPLIED BY DIGITAL OR ITS AFFILIATED  
COMPANIES

COPYRIGHT (C) 1985 BY DIGITAL EQUIPMENT CORPORATION

1  
2  
3  
4  
5  
6  
7  
8  
9  
10  
11  
12  
13  
14  
15  
16  
17  
18  
19  
20  
21  
22  
23  
24  
25  
26  
27  
28  
29  
30  
31  
32  
33  
34  
35  
36  
37  
38  
39  
40  
41  
42  
43  
44  
45

1  
2  
3  
4  
5  
6  
7  
8

1. ABSTRACT

THE DM11 SINGLE LINE DATA TEST VERIFIES THAT ALL  
CHARACTERS (0-377), EACH LINE CAN TRANSMIT AND RECEIVE  
AT ALL SPEEDS (8 BITS PER CHARACTER) AND ALL CHARACTER  
LENGTHS (AT A SPEED OF 9600 BAUD).

1  
2  
3  
4  
5  
6  
7  
8  
9  
10  
11  
12  
13  
14  
15  
16  
17  
18  
19  
20  
21  
22  
23  
24  
25  
26  
27  
28  
29  
30  
31  
32  
33  
34  
35  
36  
37  
38  
39  
40  
41  
42  
43  
44  
45  
46  
47  
48  
49  
50  
51  
52  
53  
54  
55

## 2. REQUIREMENTS

### 2.1 EQUIPMENT

PDP-11 FAMILY STANDARD COMPUTER WITH 4KW OF MEMORY  
ASR-33 TELETYPE OR EQUIVALENT  
DH11 ASYNCHRONOUS MULTIPLEXER  
DM11 MAINTENANCE CARD INSTALLED

### 2.2 STORAGE

THE PROGRAM LOADS INTO 4KW OF MEMORY

## 3. LOADING PROCEDURE

THE STANDART PROCEDURE FOR LOADING ABSOLUTE BINARY TAPES  
IS TO BE USED

## 4. STARTING PROCEDURE

### 4.1 CONTROL SWITCH SETTINGS

#### 4.1.1 AFTER PROGRAM LOAD (INITIAL PROGRAM START)

ALL CONSOLE SWITCHES DOWN

#### 4.1.2 TO MODIFY DEVICE VECTOR AND CONTROL REGISTER ADDRESSES AFTER PROGRAM RESTART

SW00=1

#### 4.1.3 TO START PROGRAM AT SELECTED TEST AFTER PROGRAM RESTART

SW01=1

### 4.2 STARTING ADDRESS

THE STARTING ADDRESS FOR ALL TESTS IS 000200

THE RESTART ADDRESS FOR ALL TESTS I 0002000

THE STARTING ADDRESS TO ENTER A SELECTED TEST IS 000200

### 4.3 PROGRAM AND/OR OPERATOR ACTION

#### 4.3.1 INITIAL PROGRAM START

##### 4.3.1.1 LOAD PROGRAM INTO MEMORY

##### 4.3.1.2 LOAD ADDRESS 000200

##### 4.3.1.3 CLEAR CONSOLE SWITCHES

##### 4.3.1.4 PRESS START

##### 4.3.1.5 THE PROGRAM WILL TYPE "DH11 SINGLE LINE DATA TEST" AND WILL THEN TYPE "VECTOR ADDRESS-" AND WAIT FOR AN INPUT FROM THE TELETYPE KEYBOARD.

## 4.3 (CONT'D)

4.3.1.6 TYPE IN THE ADDRESS OF THE RECEIVER INTERRUPT VECTOR  
FOR THE DH11 TO BE TESTED FOLLOWED BY <CARRIAGE RETURN>

NOTE: WORDS IN ANGLE BRACKETS, I.E. <CARRIAGE RETURN> MEAN THAT  
THE TELETYPE KEY WITH THE NAMED FUNCTION SHOULD BE STRUCK

IF AN INCORRECT ADDRESS IS ENTERED, THE PROGRAM  
WILL TYPE "?" AND WILL REPEAT THE SECOND MESSAGE OF 4.3.1.5  
4.3.1.7 THE PROGRAM WILL TYPE "CONTROL REGISTER ADDRESS-"  
AND WAIT FOR AN INPUT FROM THE TELETYPE KEYBOARD

4.3.1.8 TYPE IN THE ADDRESS OF THE SYSTEM CONTROL REGISTER OF THE  
DH11 TO BE TESTED FOLLOWED BY <CARRIAGE RETURN>

IF AN INCORRECT ADDRESS IS TYPED, THE PROGRAM WILL TYPE  
"?" AND WILL THEN REPEAT THE MESSAGE OF 4.3.1.7  
4.3.1.9 THE PROGRAM WILL TYPE "R" TO INDICATE THAT IT IS  
ABOUT TO START TESTING, AND THEN TESTING WILL BEGIN

## 4.3.2 PROGRAM RESTART WITH ALL SWITCHES DOWN

4.3.2.1 PERFORM 4.3.1.2 TO 4.3.1.5  
4.3.2.2 THE PROGRAM WILL TYPE 'DH11 SINGLE LINE DATA TEST'  
AND WILL THEN CONTINUE AS DESCRIBED IN 4.3.1.9

## 4.3.3 PROGRAM RESTART WITH SW00=1

4.3.3.1 LOAD ADDRESS 000200  
4.3.3.2 SET SW01=1  
4.3.3.3 PRESS START  
4.3.3.4 THE PROGRAM WILL PERFORM AS DESCRIBED IN 4.3.1.5 TO 4.3.1.9

## 4.3.4 PROGRAM RESTART WITH SW01=1

4.3.4.1 LOAD ADDRESS 000200  
4.3.4.2 SET SW01=1  
4.3.4.3 PRESS START  
4.3.4.4 THE PROGRAM WILL TYPE "DH11 SINGLE LINE DATA TEST"  
AND WILL THEN TYPE "TEST PC-" AND WILL WAIT FOR AN INPUT  
FROM THE TELETYPE KEYBOARD  
4.3.4.5 TYPE IN THE ADDRESS OF THE TEST AT WHICH THE PROGRAM IS TO  
BE STARTED FOLLOWED BY <CARRIAGE RETURN>  
4.3.4.6 THE PROGRAM WILL TYPE R TO INDICATE THAT IT HAS STARTED  
AND WILL START TESTING AT THE SELECTED TEST.

NOTE: CARE MUST BE TAKEN WHEN THIS FEATURE IS USED, SINCE  
THERE IS NO PROTECTION AGAINST SELECTING AN ADDRESS THAT  
IS IN THE MIDDLE OF A TEST

NOTE: IF IT IS DESIRED TO LOOP ON THE TEST THAT IS SELECTED  
SET SW14=1 BEFORE ENTERING THE TEST ADDRESS

## 5. OPERATING PROCEDURE

## 5.1 OPERATIONAL SWITCH SETTINGS

SW15=1, HALT ON ERROR  
SW14=1, LOOP ON CURRENT TEST  
SW13=1, SUPPRESS ERROR TYPEOUT  
SW11=1, INHIBIT ITERATIONS  
SW10=1, ESCAPE TO NEXT TEST ON ERROR  
SW09=1, FREEZE VARIABLE PARAMETER IN CURRENT TEST  
SW01=1, START PROGRAM AT SELECTED TEST  
SW00=1, CHANGE PARAMETERS AT PROGRAM RESTART

## 5.2 SUBROUTINE ABSTRACTS

## 5.2.1 TRAPCATCHER (LOCATIONS 000000-000776)

THIS ROUTINE IS USED TO INTERCEPT UNEXPECTED INTERRUPTS  
AND TRAPS. THE AREA FROM 000000-000776 IS LOADED  
WITH THE FOLLOWING SEQUENCE

2  
0  
4  
0  
...  
772  
0  
776  
0

IF AN UNEXPECTED INTERRUPT OR TRAP OCCURS, THE PROGRAM  
WILL HALT WITH THE PC 2 GREATER THAN THE ADDRESS TO  
WHICH THE PROGRAM TRAPPED. THE PROCESSOR STACK MAY  
BE EXAMINED TO DETERMINE WHERE THE PROGRAM WAS WHEN THE  
TRAP OR INTERRUPT OCCURED.

## 5.2.2 START (PROGRAM INITIALIZATION)

THIS ROUTINE INITIALIZES ALL PROGRAM FLAGS AND COUNTERS,  
TYPES THE PROGRAM TITLE MESSAGE, AND INPUTS THE VECTOR  
AND CONTROL REGISTER ADDRESSES OF THE DH11 TO BE TESTED.

## 5.2.3 BEGIN (PROGRAM START AND RESTART)

THIS ROUTINE IS ENTERED IMMEDIATELY AFTER "START"  
AND EACH TIME A PROGRAM PASS HAS BEEN COMPLETED.  
THE ROUTINE SETS UP THE PROCESSOR STACK AND STATUS WORD  
AND THEN TRANSFERS CONTROL TO THE TEST AT WHICH  
TESTING WILL BEGIN. IF SW01=0 WHEN THIS ROUTINE IS ENTERED  
TESTING WILL START AT T1 (TEST 1). IF SW01=1 WHEN  
THIS ROUTINE IS ENTERED, TESTING WILL START AT THE PC  
ENTERED FROM THE TELETYPE KEYBOARD.

## 5.2.4 EOP (END OF PASS)

THIS ROUTINE IS ENTERED ONCE PER PASS AFTER ALL TESTS HAVE BEEN COMPLETED. THIS ROUTINE TYPES THE MAINDEC IDENTIFICATION CODE OF THE PROGRAM, CLEARS ERROR FLAGS AND UPDATES THE PASS COUNT. IF THE PROGRAM WAS LOADED UNDER ACT11 OR DDP, THE ROUTINE CHECKS FOR RETURN TO THE ACT11 OR DDP MONITOR. IF THE PROGRAM IS NOT UNDER MONITOR CONTROL, THE ROUTINE TRANSFERS TO BEGIN.

## 5.2.5 SCOPER (SCOPE LOOP AND ITERATION HANDLER)

THIS ROUTINE IS ENTERED EACH TIME A TEST IS COMPLETED. THE ROUTINE CHECKS FOR THE FOLLOWING UPON ENTRY  
A) IF SW10=1, THE ROUTINE WILL TRANSFER TO THE NEXT TEST IN SEQUENCE, AFTER CLEARING ERROR FLAGS.  
B) IF SW11=1, THE ROUTINE WILL TRANSFER TO THE NEXT TEST IN SEQUENCE, AFTER CLEARING ERROR FLAGS.  
C) IF SW14=1, THE ROUTINE WILL LOOP ON THE CURRENT TEST REGARDLESS OF THE ITERATION COUNT.

IF NONE OF THE ABOVE IS TRUE, THE ROUTINE WILL ADD 1 TO THE COUNT OF TEST ITERATIONS, AND COMPARE THIS VALUE TO THE NUMBER OF ITERATIONS THAT SHOULD BE PERFORMED. IF THESE NUMBERS ARE EQUAL, THE ROUTINE WILL TRANSFER TO THE NEXT TEST IN SEQUENCE. IF THE NUMBERS ARE NOT EQUAL, THE TEST CURRENTLY IN PROGRESS WILL BE REPEATED.

## 5.2.6 SCOP1R (FREEZE ON CURRENT DATA)

THE CALL TO THIS ROUTINE FOLLOWS IMMEDIATELY AFTER THE CALL TO THE ERROR HANDLER IN THOSE TESTS THAT HAVE VARIABLE PARAMETERS. THIS ROUTINE IS ALWAYS ENTERED IN THOSE TESTS, WHETHER OR NOT AN ERROR OCCURS. IF SW09=1, THE ROUTINE WILL TRANSFER CONTROL BACK TO THE TEST AT A POINT WHICH WILL ALLOW REPEATING THE FUNCTION UNDER TEST CONTINUOUSLY WITH THE SAME DATA. IF THIS OPTION IS SELECTED, THE ROUTINE "SCOPER" IS NEVER ENTERED AND ITERATION COUNTS WILL NOT BE UPDATED.

## 5.2.7 ERRORS (ERROR HANDLER)

THIS ROUTINE IS ENTERED UPON ERROR DETECTION ONLY.  
WITH ALL CONSOLE SWITCHES DOWN, THE ROUTINE PROCEEDS AS FOLLOWS:

- A) THE PC OF THE INSTRUCTION THAT CALLED THE ERROR HANDLER IS ACCESSED THRU THE STACK, AND THEN THE EMT INSTRUCTION ITSELF IS FETCHED. THE 8 LSB OF THE EMT INSTRUCTION ARE THE ERROR CODE. THIS CODE IS USED TO ACCESS A TABLE OF ERROR MESSAGES AND ERROR DATA STORAGE LOCATIONS.
- B) IF THE TEST THAT FAILED DID NOT FAIL PREVIOUSLY DURING THIS PASS, A COMPLETE ERROR REPORT IS MADE IF THE TEST THAT FAILED FAILED MOR THAT ONCE DURING THE CURRENT PASS, ONLY THE DATA RELATING TO THE FAILUER IS TYPED. IF SW13=1, NO ERROR TYPEOUT IS MADE.
- C) THE ROUTINE NOW CHECKS FOR HALT ON ERROR. IF SW15=1 THE PROGRAM WILL HALT WITH THE PC OF THE CALL TO THE ERROR ROUTINE IN R0. IF SW15=0, THE PROGRAM WILL NOT HALT, BUT WILL CHECK FOR ESCAPE TO NEXT TEST.
- D) IF SW10=0, THE ROUTINE WILL RETURN TO THE TEST IN PROGRESS. IF SW10=1, THE ROUTINE WILL ABORT THE CURRENT TEST, AND TRANSFER TO THE NEXT TEST IN SEQUENCE, THRU THE ROUTINE "SCOPER".

## 5.2.8 TRPSRV (TRAP DECODE AND DISPATCH)

THIS ROUTINE DECODES THE 8 LSB OF THE TRAP INSTRUCTION THAT CAUSED TH PROGRAM INTERRUPT, AND TRANSFERS CONTROL TO THE ROUTINE THRU THE TABLE "TRPTAB" USING THE 8 LSB OF THE TRAP INSTRUCTION AS AN OFFSET TO THE POINTER TO THE ROUTINE TO BE ENTERED.



- 1  
2  
3  
4  
5  
6  
7  
8  
9  
10  
11  
12  
13  
14  
15  
16  
17  
18  
19  
20  
21  
22  
23  
24  
25  
26  
27  
28  
29  
30  
31  
32  
33  
34  
35  
36  
37  
38  
39  
40  
41  
42  
43  
44  
45  
46  
47  
48  
49  
50  
51  
52  
53  
54  
55
- 5.3 PROGRAM AND OR OPERATOR ACTION
  - 5.3.1 PROGRAM START WITH ALL SWITCHES DOWN
    - 5.3.1.1 REFER TO SECTIONS 4.3.1 AND 4.3.2 FOR INITIAL PROGRAM BEHAVIOR.
    - 5.3.1.2 AFTER "R" HAS BEEN TYPED BY THE PROGRAM, TEST EXECUTION WILL BEGIN. EACH TEST WILL BE REPEATED A SELECTED NUMBER OF ITERATIONS (SEE LISTING FOR EXACT NUMBER FOR EACH TEST) AND THEN THE PROGRAM WILL PROCEED TO THE NEXT TEST.
    - 5.3.1.3 WHEN ALL ITERATIONS HAVE BEEN COMPLETED, THE PROGRAM WILL TYPE "CZDHF-C" AND THEN RESTART TESTING AT TEST 1 (LOCATION T1 IN THE PROGRAM).
    - 5.3.1.4 IF AN ERROR OCCURS, THE PROGRAM WILL TYPE AN APPROPRIATE ERROR MESSAGE, AND THEN CONTINUE THE TEST IN PROGRESS.
  - 5.3.2 PROGRAM START WITH SW00=1
    - THE PROGRAM WILL PERFORM AS DESCRIBED IN 4.3.1 AND 5.3.1
  - 5.3.3 PROGRAM START WITH SW01=1
    - 5.3.3.1 REFER TO SECTION 4.3.4 FOR INITIAL PROGRAM BEHAVIOR
    - 5.3.3.2 TEST EXECUTION WILL START AT THE ADDRESS SPECIFIED AND WILL CONTINUE AS DESCRIBED IN 5.3.1.2
    - 5.3.3.3 AFTER "CZDHF-C" HAS BEEN TYPED, THE PROGRAM WILL RESUME TESTING AT TEST 1
  - 5.3.4 PROGRAM OPERATION WITH SW15=1
    - SAME AS 5.3.1, EXCEPT THAT IN THE CASE OF AN ERROR, THE PROGRAM WILL HALT AFTER THE ERROR TYPEOUT, AND THE PC+2 OF THE CALL TO THE ERROR ROUTINE WILL BE DISPLAYED IN R0.
  - 5.3.5 PROGRAM OPERATION WITH SW13=1
    - SAME AS 5.3.1 EXCEPT THAT NO ERROR TYPEOUTS WILL OCCUR
  - 5.3.6 PROGRAM OPERATION WITH SW11=1
    - SAME AS 5.3.1 EXCEPT THAT EACH TEST WILL BE REPEATED ONCE ONLY
  - 5.3.7 PROGRAM OPERATION WITH SW10=1
    - SAME AS 5.3.1, EXCEPT THAT IN THE CASE OF AN ERROR THE CURRENT TEST WILL BE ABORTED, AND THE PROGRAM WILL PROCEED TO THE NEXT TEST IN SEQUENCE.

## 5. (CONT'D)

## 5.3.8 PROGRAM OPERATION WITH SW14=1, OR SW09=1

THESE FUNCTIONS ARE NORMALLY USED FOR TROUBLE SHOOTING.  
SEE SECTION 6.3 FOR THEIR USE.

## 6. ERRORS

## 6.1 ERROR HALTS

THE ERROR MESSAGE FORMAT FOR ALL ERROR TYPEOUTS  
IS AS FOLLOWS

PC+2 MESSAGE  
HEADER (IF APPLICABLE)  
DATA (IF APPLICABLE)

WHERE

PC+2 IS THE ADDRESS OF THE CALL TO THE ERROR HANDLER + 2  
MESSAGE IS AN ASCII MESSAGE DESCRIBING (BRIEFLY) THE FAILURE  
HEADER IS A DESCRIPTION OF THE DATA TO FOLLOW  
DATA IS OCTAL INFORMATION RELATING TO THE CAUSE OF THE FAILURE  
IF THE SAME ERROR OCCURS IN A GIVEN TEST ON THE SAME  
PASS, AND IF DATA IS ASSOCIATED WITH THAT ERROR, ONLY  
DATA IS TYPE ON SUCCEEDING ERROR TYPEOUTS

IF NO DATA IS ASSOCIATED WITH THE ERROR  
THE COMPLETE ERROR MESSAGE IS TYPED.

## 6.1.1 ERROR DESCRIPTIONS

SEE LISTING FOR DETAILS OF ERRORS

## 6.2 ERROR RECOVERY

## 6.2.1 SW15=0

IF THE PROGRAM IS RUN WITH SW15=0, NO OPERATOR ACTION IS  
REQUIRED TO CONTINUE TESTING

## 6.2.2 SW15=1

IF THE PROGRAM IS RUN WITH SW15=1, TO CONTINUE TESTING  
AFTER THE PROGRAM HAS HALTED, PRESS THE PROCESSOR  
CONSOLE CONTINUE SWITCH

## 6.2.3 ILLEGAL INTERRUPTS

IF AN INTERRUPT OCCURS TO A VECTOR ADDRESS NOT  
SELECTED DURING PROGRAM INITIALIZATION, THE PROGRAM WILL  
HALT IN THE TRAPCATCHER. THE ADDRESS AT WHICH  
THE PROGRAM HALTS IS 2 GREATER THAN THE ADDRESS  
TO WHICH THE INTERRUPT OCCURED. THE PROGRAM MUST BE  
RESTARTED AT 200 TO RECOVER FROM THIS ERROR.

## 6.3 SCOPE LOOPING

6.3.1 TO SCOPE ON A SPECIFIC TEST, SET SW14=1 AND SW13=1  
THIS WILL CAUSE THE PROGRAM TO CONTINUOUSLY LOOP ON THE  
SAME TEST, AND WILL CAUSE ALL ERROR TYPEOUTS TO BE INHIBITED

6.3.2 TO SCOPE ON A SPECIFIC VALUE OF A PARAMETER WITHIN  
A TEST, SET SW09=1 TO FREEZE THE DATA  
(SEE LISTING FOR THOSE TESTS THAT INCORPORATE THIS FEATURE)

## 6. (CONT'D)

## 6.3.3 PROGRAM START TO SCOPE LOOP ON SELECTED TEST

PERFORM SECTION 4.3.4 WITH SW14=1

## 7. RESTRICTIONS

## 7.1 STARTING

THE DH11 TEST CARD MUST BE INSTALLED

## 7.2 RUNNING

NONE

## 8. MISCELLANEOUS

## 8.1 EXECUTION TIME

THE TIME FOR ONE PASS OF THE PROGRAM (END OF  
TYPEOUT OF CZDHF-C TO END OF TYPEOUT OF CZDHF-C)  
IS GIVEN FOR VARIOUS PROCESSORS IN THE TABLE BELOW

TIME	
PROCESSOR	
PDP-11/05.10	
PDP-11/20	
PDP-11/40	
PDP-11/45	

## 9. PROGRAM DESCRIPTION

THE FIRST GROUP OF TESTS TRANSMITS ALL CHARACTERS (0-377) ONE AT A TIME AT A LINE SPEED OF 9600 BAUD AND A CHARACTER LENGTH OF 8 BITS. EACH LINE IS CHECKED IN AN INDIVIDUAL LOOP. EACH TEST IN THIS GROUP CAN BE SET UP UNDER PROGRAM CONTROL TO LOOP ON A SINGLE CHARACTER USING THE FREEZE ON DATA (SW09) OPTION.

THE NEXT GROUP OF TESTS VERIFIES THAT ALL CHARACTERS CAN BE TRANSMITTED AT EACH STANDARD SPEED (50-9600 BAUD) AT 8 BITS PER CHARACTER. EACH LINE IS TESTED IN AN INDIVIDUAL TEST LOOP, AND A PARTICULAR SPEED CAN BE CHOSEN FOR SCOPING BY USING THE FREEZE ON DATA OPTION.

THE FINAL GROUP OF TESTS TRANSMITS ALL CHARACTERS AT EACH CHARACTER LENGTH (5-8 BITS) AT 9600 BAUD ON A SINGLE LINE. EACH LINE IS TESTED IN AN INDIVIDUAL TEST LOOP AND A PARTICULAR CHARACTER LENGTH CAN BE CHOSEN FOR SCOPING USING THE FREEZE ON DATA (SW09) OPTION.

## 10. LISTING

!

1 ; DHMAC-A - DH11 MACRO LIBRARY  
2 ; COPYRIGHT 1985, DIGITAL EQUIPMENT CORP., MAYNARD, MASS. 01754  
3  
4

5 .LIST ME  
6 .NLIST MC,MD,CND  
7

; 3

712 ; CMS REPLACEMENT HISTORY  
713  
714  
715

716 ; \*9 SKONETSKI 26 APR-1985 16:23:08 "FIXED TYPO CAUSING ASSEMBLY ERRORS"  
717 ; \*8 SKONETSKI 22-APR-1985 16:48:03 "TYPO ERROR IN VECTOR CHANGE CODE SOURCE FIXED"  
718 ; \*7 SKONETSKI 22-APR 1985 16:26:04 "ADDED CODE TO SET VECTORS FOR PWR FAIL, ERRORS, AND EMT

719 ; \*6 SKONETSKI 22-APR-1985 14:22:35 "FIXED BRANCH ERROR IN END OF PASS ROUTINE"  
720 ; \*5 SKONETSKI 22-APR-1985 08:28:54 "FIXED BUG (AN OCTASC MACRO CALL WAS WRONG) AND ADDED A

721 ; \*4 SKONETSKI 18-APR-1985 14:20:15 "ADDED SOFTWARE SWITCH REG SUPPORT, BUT UNTESTED"  
722 ; \*3 SKONETSKI 12-APR-1985 10:34:52 "FIXED PROBLEMS WITH SPURIOUS CR/LFS"  
723 ; \*2 SKONETSKI 11-APR-1985 16:00:24 "ADDED MACRO FROM SYSMAC.SHL THAT SIZES FOR SOFTWARE SWI

724 ; \*1 SKONETSKI 11-APR-1985 15:49:05 "LIBRARY FOR DH11 DIAGNOSTICS"

104  
119  
131  
148  
158  
167  
303  
339  
373  
520  
563  
595  
607  
652  
664  
691  
712  
743  
744  
745  
746  
747  
748  
TRAPS."  
749  
750  
CLEAN END OF PASS  
MESSAGE.

751  
752  
753  
TCH REGISTER  
754



2  
3  
5 000000

.LIST ME  
.NLIST MC,MD,CND  
.HEADER +/1972, 1976, 1985/,+/DH11 SINGLE LINE DATA TEST/,+/CZDHF-CO/

;STARTING PROCEDURE  
;LOAD PROGRAM  
;LOAD ADDRESS 000200  
;PRESS START  
;PROGRAM WILL TYPE DH11 SINGLE LINE DATA TEST  
;PROGRAM WILL TYPE "VECTOR ADDRESS-"  
;TYPE IN THE ADDRESS OF THE RECEIVER INTERRUPT VECTOR  
;FOR THE DH11 TO BE TESTED, FOLLOWED BY <CARRIAGE RETURN>  
;PROGRAM WILL TYPE "CONTROL REGISTER ADDRESS-"  
;TYPE IN THE ADDRESS OF THE SYSTEM CONTROL REGISTER  
;FOR THE DH11 TO BE TESTED, FOLLOWED BY <CARRIAGE RETURN> ; 3  
;PROGRAM WILL TYPE "R" TO INDICATE THAT TESTING HAS STARTED  
;AT THE END OF A PASS, PROGRAM WILL TYPE " CZDHF-CO "  
;AND THEN RESUM TESTING

000000

.TITLE CZDHF-CO  
.ENABLE ABS  
.NLIST MC,MD,CND  
.LIST ME  
.SYMBOLS

6 000000

;SWITCH REGISTER OPTIONS

100000	SW15=100000	;=1,HALT ON ERROR	
040000	SW14=40000	;=1,LOOP ON CURRENT TEST	
020000	SW13=20000	;=1,INHIBIT ERROR TYPEOUT	
010000	SW12=10000		
004000	SW11=4000	;=1,INHIBIT ITERATIONS	
002000	SW10=2000	;=1,ESCAPE TO NEXT TEST ON ERROR	; 3
001000	SW09=1000	;=1,LOOP WITH CURRENT DATA	
000400	SW08=400		
000100	SW06=100		
000040	SW05=40		
000020	SW04=20		
000010	SW03=10		
000004	SW02=4		
000002	SW01=2	;RESTART PROGRAM AT SELECTED TEST	
000001	SW00=1	;RESELECT VECTOR AND CONTROL REGISTER	
		;ADDRESS AFTER PROGRAM RESTART	

0

## ;REGISTER DEFINITIONS

000000	R0=%0	;GENERAL REGISTER
000001	R1=%1	;GENERAL REGISTER
000002	R2=%2	;GENERAL REGISTER
000003	R3=%3	;GENERAL REGISTER
000004	R4=%4	;GENERAL REGISTER
000005	R5=%5	;GENERAL REGISTER
000006	SP=%6	;PROCESSOR STACK POINTER
000007	PC=%7	;PROGRAM COUNTER

## ;LOCATION EQUIVALENCIES

	;SWR=177570	;CONSOLE SWITCH REGISTER	; 3
	;LIGHTS=177570	;PDP-11/45 DISPLAY REGISTER	; 4
177776	PS=177776	;PROCESSOR STATUS WORD	; 4
020164	STACK=ENDCOD+200	;START OF PROCESSOR STACK	; 3

## ;INSTRUCTION DEFINITIONS

005746	PUSH1SP=5746	;DECREMENT PROCESSOR STACK 1 WORD
005726	POP1SP=5726	;INCREMENT PROCESSOR STACK 1 WORD
010046	PUSHR0=10046	;SAVE R0 ON STACK
012600	POP R0=12600	;RESTORE R0 FROM STACK
024646	PUSH2SP=24646	;DECREMENT STACK TWICE
022626	POP2SP=22626	;INCREMENT STACK TWICE

```

;
.MACRO HLT      $A
          EMT    $A
.ENDM HLT
;
;

```

100000	BIT15=100000	
040000	BIT14=40000	; 3
020000	BIT13=20000	
010000	BIT12=10000	
004000	BIT11=4000	
002000	BIT10=2000	
001000	BIT09=1000	
000400	BIT08=400	
000200	BIT07=200	
000100	BIT06=100	
000040	BIT05=40	
000020	BIT04=20	
000010	BIT03=10	
000004	BIT02=4	
000002	BIT01=2	
000001	BIT00=1	
1 000000	.CATCH	



000146	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000150	000152	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000152	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000154	000156	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000156	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000160	000162	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000162	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000164	000166	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000166	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000170	000172	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000172	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000174	000176	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000176	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000200	000202	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000202	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000204	000206	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000206	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000210	000212	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000212	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000214	000216	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000216	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000220	000222	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000222	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000224	000226	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000226	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000230	000232	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000232	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000234	000236	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000236	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000240	000242	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000242	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000244	000246	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000246	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000250	000252	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000252	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000254	000256	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000256	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000260	000262	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000262	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000264	000266	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000266	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000270	000272	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000272	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000274	000276	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000276	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000300	000302	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000302	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000304	000306	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000306	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000310	000312	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000312	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000314	000316	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000316	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000320	000322	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000322	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000324	000326	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000326	000000	HALT	;EXAMINE STACK TO FIND CAUSE

000330	000332	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000332	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000334	000336	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000336	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000340	000342	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000342	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000344	000346	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000346	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000350	000352	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000352	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000354	000356	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000356	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000360	000362	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000362	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000364	000366	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000366	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000370	000372	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000372	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000374	000376	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000376	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000400	000402	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000402	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000404	000406	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000406	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000410	000412	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000412	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000414	000416	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000416	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000420	000422	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000422	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000424	000426	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000426	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000430	000432	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000432	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000434	000436	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000436	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000440	000442	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000442	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000444	000446	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000446	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000450	000452	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000452	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000454	000456	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000456	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000460	000462	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000462	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000464	000466	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000466	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000470	000472	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000472	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000474	000476	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000476	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000500	000502	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000502	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000504	000506	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000506	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000510	000512	.+2	;UNEXPECTED TRAP TO THIS LOCATION



000512	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000514	000516	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000516	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000520	000522	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000522	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000524	000526	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000526	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000530	000532	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000532	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000534	000536	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000536	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000540	000542	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000542	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000544	000546	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000546	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000550	000552	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000552	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000554	000556	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000556	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000560	000562	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000562	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000564	000566	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000566	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000570	000572	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000572	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000574	000576	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000576	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000600	000602	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000602	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000604	000606	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000606	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000610	000612	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000612	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000614	000616	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000616	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000620	000622	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000622	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000624	000626	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000626	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000630	000632	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000632	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000634	000636	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000636	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000640	000642	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000642	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000644	000646	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000646	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000650	000652	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000652	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000654	000656	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000656	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000660	000662	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000662	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000664	000666	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000666	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000670	000672	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000672	000000	HALT	;EXAMINE STACK TO FIND CAUSE

000674	000676	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000676	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000700	000702	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000702	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000704	000706	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000706	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000710	000712	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000712	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000714	000716	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000716	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000720	000722	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000722	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000724	000726	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000726	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000730	000732	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000732	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000734	000736	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000736	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000740	000742	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000742	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000744	000746	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000746	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000750	000752	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000752	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000754	000756	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000756	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000760	000762	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000762	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000764	000766	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000766	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000770	000772	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000772	000000	HALT	;EXAMINE STACK TO FIND CAUSE
000774	000776	.+2	;UNEXPECTED TRAP TO THIS LOCATION
000776	000000	HALT	;EXAMINE STACK TO FIND CAUSE
1 001000		.SETVEC	

```

0          000200          . =200      ;STANDARD INTERRUPT VECTORS
000200 000167 000600      JMP      START          ;GO TO START OF PROGRAM

1 000204          .TRPDEF

          ;DEFINITIONS FOR TRAP SUBROUTINE CALLS
          ;POINTERS TO SUBROUTINES CAN BE FOUND STARTING
          ;AT LOCATION "TRPTAB"

000204          TRPDEF  SCOPE,+/SCOPE LOOP AND ITERATION HANDLER/
          104400          SCOPE=TRAP+Y          ;SCOPE LOOP AND ITERATION HANDLER
          000001          Y=Y+1

000204          TRPDEF  TYPE,+/TELETYPE OUTPUT ROUTINE/
          104401          TYPE=TRAP+Y          ;TELETYPE OUTPUT ROUTINE
          000002          Y=Y+1

000204          TRPDEF  OCTASC,+/OCTAL TO ASCII CONVERSION/
          104402          OCTASC=TRAP+Y          ;OCTAL TO ASCII CONVERSION
          000003          Y=Y+1

000204          TRPDEF  INSTR,+/INPUT ASCII STRING/
          104403          INSTR=TRAP+Y          ;INPUT ASCII STRING
          000004          Y=Y+1

000204          TRPDEF  INSTER,+/STRING INPUT ERROR/
          104404          INSTER=TRAP+Y          ;STRING INPUT ERROR
          000005          Y=Y+1

000204          TRPDEF  PARAM,+/CONVERT STRING TO OCTAL, CHECK LIMITS/
          104405          PARAM=TRAP+Y          ;CONVERT STRING TO OCTAL, CHECK LIMITS
          000006          Y=Y+1

000204          TRPDEF  SAVOSP,+/SAVE R0-R5, PC/
          104406          SAVOSP=TRAP+Y          ;SAVE R0-R5, PC
          000007          Y=Y+1

000204          TRPDEF  RESO5,+/RESTORE R0-R5/
          104407          RESO5=TRAP+Y          ;RESTORE R0-R5
          000010          Y=Y+1

000204          TRPDEF  SCOPE1,+/CHECK FOR FREEZE ON CURRENT DATA/
          104410          SCOPE1=TRAP+Y          ;CHECK FOR FREEZE ON CURRENT DATA
          000011          Y=Y+1

2          . =46
3 000046          LOGICAL
4          . =52
5 000052          40000
6          .M^CRO
7          CODEM1
8          MOV      DHSSR,DHSLR          ;SET UP ADDRESS OF SILO
9          INC      DHSLR          ;STATUS REGISTER HIGH BYTE
10 000054          .ENDM CODEM1
          .START  DHRVEC,3,4,DHSCR,0,177776,7,10...1

```

0 001000 . =1000

```

;PROGRAM INITIALIZATION
;LOCK OUT INTERRUPTS
;SET UP PROCESSOR STACK
;SET UP POWER FAIL VECTOR
;CLEAR PROGRAM FLAGS AND COUNTS
;TYPE TITLE MESSAGE
.IIF NB <>, ; DETERMINE MEMORY SIZE
.IIF NB <>, ; SET UP TRACE TRAP RETURN

001000 177570 SWR: .WORD 177570 ; SWITCH DHSCR ADDRESS ; 4
001002 177570 LIGHTS: .WORD 177570 ; LIGHTS ; 4
; 4

001004 012767 000340 176764 START: MOV #340,PS ; LOCK OUT INTERRUPTS
001012 012706 020164 MOV #STACK,SP ; SET UP PROCESSOR STACK
001016 012702 000024 MOV #24,R2 ; POINT TO VECTOR AREA ; 7
001022 012722 016764 MOV #PFAIL,(R2)+ ; SET UP POWER FAIL TRAP ; 7
001026 012722 000340 MOV #340,(R2)+ ; SERVICE AT LEVEL 7 ; 7
001032 012722 015216 MOV #ERRORS,(R2)+ ; ERROR HANDLER ; 7
001036 012722 000340 MOV #340,(R2)+ ; SERVICE AT LEVEL 7 ; 7
001042 012722 015430 MOV #TRPSRV,(R2)+ ; GENERAL HANDLER DISPATCH SERVICE ; 7
001046 012712 000340 MOV #340,(R2) ; SERVICE AT LEVEL 7 ; 8
001052 005067 015274 CLR STFLG ; CLEAR TEST START FLAG
001056 005067 015230 CLR PASCNT ; CLEAR PASS COUNT
001062 005067 015226 CLR EPRCNT ; CLEAR ERROR COUNT
001066 005067 015216 CLR ERRFLG ; CLEAR ERROR FLAG
001072 005067 015212 CLR ERRFLG ; CLEAR LAST ERROR PC
001076 016746 176702 MOV 4,-(SP) ; PUSH TRAP VECTOR ; 4
001102 016746 176700 MOV 6,-(SP) ; ; 4
001106 012767 001122 176670 MOV #14,4 ; SET UP TRAP VECTOR ; 4
001114 005777 177660 TST @SWR ; TEST SWITCH REGISTER ADDRESS ; 4
001120 000405 BR 2$ ; IF SUCCESSFUL, LEAVE IT ALONE ; 4
001122 1$: ; ; 4
001122 012767 000176 177650 MOV #176,SWR ; POINT TO SOFT SWITCH DHSCR ; 4
001130 005067 177646 CLR LIGHTS ; 0 MEANS WE ARE NOT GOING TO USE LIGHTS ; 4
001134 2$: ; ; 5
001134 005726 TST (SP)+ ; CLEAN UP STACK ; 4
001136 005726 TST (SP)+ ; ; 4
001140 012667 176642 MOV (SP)+,6 ; ; 4
001144 012667 176634 MOV (SP)+,4 ; ; 4
001150 104401 017134 TYPE .MTITLE ; TYPE TITLE MESSAGE
001154 005767 015170 TST INIFLG ; CHECK INITIALIZATION FLAG
; IF NB <DHRVEC>
BNE VEC1 ; IF NOT 0, CHECK SWITCHES
; FOR REINITIALIZATION
.IFF
BNE BEGIN ; IF NOT 0, START TEST
.ENDC
.IF NB <>
SIZE: CLR R0
MOV #24,004 ; SET UP TIME OUT RETURN
1$: TST (R0)+ ; WILL TRAP WHEN NO MEMORY ; 9
BR 1$ ; LOCATION RESPONDED, CONTINUE
2$: MOV R0,HCORE ; R0 CONTAINS ADDRESS OF
SUB #2,HCORE ; NON EXISTANT MEMORY ; 9
MOV #6,004 ; RESTORE TRAPCATCHER

```

```

.ENDC
;IF NB <>
TRACER: MOV    #1$,#10          ;SET UP ILLEGAL INSTRUCTION TRAP RETURN
        SXT    R0              ;DO 11/40, 11/45 INSTRUCTION
        MOV    #RTT,TRTRET     ;11/40,45 RTT RETURN FROM TRACE TRAP
        BR     2$
1$:      MOV    #RTI,TRTRET     ;1105,10,20 RTI RETURN FROM TRACE TRAP
        MOV    #12,$10        ;RESTORE TRAPCATCHER
        MOV    #TRTRET,$16     ;SET UP TRACE TRAP VECTOR

.ENDC
;IF NB <DHRVEC>
;IF B <> ; 3
001162 000404 BR     VEC2

;IFF
        TST    INIFLG          ;IF INITIALIZE FLAG=0
        BEQ    VEC2           ;GET VECTOR AND CSR ADDRESS

.ENDC
001164 032777 000001 177606 VEC1: BIT    #SW00,$SWR          ;IF SW00=1, GET NEW VECTOR ; 4
001172 001445 BEQ    BEGIN    ;AND CSR ; 4
001174 VEC2: MOV    #300,R1 ; 4
001174 012701 000300 MOV    #302,R2 ; 4
001200 012702 000302 MOV    #4,R3
001204 012703 000004 MOV    #4,R3
001210 010211 1$:      MOV    R2,(R1) ;RESTORE TRAPCATCHER
001212 005012 CLR     (R2) ;IN FLOATING VECTOR AREA
001214 060301 ADD     R3,R1
001216 060302 ADD     R3,R2
001220 020127 001000 CMP    R1,$1000
001224 001371 BNE     1$
001226 104403 INSTR
001230 017175 MVECTOR
001232 104405 PARAM
001234 000300 300
001236 000770 770
001240 016300 DHRVEC
001242 003 .BYTE 3
001243 004 .BYTE 4
001244 104403 INSTR
001246 017217 MREGAD
001250 104405 PARAM
001252 000000 0
001254 177776 177776
001256 016256 DHSCR
001260 007 .BYTE 7
001261 010 .BYTE 10
.ENDC
;IF NB <1>
001262 CODEM1
001262 016767 015006 015006 MOV    DHSSR,DHSLR ;SET UP ADDRESS OF SILO
001270 005267 015002 INC     DHSLR ;STATUS REGISTER HIGH BYTE

.ENDC
001274 005767 015050 TST    INIFLG ;IF INITIALIZATION FLAG
001300 001002 BNE     BEGIN ;IS CLEARED
001302 005167 015042 COM     INIFLG ;SET IT

;PROGRAM START ; 3
;CHECK FOR PROGRAM START AT SELECTED ADDRESS

```



001306	012767	000340	176462	BEGIN:	MOV	#340,PS	;LOCK OUT INTERRUPTS	
001314	012706	020164			MOV	#STACK,SP	;SET UP PROCESSOR STACK	
001320	032777	000002	177452		BIT	#SW01,@SWR	;IF SW01=1	; 4
001326	001410				BEQ	1\$	;GET PC FOR PROGRAM START	
001330	104403				INSTR		;GET PC	
001332	017406				MTSTPC		;MESSAGE "TEST PC"	
001334	104405				PARAM		;CONVERT STRING TO OCTAL	
001336	000000				0			
001340	017500				17500			
001342	016316				RETRN			
001344	001			.BYTE	1			
001345	001			.BYTE	1			
001346	000410				BR	2\$		
001350	012767	001400	014740	1\$:	MOV	#T1,RETRN	;NORMAL START, TEST 1	
001356	005767	014770			TST	STFLG	;IF LOOPING, BYPASS TYPEOUT	
001362	001004				BNE	3\$		
001364	005167	014762			COM	STFLG		
001370	104401	017402		2\$:	TYPE	,MR	;TYPE "R" TO INDICATE START	
001374	000177	014716		3\$:	JMP	@RETRN	;START TESTING	; 3

```

1
4      000000      LINE=0
5      000000      XLINE=LINE
6      000001      BITX=1
7      000001      XBIT=BITX
9      000020      .REPT 20
10     000000      SDATA1 \LINE,\BITX
11     000000      .NLIST
12     000001      LINE=LINE+1
13     000001      BITX=BITX+BITX
14     000001      .LIST
15     000002      .ENDR
001400 SDATA1 \LINE,\BITX

```

```

;TRANSMIT ALL CHARACTERS ONE AT A TIME ON LINE 0.
;CHARACTER LENGTH IS 8 BITS.
;LINE SPEED IS 9600 BAUD.

```

```

001400 TS \XN,10,4$,1$
001400 012767 000340 176370 T1: MOV #340,PS ;DISABLE ALL INTERRUPTS
001406 012767 000010 014710 MOV #10,ICOUNT ;SET UP FOR 10 ITERATIONS
001414 012767 001540 014676 MOV #4$,ESCAPE ;SET UP TO ESCAPE TO NEXT TEST
001422 012767 001464 014672 .IF NB <1$> MOV #1$,FREEZ1 ;SET UP TO LOOP WITH DATA ; 3
001430 000002 .ENDC
001430 012777 004000 014620 XN=XN+1 MOV #BIT11,@DHSCR ;MASTER CLEAR INTERFACE
001436 012703 000000 014620 MOV #0,R3 ;SET UP LINE NUMBER
001442 012767 100000 014706 MOV #0+400+100000,TDATA ;SET EXPECTED LINE NUMBER
;AND VALID DATA FLAG
;EXPECTED DATA
;SELECT LINE 0
;SELECT 8 BITS CHARACTER
;LENGTH, 9600 BAUD SPEED
;FOR LINE 0
;TRANSMIT 1 CHARACTER
;ADDRESS OF TRANSMIT DATA
;START TRANSMITTER
;WAIT FOR CHARACTER
;TO BE RECEIVED
;GET RECEIVED CHARACTER
;COMPARE EXPECTED AND
;RECEIVED DATA
;DATA ERROR
001450 012777 000000 014600 MOV #0,@DHSCR
001456 012777 033503 014576 MOV #33503,@DHLPR
001464 012777 177777 014574 1$: MOV #-1,@DHBC
001472 012777 016356 014564 MOV #TDATA,@DHBA
001500 012777 000001 014562 MOV #1,@DHBA
001506 105777 014544 2$: TSTB @DHSCR
001512 100375 BPL 2$
001514 017704 014540 MOV @DHNR,R4
001520 020467 014632 CMP R4,TDATA
001524 001401 BEQ 3$
001526 HLT 0
001526 104000 EMT 0
001530 104410 3$: SCOPE1 ;CHECK FOR LOOP WITH CURRENT DATA
001532 105267 014620 INCB TDATA ;UPDATE TRANSMIT DATA
001536 001352 BNE 1$
001540 104400 4$: SCOPE ;CHECK FOR ITERATIONS, LOOP
000001 LINE=LINE+1
000002 BITX=BITX+BITX
001542 SDATA1 \LINE,\BITX

```

```

;TRANSMIT ALL CHARACTERS ONE AT A TIME ON LINE 1.
;CHARACTER LENGTH IS 8 BITS.
;LINE SPEED IS 9600 BAUD.

```

```

001542      TS \XN,10,4$,1$
001542 012767 000340 176226 T2:  MOV    #340,PS      ;DISABLE ALL INTERRUPTS
001550 012767 000010 014546      MOV    #10,ICOUNT    ;SET UP FOR 10 ITERATIONS
001556 012767 001702 014534      MOV    #4$,ESCAPE    ;SET UP TO ESCAPE TO NEXT TEST

001564 012767 001626 014530      .IF NB    <1$>
                                MOV    #1$,FREEZ1      ;SET UP TO LOOP WITH DATA      ; 3
                                .ENDC
                                XN=XN+1

001572      000003
001572 012777 004000 014456      MOV    #BIT11,@DHSCR    ;MASTER CLEAR INTERFACE
001600 012703 000001      MOV    #1,R3      ;SET UP LINE NUMBER
001604 012767 100400 014544      MOV    #1*400+100000,TDATA
                                ;SET EXPECTED LINE NUMBER
                                ;AND VALID DATA FLAG
                                ;EXPECTED DATA
                                ;SELECT LINE 1
                                ;SELECT 8 BITS CHARATER
                                ;LENGTH, 9600 BAUD SPEED
                                ;FOR LINE 1
                                ;TRANSMIT 1 CHARACTER
                                ;ADDRESS OF TRANSMIT DATA
                                ;START TRANSMITTER
                                ;WAIT FOR CHARACTER
                                ;TO BE RECEIVED
                                ;GET RECEIVED CHARACTER
                                ;COMPARE EXPECTED AND
                                ;RECEIVED DATA
                                ;DATA ERROR

001612 012777 000001 014436      MOV    #1,@DHSCR
001620 012777 033503 014434      MOV    #33503,@DHLPR

001626 012777 177777 014432 1$:  MOV    #-1,@DHBC
001634 012777 016356 014422      MOV    @TDATA,@DHBA
001642 012777 000002 014420      MOV    #2,@DHBAR
001650 105777 014402      2$:  TSTB    @DHSCR
001654 100375      BPL    2$
001656 017704 014376      MOV    @DHNR,R4
001662 020467 014470      CMP    R4,TDATA
001666 001401      BEQ    3$
001670      HLT    0
001670      EMT    0
001672 104410      3$:  SCOPE1
001674 105267 014456      INCB    TDATA
001700 001352      BNE    1$
001702 104400      4$:  SCOPE
                                ;CHECK FOR LOOP WITH CURRENT DATA
                                ;UPDATE TRANSMIT DATA
                                000002
                                ;CHECK FOR ITERATIONS, LOOP
                                000004

001704      LINE=LINE+1
                                BITX=BITX+BITX
                                SDATA1 \LINE,\BITX

                                ;TRANSMIT ALL CHARACTERS ONE AT A TIME ON LINE 2.
                                ;CHARACTER LENGTH IS 8 BITS.
                                ;LINE SPEED IS 9600 BAUD.

001704      TS \XN,10,4$,1$
001704 012767 000340 176064 T3:  MOV    #340,PS      ;DISABLE ALL INTERRUPTS
001712 012767 000010 014404      MOV    #10,ICOUNT    ;SET UP FOR 10 ITERATIONS
001720 012767 002044 014372      MOV    #4$,ESCAPE    ;SET UP TO ESCAPE TO NEXT TEST

001726 012767 001770 014366      .IF NB    <1$>
                                MOV    #1$,FREEZ1      ;SET UP TO LOOP WITH DATA      ; 3
                                .ENDC
                                XN=XN+1

001734      000004
001734 012777 004000 014314      MOV    #BIT11,@DHSCR    ;MASTER CLEAR INTERFACE
001742 012703 000002      MOV    #2,R3      ;SET UP LINE NUMBER
001746 012767 101000 014402      MOV    #2*400+100000,TDATA
                                ;SET EXPECTED LINE NUMBER
                                ;AND VALID DATA FLAG
                                ;EXPECTED DATA
                                ;SELECT LINE 2
                                ;SELECT 8 BITS CHARATER

001754 012777 000002 014274      MOV    #2,@DHSCR
001762 012777 033503 014272      MOV    #33503,@DHLPR

```

```

001770 012777 177777 014270 1$: MOV    #-1, @DHBC      ;LENGTH, 9600 BAUD SPEED
001776 012777 016356 014260      MOV    @TDATA, @DHBA    ;FOR LINE 2
002004 012777 000004 014256      MOV    #4, @DHBAR      ;TRANSMIT 1 CHARACTER
                                ;ADDRESS OF TRANSMIT DATA
002012 105777 014240      2$: TSTB    @DHSCR          ;START TRANSMITTER
                                ;WAIT FOR CHARACTER
002016 100375      BPL      2$                ;TO BE RECEIVED
002020 017704 014234      MOV    @DHNR, R4          ;GET RECEIVED CHARACTER
002024 020467 014326      CMP     R4, TDATA         ;COMPARE EXPECTED AND
002030 001401      BEQ      3$                ;RECEIVED DATA
002032      HLT      0                ;DATA ERROR
002032 104000      EMT      0
002034 104410      3$: SCOPE1                ;CHECK FOR LOOP WITH CURRENT DATA
002036 105267 014314      INCB    TDATA            ;UPDATE TRANSMIT DATA
002042 001352      BNE      1$
002044 104400      4$: SCOPE                ;CHECK FOR ITERATIONS, LOOP
      000003      LINE=LINE+1
      000010      BITX=BITX+BITX
002046      SDATA1 \LINE, \BITX

      ;TRANSMIT ALL CHARACTERS ONE AT A TIME ON LINE 3.
      ;CHARACTER LENGTH IS 8 BITS.
      ;LINE SPEED IS 9600 BAUD.

002046      TS \XN, 10, 4$, 1$
002046 012767 000340 175722 T4$: MOV    #340, PS      ;DISABLE ALL INTERRUPTS
002054 012767 000010 014242      MOV    #10, ICOUNT    ;SET UP FOR 10 ITERATIONS
002062 012767 002206 014230      MOV    #4$, ESCAPE    ;SET UP TO ESCAPE TO NEXT TEST
      .IF NB <1$>
002070 012767 002132 014224      MOV    #1$, FREEZ1     ;SET UP TO LOOP WITH DATA      ; 3
      .ENDC
      XN=XN+1
002076 012777 004000 014152      MOV    @BIT11, @DHSCR  ;MASTER CLEAR INTERFACE
002104 012703 000003      MOV    #3, R3                ;SET UP LINE NUMBER
002110 012767 101400 014240      MOV    #3*400+100000, TDATA
                                ;SET EXPECTED LINE NUMBER
                                ;AND VALID DATA FLAG
                                ;EXPECTED DATA
002116 012777 000003 014132      MOV    #3, @DHSCR      ;SELECT LINE 3
002124 012777 033503 014130      MOV    #33503, @DHLPR  ;SELECT 8 BITS CHARACTER
                                ;LENGTH, 9600 BAUD SPEED
                                ;FOR LINE 3
002132 012777 177777 014126 1$: MOV    #-1, @DHBC      ;TRANSMIT 1 CHARACTER
002140 012777 016356 014116      MOV    @TDATA, @DHBA    ;ADDRESS OF TRANSMIT DATA
002146 012777 000010 014114      MOV    #10, @DHBAR      ;START TRANSMITTER
002154 105777 014076      2$: TSTB    @DHSCR          ;WAIT FOR CHARACTER
002160 100375      BPL      2$                ;TO BE RECEIVED
002162 017704 014072      MOV    @DHNR, R4          ;GET RECEIVED CHARACTER
002166 020467 014164      CMP     R4, TDATA         ;COMPARE EXPECTED AND
002172 001401      BEQ      3$                ;RECEIVED DATA
002174      HLT      0                ;DATA ERROR
002174 104000      EMT      0
002176 104410      3$: SCOPE1                ;CHECK FOR LOOP WITH CURRENT DATA
002200 105267 014152      INCB    TDATA            ;UPDATE TRANSMIT DATA
002204 001352      BNE      1$
002206 104400      4$: SCOPE                ;CHECK FOR ITERATIONS, LOOP
      000004      LINE=LINE+1

```

```

002210 000020          BITX=BITX+BITX
                      SDATA1 \LINE,\BITX

                      ;TRANSMIT ALL CHARACTERS ONE AT A TIME ON LINE 4.
                      ;CHARACTER LENGTH IS 8 BITS.
                      ;LINE SPEED IS 9600 BAUD.

002210          TS \XN,10,4$,1$
002210 012767 000340 175560 T5:      MOV      #340,PS          ;DISABLE ALL INTERRUPTS
002216 012767 000010 014100          MOV      #10,ICOUNT       ;SET UP FOR 10 ITERATIONS
002224 012767 002350 014066          MOV      #4$,ESCAPE       ;SET UP TO ESCAPE TO NEXT TEST
                      .IF NB <1$>
002232 012767 002274 014062          MOV      #1$,FREEZ1        ;SET UP TO LOOP WITH DATA          ; 3
                      .ENDC
                      XN=XN+1
002240 012777 004000 014010          MOV      #BIT11,@DHSCR     ;MASTER CLEAR INTERFACE
002246 012703 000004          MOV      #4,R3                  ;SET UP LINE NUMBER
002252 012767 102000 014076          MOV      #4*400+100000,TDATA
                      ;SET EXPECTED LINE NUMBER
                      ;AND VALID DATA FLAG
                      ;EXPECTED DATA
                      ;SELECT LINE 4
                      ;SELECT 8 BITS CHARACTER
                      ;LENGTH, 9600 BAUD SPEED
                      ;FOR LINE 4
002260 012777 000004 013770          MOV      #4,@DHSCR        ;TRANSMIT 1 CHARACTER
002266 012777 033503 013766          MOV      #33503,@DHLPR     ;ADDRESS OF TRANSMIT DATA
                      ;START TRANSMITTER
                      ;WAIT FOR CHARACTER
                      ;TO BE RECEIVED
                      ;GET RECEIVED CHARACTER
                      ;COMPARE EXPECTED AND
                      ;RECEIVED DATA
                      ;DATA ERROR
002274 012777 177777 013764 1$:      MOV      #-1,@DHBC
002302 012777 016356 013754          MOV      #TDATA,@DHBA
002310 012777 000020 013752          MOV      #20,@DH8AR
002316 105777 013734          2$:      TSTB      @DHSCR
002322 100375          BPL      2$
002324 017704 013730          MOV      @DHNRC,R4
002330 020467 014022          CMP      R4,TDATA
002334 001401          BEQ      3$
002336          HLT      0
002336 104000          EMT      0
002340 104410          3$:      SCOPE1
002342 105267 014010          INCB      TDATA
002346 001352          BNE      1$
002350 104400          4$:      SCOPE
                      LINE=LINE+1
                      BITX=BITX+BITX
002352          SDATA1 \LINE,\BITX

                      ;TRANSMIT ALL CHARACTERS ONE AT A TIME ON LINE 5.
                      ;CHARACTER LENGTH IS 8 BITS.
                      ;LINE SPEED IS 9600 BAUD.

002352          TS \XN,10,4$,1$
002352 012767 000340 175416 T6:      MOV      #340,PS          ;DISABLE ALL INTERRUPTS
002360 012767 000010 013736          MOV      #10,ICOUNT       ;SET UP FOR 10 ITERATIONS
002366 012767 002512 013724          MOV      #4$,ESCAPE       ;SET UP TO ESCAPE TO NEXT TEST
                      .IF NB <1$>
002374 012767 002436 013720          MOV      #1$,FREEZ1        ;SET UP TO LOOP WITH DATA          ; 3
                      .ENDC
                      XN=XN+1
002402 012777 004000 013646          MOV      #BIT11,@DHSCR     ;MASTER CLEAR INTERFACE
002410 012703 000005          MOV      #5,R3                  ;SET UP LINE NUMBER

```



```

002414 012767 102400 013734      MOV      #5*400+100000,TDATA
;SET EXPECTED LINE NUMBER
;AND VALID DATA FLAG
;EXPECTED DATA
002422 012777 000005 013626      MOV      #5,@DHSCR
;SELECT LINE 5
002430 012777 033503 013624      MOV      #33503,@DHLPR
;SELECT 8 BITS CHARATER
;LENGTH, 9600 BAUD SPEED
;FOR LINE 5
002436 012777 177777 013622 1$:  MOV      #-1,@DHBC
;TRANSMIT 1 CHARACTER
002444 012777 016356 013612      MOV      #TDATA,@DHBA
;ADDRESS OF TRANSMIT DATA
002452 012777 000040 013610      MOV      #40,@DHBAR
;START TRANSMITTER
002460 105777 013572 2$:  TSTB      @DHSCR
;WAIT FOR CHARACTER
002464 100375      BPL      2$
;TO BE RECEIVED
002466 017704 013566      MOV      @DHNR,R4
;GET RECEIVED CHARACTER
002472 020467 013660      CMP      R4,TDATA
;COMPARE EXPECTED AND
002476 001401      BEQ      3$
;RECEIVED DATA
002500      HLT      0
;DATA ERROR
002500 104000      EMT      0
002502 104410      3$:  SCOPE1
;CHECK FOR LOOP WITH CURRENT DATA
002504 105267 013646      INCB      TDATA
;UPDATE TRANSMIT DATA
002510 001352      BNE      1$
002512 104400      4$:  SCOPE
;CHECK FOR ITERATIONS, LOOP
000006      LINE=LINE+1
000100      BITX=BITX+BITX
SDATA1 \LINE,\BITX

;TRANSMIT ALL CHARACTERS ONE AT A TIME ON LINE 6.
;CHARACTER LENGTH IS 8 BITS.
;LINE SPEED IS 9600 BAUD.

002514      TS \XN,10,4$,1$
002514 012767 000340 175254 T7:  MOV      #340,PS
;DISABLE ALL INTERRUPTS
002522 012767 000010 013574      MOV      #10,ICOUNT
;SET UP FOR 10 ITERATIONS
002530 012767 002654 013562      MOV      #4$,ESCAPE
;SET UP TO ESCAPE TO NEXT TEST
002536 012767 002600 013556      MOV      #1$,FREEZ1
;SET UP TO LOOP WITH DATA : 3
000010      .IF NB <1$>
002544 012777 004000 013504      .ENDC
;MASTER CLEAR INTERFACE
002552 012703 000006      XN=XN+1
;SET UP LINE NUMBER
002556 012767 103000 013572      MOV      @BIT11,@DHSCR
MOV      #6,R3
MOV      #6*400+100000,TDATA
;SET EXPECTED LINE NUMBER
;AND VALID DATA FLAG
;EXPECTED DATA
002564 012777 000006 013464      MOV      #6,@DHSCR
;SELECT LINE 6
002572 012777 033503 013462      MOV      #33503,@DHLPR
;SELECT 8 BITS CHARATER
;LENGTH, 9600 BAUD SPEED
;FOR LINE 6
002600 012777 177777 013460 1$:  MOV      #-1,@DHBC
;TRANSMIT 1 CHARACTER
002606 012777 016356 013450      MOV      #TDATA,@DHBA
;ADDRESS OF TRANSMIT DATA
002614 012777 000100 013446      MOV      #100,@DHBAR
;START TRANSMITTER
002622 105777 013430 2$:  TSTB      @DHSCR
;WAIT FOR CHARACTER
002626 100375      BPL      2$
;TO BE RECEIVED
002630 017704 013424      MOV      @DHNR,R4
;GET RECEIVED CHARACTER
002634 020467 013516      CMP      R4,TDATA
;COMPARE EXPECTED AND
002640 001401      BEQ      3$
;RECEIVED DATA
002642      HLT      0
;DATA ERROR

```

```

002642 104000          EMT      0
002644 104410          3$: SCOPE1
002646 105267 013504    INCB     TDATA      ;CHECK FOR LOOP WITH CURRENT DATA
002652 001352          BNE      1$         ;UPDATE TRANSMIT DATA
002654 104400          4$: SCOPE          ;CHECK FOR ITERATIONS, LOOP
      000007    LINE=LINE+1
      000200    BITX=BITX+BITX
002656          SDATA1 \LINE,\BITX

      ;TRANSMIT ALL CHARACTERS ONE AT A TIME ON LINE 7.
      ;CHARACTER LENGTH IS 8 BITS.
      ;LINE SPEED IS 9600 BAUD.

002656          TS \XN,10,4$,1$
002656 012767 000340 175112 T10:  MOV     #340,PS      ;DISABLE ALL INTERRUPTS
002664 012767 000010 013432      MOV     #10,ICOUNT    ;SET UP FOR 10 ITERATIONS
002672 012767 003016 013420      MOV     #4$,ESCAPE    ;SET UP TO ESCAPE TO NEXT TEST
      .IF NB <1$>
002700 012767 002742 013414      MOV     #1$,FREEZ1      ;SET UP TO LOOP WITH DATA      ; 3
      .ENDC
      XN=XN+1
002706 012777 004000 013342      MOV     @BIT11,@DHSCR    ;MASTER CLEAR INTERFACE
002714 012703 000007          MOV     #7,R3      ;SET UP LINE NUMBER
002720 012767 103400 013430      MOV     #7*400+100000,TDATA
      ;SET EXPECTED LINE NUMBER
      ;AND VALID DATA FLAG
      ;EXPECTED DATA
      ;SELECT LINE 7
      ;SELECT 8 BITS CHARACTER
      ;LENGTH, 9600 BAUD SPEED
      ;FOR LINE 7
002726 012777 000007 013322      MOV     #7,@DHSCR
002734 012777 033503 013320      MOV     #33503,@DHLPR
      ;TRANSMIT 1 CHARACTER
      ;ADDRESS OF TRANSMIT DATA
002742 012777 177777 013316 1$: MOV     #-1,@DHBC
002750 012777 016356 013306      MOV     @TDATA,@DHBA
002756 012777 000200 013304      MOV     #200,@DHBA
002764 105777 013266          2$: TSTB     @DHSCR
002770 100375          BPL      2$
002772 017704 013262      MOV     @DHNR,R4
002776 020467 013354      CMP     R4,TDATA
003002 001401          BEQ      3$
003004          HLT      0
003004          EMT      0
003006 104410          3$: SCOPE1
003010 105267 013342    INCB     TDATA      ;CHECK FOR LOOP WITH CURRENT DATA
003014 001352          BNE      1$         ;UPDATE TRANSMIT DATA
003016 104400          4$: SCOPE          ;CHECK FOR ITERATIONS, LOOP
      000010    LINE=LINE+1
      000400    BITX=BITX+BITX
003020          SDATA1 \LINE,\BITX

      ;TRANSMIT ALL CHARACTERS ONE AT A TIME ON LINE 10.
      ;CHARACTER LENGTH IS 8 BITS.
      ;LINE SPEED IS 9600 BAUD.

003020          TS \XN,10,4$,1$
003020 012767 000340 174750 T11:  MOV     #340,PS      ;DISABLE ALL INTERRUPTS
003026 012767 000010 013270      MOV     #10,ICOUNT    ;SET UP FOR 10 ITERATIONS
003034 012767 003160 013256      MOV     #4$,ESCAPE    ;SET UP TO ESCAPE TO NEXT TEST

```

```

003042 012767 003104 013252 .IF NB <1>
                                MOV     #1$,FREEZ1          ;SET UP TO LOOP WITH DATA      ; 3
                                .ENDC
                                XN=XN+1
003050 012777 004000 013200      MOV     #BIT11,@DHSCR          ;MASTER CLEAR INTERFACE
003056 012703 000010 013200      MOV     #10,R3              ;SET UP LINE NUMBER
003062 012767 104000 013266      MOV     #10*400+100000,TDATA
                                ;SET EXPECTED LINE NUMBER
                                ;AND VALID DATA FLAG
                                ;EXPECTED DATA
                                ;SELECT LINE 10
                                ;SELECT 8 BITS CHARATER
                                ;LENGTH, 9600 BAUD SPEED
                                ;FOR LINE 10
                                ;TRANSMIT 1 CHARACTER
                                ;ADDRESS OF TRANSMIT DATA
                                ;START TRANSMITTER
                                ;WAIT FOR CHARACTER
                                ;TO BE RECEIVED
                                ;GET RECEIVED CHARACTER
                                ;COMPARE EXPECTED AND
                                ;RECEIVED DATA
                                ;DATA ERROR
003070 012777 000010 013160      MOV     #10,@DHSCR
003076 012777 033503 013156      MOV     #33503,@DHLPR
                                ;SELECT 8 BITS CHARATER
                                ;LENGTH, 9600 BAUD SPEED
                                ;FOR LINE 10
                                ;TRANSMIT 1 CHARACTER
                                ;ADDRESS OF TRANSMIT DATA
                                ;START TRANSMITTER
                                ;WAIT FOR CHARACTER
                                ;TO BE RECEIVED
                                ;GET RECEIVED CHARACTER
                                ;COMPARE EXPECTED AND
                                ;RECEIVED DATA
                                ;DATA ERROR
003104 012777 177777 013154 1$: MOV     #-1,@DHBC
003112 012777 016356 013144      MOV     #TDATA,@DHBA
003120 012777 000400 013142      MOV     #400,@DHBAR
003126 105777 013124 2$: TSTB     @DHSCR
003132 100375 013124      BPL      2$
003134 017704 013120      MOV     @DHNRC,R4
003140 020467 013212      CMP     R4,TDATA
003144 001401      BEQ      3$
003146      HLT      0
003146      EMT      0
003150 104410 3$: SCOPE1
003152 105267 013200      INCB     TDATA
003156 001352      BNE      1$
003160 104400 4$: SCOPE
                                ;CHECK FOR LOOP WITH CURRENT DATA
                                ;UPDATE TRANSMIT DATA
                                ;CHECK FOR ITERATIONS, LOOP
                                LINE=LINE+1
                                BITX=BITX+BITX
                                SDA'A1 \LINE,\BITX
003162
                                ;TRANSMIT ALL CHARACTERS ONE AT A TIME ON LINE 11.
                                ;CHARACTER LENGTH IS 8 BITS.
                                ;LINE SPEED IS 9600 BAUD.
003162 TS \XN,10,4$,1$
003162 012767 000340 174606 T12: MOV     #340,PS          ;DISABLE ALL INTERRUPTS
003170 012767 000010 013126      MOV     #10,ICOUNT        ;SET UP FOR 10 ITERATIONS
003176 012767 003322 013114      MOV     #4$,ESCAPE      ;SET UP TO ESCAPE TO NEXT TEST
                                .IF NB <1>
003204 012767 003246 013110      MOV     #1$,FREEZ1          ;SET UP TO LOOP WITH DATA      ; 3
                                .ENDC
                                XN=XN+1
003212 012777 004000 013036      MOV     #BIT11,@DHSCR          ;MASTER CLEAR INTERFACE
003220 012703 000011 013124      MOV     #11,R3              ;SET UP LINE NUMBER
003224 012767 104400 013124      MOV     #11*400+100000,TDATA
                                ;SET EXPECTED LINE NUMBER
                                ;AND VALID DATA FLAG
                                ;EXPECTED DATA
                                ;SELECT LINE 11
                                ;SELECT 8 BITS CHARATER
                                ;LENGTH, 9600 BAUD SPEED
                                ;FOR LINE 11
                                ;TRANSMIT 1 CHARACTER
                                ;ADDRESS OF TRANSMIT DATA
                                ;START TRANSMITTER
003232 012777 000011 013016      MOV     #11,@DHSCR
003240 012777 033503 013014      MOV     #33503,@DHLPR
                                ;SELECT 8 BITS CHARATER
                                ;LENGTH, 9600 BAUD SPEED
                                ;FOR LINE 11
                                ;TRANSMIT 1 CHARACTER
                                ;ADDRESS OF TRANSMIT DATA
                                ;START TRANSMITTER
003246 012777 177777 013012 1$: MOV     #-1,@DHBC
003254 012777 016356 013002      MOV     #TDATA,@DHBA
003262 012777 001000 013000      MOV     #1000,@DHBAR

```

```

003270 105777 012762      2$:  TSTB  @DHSCR      ;WAIT FOR CHARACTER
003274 100375              BPL  2$           ;TO BE RECEIVED
003276 017704 012756      MOV  @DHNR,R4      ;GET RECEIVED CHARACTER
003302 020467 013050      CMP  R4,TDATA     ;COMPARE EXPECTED AND
003306 001401              BEQ  3$           ;RECEIVED DATA
003310              HLT  0                   ;DATA ERROR
003310 104000              EMT  0
003312 104410      3$:  SCOPE1              ;CHECK FOR LOOP WITH CURRENT DATA
003314 105267 013036      INCB  TDATA       ;UPDATE TRANSMIT DATA
003320 001352              BNE  1$
003322 104400      4$:  SCOPE              ;CHECK FOR ITERATIONS, LOOP
      000012      LINE=LINE+1
      002000      BITX=BITX+BITX
003324      SDATA1 \LINE,\BITX

      ;TRANSMIT ALL CHARACTERS ONE AT A TIME ON LINE 12.
      ;CHARACTER LENGTH IS 8 BITS.
      ;LINE SPEED IS 9600 BAUD.

003324      TS \XN,10,4$,1$
003324 012767 000340 174444 T13:  MOV  @340,PS      ;DISABLE ALL INTERRUPTS
003332 012767 000010 012764      MOV  @10,ICOUNT   ;SET UP FOR 10 ITERATIONS
003340 012767 003464 012752      MOV  @4$,ESCAPE   ;SET UP TO ESCAPE TO NEXT TEST
      .IF NB <1$>
003346 012767 003410 012746      MOV  @1$,FREEZ1    ;SET UP TO LOOP WITH DATA      ; 3
      .ENDC
      XN=XN+1
003354 012777 004000 012674      MOV  @BIT11,@DHSCR ;MASTER CLEAR INTERFACE
003362 012703 000012              MOV  @12,R3      ;SET UP LINE NUMBER
003366 012767 105000 012762      MOV  @12*400+100000,TDATA
      ;SET EXPECTED LINE NUMBER
      ;AND VALID DATA FLAG
      ;EXPECTED DATA
      ;SELECT LINE 12
      ;SELECT 8 BITS CHARACTER
      ;LENGTH, 9600 BAUD SPEED
      ;FOR LINE 12
003374 012777 000012 012654      MOV  @12,@DHSCR   ;TRANSMIT 1 CHARACTER
003402 012777 033503 012652      MOV  @33503,@DHLPR ;ADDRESS OF TRANSMIT DATA
      ;START TRANSMITTER
      ;WAIT FOR CHARACTER
      ;TO BE RECEIVED
      ;GET RECEIVED CHARACTER
      ;COMPARE EXPECTED AND
      ;RECEIVED DATA
      ;DATA ERROR
003410 012777 177777 012650 1$:  MOV  @-1,@DHBC    ;CHECK FOR LOOP WITH CURRENT DATA
003416 012777 016356 012640      MOV  @TDATA,@DHBA ;UPDATE TRANSMIT DATA
003424 012777 002000 012636      MOV  @2000,@DHBA
003432 105777 012620      2$:  TSTB  @DHSCR      ;CHECK FOR ITERATIONS, LOOP
003436 100375              BPL  2$
003440 017704 012614      MOV  @DHNR,R4
003444 020467 012706      CMP  R4,TDATA
003450 001401              BEQ  3$
003452              HLT  0
003452 104000              EMT  0
003454 104410      3$:  SCOPE1
003456 105267 012674      INCB  TDATA
003462 001352              BNE  1$
003464 104400      4$:  SCOPE
      000013      LINE=LINE+1
      004000      BITX=BITX+BITX
003466      SDATA1 \LINE,\BITX

      ;TRANSMIT ALL CHARACTERS ONE AT A TIME ON LINE 13.
      ;CHARACTER LENGTH IS 8 BITS.

```

;LINE SPEED IS 9600 BAUD.

```

003466      012767 000340 174302 TS \XN,10,4$,1$
003466      012767 000010 012622 T14:  MOV    #340,PS          ;DISABLE ALL INTERRUPTS
003474      012767 000010 012622      MOV    #10,ICOUNT      ;SET UP FOR 10 ITERATIONS
003502      012767 003626 012610      MOV    #4$,ESCAPE      ;SET UP TO ESCAPE TO NEXT TEST
                                .IF NB  <1$>
003510      012767 003552 012604      MOV    #1$,FREEZ1      ;SET UP TO LOOP WITH DATA          ; 3
                                .ENDC
                                XN=XN+1
003516      012777 004000 012532      MOV    #BIT11,0DHSCR      ;MASTER CLEAR INTERFACE
003524      012703 000013 012620      MOV    #13,R3          ;SET UP LINE NUMBER
003530      012767 105400 012620      MOV    #13*400+100000,TDATA
                                ;SET EXPECTED LINE NUMBER
                                ;AND VALID DATA FLAG
                                ;EXPECTED DATA
003536      012777 000013 012512      MOV    #13,0DHSCR      ;SELECT LINE 13
003544      012777 033503 012510      MOV    #33503,0DHLPR      ;SELECT 8 BITS CHARATER
                                ;LENGTH, 9600 BAUD SPEED
                                ;FOR LINE 13
003552      012777 177777 012506 1$:  MOV    #-1,0DHBC      ;TRANSMIT 1 CHARACTER
003560      012777 016356 012476      MOV    #TDATA,0DH9A      ;ADDRESS OF TRANSMIT DATA
003566      012777 004000 012474      MOV    #4000,0DH8AR      ;START TRANSMITTER
003574      105777 012456 012474 2$:  TSTB    0DHSCR      ;WAIT FOR CHARACTER
003600      100375 012452 012474      BPL     2$          ;TO BE RECEIVED
003602      017704 012452 012474      MOV    0DHNR, R4      ;GET RECEIVED CHARACTER
003606      020467 012544 012474      CMP     R4,TDATA      ;COMPARE EXPECTED AND
003612      001401 012544 012474      BEQ     3$          ;RECEIVED DATA
003614      104000 012544 012474      HLT     0          ;DATA ERROR
003614      104410 012544 012474      EMT     0
003616      104410 012544 012474 3$:  SCOPE1
003620      105267 012532 012474      INCB    TDATA      ;CHECK FOR LOOP WITH CURRENT DATA
003624      001352 012532 012474      BNE     1$          ;UPDATE TRANSMIT DATA
003626      10~400 012532 012474 4$:  SCOPE
                                LINE=LINE+1
                                BITX=BITX+BITX
                                SDATA1 \LINE,\BITX
                                ;CHECK FOR ITERATIONS. LOOP
003630      010000 012532 012474

```

```

;TRANSMIT ALL CHARACTERS ONE AT A TIME ON LINE 14.
;CHARACTER LENGTH IS 8 BITS.
;LINE SPEED IS 9600 BAUD.

```

```

003630      012767 000340 174140 TS \XN,10,4$,1$
003630      012767 000010 012460 T15:  MOV    #340,PS          ;DISABLE ALL INTERRUPTS
003636      012767 000010 012460      MOV    #10,ICOUNT      ;SET UP FOR 10 ITERATIONS
003644      012767 003770 012446      MOV    #4$,ESCAPE      ;SET UP TO ESCAPE TO NEXT TEST
                                .IF NB  <1$>
003652      012767 003714 012442      MOV    #1$,FREEZ1      ;SET UP TO LOOP WITH DATA          ; 3
                                .ENDC
                                XN=XN+1
003660      012777 004000 012370      MOV    #BIT11,0DHSCR      ;MASTER CLEAR INTERFACE
003666      012703 000014 012370      MOV    #14,R3          ;SET UP LINE NUMBER
003672      012767 106000 012456      MOV    #14*400+100000,TDATA
                                ;SET EXPECTED LINE NUMBER
                                ;AND VALID DATA FLAG
                                ;EXPECTED DATA
003700      012777 000014 012350      MOV    #14,0DHSCR      ;SELECT LINE 14

```

```

003706 012777 033503 012346      MOV      #33503, @DHLPR      ;SELECT 8 BITS CHARATER
                                           ;LENGTH, 9600 BAUD SPEED
                                           ;FOR LINE 14
003714 012777 177777 012344 1$:  MOV      #-1, @DHBC      ;TRANSMIT 1 CHARACTER
003722 012777 016356 012334      MOV      #TDATA, @DHBA      ;ADDRESS OF TRANSMIT DATA
003730 012777 010000 012332      MOV      #10000, @DHBAR      ;START TRANSMITTER
003736 105777 012314      2$:  TSTB      @DHSCR      ;WAIT FOR CHARACTER
003742 100375      BPL      2$      ;TO BE RECEIVED
003744 017704 012310      MOV      @DHNRC, R4      ;GET RECEIVED CHARACTER
003750 020467 012402      CMP      R4, TDATA      ;COMPARE EXPECTED AND
003754 001401      BEQ      3$      ;RECEIVED DATA
003756      HLT      0      ;DATA ERROR
003756 104000      EMT      0
003760 104410      3$:  SCOPE1      ;CHECK FOR LOOP WITH CURRENT DATA
003762 105267 012370      INCB      TDATA      ;UPDATE TRANSMIT DATA
003766 001352      BNE      1$
003770 104400      4$:  SCOPE      ;CHECK FOR ITERATIONS, LOOP
      000015      LINE=LINE+1
      020000      BITX=BITX+BITX
003772      SDATA1 \LINE, \BITX

      ;TRANSMIT ALL CHARACTERS ONE AT A TIME ON LINE 15.
      ;CHARACTER LENGTH IS 8 BITS.
      ;LINE SPEED IS 9600 BAUD.

003772      TS \XN, 10, 4$, 1$
003772 012767 000340 173776 T16:  MOV      #340, PS      ;DISABLE ALL INTERRUPTS
004000 012767 000010 012316      MOV      #10, ICOUNT      ;SET UP FOR 10 ITERATIONS
004006 012767 004132 012304      MOV      #4$, ESCAPE      ;SET UP TO ESCAPE TO NEXT TEST
      .IF NB <1$>
004014 012767 004056 012300      MOV      #1$, FREEZ1      ;SET UP TO LOOP WITH DATA      ; 3
      .ENDC
      XN=XN+1
004022 012777 004000 012226      MOV      @BIT11, @DHSCR      ;MASTER CLEAR INTERFACE
004030 012703 000015      MOV      #15, R3      ;SET UP LINE NUMBER
004034 012767 106400 012314      MOV      #15*400+100000, TDATA
                                           ;SET EXPECTED LINE NUMBER
                                           ;AND VALID DATA FLAG
                                           ;EXPECTED DATA
004042 012777 000015 012206      MOV      #15, @DHSCR      ;SELECT LINE 15
004050 012777 033503 012204      MOV      #33503, @DHLPR      ;SELECT 8 BITS CHARATER
                                           ;LENGTH, 9600 BAUD SPEED
                                           ;FOR LINE 15
004056 012777 177777 012202 1$:  MOV      #-1, @DHBC      ;TRANSMIT 1 CHARACTER
004064 012777 016356 012172      MOV      #TDATA, @DHBA      ;ADDRESS OF TRANSMIT DATA
004072 012777 020000 012170      MOV      #20000, @DHBAR      ;START TRANSMITTER
004100 105777 012152      2$:  TSTB      @DHSCR      ;WAIT FOR CHARACTER
004104 100375      BPL      2$      ;TO BE RECEIVED
004106 017704 012146      MOV      @DHNRC, R4      ;GET RECEIVED CHARACTER
004112 020467 012240      CMP      R4, TDATA      ;COMPARE EXPECTED AND
004116 001401      BEQ      3$      ;RECEIVED DATA
004120      HLT      0      ;DATA ERROR
004120 104000      EMT      0
004122 104410      3$:  SCOPE1      ;CHECK FOR LOOP WITH CURRENT DATA
004124 105267 012226      INCB      TDATA      ;UPDATE TRANSMIT DATA
004130 001352      BNE      1$
004132 104400      4$:  SCOPE      ;CHECK FOR ITERATIONS, LOOP

```

```
000016
000000
004134 LINE=LINE+1
        BITX=BITX+BITX
        SDATA1 \LINE,\BITX

        ;TRANSMIT ALL CHARACTERS ONE AT A TIME ON LINE 16.
        ;CHARACTER LENGTH IS 8 BITS.
        ;LINE SPEED IS 9600 BAUD.

004134 TS \XN,10,4$,1$
004134 012767 000340 173634 T17: MOV #340,PS ;DISABLE ALL INTERRUPTS
004142 012767 000010 012154 MOV #10,ICOUNT ;SET UP FOR 10 ITERATIONS
004150 012767 004274 012142 MOV #4$,ESCAPE ;SET UP TO ESCAPE TO NEXT TEST

004156 012767 004220 012136 .IF NB <1$> MOV #1$,FREEZ1 ;SET UP TO LOOP WITH DATA ; 3
        .ENDC
        XN=XN+1

004164 000020
004164 012777 004000 012064 MOV #BIT11,@DHSCR ;MASTER CLEAR INTERFACE
004172 012703 000016 MOV #16,R3 ;SET UP LINE NUMBER
004176 012767 107000 012152 MOV #16*400+100000,TDATA ;SET EXPECTED LINE NUMBER
                                ;AND VALID DATA FLAG
                                ;EXPECTED DATA
                                ;SELECT LINE 16
                                ;SELECT 8 BITS CHARACTER
                                ;LENGTH, 9600 BAUD SPEED
                                ;FOR LINE 16
                                ;TRANSMIT 1 CHARACTER
                                ;ADDRESS OF TRANSMIT DATA
                                ;START TRANSMITTER
                                ;WAIT FOR CHARACTER
                                ;TO BE RECEIVED
                                ;GET RECEIVED CHARACTER
                                ;COMPARE EXPECTED AND
                                ;RECEIVED DATA
                                ;DATA ERROR

004204 012777 000016 012044 MOV #16,@DHSCR
004212 012777 033503 012042 MOV #33503,@DHLPR

004220 012777 177777 012040 1$: MOV #-1,@DHBC
004226 012777 016356 012030 MOV #TDATA,@DHBA ;TRANSMIT 1 CHARACTER
004234 012777 040000 012026 MOV #40000,@DHBAR ;ADDRESS OF TRANSMIT DATA
004242 105777 012010 2$: TSTB @DHSCR ;START TRANSMITTER
004246 100375 BPL 2$ ;WAIT FOR CHARACTER
004250 017704 012004 MOV @DHNR,R4 ;TO BE RECEIVED
004254 020467 012076 CMP R4,TDATA ;GET RECEIVED CHARACTER
004260 001401 BEQ 3$ ;COMPARE EXPECTED AND
004262 HLT 0 ;RECEIVED DATA
004262 104000 EMT 0 ;DATA ERROR
004264 104410 3$: SCOPE1 ;CHECK FOR LOOP WITH CURRENT DATA
004266 105267 012064 INCB TDATA ;UPDATE TRANSMIT DATA
004272 001352 BNE 1$
004274 104400 4$: SCOPE ;CHECK FOR ITERATIONS, LOOP
        LINE=LINE+1
        BITX=BITX+BITX
        SDATA1 \LINE,\BITX

        ;TRANSMIT ALL CHARACTERS ONE AT A TIME ON LINE 17.
        ;CHARACTER LENGTH IS 8 BITS.
        ;LINE SPEED IS 9600 BAUD.

004276 TS \XN,10,4$,1$
004276 012767 000340 173472 T20: MOV #340,PS ;DISABLE ALL INTERRUPTS
004304 012767 000010 012012 MOV #10,ICOUNT ;SET UP FOR 10 ITERATIONS
004312 012767 004436 012000 MOV #4$,ESCAPE ;SET UP TO ESCAPE TO NEXT TEST

004320 012767 004362 011774 .IF NB <1$> MOV #1$,FREEZ1 ;SET UP TO LOOP WITH DATA ; 3
        .ENDC
        XN=XN+1

004326 000021
004326 012777 004000 011722 MOV #BIT11,@DHSCR ;MASTER CLEAR INTERFACE
```

```

004334 012703 000017      MOV    #17,R3      ;SET UP LINE NUMBER
004340 012767 107400 012010  MOV    #17*400+100000,TDATA      ;SET EXPECTED LINE NUMBER
                                           ;AND VALID DATA FLAG
                                           ;EXPECTED DATA
004346 012777 000017 011702  MOV    #17,0DHSCR      ;SELECT LINE 17
004354 012777 033503 011700  MOV    #33503,0DHLPR      ;SELECT 8 BITS CHARACTER
                                           ;LENGTH, 9600 BAUD SPEED
                                           ;FOR LINE 17
004362 012777 171777 011676 1$:  MOV    #-1,0DHBC      ;TRANSMIT 1 CHARACTER
004370 012777 016356 011666  MOV    #TDATA,0DHBA      ;ADDRESS OF TRANSMIT DATA
004376 012777 100000 011664  MOV    #100000,0DHBA      ;START TRANSMITTER
004404 105777 011646      2$:  TSTB    0DHSCR      ;WAIT FOR CHARACTER
004410 100375      BPL     2$      ;TO BE RECEIVED
004412 017704 011642      MOV    0DHNRC,R4      ;GET RECEIVED CHARACTER
004416 020467 011734      CMP     R4,TDATA      ;COMPARE EXPECTED AND
004422 001401      BEQ     3$      ;RECEIVED DATA
004424      HLT     0      ;DATA ERROR
004424 104000      EMT     0
004426 104410      3$:  SCOPE1      ;CHECK FOR LOOP WITH CURRENT DATA
004430 105267 011722      INCB    TDATA      ;UPDATE TRANSMIT DATA
004434 001352      BNE     1$
004436 104400      4$:  SCOPE      ;CHECK FOR ITERATIONS, LOOP
      000020      LINE=LINE+1
      000000      BITX=BITX+BITX
      000000      LINE=0
      000000      XLINE=LINE
      000001      BITX=1
      000001      XBIT=BITX
      000020      .REPT    20
      000000      SDATA2  \LINE,\BITX
      000000      .NLIST
      000001      LINE=LINE+1
      000001      BITX=BITX+BITX
      000001      .LIST
      000020      .ENDR
004440      SDATA2  \LINE,\BITX

      ;SINGLE LINE DATA TEST
      ;TRANSMIT A BLOCK OF 400 (OCTAL) CHARACTERS ON LINE 0
      ;CHARACTER LENGTH IS 8 BITS
      ;LINE SPEED WILL START AT 50 BAUD AND BE INCREMENTED
      ;TO 9600 BAUD.
      ;A BLOCK OF 400 CHARACTERS WILL BE TRANSMITTED
      ;AT EACH SPEED

004440      TS  \XN,1,4$,1$
004440 012767 000340 173330 T21:  MOV    #340,PS      ;DISABLE ALL INTERRUPTS
004446 012767 000001 011650  MOV    #1,ICOUNT      ;SET UP FOR 1 ITERATIONS
004454 012767 004634 011636  MOV    #4$,ESCAPE      ;SET UP TO ESCAPE TO NEXT TEST
                                           ; 3
004462 012767 004524 011632  MOV    #1$,FREEZ1      ;SET UP TO LOOP WITH DATA
      .ENDC
      XN=XN+1
004470 000022      MOV    #BIT11,0DHSCR      ;MASTER CLEAR INTERFACE
004476 012777 004000 011560  MOV    #1,R2      ;FIRST SPEED CODE
004502 012705 000000      MOV    #0,R5      ;LINE 0 WILL BE TESTED

```



```

004506 012767 100000 011644      MOV      #0*400+100000,RDATA      ;SET EXPECTED LINE NUMBER
                                           ;AND VALID DATA FLAG
                                           ;EXPECTED DATA
004514 012700 000015      MOV      #15,R0      ;13 SPEEDS WILL BE TESTED
004520 012701 002103      MOV      #2103,R1      ;FIRST SPEED =50 BAUD,
                                           ;8 BITS PER CHARACTER
004524 010577 011526      1$:      MOV      R5,@DHSCR      ;SELECT LINE 0
004530 010177 011526      MOV      R1,@DHLPR      ;SET LINE SPEED AND
                                           ;CHARACTER LENGTH
004534 012777 016364 011522      MOV      #TBUF,@DHBA      ;ADDRESS OF TRANSMITTER
                                           ;DATA BUFFER
004542 012777 177400 011516      MOV      #-400,@DHBC      ;400 (OCTAL) BYTES
                                           ;WILL BE TRANSMITTED
004550 012777 000001 011512      MOV      #1,@DHBAR      ;START TRANSMITTER
004556 105777 011474      2$:      TSTB      @DHSCR      ;WAIT FOR DATA TO BE RECEIVED
004562 100375      BPL      2$
004564 017703 011470      MOV      @DHNR,R3      ;GET RECEIVED DATA
004570 020367 011564      CMP      R3,RDATA      ;COMPER EXPECTED AND RECEIVED DATA
004574 001407      BEQ      3$
004576 005077 011466      CLR      @DHBAR      ;STOP TRANSMITTER
004602      HLT      1      ;DATA ERROR
004602 104001      EMT      1
004604 104410      SCOPE1
004606 012777 000001 011454      MOV      #1,@DHBAR      ;CHECK FOR LOOP AT CURRENT SPEED
004614 105267 011540      3$:      INCB      RDATA      ;RESTART TRANSMITTER
004620 001356      BNE      2$      ;UPDATA EXPECTED DATA
004622 062701 002100      ADD      #2100,R1      ;UPDATE LINE SPEED
004626 005202      INC      R2      ;UPDATE SPEED CODE
004630 005300      DEC      R0
004632 001334      BNE      1$
004634 104400      4$:      SCOPE
000001      LINE=LINE+1
000002      BITX=BITX+BITX
004636      SDATA2 \LINE,\BITX

                                           ;SINGLE LINE DATA TEST
                                           ;TRANSMIT A BLOCK OF 400 (OCTAL) CHARACTERS ON LINE 1
                                           ;CHARATER LENGTH IS 8 BITS
                                           ;LINE SPEED WILL START AT 50 BAUD AND BE INCREMENTED
                                           ;TO 9600 BAUD.
                                           ;A BLOCK OF 400 CHARACTERS WILL BE TRANSMITTED
                                           ;AT EACH SPEED

004636      TS \XN,1,4$,1$
004636 012767 000340 173132      T22:      MOV      #340,PS      ;DISABLE ALL INTERRUPTS
004644 012767 000001 011452      MOV      #1,ICOUNT      ;SET UP FOR 1 ITERATIONS
004652 012767 005032 011440      MOV      #4$,ESCAPE      ;SET UP TO ESCAPE TO NEXT TEST
                                           ;IF NB <1$>
004660 012767 004722 011434      MOV      #1$,FREEZ1      ;SET UP TO LOOP WITH DATA      ; 3
                                           ;ENDC
                                           XN=XN+1
004666 012777 004000 011362      MOV      @BIT11,@DHSCR      ;MASTER CLEAR INTERFACE
004674 012702 000001      MOV      #1,R2      ;FIRST SPEED CODE
004700 012705 000001      MOV      #1,R5      ;LINE 1 WILL BE TESTED
004704 012767 100400 011446      MOV      #1*400+100000,RDATA      ;SET EXPECTED LINE NUMBER

```

```

004712 012700 000015      MOV    #15,R0      ;AND VALID DATA FLAG
004716 012701 002103      MOV    #2103,R1    ;EXPECTED DATA
                                ;13 SPEEDS WILL BE TESTED
004722 010577 011330      1$:  MOV    R5,@DHSCR  ;FIRST SPEED =50 BAUD,
004726 010177 011330      MOV    R1,@DHLPR   ;8 BITS PER CHARACTER
                                ;SELECT LINE 1
004732 012777 016364 011324  MOV    #TBUF,@DHBA ;SET LINE SPEED AND
                                ;CHARACTER LENGTH
004740 012777 177400 011320  MOV    #-400,@DHBC ;ADDRESS OF TRANSMITTER
                                ;DATA BUFFER
004746 012777 000002 011314  MOV    #2,@DHBAR  ;400 (OCTAL) BYTES
004754 105777 011276      2$:  TSTB    @DHSCR   ;WILL BE TRANSMITTED
004760 100375              BPL     2$         ;START TRANSMITTER
004762 017703 011272      MOV    @DHNR,R3     ;WAIT FOR DATA TO BE RECEIVED
004766 020367 011366      CMP     R3,RDATA    ;GET RECEIVED DATA
004772 001407              BEQ     3$         ;COMPER EXPECTED AND RECEIVED DATA
004774 005077 011270      CLR     @DHBAR      ;STOP TRANSMITTER
005000              HLT     1                 ;DATA ERROR
005000 104001              EMT     1
005002 104410              SCOPE1
005004 012777 000002 011256  MOV    #2,@DHBAR  ;CHECK FOR LOOP AT CURRENT SPEED
005012 105267 011342      3$:  INCB    RDATA    ;RESTART TRANSMITTER
005016 001356              BNE     2$         ;UPDATA EXPECTED DATA
005020 062701 002100      ADD     #2100,R1     ;UPDATE LINE SPEED
005024 005202              INC     R2         ;UPDATE SPEED CODE
005026 005300              DEC     R0
005030 001334              BNE     1$
005032 104400      4$:  SCOPE
                        LINE=LINE+1
                        BITX=BITX+BITX
                        SDATA2 \LINE,\BITX
005034

                                ;SINGLE LINE DATA TEST
                                ;TRANSMIT A BLOCK OF 400 (OCTAL) CHARACTERS ON LINE 2
                                ;CHARATER LENGTH IS 8 BITS
                                ;LINE SPEED WILL START AT 50 BAUD AND BE INCREMENTED
                                ;TO 9600 BAUD.
                                ;A BLOCK OF 400 CHARACTERS WILL BE TRANSMITTED
                                ;AT EACH SPEED

005034      TS \XN,1,4$,1$
005034 012767 000340 172734 T23:  MOV    #340,PS      ;DISABLE ALL INTERRUPTS
005042 012767 000001 011254      MOV    #1,ICOUNT   ;SET UP FOR 1 ITERATTIONS
005050 012767 005230 011242      MOV    #4$,ESCAPE  ;SET UP TO ESCAPE TO NEXT TEST
                                .IF NB <1$>
005056 012767 005120 011236      MOV    #1$,FREEZ1  ;SET UP TO LOOP WITH DATA      : 3
                                .ENDC
                                XN=XN+1
005064 012777 004000 011164      MOV    @BIT11,@DHSCR ;MASTER CLEAR INTERFACE
005072 012702 000001              MOV    #1,R2      ;FIRST SPEED CODE
005076 012705 000002              MOV    #2,R5      ;LINE 2 WILL BE TESTED
005102 012767 101000 011250      MOV    #2*400+100000,RDATA
                                ;SET EXPECTED LINE NUMBER
                                ;AND VALID DATA FLAG
                                ;EXPECTED DATA

```

```

005110 012700 000015      MOV    #15,R0      ;13 SPEEDS WILL BE TESTED
005114 012701 002103      MOV    #2103,R1    ;FIRST SPEED =50 BAUD,
                                ;8 BITS PER CHARACTER
005120 010577 011132      1$:  MOV    R5,0DHSCR    ;SELECT LINE 2
005124 010177 011132      MOV    R1,0DHLPR    ;SET LINE SPEED AND
                                ;CHARACTER LENGTH
005130 012777 016364 011126  MOV    #TBUF,0DHBA    ;ADDRESS OF TRANSMITTER
                                ;DATA BUFFER
005136 012777 177400 011122  MOV    #-400,0DHBC    ;400 (OCTAL) BYTES
                                ;WILL BE TRANSMITTED
005144 012777 000004 011116  2$:  MOV    #4,0DHBAR    ;START TRANSMITTER
005152 105777 011100      TSTB    0DHSCR        ;WAIT FOR DATA TO BE RECEIVED
005156 100375              BPL     2$
005160 017703 011074      MOV    0DHNRC,R3      ;GET RECEIVED DATA
005164 020367 011170      CMP     R3,RDATA      ;COMPER EXPECTED AND RECEIVED DATA
005170 001407              BEQ     3$
005172 005077 011072      CLR     0DHBAR        ;STOP TRANSMITTER
005176              HLT     1                    ;DATA ERROR
005176 104001              EMT     1
005200 104410              SCOPE1
005202 012777 000004 011060  3$:  MOV    #4,0DHBAR    ;CHECK FOR LOOP AT CURRENT SPEED
005210 105267 011144      INCB    RDATA        ;RESTART TRANSMITTER
005214 001356              BNE     2$            ;UPDATE EXPECTED DATA
005216 062701 002100      ADD     #2100,R1      ;UPDATE LINE SPEED
005222 005202              INC     R2            ;UPDATE SPEED CODE
005224 005300              DEC     R0
005226 001334              BNE     1$
005230 104400      4$:  SCOPE
005230 000003      LINE=LINE+1
005230 000010      BITX=BITX+BITX
005232      SDATA2 \LINE,\BITX

                                ;SINGLE LINE DATA TEST
                                ;TRANSMIT A BLOCK OF 400 (OCTAL) CHARACTERS ON LINE 3
                                ;CHARATER LENGTH IS 8 BITS
                                ;LINE SPEED WILL START AT 50 BAUD AND BE INCREMENTED
                                ;TO 9600 BAUD.
                                ;A BLOCK OF 400 CHARACTER, WILL BE TRANSMITTED
                                ;AT EACH SPEED

005232      TS \XN,1,4$,1$
005232 012767 000340 172536 T24:  MOV    #340,PS      ;DISABLE ALL INTERRUPTS
005240 012767 000001 011056      MOV    #1,ICOUNT    ;SET UP FOR 1 ITERATIONS
005246 012767 005426 011044      MOV    #4$,ESCAPE    ;SET UP TO ESCAPE TO NEXT TEST
                                .IF #8 <1$>
005254 012767 005316 011040      MOV    #1$,FREEZ1    ;SET UP TO LOOP WITH DATA      ; 3
                                .ENDC
                                XN=XN+1
005262 000025              MOV    #BIT11,0DHSCR    ;MASTER CLEAR INTERFACE
005270 012702 000001 010766      MOV    #1,R2        ;FIRST SPEED CODE
005274 012705 000003              MOV    #3,R5        ;LINE 3 WILL BE TESTED
005300 012767 101400 011052      MOV    #3*400+100000,RDATA
                                ;SET EXPECTED LINE NUMBER
                                ;AND VALID DATA FLAG
                                ;EXPECTED DATA
005306 012700 000015      MOV    #15,R0      ;13 SPEEDS WILL BE TESTED
005312 012701 002103      MOV    #2103,R1    ;FIRST SPEED =50 BAUD.

```

```

005316 010577 010734      1$:  MOV    R5, @DHSCR      ;8 BITS PER CHARACTER
005322 010177 010734      MCX    R1, @DHLPR      ;SELECT LINE 3
                                ;SET LINE SPEED AND
                                ;CHARACTER LENGTH
005326 012777 016364 010730      MOV    @TBUF, @DHBA      ;ADDRESS OF TRANSMITTER
                                ;DATA BUFFER
005334 012777 177400 010724      MOV    #-400, @DHBC      ;400 (OCTAL) BYTES
                                ;WILL BE TRANSMITTED
                                ;START TRANSMITTER
005342 012777 000010 010720      MOV    #10, @DHBAR      ;WAIT FOR DATA TO BE RECEIVED
005350 105777 010702      2$:  TSTB    @DHSCR
005354 100375                BPL     2$
005356 017703 010676      MOV    @DHNR, R3      ;GET RECEIVED DATA
005362 020367 010772      CMP     R3, RDATA      ;COMPER EXPECTED AND RECEIVED DATA
005366 001407                BEQ     3$
005370 005077 010674      CLR     @DHBAR
005374                HLT     1
                                ;STOP TRANSMITTER
                                ;DATA ERROR
005374 104001                EMT     1
005376 104410                SCOPE1
005400 012777 000010 010662      MOV    #10, @DHBAR      ;CHECK FOR LOOP AT CURRENT SPEED
005406 105267 010746      3$:  INCB    RDATA      ;RESTART TRANSMITTER
                                ;UPDATA EXPECTED DATA
005412 001356                BNE     2$
005414 062701 002100      ADD     @2100, R1      ;UPDATE LINE SPEED
005420 005202                INC     R2          ;UPDATE SPEED CODE
005422 005300                DEC     R0
005424 001334                BNE     1$
005426 104400      4$:  SCOPE
                                LINE=LINE+1
                                BITX=BITX+BITX
                                SDATA2 \LINE, \BITX
005430                ;SINGLE LINE DATA TEST
                                ;TRANSMIT A BLOCK OF 400 (OCTAL) CHARACTERS ON LINE 4
                                ;CHARATER LENGTH IS 8 BITS
                                ;LINE SPEED WILL START AT 50 BAUD AND BE INCREMENTED
                                ;TO 9600 BAUD.
                                ;A BLOCK OF 400 CHARACTERS WILL BE TRANSMITTED
                                ;AT EACH SPEED

005430      TS \XN, 1, 4$, 1$
005430 012767 000340 172340      T25:  MOV    #340, PS      ;DISABLE ALL INTERRUPTS
005436 012767 000001 010660      MOV    #1, ICOUNT      ;SET UP FOR 1 ITERATIONS
005444 012767 005624 010646      MOV    #4$, ESCAPE      ;SET UP TO ESCAPE TO NEXT TEST
                                .IF NB <1$>
005452 012767 005514 010642      MOV    #1$, FREEZ1      ;SET UP TO LOOP WITH DATA      ; 3
                                .ENDC
                                XN=XN+1
005460 012777 004000 010570      MOV    @BIT11, @DHSCR      ;MASTER CLEAR INTERFACE
005466 012702 000001                MOV    #1, R2          ;FIRST SPEED CODE
005472 012705 000004                MOV    #4, R5          ;LINE 4 WILL BE TESTED
005476 012767 102000 010654      MOV    #4*400+100000, RDATA
                                ;SET EXPECTED LINE NUMBER
                                ;AND VALID DATA FLAG
                                ;EXPECTED DATA
005504 012700 000015                MOV    #15, R0      ;13 SPEEDS WILL BE TESTED
005510 012701 002103                MOV    #2103, R1     ;FIRST SPEED =50 BAUD.
                                ;8 BITS PER CHARACTER
005514 010577 010536      1$:  MOV    R5, @DHSCR      ;SELECT LINE 4

```

```

005520 010177 010536      MOV      R1,@DHLPR      ;SET LINE SPEED AND
005524 012777 016364 010532      MOV      @TBUF,@DHBA      ;CHARACTER LENGTH
005532 012777 177400 010526      MOV      @-400,@DHBC      ;ADDRESS OF TRANSMITTER
005540 012777 000020 010522      MOV      @20,@DHBAR      ;DATA BUFFER
005546 105777 010504      2$:      TSTB      @DHSCR      ;400 (OCTAL) BYTES
005552 100375      BPL      2$      ;WILL BE TRANSMITTED
005554 017703 010500      MOV      @DHNR,R3      ;START TRANSMITTER
005560 020367 010574      CMP      R3,RDATA      ;WAIT FOR DATA TO BE RECEIVED
005564 001407      BEQ      3$      ;GET RECEIVED DATA
005566 005077 010476      CLR      @DHBAR      ;COMPER EXPECTED AND RECEIVED DATA
005572      HLT      1      ;STOP TRANSMITTER
005572 104001      EMT      1      ;DATA ERROR
005574 104410      SCOPE1      ;CHECK FOR LOOP AT CURRENT SPEED
005576 012777 000020 010464      MOV      @20,@DHBAR      ;RESTART TRANSMITTER
005604 105267 010550      3$:      INCB      RDATA      ;UPDATA EXPECTED DATA
005610 001356      BNE      2$
005612 062701 002100      ADD      @2100,R1      ;UPDATE LINE SPEED
005616 005202      INC      R2      ;UPDATE SPEED CODE
005620 005300      DEC      R0
005622 001334      BNE      1$
005624 104400      4$:      SCOPE      ;SINGLE LINE DATA TEST
000005      LINE=LINE+1      ;TRANSMIT A BLOCK OF 400 (OCTAL) CHARACTERS ON LINE 5
000040      BITX=BITX+BITX      ;CHARATER LENGTH IS 8 BITS
005626      SDATA2 \LINE,\BITX      ;LINE SPEED WILL START AT 50 BAUD AND BE INCREMENTED
                                ;TO 9600 BAUD.
                                ;A BLOCK OF 400 CHARACTERS WILL BE TRANSMITTED
                                ;AT EACH SPEED

005626      TS \XN,1,4$,1$
005626 012767 000340 172142      T26:      MOV      @340,PS      ;DISABLE ALL INTERRUPTS
005634 012767 000001 010462      MOV      @1,ICOUNT      ;SET UP FOR 1 ITERATIONS
005642 012767 006022 010450      MOV      @4$,ESCAPE      ;SET UP TO ESCAPE TO NEXT TEST
                                ;IF NB <1$>
005650 012767 005712 010444      MOV      @1$,FREEZ1      ;SET UP TO LOOP WITH DATA      ; 3
                                .ENDC
                                XN=XN+1
005656 012777 004000 010372      MOV      @BIT11,@DHSCR      ;MASTER CLEAR INTERFACE
005664 012702 000001      MOV      @1,R2      ;FIRST SPEED CODE
005670 012705 000005      MOV      @5,R5      ;LINE 5 WILL BE TESTED
005674 012767 102400 010456      MOV      @5*400+100000,RDATA      ;SET EXPECTED LINE NUMBER
                                ;AND VALID DATA FLAG
                                ;EXPECTED DATA
005702 012700 000015      MOV      @15,R0      ;13 SPEEDS WILL BE TESTED
005706 012701 002103      MOV      @2103,R1      ;FIRST SPEED =50 BAUD,
                                ;8 BITS PER CHARACTER
005712 010577 010340      1$:      MOV      R5,@DHSCR      ;SELECT LINE 5
005716 010177 010340      MOV      R1,@DHLPR      ;SET LINE SPEED AND
                                ;CHARACTER LENGTH

```

```

005722 012777 016364 010334      MOV      #TBUF, @DHBA      ; ADDRESS OF TRANSMITTER
005730 012777 177400 010330      MOV      #-400, @DHBC      ; DATA BUFFER
005736 012777 000040 010324      MOV      #40, @DHBAR      ; 400 (OCTAL) BYTES
005744 105777 010306      2$: TSTB      @DHSCR      ; WILL BE TRANSMITTED
005750 100375      BPL      2$      ; START TRANSMITTER
005752 017703 010302      MOV      @DHNR, R3      ; GET RECEIVED DATA
005756 020367 010376      CMP      R3, RDATA      ; COMPARE EXPECTED AND RECEIVED DATA
005762 001407      BEQ      3$      ; STOP TRANSMITTER
005764 005077 010300      CLR      @DHBAR      ; DATA ERROR
005770      HLT      1
005770      EMT      1
005772 104410      SCOPE1
005774 012777 000040 010266      MOV      #40, @DHBAR      ; CHECK FOR LOOP AT CURRENT SPEED
006002 105267 010352      3$: INCB      RDATA      ; RESTART TRANSMITTER
006006 001356      BNE      2$      ; UPDATE EXPECTED DATA
006010 062701 002100      ADD      #2100, R1      ; UPDATE LINE SPEED
006014 005202      INC      R2      ; UPDATE SPEED CODE
006016 005300      DEC      R0
006020 001334      BNE      1$
006022 104400      4$: SCOPE
      000006      LINE=LINE+1
      000100      BITX=BITX+BITX
006024      SDATA2 \LINE, \BITX

      ; SINGLE LINE DATA TEST
      ; TRANSMIT A BLOCK OF 400 (OCTAL) CHARACTERS ON LINE 6
      ; CHARACTER LENGTH IS 8 BITS
      ; LINE SPEED WILL START AT 50 BAUD AND BE INCREMENTED
      ; TO 9600 BAUD.
      ; A BLOCK OF 400 CHARACTERS WILL BE TRANSMITTED
      ; AT EACH SPEED

006024      TS \XN, 1, 4$, 1$
006024 012767 000340 171744      T27: MOV      #340, PS      ; DISABLE ALL INTERRUPTS
006032 012767 000001 010264      MOV      #1, ICOUNT      ; SET UP FOR 1 ITERATIONS
006040 012767 006220 010252      MOV      #4$, ESCAPE      ; SET UP TO ESCAPE TO NEXT TEST
      .IF NB <1$>
006046 012767 006110 010246      MOV      #1$, FREEZ1      ; SET UP TO LOOP WITH DATA      ; 3
      .ENDC
      XN=XN+1
006054 012777 004000 010174      MOV      @BIT11, @DHSCR      ; MASTER CLEAR INTERFACE
006062 012702 000001      MOV      #1, R2      ; FIRST SPEED CODE
006066 012705 000006      MOV      #6, R5      ; LINE 6 WILL BE TESTED
006072 012767 103000 010260      MOV      #6*400+100000, RDATA
      ; SET EXPECTED LINE NUMBER
      ; AND VALID DATA FLAG
      ; EXPECTED DATA
      ; 13 SPEEDS WILL BE TESTED
      ; FIRST SPEED = 50 BAUD.
      ; 8 BITS PER CHARACTER
006100 012700 000015      MOV      #15, R0      ; SELECT LINE 6
006104 012701 002103      MOV      #2103, R1      ; SET LINE SPEED AND
      ; CHARACTER LENGTH
006110 010577 010142      1$: MOV      R5, @DHSCR      ; ADDRESS OF TRANSMITTER
006114 010177 010142      MOV      R1, @DHLPR      ; DATA BUFFER
006120 012777 016364 010136      MOV      #TBUF, @DHBA

```

```

006126 012777 177400 010132      MOV      # 400,@DHBC      ;400 (OCTAL) BYTES
;400 (OCTAL) BYTES
006134 012777 000100 010126      MOV      #100,@DHBAR    ;WILL BE TRANSMITTED
;WILL BE TRANSMITTED
006142 105777 010110      2$:    TSTB      @DHSCR      ;START TRANSMITTER
;START TRANSMITTER
006146 100375      BPL      2$      ;WAIT FOR DATA TO BE RECEIVED
;WAIT FOR DATA TO BE RECEIVED
006150 017703 010104      MOV      @DHNR,R3      ;GET RECEIVED DATA
;GET RECEIVED DATA
006154 020367 010200      CMP      R3,RDATA    ;COMPER EXPECTED AND RECEIVED DATA
;COMPER EXPECTED AND RECEIVED DATA
006160 001407      BEQ      3$      ;
;
006162 005077 010102      CLR      @DHBAR    ;STOP TRANSMITTER
;STOP TRANSMITTER
006166      HLT      1      ;DATA ERROR
;DATA ERROR
006166 104001      EMT      1      ;
;
006170 104410      SCOPE1      ;CHECK FOR LOOP AT CURRENT SPEED
;CHECK FOR LOOP AT CURRENT SPEED
006172 012777 000100 010070      MOV      #100,@DHBAR    ;RESTART TRANSMITTER
;RESTART TRANSMITTER
006200 105267 010154      3$:    INCB      RDATA      ;UPDATA EXPECTED DATA
;UPDATA EXPECTED DATA
006204 001356      BNE      2$      ;
;
006206 062701 002100      ADD      #2100,R1      ;UPDATE LINE SPEED
;UPDATE LINE SPEED
006212 005202      INC      R2      ;UPDATE SPEED CODE
;UPDATE SPEED CODE
006214 005300      DEC      R0      ;
;
006216 001334      BNE      1$      ;
;
006220 104400      4$:    SCOPE      ;
;
000007      LINE=LINE+1      ;
;
000200      BITX=BITX+BITX      ;
;
006222      SDATA2 \LINE,\BITX      ;
;

;SINGLE LINE DATA TEST
;TRANSMIT A BLOCK OF 400 (OCTAL) CHARACTERS ON LINE 7
;CHARATER LENGTH IS 8 BITS
;LINE SPEED WILL START AT 50 BAUD AND BE INCREMENTED
;TO 9600 BAUD.
;A BLOCK OF 400 CHARACTERS WILL BE TRANSMITTED
;AT EACH SPEED

006222      TS \XN,1,4$,1$      ;
;
006222 012767 000340 171546      T30:    MOV      #340,PS      ;DISABLE ALL INTERRUPTS
;DISABLE ALL INTERRUPTS
006230 012767 000001 010066      MOV      #1,ICOUNT    ;SET UP FOR 1 ITERATIONS
;SET UP FOR 1 ITERATIONS
006236 012767 006416 010054      MOV      #4$,ESCAPE    ;SET UP TO ESCAPE TO NEXT TEST
;SET UP TO ESCAPE TO NEXT TEST

006244 012767 006306 010050      .IF NB <1$>      ;
;
000031      MOV      #1$,FREEZ1      ;SET UP TO LOOP WITH DATA      : 3
;SET UP TO LOOP WITH DATA      : 3
006252 012777 004000 007776      .ENDC      ;
;
006260 012702 000001      XN=XN+1      ;
;
006264 012705 000007      MOV      #BIT11,@DHSCR    ;MASTER CLEAR INTERFACE
;MASTER CLEAR INTERFACE
006270 012767 103400 010062      MOV      #1,R2      ;FIRST SPEED CODE
;FIRST SPEED CODE
MOV      #7,R5      ;LINE 7 WILL BE TESTED
;LINE 7 WILL BE TESTED
MOV      #7*400+100000,RDATA      ;
;
;SET EXPECTED LINE NUMBER
;AND VALID DATA FLAG
;EXPECTED DATA
;13 SPEEDS WILL BE TESTED
;FIRST SPEED =50 BAUD,
;8 BITS PER CHARACTER
;SELECT LINE 7
;SET LINE SPEED AND
;CHARACTER LENGTH
;ADDRESS OF TRANSMITTER
;DATA BUFFER
;400 (OCTAL) BYTES
;WILL BE TRANSMITTED

006276 012700 000015      MOV      #15,R0      ;
;
006302 012701 002103      MOV      #2103,R1      ;
;

006306 010577 007744      1$:    MOV      R5,@DHSCR    ;
;
006312 010177 007744      MOV      R1,@DHLPR    ;
;

006316 012777 016364 007740      MOV      #TBUF,@DHBA      ;
;

006324 012777 177400 007734      MOV      #-400,@DHBC      ;
;

```

```

006332 012777 000200 007730      MOV    #200, @DHBAR      ;START TRANSMITTER
006340 105777 007712      2$:    TSTB    @DHSCR      ;WAIT FOR DATA TO BE RECEIVED
006344 100375              BPL      2$
006346 017703 007706      MOV    @DHNR, R3      ;GET RECEIVED DATA
006352 020367 010002      CMP     R3, RDATA      ;COMPER EXPECTED AND RECEIVED DATA
006356 001407              BEQ     3$
006360 005077 007704      CLR     @DHBAR      ;STOP TRANSMITTER
006364              HLT      1      ;DATA ERROR
006364 104001              EMT      1
006366 104410              SCOPE1
006370 012777 000200 007672      MOV    #200, @DHBAR      ;CHECK FOR LOOP AT CURRENT SPEED
006376 105267 007756      3$:    INCB    RDATA      ;RESTART TRANSMITTER
006402 001356              BNE     2$      ;UPDATA EXPECTED DATA
006404 062701 002100      ADD     #2100, R1      ;UPDATE LINE SPEED
006410 005202              INC     R2      ;UPDATE SPEED CODE
006412 005300              DEC     R0
006414 001334              BNE     1$
006416 104400              4$:    SCOPE
000010      LINE=LINE+1
000400      BITX=BITX+BITX
006420      SDATA2 \LINE, \BITX

;SINGLE LINE DATA TEST
;TRANSMIT A BLOCK OF 400 (OCTAL) CHARACTERS ON LINE 10
;CHARATER LENGTH IS 8 BITS
;LINE SPEED WILL START AT 50 BAUD AND BE INCREMENTED
;TC 9600 BAUD.
;A BLOCK OF 400 CHARACTERS WILL BE TRANSMITTED
;AT EACH SPEED

006420      TS \XN, 1, 4$, 1$
006420 012767 000340 171350      T31:    MOV    #340, PS      ;DISABLE ALL INTERRUPTS
006426 012767 000001 007670      MOV    #1, ICOUNT      ;SET UP FOR 1 ITERATIONS
006434 012767 006614 007656      MOV    #4$, ESCAPE      ;SET UP TO ESCAPE TO NEXT TEST
006442 012767 006504 007652      .IF NB <1$>
000032      MOV    #1$, FREEZ1      ;SET UP TO LOOP WITH DATA ; 3
006450 012777 004000 007600      .ENDC
006456 012702 000001      XN=XN+1
006462 012705 000010      MOV    #BIT11, @DHSCR      ;MASTER CLEAR INTERFACE
006466 012767 104000 007664      MOV    #1, R2      ;FIRST SPEED CODE
000010      MOV    #10, R5      ;LINE 10 WILL BE TESTED
000000      MOV    #10*400+100000, RDATA
006474 012700 000015      ;SET EXPECTED LINE NUMBER
006500 012701 002103      ;AND VALID DATA FLAG
000015      MOV    #15, R0      ;EXPECTED DATA
000003      MOV    #2103, R1      ;13 SPEEDS WILL BE TESTED
006504 010577 007546      ;FIRST SPEED =50 BAUD,
006510 010177 007546      1$:    MOV    R5, @DHSCR      ;8 BITS PER CHARACTER
000000      MOV    R1, @DHLPR      ;SELECT LINE 10
006514 012777 016364 007542      ;SET LINE SPEED AND
000000      MOV    #TBUF, @DHBA      ;CHARACTER LENGTH
006522 012777 177400 007536      ;ADDRESS OF TRANSMITTER
000000      MOV    #-400, @DHBC      ;DATA BUFFER
000000      ;400 (OCTAL) BYTES
006530 012777 000400 007532      ;WILL BE TRANSMITTED
006536 105777 007514      2$:    MOV    #400, @DHBAR      ;START TRANSMITTER
000000      TSTB    @DHSCR      ;WAIT FOR DATA TO BE RECEIVED

```



```

006542 100375      BPL      2$
006544 017703 007510      MOV      @DHNRC,R3      ;GET RECEIVED DATA
006550 020367 007604      CMP      R3,RDATA      ;COMPER EXPECTED AND RECEIVED DATA
006554 001407      BEQ      3$
006556 005077 007506      CLR      @DHBAR      ;STOP TRANSMITTER
006562      HLT      1      ;DATA ERROR
006562 104001      EMT      1
006564 104410      SCOPE1
006566 012777 000400 007474      MOV      #400,@DHBAR      ;CHECK FOR LOOP AT CURRENT SPEED
006574 105267 007560      3$: INCB      RDATA      ;RESTART TRANSMITTER
006600 001356      BNE      2$      ;UPDATA EXPECTED DATA
006602 062701 002100      ADD      #2100,R1      ;UPDATE LINE SPEED
006606 005202      INC      R2      ;UPDATE SPEED CODE
006610 005300      DEC      R0
006612 001334      BNE      1$
006614 104400      4$: SCOPE
      000011      LINE=LINE+1
      001000      BITX=BITX+BITX
006616      SDATA2 \LINE,\BITX

      ;SINGLE LINE DATA TEST
      ;TRANSMIT A BLOCK OF 400 (OCTAL) CHARACTERS ON LINE 11
      ;CHARATER LENGTH IS 8 BITS
      ;LINE SPEED WILL START AT 50 BAUD AND BE INCREMENTED
      ;TO 9600 BAUD.
      ;A BLOCK OF 400 CHARACTERS WILL BE TRANSMITTED
      ;AT EACH SPEED

006616      TS \XN,1,4$,1$
006616 012767 000340 171152      T32: MOV      #340,PS      ;DISABLE ALL INTERRUPTS
006624 012767 000001 007472      MOV      #1,ICOUNT      ;SET UP FOR 1 ITERATIONS
006632 012767 007012 007460      MOV      #4$,ESCAPE      ;SET UP TO ESCAPE TO NEXT TEST
      .IF NB <1$>
006640 012767 006702 007454      MOV      #1$,FREEZ1      ;SET UP TO LOOP WITH DATA      ; 3
      .ENDC
      XN=XN+1
006646 012777 004000 007402      MOV      @BIT11,@DHSCR      ;MASTER CLEAR INTERFACE
006654 012702 000001      MOV      #1,R2      ;FIRST SPEED CODE
006660 012705 000011      MOV      #11,R5      ;LINE 11 WILL BE TESTED
006664 012767 104400 007466      MOV      #11*400+100000,RDATA
      ;SET EXPECTED LINE NUMBER
      ;AND VALID DATA FLAG
      ;EXPECTED DATA
      ;13 SPEEDS WILL BE TESTED
      ;FIRST SPEED =50 BAUD,
      ;8 BITS PER CHARACTER
006672 012700 000015      MOV      #15,R0      ;SELECT LINE 11
006676 012701 002103      MOV      #2103,R1      ;SET LINE SPEED AND
      ;CHARACTER LENGTH
006702 010577 007350      1$: MOV      R5,@DHSCR      ;ADDRESS OF TRANSMITTER
006706 010177 007350      MOV      R1,@DHLPR      ;DATA BUFFER
      ;400 (OCTAL) BYTES
      ;WILL BE TRANSMITTED
006712 012777 016364 007344      MOV      @TBUF,@DHBA      ;START TRANSMITTER
006720 012777 177400 007340      MOV      #-400,@DHBC      ;WAIT FOR DATA TO BE RECEIVED
      ;GET RECEIVED DATA
006726 012777 001000 007334      MOV      #1000,@DHBAR
006734 105777 007316      2$: TSTB      @DHSCR
006740 100375      BPL      2$
006742 017703 007312      MOV      @DHNRC,R3

```

```

006746 020367 007406      CMP      R3,RDATA      ;COMPER EXPECTED AND RECEIVED DATA
006752 001407              BEQ       3$
006754 005077 007310      CLR      @DHBAR      ;STOP TRANSMITTER
006760              HLT       1              ;DATA ERROR
006760 104001              EMT       1
006762 104410              SCOPE1
006764 012777 001000 007276 3$: MOV     #1000,@DHBAR      ;CHECK FOR LOOP AT CURREN' SPEED
006772 105267 007362      INCB     RDATA      ;RESTART TRANSMITTER
006776 001356              BNE      2$      ;UPDATA EXPECTED DATA
007000 062701 002100      ADD      #2100,R1      ;UPDATE LINE SPEED
007004 005202              INC      R2      ;UPDATE SPEED CODE
007006 005300              DEC      R0
007010 001334              BNE      1$
007012 104400              4$: SCOPE
      000012      LINE=LINE+1
      002000      BITX=BITX+BITX
007014      SDATA2 \LINE,\BITX

      ;SINGLE LINE DATA TEST
      ;TRANSMIT A BLOCK OF 400 (OCTAL) CHARACTERS ON LINE 12
      ;CHARATER LENGTH IS 8 BITS
      ;LINE SPEED WILL START AT 50 BAUD AND BE INCREMENTED
      ;TO 9600 BAUD.
      ;A BLOCK OF 400 CHARACTERS WILL BE TRANSMITTED
      ;AT EACH SPEED

007014      TS \XN,1,4$,1$
007014 012767 000340 170754 T33: MOV     #340,PS      ;DISABLE ALL INTERRUPTS
007022 012767 000001 007274      MOV     #1,ICOUNT      ;SET UP FOR 1 ITERATIONS
007030 012767 007210 007262      MOV     #4$,ESCAPE      ;SET UP TO ESCAPE TO NEXT TEST
      .IF NB <1$>
007036 012767 007100 007256      MOV     #1$,FREEZ1      ;SET UP TO LOOP WITH DATA      ; 3
      .ENDC
      XN=XN+1
007044 012777 004000 007204      MOV     #BIT11,@DHSCR      ;MASTER CLEAR INTERFACE
007052 012702 000001          MOV     #1,R2      ;FIRST SPEED CODE
007056 012705 000012          MOV     #12,R5      ;LINE 12 WILL BE TESTED
007062 012767 105000 007270      MOV     #12*400+100000,RDATA
      ;SET EXPECTED LINE NUMBER
      ;AND VALID DATA FLAG
      ;EXPECTED DATA
      ;13 SPEEDS WILL BE TESTED
      ;FIRST SPEED =50 BAUD.
      ;8 BITS PER CHARACTER
      ;SELECT LINE 12
      ;SET LINE SPEED AND
      ;CHARACTER LENGTH
      ;ADDRESS OF TRANSMITTER
      ;DATA BUFFER
      ;400 (OCTAL) BYTES
      ;WILL BE TRANSMITTED
      ;START TRANSMITTER
      ;WAIT FOR DATA TO BE RECEIVED

007070 012700 000015          MOV     #15,R0
007074 012701 002103          MOV     #2103,R1
      ;GET RECEIVED DATA
      ;COMPER EXPECTED AND RECEIVED DATA

007100 010577 007152      1$: MOV     R5,@DHSCR
007104 010177 007152      MOV     R1,@DHLPR
007110 012777 016364 007146      MOV     #TBUF,@DHBA
007116 012777 177400 007142      MOV     #-400,@DHBC
007124 012777 002000 007136      MOV     #2000,@DHBAR
007132 105777 007120      2$: TSTB     @DHSCR
007136 100375          BPL
007140 017703 007114          MOV     @DHNR,R3
007144 020367 007210      CMP      R3,RDATA
007150 001407          BEQ       3$

```

```

007152 005077 007112          CLR      @DHBAR          ;STOP TRANSMITTER
007156                                HLT      1          ;DATA ERROR
007156 104001          EMT      1
007160 104410          SCOPE1
007162 012777 002000 007100    MOV      #2000,@DHBAR      ;CHECK FOR LOOP AT CURRENT SPEED
007170 105267 007164          3$: INCB      RDATA          ;RESTART TRANSMITTER
007174 001356          BNE      2$          ;UPDATA EXPECTED DATA
007176 062701 002100          ADD      #2100,R1          ;UPDATE LINE SPEED
007202 005202          INC      R2          ;UPDATE SPEED CODE
007204 005300          DEC      R0
007206 001334          BNE      1$
007210 104400          4$: SCOPE
007210 000013          LINE=LINE+1
007210 004000          BITX=BITX+BITX
007212          SDATA2 \LINE,\BITX

          ;SINGLE LINE DATA TEST
          ;TRANSMIT A BLOCK OF 400 (OCTAL) CHARACTERS ON LINE 13
          ;CHARATER LENGTH IS 8 BITS
          ;LINE SPEED WILL START AT 50 BAUD AND BE INCREMENTED
          ;TO 9600 RAUD.
          ;A BLOCK OF 400 CHARACTERS WILL BE TRANSMITTED
          ;AT EACH SPEED

007212          TS \XN,1,4$,1$
007212 012767 000340 170556    T34: MOV      #340,PS          ;DISABLE ALL INTERRUPTS
007220 012767 000001 007076    MOV      #1,ICOUNT          ;SET UP FOR 1 ITERATIONS
007226 012767 007406 007064    MOV      #4$,ESCAPE          ;SET UP TO ESCAPE TO NEXT TEST
          .IF NB <1$>
007234 012767 007276 007060    MOV      #1$,FREEZ1          ;SET UP TO LOOP WITH DATA          ; 3
          .ENDC
          XN=XN+1
007242 012777 004000 007006    MOV      @BIT11,@DHSCR          ;MASTER CLEAR INTERFACE
007250 012702 000001          MOV      #1,R2          ;FIRST SPEED CODE
007254 012705 000013          MOV      #13,R5          ;LINE 13 WILL BE TESTED
007260 012767 105400 007072    MOV      #13*400+100000,RDATA
          ;SET EXPECTED LINE NUMBER
          ;AND VALID DATA FLAG
          ;EXPECTED DATA
          ;13 SPEEDS WILL BE TESTED
          ;FIRST SPEED =50 BAUD,
          ;8 BITS PER CHARACTER
          ;SELECT LINE 13
          ;SET LINE SPEED AND
          ;CHARACTER LENGTH
          ;ADDRESS OF TRANSMITTER
          ;DATA BUFFER
          ;400 (OCTAL) BYTES
          ;WILL BE TRANSMITTED
          ;START TRANSMITTER
          ;WAIT FOR DATA TO BE RECEIVED

007266 012700 000015          MOV      #15,R0
007272 012701 002103          MOV      #2103,R1
          ;GET RECEIVED DATA
          ;COMPER EXPECTED AND RECEIVED DATA

007276 010577 006754          1$: MOV      R5,@DHSCR
007302 010177 006754          MOV      R1,@DHLPR
          ;STOP TRANSMITTER
          ;DATA ERROR

007306 012777 016364 006750    MOV      #TBUF,@DH8A
007314 012777 177400 006744    MOV      #-400,@DH8C
          ;STOP TRANSMITTER
          ;DATA ERROR

007322 012777 004000 006740    MOV      #4000,@DHBAR
007330 105777 006722          2$: TSTB      @DHSCR
007334 100375          BPL      2$
007336 017703 006716          MOV      @DHNR3,R3
007342 020367 007012          CMP      R3,RDATA
007346 001407          BEQ      3$
007350 005077 006714          CLR      @DHBAR
007354          HLT      1

```

```

007354 104001          EMT      1
007356 104410          SCOPE1
007360 012777 004000 006702 3$: MOV    #4000, @DHBAR      ;CHECK FOR LOOP AT CURRENT SPEED
007366 105267 006766      INCB    RDATA      ;RESTART TRANSMITTER
007372 001356      BNE     2$      ;UPDATE EXPECTED DATA
007374 062701 002100      ADD     #2100, R1      ;UPDATE LINE SPEED
007400 005202      INC      R2      ;UPDATE SPEED CODE
007402 005300      DEC      R0
007404 001334      BNE     1$
007406 104400      4$:  SCOPE
      000014      LINE=LINE+1
      010000      BITX=BITX+BITX
007410      SDATA2 \LINE, \BITX

      ;SINGLE LINE DATA TEST
      ;TRANSMIT A BLOCK OF 400 (OCTAL) CHARACTERS ON LINE 14
      ;CHARACTER LENGTH IS 8 BITS
      ;LINE SPEED WILL START AT 50 BAUD AND BE INCREMENTED
      ;TO 9600 BAUD.
      ;A BLOCK OF 400 CHARACTERS WILL BE TRANSMITTED
      ;AT EACH SPEED

007410      1$ \XN, 1, 4$, 1$
007410 012767 000340 170360 T35:  MOV    #340, PS      ;DISABLE ALL INTERRUPTS
007416 012767 000001 006700      MOV    #1, ICOUNT    ;SET UP FOR 1 ITERATIONS
007424 012767 007604 006666      MOV    #4$, ESCAPE    ;SET UP TO ESCAPE TO NEXT TEST
      .IF NB <1$>
007432 012767 007474 006662      MOV    #1$, FREEZ1    ;SET UP TO LOOP WITH DATA      ; 3
      .ENDC
      XN=XN+1
007440 012777 004000 006610      MOV    #BIT11, @DHSCR    ;MASTER CLEAR INTERFACE
007446 012702 000001      MOV    #1, R2      ;FIRST SPEED CODE
007452 012705 000014      MOV    #14, R5      ;LINE 14 WILL BE TESTED
007456 012767 106000 006674      MOV    #14*400+100000, RDATA
      ;SET EXPECTED LINE NUMBER
      ;AND VALID DATA FLAG
      ;EXPECTED DATA
      ;13 SPEEDS WILL BE TESTED
      ;FIRST SPEED =50 BAUD,
      ;8 BITS PER CHARACTER
      ;SELECT LINE 14
      ;SET LINE SPEED AND
      ;CHARACTER LENGTH
      ;ADDRESS OF TRANSMITTER
      ;DATA BUFFER
      ;400 (OCTAL) BYTES
      ;WILL BE TRANSMITTED
      ;START TRANSMITTER
      ;WAIT FOR DATA TO BE RECEIVED

007464 012700 000015      MOV    #15, R0
007470 012701 002103      MOV    #2103, R1
      ;GET RECEIVED DATA
      ;COMPER EXPECTED AND RECEIVED DATA

007474 010577 006556      1$:  MOV    R5, @DHSCR
007500 010177 006556      MOV    R1, @DHLPR
      ;STOP TRANSMITTER
      ;DATA ERROR

007504 012777 016364 006552      MOV    #1BUF, @DHBA
007512 012777 177400 006546      MOV    #-400, @DHBC
      ;CHECK FOR LOOP AT CURRENT SPEED

007520 012777 010000 006542      MOV    #10000, @DHBAR
007526 105777 006524      2$:  TSTB    @DHSCR
007532 100375      BPL     2$
007534 017703 006520      MOV    @DHNR, R3
007540 020367 006614      CMP     R3, RDATA
007544 001407      BEQ     3$
007546 005077 006516      CLR     @DHBAR
007552      HLT      1
007552 104001      EMT      1
007554 104410      SCOPE1

```

```

007556 012777 010000 006504      MOV    #10000,@DHBAR      ;RESTART TRANSMITTER
007564 105267 006570      3$:    INCB   RDATA          ;UPDATA EXPECTED DATA
007570 001356      BNE    2$
007572 062701 002100      ADD    #2100,R1          ;UPDATE LINE SPEED
007576 005202      INC     R2              ;UPDATE SPEED CODE
007600 005300      DEC     R0
007602 001334      BNE    1$
007604 104400      4$:    SCOPE
      000015      LINE=LINE+1
      020000      BITX=BITX+BITX
007606      SDATA2 \LINE,\BITX

      ;SINGLE LINE DATA TEST
      ;TRANSMIT A BLOCK OF 400 (OCTAL) CHARACTERS ON LINE 15
      ;CHARATER LENGTH IS 8 BITS
      ;LINE SPEED WILL START AT 50 BAUD AND BE INCREMENTED
      ;TO 9600 BAUD.
      ;A BLOCK OF 400 CHARACTERS WILL BE TRANSMITTED
      ;AT EACH SPEED

007606      TS \XN,1,4$,1$
007606 012767 000340 170162      T36:    MOV    #340,PS          ;DISABLE ALL INTERRUPTS
007614 012767 000001 006502      MOV    #1,ICOUNT      ;SET UP FOR 1 ITERATIONS
007622 012767 010002 006470      MOV    #4$,ESCAPE      ;SET UP TO ESCAPE TO NEXT TEST

007630 012767 007672 006464      .IF NB <1$>
      MOV    #1$,FREEZ1          ;SET UP TO LOOP WITH DATA      ; 3
      .ENDC
      XN=XN+1

007636 012777 004000 006412      MOV    #BIT11,@DHSCR      ;MASTER CLEAR INTERFACE
007644 012702 000001      MOV    #1,R2          ;FIRST SPEED CODE
007650 012705 000015      MOV    #15,R5          ;LINE 15 WILL BE TESTED
007654 012767 106400 006476      MOV    #15*400+100000,RDATA

      ;SET EXPECTED LINE NUMBER
      ;AND VALID DATA FLAG
      ;EXPECTED DATA
      ;13 SPEEDS WILL BE TESTED
      ;FIRST SPEED =50 BAUD.
      ;8 BITS PER CHARACTER
      ;SELECT LINE 15
      ;SET LINE SPEED AND
      ;CHARACTER LENGTH
      ;ADDRESS OF TRANSMITTER
      ;DATA BUFFER
      ;400 (OCTAL) BYTES
      ;WILL BE TRANSMITTED
      ;START TRANSMITTER
      ;WAIT FOR DATA TO BE RECEIVED

007662 012700 000015      MOV    #15,R0
007666 012701 002103      MOV    #2103,R1

007672 010577 006360      1$:    MOV    R5,@DHSCR
007676 010177 006360      MOV    R1,@DHLPR

007702 012777 016364 006354      MOV    #TBUF,@DHBA
007710 012777 177400 006350      MOV    #-400,@DHBC

007716 012777 020000 006344      MOV    #20000,@DHBAR
007724 105777 006326      2$:    TSTB   @DHSCR
007730 100375      BPL    2$
007732 017703 006322      MOV    @DHNR3,R3
007736 020367 006416      CMP     R3,RDATA
007742 001407      BEQ    3$
007744 005077 006320      CLR     @DHBAR
007750      HLT     1
007750      EMT     1
007752 104410      SCOPE1
007754 012777 020000 006306      MOV    #20000,@DHBAR
007762 105267 006372      3$:    INCB   RDATA
      ;CHECK FOR LOOP AT CURRENT SPEED
      ;RESTART TRANSMITTER
      ;UPDATA EXPECTED DATA

```

```

007766 001356      BNE      2$
007770 062701 002100  ADD      #2100,R1      ;UPDATE LINE SPEED
007774 005202      INC      R2      ;UPDATE SPEED CODE
007776 005300      DEC      R0
010000 001334      BNE      1$
010002 104400      4$: SCOPE
      LINE=LINE+1
      BITX=BITX+BITX
010004 040000      SDATA2 \LINE,\BITX

      ;SINGLE LINE DATA TEST
      ;TRANSMIT A BLOCK OF 400 (OCTAL) CHARACTERS ON LINE 16
      ;CHARATER LENGTH IS 8 BITS
      ;LINE SPEED WILL START AT 50 BAUD AND BE INCREMENTED
      ;TO 9600 BAUD.
      ;A BLOCK OF 400 CHARACTERS WILL BE TRANSMITTED
      ;AT EACH SPEED

010004      TS \XN,1,4$,1$
010004 012767 000340 167764 T37: MOV      #340,PS      ;DISABLE ALL INTERRUPTS
010012 012767 000001 006304      MOV      #1,ICOUNT      ;SET UP FOR 1 ITERATIONS
010020 012767 010200 006272      MOV      #4$,ESCAPE      ;SET UP TO ESCAPE TO NEXT TEST

010026 012767 010070 006266      .IF NB <1$>
      MOV      #1$,FREEZ1      ;SET UP TO LOOP WITH DATA      ; 3
      .ENDC
      XN=XN+1

010034 012777 004000 006214      MOV      #BIT11,@DHSCR      ;MASTER CLEAR INTERFACE
010042 012702 000001      MOV      #1,R2      ;FIRST SPEED CODE
010046 012705 000016      MOV      #16,R5      ;LINE 16 WILL BE TESTED
010052 012767 107000 006300      MOV      #16*400+100000,RDATA

      ;SET EXPECTED LINE NUMBER
      ;AND VALID DATA FLAG
      ;EXPECTED DATA
      ;13 SPEEDS WILL BE TESTED
      ;FIRST SPEED =50 BAUD,
      ;8 BITS PER CHARACTER
      ;SELECT LINE 16
      ;SET LINE SPEED AND
      ;CHARACTER LENGTH
      ;ADDRESS OF TRANSMITTER
      ;DATA BUFFER
      ;400 (OCTAL) BYTES
      ;WILL BE TRANSMITTED
      ;START TRANSMITTER
      ;WAIT FOR DATA TO BE RECEIVED

010060 012700 000015      MOV      #15,R0
010064 012701 002103      MOV      #2103,R1

010070 010577 006162      1$: MOV      R5,@DHSCR
010074 010177 006162      MOV      R1,@DHLPR

      ;GET RECEIVED DATA
      ;COMPER EXPECTED AND RECEIVED DATA

010100 012777 016364 006156      MOV      #TBUF,@DHBA
010106 012777 177400 006152      MOV      #-400,@DHBC

      ;STOP TRANSMITTER
      ;DATA ERROR

010114 012777 040000 006146      MOV      #40000,@DHBAR
010122 105777 006130      2$: TSTB      @DHSCR
010126 100375      BPL      2$
010130 017703 006124      MOV      @DHNR,R3
010134 020367 006220      CMP      R3,RDATA
010140 001407      BEQ      3$
010142 005077 006122      CLR      @DHBAR
010146      HLT      1
010146 104001      EMT      1
010150 104410      SCOPE1
010152 012777 040000 006110      MOV      #40000,@DHBAR
010160 105267 006174      3$: INCB      RDATA
010164 001356      BNE      2$
010166 062701 002100      ADD      #2100,R1      ;UPDATE LINE SPEED

```

```

010172 005202          INC      R2          ;UPDATE SPEED CODE
010174 005300          DEC      R0
010176 001334          BNE      1$
010200 104400          4$: SCOPE
          000017      LINE=LINE+1
          100000      BITX=BITX+BITX
010202          SDATA2 \LINE,\BITX

          ;SINGLE LINE DATA TEST
          ;TRANSMIT A BLOCK OF 400 (OCTAL) CHARACTERS ON LINE 17
          ;CHARATER LENGTH IS 8 BITS
          ;LINE SPEED WILL START AT 50 BAUD AND BE INCREMENTED
          ;TO 9600 BAUD.
          ;A BLOCK OF 400 CHARACTERS WILL BE TRANSMITTED
          ;AT EACH SPEED

010202          TS \XN,1,4$,1'
010202 012767 000340 167566 T40: MOV      #340,PS          ;DISABLE ALL INTERRUPTS
010210 012767 000001 006106      MOV      #1,ICOUNT        ;SET UP FOR 1 ITERATIONS
010216 012767 010376 006074      MOV      #4$,ESCAPE        ;SET UP TO ESCAPE TO NEXT TEST
          .IF NB <1$>
010224 012767 010266 006070      MOV      #1$,FREEZ1        ;SET UP TO LOOP WITH DATA          ; 3
          .ENDC
          XN=XN+1
010232 000041          MOV      #BIT11,@DHSCR          ;MASTER CLEAR INTERFACE
010240 012772 004000 006016      MOV      #1,R2          ;FIRST SPEED CODE
010244 012705 000017          MOV      #17,R5          ;LINE 17 WILL BE TESTED
010250 012767 107400 006102      MOV      #17*400+100000,RDATA
          ;SET EXPECTED LINE NUMBER
          ;AND VALID DATA FLAG
          ;EXPECTED DATA
          ;13 SPEEDS WILL BE TESTED
          ;FIRST SPEED =50 BAUD,
          ;8 BITS PER CHARACTER
          ;SELECT LINE 17
          ;SET LINE SPEED AND
          ;CHARACTER LENGTH
          ;ADDRESS OF TRANSMITTER
          ;DATA BUFFER
          ;400 (OCTAL) BYTES
          ;WILL BE TRANSMITTED
          ;START TRANSMITTER
          ;WAIT FOR DATA TO BE RECEIVED

010256 012700 000015          MOV      #15,R0
010262 012701 002103          MOV      #2103,R1
          ;GET RECEIVED DATA
          ;COMPER EXPECTED AND RECEIVED DATA

010266 010577 005764          1$: MOV      R5,@DHSCR
010272 010177 005764          MOV      R1,@DHLPR
          ;STOP TRANSMITTER
          ;DATA ERROR

010276 012777 016364 005760      MOV      #TBUF,@DHBA
          ;CHECK FOR LOOP AT CURRENT SPEED
010304 012777 177400 005754      MOV      #-400,@DHBC
          ;RESTART TRANSMITTER
          ;UPDATA EXPECTED DATA

010312 012777 100000 005750      MOV      #100000,@DHBAR
010320 105777 005732          2$: TSTB      @DHSCR
010324 100375          BPL      2$
          ;UPDATE LINE SPEED
          ;UPDATE SPEED CODE
010326 017703 005726          MOV      @DHNR,R3
010332 020367 006022          CMP      R3,RDATA
010336 001407          BEQ      3$
010340 005077 005724          CLR      @DHBAR
010344          HLT      1
010344 104001          EMT      1
          ;CHECK FOR LOOP AT CURRENT SPEED
010346 104410          SCOPE1
010350 012777 100000 005712      MOV      #100000,@DHBAR
010356 105267 005776          3$: INCB      RDATA
010362 001356          BNE      2$
010364 062701 002100          ADD      #2100,R1
010370 005202          INC      R2
010372 005300          DEC      R0

```

```

010374 001334      BNE      1$
010376 104400      4$:      SCOPE
                                LINE=LINE+1
                                BITX=BITX+BITX
30      000020      LINE=0
31      000000      XLINE=LINE
32      000001      BITX=1
33      000001      XBIT=BITX
35      000020      .REPT    20
36      SDATA3      \LINE,\BITX
37      .NLIST
38      LINE=LINE+1
39      BITX=BITX+BITX
40      .LIST
41      .ENDR
010400      SDATA3      \LINE,\BITX

                                ;SINGLE LINE DATA TEST
                                ;TRANSMIT A BLOCK OF 400 (OCTAL) CHARACTERS ON LINE 0
                                ;LINE SPEED IS 9600 BAUD
                                ;CHARACTER LENGTH WILL START AT 5 BITS AND BE INCREMENTED
                                ;TO 8 BITS
                                ;A BLOCK OF 400 CHARACTERS WILL BE TRANSMITTED
                                ;AT EACH CHARACTER LENGTH

010400      TS \XN,1,4$,1$
010400 012767 000340 167370 T41:      MOV      #340,PS      ;DISABLE ALL INTERRUPTS
010406 012767 000001 005710      MOV      #1,ICOUNT      ;SET UP FOR 1 ITERATIONS
010414 012767 010616 005676      MOV      #4$,ESCAPE      ;SET UP TO ESCAPE TO NEXT TEST
                                .IF NB <1$>
010422 012767 010470 005672      MOV      #1$,FREEZ1      ;SET UP TO LOOP WITH DATA      ; 3
                                .ENDC
                                XN=XN+1
010430 012777 004000 005620      MOV      #BIT11,@DHSCR      ;MASTER CLEAR INTERFACE
010436 005004      CLR      R4      ;FIRST CHARACTER LENGTH CODE (5 BITS)
010440 012705 000000      MOV      #0,R5      ;LINE 0 WILL BE TESTED
010444 012767 100000 005706      MOV      #0*400+100000,RDATA
                                ;SET EXPECTED LINE NUMBER
                                ;AND VALID DATA FLAG
                                ;EXPECTED DATA
                                ;4CHARACTER LENGTHS
                                ;WILL BE TESTED
                                ;FIRST CHARACTER LENGTH =5 BITS..
                                ;LINE SPEED =9600 BAUD
                                ;40 CHARACTERS AT 5 BITS
                                ;SELECT LINE 0

010452 012700 000004      MOV      #4,R0
010456 012701 033500      MOV      #33500,R1
                                ;SET LINE SPEED AND
                                ;CHARACTER LENGTH
                                ;ADDRESS OF TRANSMITTER
                                ;DATA BUFFER
                                ;400 (OCTAL) BYTES
                                ;WILL BE TRANSMITTED
                                ;START TRANSMITTER
                                ;WAIT FOR DATA TO BE RECEIVED

010462 012767 177740 005672      MOV      #-40,BYTCNT
010470 010577 005562      1$:      MOV      R5,@DHSCR
010474 016702 005662      MOV      BYTCNT,R2
010500 005402      NEG      R2
010502 010177 005554      MOV      R1,@DHLPR
                                ;SET LINE SPEED AND
                                ;CHARACTER LENGTH
                                ;ADDRESS OF TRANSMITTER
                                ;DATA BUFFER
                                ;400 (OCTAL) BYTES
                                ;WILL BE TRANSMITTED
                                ;START TRANSMITTER
                                ;WAIT FOR DATA TO BE RECEIVED

010506 012777 016364 005550      MOV      #TBUF,@DHBA
010514 016777 005642 005544      MOV      BYTCNT,@DHBC
010522 012777 000001 005540      MOV      #1,@DHBAR
010530 105777 005522      2$:      TSTB      @DHSCR
010534 100375      BPL      2$

```



```

010536 017703 005516      MOV      @DHNRC,R3      ;GET RECEIVED DATA
010542 020367 005612      CMP      R3,RDATA      ;COMPER EXPECTED AND RECEIVED DATA
010546 001407              BEQ      3$
010550 005077 005514      CLR      @DHBAR      ;STOP TRANSMITTER
010554              HLT      2      ;DATA ERROR
010554 104002              EMT      2
010556 104410              SCOPE1
010560 012777 000001 005502 3$: MOV      @1,@DHBAR      ;CHECK FOR LOOP AT CURRENT SPLEED
010566 105267 005566      INCB      RDATA      ;RESTART TRANSMITTER
010572 005302              DEC      R2      ;UPDATA EXPECTED DATA
010574 001355              BNE      2$
010576 105067 005556      CLRB      RDATA
                                ;INITIALIZE EXPECTED
                                ;RECEIVED DATA
                                ;UPDATA CHARACTER LENGTH
010602 005201              INC      R1
010604 005204              INC      R4
010606 006367 005550      ASL      BYTCNT
010612 005300              DEC      R0
010614 001325              BNE      1$
010616 104400              4$: SCOPE
                                LINE=LINE+1
                                BITX=BITX+BITX
                                SDATA3 \LINE,\BITX
                                ;SINGLE LINE DATA TEST
                                ;TRANSMIT A BLOCK OF 400 (OCTAL) CHARACTERS ON LINE 1
                                ;LINE SPEED IS 9600 BAUD
                                ;CHARACTER LENGTH WILL START AT 5 BITS AND BE INCREMENTED
                                ;TO 8 BITS
                                ;A BLOCK OF 400 CHARACTERS WILL BE TRANSMITTED
                                ;AT EACH CHARACTER LENGTH
010620              TS \XN,1,4$,1$
010620 012767 000340 167150 T42: MOV      @340,PS      ;DISABLE ALL INTERRUPTS
010626 012767 000001 005470      MOV      @1,ICOUNT      ;SET UP FOR 1 ITERATIONS
010634 012767 011036 005456      MOV      @4$,ESCAPE      ;SET UP TO ESCAPE TO NEXT TEST
                                .IF NB <1$>
010642 012767 010710 005452      MOV      @1$,FREEZ1      ;SET UP TO LOOP WITH DATA      ; 3
                                .ENDC
                                XN=XN+1
010650 012777 004000 005400      MOV      @BIT11,@DHSCR      ;MASTER CLEAR INTERFACE
010656 005004              CLR      R4      ;FIRST CHARACTER LENGTH CODE (5 BITS)
010660 012705 000001              MOV      @1,R5      ;LINE 1 WILL BE TESTED
010664 012767 100400 005466      MOV      @1*400+100000,RDATA
                                ;SET EXPECTED LINE NUMBER
                                ;AND VALID DATA FLAG
                                ;EXPECTED DATA
                                ;4CHARACTER LENGTHS
                                ;WILL BE TESTED
                                ;FIRST CHARACTER LENGTH =5 BITS..
                                ;LINE SPEED =9600 BAUD
                                ;40 CHARACTERS AT 5 BITS
                                ;SELECT LINE 1
010672 012700 000004              MOV      @4,R0
010676 012701 033500              MOV      @33500,R1
010702 012767 177740 005452      MOV      @-40,BYTCNT
010710 010577 005342      1$: MOV      R5,@DHSCR
010714 016702 005442              MOV      BYTCNT,R2
010720 005402              NEG      R2
010722 010177 005334              MOV      R1,@DHLPR
                                ;SET LINE SPEED AND
                                ;CHARACTER LENGTH
                                ;ADDRESS OF TRANSMITTER
010726 012777 016364 005330      MOV      @TBUF,@DHBA

```

```

010734 016777 005422 005324      MOV      BYTCNT, @DHBC      ;DATA BUFFER
                                ;400 (OCTAL) BYTES
010742 012777 000002 005320      MOV      #2, @DHBAR      ;WILL BE TRANSMITTED
010750 105777 005302      2$:    TSTB      @DHSCR      ;START TRANSMITTER
010754 100375      BPL      2$      ;WAIT FOR DATA TO BE RECEIVED
010756 017703 005276      MOV      @DHNR, R3      ;GET RECEIVED DATA
010762 020367 005372      CMP      R3, RDATA      ;COMPER EXPECTED AND RECEIVED DATA
010766 001407      BEQ      3$
010770 005077 005274      CLR      @DHBAR      ;STOP TRANSMITTER
010774      HLT      2      ;DATA ERROR
010774 104002      EMT      2
010776 104410      SCOPE1
011000 012777 000002 005262      MOV      #2, @DHBAR      ;CHECK FOR LOOP AT CURRENT SPEED
011006 105267 005346      3$:    INCB      RDATA      ;RESTART TRANSMITTER
011012 005302      DEC      R2      ;UPDATA EXPECTED DATA
011014 001355      BNE      2$
011016 105067 005336      CLRB      RDATA      ;INITIALIZE EXPECTED
                                ;RECEIVED DATA
                                ;UPDATA CHARACTER LENGTH
011022 005201      INC      R1
011024 005204      INC      R4
011026 006367 005330      ASL      BYTCNT
011032 005300      DEC      R0
011034 001325      BNE      1$
011036 104400      4$:    SCOPE
                                LINE=LINE+1
                                BITX=BITX+BITX
011040 000002      SDATA3 \LINE, \BITX
                                ;SINGLE LINE DATA TEST
                                ;TRANSMIT A BLOCK OF 400 (OCTAL) CHARACTERS ON LINE 2
                                ;LINE SPEED IS 9600 BAUD
                                ;CHARACTER LENGTH WILL START AT 5 BITS AND BE INCREMENTED
                                ;TO 8 BITS
                                ;A BLOCK OF 400 CHARACTERS WILL BE TRANSMITTED
                                ;AT EACH CHARACTER LENGTH

011040      TS \XN, 1, 4$, 1$
011040 012767 000340 166730      T43:    MOV      #340, PS      ;DISABLE ALL INTERRUPTS
011046 012767 000001 005250      MOV      #1, ICOUNT      ;SET UP FOR 1 ITERATIONS
011054 012767 011256 005236      MOV      #4$, ESCAPE      ;SET UP TO ESCAPE TO NEXT TEST
                                .IF NB <1$>
011062 012767 011130 005232      MOV      #1$, FREEZ1      ;SET UP TO LOOP WITH DATA      : 3
                                .ENDC
                                XN=XN+1
011070 012777 004000 005160      MOV      @BIT11, @DHSCR      ;MASTER CLEAR INTERFACE
011076 005004      CLR      R4      ;FIRST CHARACTER LENGTH CODE (5 BITS)
011100 012705 000002      MOV      #2, R5      ;LINE 2 WILL BE TESTED
011104 012767 101000 005246      MOV      #2*400+100000, RDATA
                                ;SET EXPECTED LINE NUMBER
                                ;AND VALID DATA FLAG
                                ;EXPECTED DATA
                                ;4CHARACTER LENGTHS
                                ;WILL BE TESTED
                                ;FIRST CHARACTER LENGTH =5 BITS..
                                ;LINE SPEED =9600 BAUD
                                ;40 CHARACTERS AT 5 BITS
011112 012700 000004      MOV      #4, R0
011116 012701 033500      MOV      #33500, R1
011122 012767 177740 005232      MOV      # 40, BYTCNT

```

```

011130 010577 005122      1$:  MOV    R5,@DHSCR      ;SELECT LINE 2
011134 016702 005222      MOV    BYTCNT,R2
011140 005402              NEG    R2
011142 010177 005114      MOV    R1,@DHLPR      ;SET LINE SPEED AND
                                ;CHARACTER LENGTH
011146 012777 016364 005110  MOV    @TBUF,@DHBA      ;ADDRESS OF TRANSMITTER
                                ;DATA BUFFER
011154 016777 005202 005104  MOV    BYTCNT,@DHBC      ;400 (OCTAL) BYTES
                                ;WILL BE TRANSMITTED
011162 012777 000004 005100  MOV    #4,@DHBAR      ;START TRANSMITTER
011170 105777 005062      2$:  TSTB    @DHSCR      ;WAIT FOR DATA TO BE RECEIVED
011174 100375              BPL     2$
011176 017703 005056      MOV    @DHNR,R3      ;GET RECEIVED DATA
011202 020367 005152      CMP     R3,RDATA      ;COMPER EXPECTED AND RECEIVED DATA
011206 001407              BEQ     3$
011210 005077 005054      CLR     @DHBA      ;STOP TRANSMITTER
011214              HLT     2      ;DATA ERROR
011214 104002              EMT     2
011216 104410              SCOPE1
011220 012777 000004 005042  MOV    #4,@DHBAR      ;CHECK FOR LOOP AT CURRENT SPEED
011226 105267 005126      3$:  INCB    RDATA      ;RESTART TRANSMITTER
011232 005302              DEC     R2      ;UPDATA EXPECTED DATA
011234 001355              BNE     2$
011236 105067 005116      CLRB    RDATA
                                ;INITIALIZE EXPECTED
                                ;RECEIVED DATA
                                ;UPDATA CHARACTER LENGTH
011242 005201              INC     R1
011244 005204              INC     R4
011246 006367 005110      ASL     BYTCNT
011252 005300              DEC     R0
011254 001325              BNE     1$
011256 104400      4$:  SCOPE
                                LINE=LINE+1
                                BITX=BITX+BITX
                                SDATA3 \LINE,\BITX
011260      ;SINGLE LINE DATA TEST
                                ;TRANSMIT A BLOCK OF 400 (OCTAL) CHARACTERS ON LINE 3
                                ;LINE SPEED IS 9600 BAUD
                                ;CHARACTER LENGTH WILL START AT 5 BITS AND BE INCREMENTED
                                ;TO 8 BITS
                                ;A BLOCK OF 400 CHARACTERS WILL BE TRANSMITTED
                                ;AT EACH CHARACTER LENGTH

011260      TS \XN,1,4$,1$
011260 012767 000340 166510 T44:  MOV    #340,PS      ;DISABLE ALL INTERRUPTS
011266 012767 000001 005030      MOV    #1,ICOUNT      ;SET UP FOR 1 ITERATIONS
011274 012767 011476 005016      MOV    #4$,ESCAPE      ;SET UP TO ESCAPE TO NEXT TEST
                                .IF NB <1$>
011302 012767 011350 005012      MOV    #1$,FREEZ1      ;SET UP TO LOOP WITH DATA      : 3
                                .ENDC
                                XN=XN+1
011310 012777 004000 004740      MOV    #BIT11,@DHSCR      ;MASTER CLEAR INTERFACE
011316 005004              CLR     R4      ;FIRST CHARACTER LENGTH CODE (5 BITS)
011320 012705 000003              MOV    #3,R5      ;LINE 3 WILL BE TESTED
011324 012767 101400 005026      MOV    #3*400+100000,RDATA
                                ;SET EXPECTED LINE NUMBER
                                ;AND VALID DATA FLAG

```

```

011332 012700 000004      MOV      #4,R0      ;EXPECTED DATA
011336 012701 033500      MOV      #33500,R1    ;4CHARACTER LENGTHS
011342 012767 177740 005012  MOV      #-40,BYTCNT ;WILL BE TESTED
011350 010577 004702      1$: MOV      R5,@DHSCR ;FIRST CHARACTER LENGTH =5 BITS,,
011354 016702 005002      MOV      BYTCNT,R2    ;LINE SPEED =9600 BAUD
011360 005402              NEG      R2          ;40 CHARACTERS AT 5 BITS
011362 010177 004674      MOV      R1,@DHLPR    ;SELECT LINE 3

011366 012777 016364 004670  MOV      #TBUF,@DHBA ;SET LINE SPEED AND
011374 016777 004762 004664  MOV      BYTCNT,@DHBC ;CHARACTER LENGTH
011402 012777 000010 004660  MOV      #10,@DHBAR ;ADDRESS OF TRANSMITTER
011410 105777 004642      2$: TSTB      @DHSCR ;DATA BUFFER
011414 100375              BPL      2$          ;400 (OCTAL) BYTES
011416 017703 004636      MOV      @DHNR,R3    ;WILL BE TRANSMITTED
011422 020367 004732      CMP      R3,RDATA    ;START TRANSMITTER
011426 001407              BEQ      3$          ;WAIT FOR DATA TO BE RECEIVED
011430 005077 004634      CLR      @DHBAR      ;GET RECEIVED DATA
011434              HLT      2$                ;COMPER EXPECTED AND RECEIVED DATA
011436 104002              EMT      2$          ;STOP TRANSMITTER
011440 012777 000010 004622  MOV      #10,@DHBAR ;DATA ERROR
011446 105267 004706      3$: INCB      RDATA    ;CHECK FOR LOOP AT CURRENT SPEED
011452 005302              DEC      R2          ;RESTART TRANSMITTER
011454 001355              BNE      2$          ;UPDATA EXPECTED DATA
011456 105067 004670      CLRB      RDATA      ;INITIALIZE EXPECTED
011462 005201              INC      R1          ;RECEIVED DATA
011464 005204              INC      R4          ;UPDATA CHARACTER LENGTH
011466 006367 004670      ASL      BYTCNT
011472 005300              DEC      R0
011474 001325              BNE      1$
011476 104400      4$: SCOPE
000004      LINE=LINE+1
000020      BITX=BITX+BITX
011500      SDATA3 \LINE,\BITX

;SINGLE LINE DATA TEST
;TRANSMIT A BLOCK OF 400 (OCTAL) CHARACTERS ON LINE 4
;LINE SPEED IS 9600 BAUD
;CHARACTER LENGTH WILL START AT 5 BITS AND BE INCREMENTED
;TO 8 BITS
;A BLOCK OF 400 CHARACTERS WILL BE TRANSMITTED
;AT EACH CHARACTER LENGTH

011500      TS \XN,1,4$,1$
011500 012767 000340 166270 T45: MOV      #340,PS      ;DISABLE ALL INTERRUPTS
011506 012767 000001 004610 MOV      #1,ICOUNT ;SET UP FOR 1 ITERATIONS
011514 012767 011716 004576 MOV      #4$,ESCAPE ;SET UP TO ESCAPE TO NEXT TEST

011522 012767 011570 004572 .IF NB <1$> MOV      #1$,FREEZ1 ;SET UP TO LOOP WITH DATA ; 3
000046      .ENDC
XN=XN+1

```

```

011530 012777 004000 004520      MOV    #BIT11, @DHSCR      ;MASTER CLEAR INTERFACE
011536 005004                      CLR    R4                ;FIRST CHARACTER LENGTH CODE (5 BITS)
011540 012705 000004                      MOV    #4, R5                ;LINE 4 WILL BE TESTED
011544 012767 102000 004606      MOV    #4*400+100000, RDATA      ;SET EXPECTED LINE NUMBER
                                           ;AND VALID DATA FLAG
                                           ;EXPECTED DATA
                                           ;4 CHARACTER LENGTHS
                                           ;WILL BE TESTED
011552 012700 000004                      MOV    #4, R0                ;FIRST CHARACTER LENGTH =5 BITS,,
011556 012701 033500                      MOV    #33500, R1          ;LINE SPEED =9600 BAUD
                                           ;40 CHARACTERS AT 5 BITS
                                           ;SELECT LINE 4
011562 012767 177740 004572      MOV    # 40, BYTCNT
011570 010577 004462      1$:      MOV    R5, @DHSCR
011574 016702 004562      MOV    BYTCNT, R2
011600 005402                      NEG    R2
011602 010177 004454                      MOV    R1, @DHLPR
                                           ;SET LINE SPEED AND
                                           ;CHARACTER LENGTH
011606 012777 016364 004450      MOV    #TBUF, @DHBA      ;ADDRESS OF TRANSMITTER
                                           ;DATA BUFFER
011614 016777 004542 004444      MOV    BYTCNT, @DHBC      ;400 (OCTAL) BYTES
                                           ;WILL BE TRANSMITTED
                                           ;START TRANSMITTER
011622 012777 000020 004440      MOV    #20, @DHBAR      ;WAIT FOR DATA TO BE RECEIVED
011630 105777 004422      2$:      TSTB    @DHSCR
011634 100375                      BPL     2$
011636 017703 004416      MOV    @DHNR, R3
011642 020367 004512      CMP     R3, RDATA
011646 001407                      BEQ     3$
011650 005077 004414      CLR     @DHBAR
011654                      HLT     2
011654 104002                      EMT     2
011656 104410                      SCOPE1
011660 012777 000020 004402      MOV    #20, @DHBAR
011666 105267 004466      3$:      INCB    RDATA
011672 005302                      DEC     R2
011674 001355                      BNE     2$
011676 105067 004456      CLRB    RDATA
                                           ;GET RECEIVED DATA
                                           ;COMPER EXPECTED AND RECEIVED DATA
                                           ;STOP TRANSMITTER
                                           ;DATA ERROR
011702 005201                      INC     R1
011704 005204                      INC     R4
011706 006367 004450      ASL     BYTCNT
011712 005300                      DEC     R0
011714 001325                      BNE     1$
011716 104400      4$:      SCOPE
011716 000005      LINE=LINE+1
011716 000040      BITX=BITX+BITX
011720      SDATA3 \LINE, \BITX
                                           ;SINGLE LINE DATA TEST
                                           ;TRANSMIT A BLOCK OF 400 (OCTAL) CHARACTERS ON LINE 5
                                           ;LINE SPEED IS 9600 BAUD
                                           ;CHARACTER LENGTH WILL START AT 5 BITS AND BE INCREMENTED
                                           ;TO 8 BITS
                                           ;A BLOCK OF 400 CHARACTERS WILL BE TRANSMITTED
                                           ;AT EACH CHARACTER LENGTH
011720      TS \XN, 1, 4$, 1$
011720 012767 000340 166050      T46:      MOV    #340, PS      ;DISABLE ALL INTERRUPTS

```

```

011726 012767 000001 004370      MOV    #1,ICOUNT      ;SET UP FOR 1 ITERATIONS
011734 012767 012136 004356      MOV    #4$,ESCAPE    ;SET UP TO ESCAPE TO NEXT TEST
                                .IF NB <1$>
011742 012767 012010 004352      MOV    #1$,FREEZ1      ;SET UP TO LOOP WITH DATA      ; 3
                                .ENDC
                                XN=XN+1
011750 012777 004000 004300      MOV    #BIT11,SDHSCR    ;MASTER CLEAR INTERFACE
011756 005004                      CLR    R4              ;FIRST CHARACTER LENGTH CODE (5 BITS)
011760 012705 000005                      MOV    #5,R5          ;LINE 5 WILL BE TESTED
011764 012767 102400 004366      MOV    #5*400+100000,RDATA
                                ;SET EXPECTED LINE NUMBER
                                ;AND VALID DATA FLAG
                                ;EXPECTED DATA
                                ;4 CHARACTER LENGTHS
                                ;WILL BE TESTED
                                ;FIRST CHARACTER LENGTH =5 BITS,,
                                ;LINE SPEED =9600 BAUD
                                ;40 CHARACTERS AT 5 BITS
                                ;SELECT LINE 5

011772 012700 000004                      MOV    #4,R0
011776 012701 033500                      MOV    #33500,R1
                                ;SET LINE SPEED AND
                                ;CHARACTER LENGTH
                                ;ADDRESS OF TRANSMITTER
                                ;DATA BUFFER
                                ;400 (OCTAL) BYTES
                                ;WILL BE TRANSMITTED
                                ;START TRANSMITTER
                                ;WAIT FOR DATA TO BE RECEIVED

012002 012767 177740 004352      MOV    #-40,BYTCNT
012010 010577 004242      1$:      MOV    R5,SDHSCR
012014 016702 004342      MOV    BYTCNT,R2
012020 005402                      NEG    R2
012022 010177 004234      MOV    R1,SDHLPR
                                ;GET RECEIVED DATA
                                ;COMPER EXPECTED AND RECEIVED DATA

012026 012777 016364 004230      MOV    #TBUF,SDHBA
012034 016777 004322 004224      MOV    BYTCNT,SDHBC
                                ;STOP TRANSMITTER
                                ;DATA ERROR

012042 012777 000040 004220      MOV    #40,SDHBAR
012050 105777 004202      2$:      TSTB   SDHSCR
012054 100375                      BPL    2$
012056 017703 004176      MOV    SDHNR, R3
012062 020367 004272      CMP     R3,RDATA
012066 001407                      BEQ    3$
012070 005077 004174      CLR     SDHBAR
012074                      HLT     2
012074 104002                      EMT     2
012076 104410                      SCOPE1
012100 012777 000040 004162      MOV    #40,SDHBAR
012106 105267 004246      3$:      INCB   RDATA
012112 005302                      DEC    R2
012114 001355                      BNE    2$
012116 105067 004236      CLRB   RDATA
                                ;CHECK FOR LOOP AT CURRENT SPEED
                                ;RESTART TRANSMITTER
                                ;UPDATA EXPECTED DATA

                                ;INITIALIZE EXPECTED
                                ;RECEIVED DATA
                                ;UPDATA CHARACTER LENGTH

012122 005201                      INC    R1
012124 005204                      INC    R4
012126 006367 004230      ASL     BYTCNT
012132 005300                      DEC    R0
012134 001325                      BNE    1$
012136 104400      4$:      SCOPE
                                LINE=LINE+1
                                BITX=BITX+BITX
                                SDATA3 \LINE,\BITX

012140                                ;SINGLE LINE DATA TEST
                                ;TRANSMIT A BLOCK OF 400 (OCTAL) CHARACTERS ON LINE 6
                                ;LINE SPEED IS 9600 BAUD
                                ;CHARACTER LENGTH WILL START AT 5 BITS AND BE INCREMENTED

```

;TO 8 BITS  
;A BLOCK OF 400 CHARACTERS WILL BE TRANSMITTED  
;AT EACH CHARACTER LENGTH

012140				TS \XN,1,4\$,1\$		
012140	012767	000340	165630	T47:	MOV	#340,PS
012146	012767	000001	004150		MOV	#1,ICOUNT
012154	012767	012356	004136		MOV	#4\$,ESCAPE
				.IF NB	<1\$>	
012162	012767	012230	004132		MOV	#1\$,FREEZ1
				.ENDC		
	000050			XN=XN+1		
012170	012777	004000	004060		MOV	#8IT11,@DHSCR
012176	005004				CLR	R4
012200	012705	000006			MOV	#6,R5
012204	012767	103000	004146		MOV	#6*400+100000,RDATA
						;LINE 6
						WILL BE TESTED
						;SET EXPECTED LINE NUMBER
						;AND VALID DATA FLAG
						;EXPECTED DATA
						;4CHARACTER LENGTHS
						;WILL BE TESTED
						;FIRST CHARACTER LENGTH =5 BITS,,
						;LINE SPEED =9600 BAUD
						;40 CHARACTERS AT 5 BITS
						;SELECT LINE 6
012212	012700	000004			MOV	#4,R0
012216	012701	033500			MOV	#33500,R1
012222	012767	177740	004132		MOV	#-40,BYTCNT
012230	010577	004022		1\$:	MOV	R5,@DHSCR
012234	016702	004122			MOV	BYTCNT,R2
012240	005402				NEG	R2
012242	010177	004014			MOV	R1,@DHLPR
						;SET LINE SPEED AND
						;CHARACTER LENGTH
012246	012777	016364	004010		MOV	#TBUF,@DHBA
						;ADDRESS OF TRANSMITTER
012254	016777	004102	004004		MOV	BYTCNT,@DHBC
						;DATA BUFFER
						;400 (OCTAL) BYTES
						;WILL BE TRANSMITTED
012262	012777	000100	004000		MOV	#100,@DHBAR
012270	105777	003762		2\$:	TSTB	@DHSCR
012274	100375				BPL	2\$
012276	017703	003756			MOV	@DHNR,R3
012302	020367	004052			CMP	R3,RDATA
012306	001407				BEQ	3\$
012310	005077	003754			CLR	@DHBAR
012314					HLT	2
012314	104002				EMT	2
012316	104410				SCOPE1	
012320	012777	000100	003742		MOV	#100,@DHBAR
012326	105267	004026		3\$:	INCB	RDATA
012332	005302				DEC	R2
012334	001355				BNE	2\$
012336	105067	004016			CLRB	RDATA
						;INITIALIZE EXPECTED
						;RECEIVED DATA
						;UPDATA CHARACTER LENGTH
012342	005201				INC	R1
012344	005204				INC	R4
012346	006367	004010			ASL	BYTCNT
012352	005300				DEC	R0
012354	001325				BNE	1\$
012356	104400			4\$:	SCOPE	
	000007				LINE=LINE+1	
	000200				BITX=BITX+BITX	

012360

SDATA3 \LINE,\BITX

```

;SINGLE LINE DATA TEST
;TRANSMIT A BLOCK OF 400 (OCTAL) CHARACTERS ON LINE 7
;LINE SPEED IS 9600 BAUD
;CHARACTER LENGTH WILL START AT 5 BITS AND BE INCREMENTED
;TO 8 BITS
;A BLOCK OF 400 CHARACTERS WILL BE TRANSMITTED
;AT EACH CHARACTER LENGTH

```

012360				TS \XN,1,4\$,1\$		
012360	012767	000340	165410	T50:	MOV	#340,PS ;DISABLE ALL INTERRUPTS
012366	012767	000001	003730		MOV	#1,ICOUNT ;SET UP FOR 1 ITERATIONS
012374	012767	012576	003716		MOV	#4\$,ESCAPE ;SET UP TO ESCAPE TO NEXT TEST
				.IF NB	<1\$>	
012402	012767	012450	003712		MOV	#1\$,FREEZ1 ;SET UP TO LOOP WITH DATA ; 3
				.ENDC		
		000051		XN=XN+1		
012410	012777	004000	003640		MOV	#BIT11,@DHSCR ;MASTER CLEAR INTERFACE
012416	005004				CLR	R4 ;FIRST CHARACTER LENGTH CODE (5 BITS)
012420	012705	000007			MOV	#7,R5 ;LINE 7 WILL BE TESTED
012424	012767	103400	003726		MOV	#7*400+100000,RDATA
						;SET EXPECTED LINE NUMBER
						;AND VALID DATA FLAG
012432	012700	000004			MOV	#4,R0 ;EXPECTED DATA
						;4 CHARACTER LENGTHS
012436	012701	033500			MOV	#33500,R1 ;WILL BE TESTED
						;FIRST CHARACTER LENGTH =5 BITS,,
012442	012767	177740	003712		MOV	#-40,BYTCNT ;LINE SPEED =9600 BAUD
012450	010577	003602		1\$:	MOV	R5,@DHSCR ;40 CHARACTERS AT 5 BITS
012454	016702	003702			MOV	BYTCNT,R2 ;SELECT LINE 7
012460	005402				NEG	R2
012462	010177	003574			MOV	R1,@DHLPR
						;SET LINE SPEED AND
						;CHARACTER LENGTH
012466	012777	016364	003570		MOV	#TBUF,@DHBA ;ADDRESS OF TRANSMITTER
						;DATA BUFFER
012474	016777	003662	003564		MOV	BYTCNT,@DHBC ;400 (OCTAL) BYTES
						;WILL BE TRANSMITTED
012502	012777	000200	003560		MOV	#200,@DHBAR ;START TRANSMITTER
012510	105777	003542		2\$:	TSTB	@DHSCR ;WAIT FOR DATA TO BE RECEIVED
012514	100375				BPL	2\$
012516	017703	003536			MOV	@DHNR, R3 ;GET RECEIVED DATA
012522	020367	003632			CMP	R3,RDATA ;COMPER EXPECTED AND RECEIVED DATA
012526	001407				BEQ	3\$
012530	005077	003534			CLR	@DHBAR ;STOP TRANSMITTER
012534					HLT	2 ;DATA ERROR
012534	104002				EMT	2
012536	104410				SCOPE1	
012540	012777	000200	003522		MOV	#200,@DHBAR ;CHECK FOR LOOP AT CURRENT SPEED
012546	105267	003606		3\$:	INCB	RDATA ;RESTART TRANSMITTER
					DEC	R2 ;UPDATA EXPECTED DATA
012552	005302				BNE	2\$
012554	001355				CLRB	RDATA
012556	105067	003576				;INITIALIZE EXPECTED
						;RECEIVED DATA
012562	005201				INC	R1 ;UPDATA CHARACTER LENGTH
012564	005204				INC	R4



012566 006367 003570  
012572 005300  
012574 001325  
012576 104400  
000010  
000400  
012600

```

        ASL      BYTCNT
        DEC      RO
        BNE      1$
4$:      SCOPE
        LINE=LINE+1
        BITX=BITX+BITX
        SDATA3  \LINE.\BITX

```

```
;SINGLE LINE DATA TEST
;TRANSMIT A BLOCK OF 400 (OCTAL) CHARACTERS ON LINE 10
;LINE SPEED IS 9600 BAUD
;CHARACTER LENGTH WILL START AT 5 BITS AND BE INCREMENTED
;TO 8 BITS
;A BLOCK OF 400 CHARACTERS WILL BE TRANSMITTED
;AT EACH CHARACTER LENGTH
```

Address	Offset	Hex Data	Assembly	Comments
012600	012767	000340	165170	TS \XN,1,4\$,1\$
012606	012767	000001	003510	T51: MOV #340,PS ;DISABLE ALL INTERRUPTS
012614	012767	013016	003476	MOV #1,ICOUNT ;SET UP FOR 1 ITERATIONS
				MOV #4\$,ESCAPE ;SET UP TO ESCAPE TO NEXT TEST
				.IF NB <1\$>
012622	012767	012670	003472	MOV #1\$,FREEZ1 ;SET UP TO LOOP WITH DATA ; 3
				.ENDC
	000052			XN=XN+1
012630	012777	004000	003420	MOV #BIT11,@DHSCR ;MASTER CLEAR INTERFACE
012636	005004			CLR R4 ;FIRST CHARACTER LENGTH CODE (5 BITS)
012640	012705	000010		MOV #10,R5 ;LINE 10 WILL BE TESTED
012644	012767	104000	003506	MOV #10*400+100000,RDATA ;SET EXPECTED LINE NUMBER
				;AND VALID DATA FLAG
				;EXPECTED DATA
012652	012700	000004		MOV #4,R0 ;4 CHARACTER LENGTHS
				;WILL BE TESTED
012656	012701	033500		MOV #33500,R1 ;FIRST CHARACTER LENGTH =5 BITS..
				;LINE SPEED =9600 BAUD
012662	012767	177740	003472	MOV #-40,BYTCNT ;40 CHARACTERS AT 5 BITS
012670	010577	003362		1\$: MOV R5,@DHSCR ;SELECT LINE 10
012674	016702	003462		MOV BYTCNT,R2
012700	005402			NEG R2
012702	010177	003354		MOV R1,@DHLPR ;SET LINE SPEED AND
				;CHARACTER LENGTH
012706	012777	016364	003350	MOV #TBUF,@DHBA ;ADDRESS OF TRANSMITTER
				;DATA BUFFER
012714	016777	003442	003344	MOV BYTCNT,@DHBC ;400 (OCTAL) BYTES
				;WILL BE TRANSMITTED
012722	012777	000400	003340	MOV #400,@DHBAR ;START TRANSMITTER
012730	105777	003322		2\$: TSTB @DHSCR ;WAIT FOR DATA TO BE RECEIVED
012734	100375			BPL 2\$
012736	017703	003316		MOV @DHNRC,R3 ;GET RECEIVED DATA
012742	020367	003412		CMP R3,RDATA ;COMPER EXPECTED AND RECEIVED DATA
012746	001407			BEQ 3\$
012750	005077	003314		CLR @DHBAR ;STOP TRANSMITTER
012754				HLT 2 ;DATA ERROR
012754	104002			EMT 2
012756	104410			SCOPE1
012760	012777	000400	003302	MOV #400,@DHBAR ;CHECK FOR LOOP AT CURRENT SPEED
012766	105267	003366		3\$: INCB RDATA ;RESTART TRANSMITTER
				;UPDATA EXPECTED DATA

012772 005302  
012774 001355  
012776 105067 003356

```
DEC      R2
BNE      2$
CLRB     RDATA
```

```
;INITIALIZE EXPECTED
;RECEIVED DATA
;UPDATA CHARACTER LENGTH
```

013002	005201	
013004	005204	
013006	006367	003350
013012	005300	
013014	001325	
013016	104400	
	000011	
	001000	

```

INC      R1
INC      R4
ASL      BYTCNT
DEC      R0
BNE      1$
4$:      SCOPE
LINE=LINE+1
BITX=BITX+BITX
SDATA3   \LINE,\BITX

```

```

;SINGLE LINE DATA TEST
;TRANSMIT A BLOCK OF 400 (OCTAL) CHARACTERS ON LINE 11
;LINE SPEED IS 9600 BAUD
;CHARACTER LENGTH WILL START AT 5 BITS AND BE INCREMENTED
;TO 8 BITS
;A BLOCK OF 400 CHARACTERS WILL BE TRANSMITTED
;AT EACH CHARACTER LENGTH

```

013020			
013020	012767	000340	164750
013026	012767	000001	003270
013034	012767	013236	003256
013042	012767	013110	003252
	000053		
013050	012777	004000	003200
013056	005004		
013060	012705	000011	
013064	012767	104400	003266

```
TS \XN,1,4$,1$
T52:      MOV
          MOV
          MOV
          .IF NB <1$>
          MOV
          .ENDC
          XN=XN+1
```

```

;DISABLE ALL INTERRUPTS
;SET UP FOR 1 ITERATIONS
;SET UP TO ESCAPE TO NEXT TEST

;SET UP TO LOOP WITH DATA          : 3

```

	000053		
013050	012777	004000	003200
013056	005004		
013060	012705	000011	
013064	012767	104400	003266

```

MOV      @BIT11,@DHSCR
CLR      R4
MOV      @11,R5          ;LINE
MOV      @11*400+100000,RDATA

```

```

;MASTER CLEAR INTERFACE
;FIRST CHARACTER LENGTH CODE (5 BITS)
1 WILL BE TESTED

```

013072 012700 000004

MOV #4,R0

```

:SET EXPECTED LINE NUMBER
:AND VALID DATA FLAG
:EXPECTED DATA
:4CHARACTER LENGTHS
:WILL BE TESTED

```

013076 012701 033500

MOV #33500,R1

```
;FIRST CHARACTER LENGTH =5 BITS..  
;LINE SPEED =9600 BAUD  
;40 CHARACTERS AT 5 BITS  
;SELECT LINE 11
```

013102	012767	177740	003252
013110	010577	003142	
013114	016702	003242	
013120	005402		
013122	010177	003134	

```

1$:  MOV     #40,BYTCNT
      MOV     R5,@DHSCR
      MOV     BYTCNT,R2
      NEG     R2
      MOV     R1,@DHLPR

```

;SET LINE SPEED AND

013126 012777 016364 003130

MOV #TBUF, BDHBA

```
; CHARACTER LENGTH
; ADDRESS OF TRANSMITTER
; DATA BUFFER
```

013134 016777 003222 003124

MOV BYTCNT, @DHBC

```

;400 (OCTAL) BYTES
;WILL BE TRANSMITTED

```

013142 012777 001000 003120

MOV #1000,8DH8AR

```
;START TRANSMITTER
;WAIT FOR DATA TO BE RECEIVED
```

013150 105777 003102

2\$: TSTB

```
;GET RECEIVED DATA
;COMPER EXPECTED AND RECEIVED DATA
```

013154 100375  
013156 013303 003036

8PL 2\$

013156 017703 003076  
013162 020367 003172

```
MOV     @DHNRC,R0  
CMP     R7,RDATA
```

013162 020367  
013166 001407

CMP	R3
BEQ	3\$

Address	Hex	Hex	Hex	Assembly	Comments
013170	005077	003074		CLR @DHBAR	;STOP TRANSMITTER
013174				HLT 2	;DATA ERROR
013174	104002			EMT 2	
013176	104410			SCOPE1	
013200	017777	001000	003062	MOV #1000,@DHBAR	;CHECK FOR LOOP AT CURRENT SPEED
013206	105267	003146		3\$: INCB RDATA	;RESTART TRANSMITTER
013212	005302			DEC R2	;UPDATA EXPECTED DATA
013214	001355			BNE 2\$	
013216	105067	003136		CLRB RDATA	;INITIALIZE EXPECTED
					;RECEIVED DATA
013222	005201			INC R1	;UPDATA CHARACTER LENGTH
013224	005204			INC R4	
013226	006367	003130		ASL BYTCNT	
013232	005300			DEC R0	
013234	001325			BNE 1\$	
013236	104400			4\$: SCOPE	
	000012			LINE=LINE+1	
	002000			BITX=BITX+BITX	
013240				SDATA3 \LINE,\BITX	
					;SINGLE LINE DATA TEST
					;TRANSMIT A BLOCK OF 400 (OCTAL) CHARACTERS ON LINE 12
					;LINE SPEED IS 9600 BAUD
					;CHARACTER LENGTH WILL START AT 5 BITS AND BE INCREMENTED
					;TO 8 BITS
					;A BLOCK OF 400 CHARACTERS WILL BE TRANSMITTED
					;AT EACH CHARACTER LENGTH
013240				TS \XN,1,4\$,1\$	
013240	012767	000340	164530	T53: MOV #340,PS	;DISABLE ALL INTERRUPTS
013246	012767	000001	003050	MOV #1,ICOUNT	;SET UP FOR 1 ITERATIONS
013254	012767	013456	003036	MOV #4\$,ESCAPE	;SET UP TO ESCAPE TO NEXT TEST
				.IF NB <1\$>	
013262	012767	013330	003032	MOV #1\$,FREEZ1	;SET UP TO LOOP WITH DATA ; 3
	000054			.ENDC	
				XN=XN+1	
013270	012777	004000	002760	MOV #BIT11,@DHSCR	;MASTER CLEAR INTERFACE
013276	005004			CLR R4	;FIRST CHARACTER LENGTH CODE (5 BITS)
013300	012705	000012		MOV #12,R5	;LINE 12 WILL BE TESTED
013304	012767	105000	003046	MOV #12*400+100000,RDATA	
					;SET EXPECTED LINE NUMBER
					;AND VALID DATA FLAG
					;EXPECTED DATA
013312	012700	000004		MOV #4,R0	;4CHARACTER LENGTHS
					;WILL BE TESTED
013316	012701	033500		MOV #33500,R1	;FIRST CHARACTER LENGTH =5 BITS..
					;LINE SPEED =9600 BAUD
013322	012767	177740	003032	MOV #-40,BYTCNT	;40 CHARACTERS AT 5 BITS
013330	010577	002722		1\$: MOV R5,@DHSCR	;SELECT LINE 12
013334	016702	003022		MOV BYTCNT,R2	
013340	005402			NEG R2	
013342	010177	002714		MOV R1,@DHLPR	;SET LINE SPEED AND
					;CHARACTER LENGTH
013346	012777	016364	002710	MOV #TBUF,@DHBA	;ADDRESS OF TRANSMITTER
					;DATA BUFFER
013354	016777	003002	002704	MOV BYTCNT,@DHBC	;400 (OCTAL) BYTES
					;WILL BE TRANSMITTED

```

013362 012777 002000 002700      MOV    #2000, @DHBAR      ;START TRANSMITTER
013370 105777 002662      2$:    TSTB    @DHSCR      ;WAIT FOR DATA TO BE RECEIVED
013374 100375      BPL     2$
013376 017703 002656      MOV    @DHNRC, R3      ;GET RECEIVED DATA
013402 020367 002752      CMP     R3, RDATA      ;COMPER EXPECTED AND RECEIVED DATA
013406 001407      BEQ     3$
013410 005077 002654      CLR     @DHBAR      ;STOP TRANSMITTER
013414      HLT     2      ;DATA ERROR
013414 104002      EMT     2
013416 104410      SCOPE1
013420 012777 002000 002642      MOV    #2000, @DHBAR      ;CHECK FOR LOOP AT CURRENT SPEED
013426 105267 002726      3$:    INCB    RDATA      ;RESTART TRANSMITTER
013432 005302      DEC     R2      ;UPDATA EXPECTED DATA
013434 001355      BNE     2$
013436 105067 002716      CLRB    RDATA      ;INITIALIZE EXPECTED
                                ;RECEIVED DATA
                                ;UPDATA CHARACTER LENGTH
013442 005201      INC     R1
013444 005204      INC     R4
013446 006367 002710      ASL     BYTCNT
013452 005300      DEC     R0
013454 001325      BNE     1$
013456 10440C      4$:    SCOPE
                                LINE=LINE+1
                                BITX=BITX+BITX
                                SDATA3 \LINE, \BITX
013460      ;SINGLE LINE DATA TEST
                                ;TRANSMIT A BLOCK OF 400 (OCTAL) CHARACTERS ON LINE 13
                                ;LINE SPEED IS 9600 BAUD
                                ;CHARACTER LENGTH WILL START AT 5 BITS AND BE INCREMENTED
                                ;TO 8 BITS
                                ;A BLOCK OF 400 CHARACTERS WILL BE TRANSMITTED
                                ;AT EACH CHARACTER LENGTH

013460      TS \XN, 1, 4$, 1$
013460 012767 000340 164310      T54:    MOV    #340, PS      ;DISABLE ALL INTERRUPTS
013466 012767 000001 002630      MOV    #1, ICOUNT      ;SET UP FOR 1 ITERATIONS
013474 012767 013676 002616      MOV    #4$, ESCAPE      ;SET UP TO ESCAPE TO NEXT TEST
                                .IF NB <1$>
013502 012767 013550 002612      MOV    #1$, FREEZ1      ;SET UP TO LOOP WITH DATA      ; 3
                                .ENDC
                                XN=XN+1
013510 012777 004000 002540      MOV    @BIT11, @DHSCR      ;MASTER CLEAR INTERFACE
013516 005004      CLR     R4      ;FIRST CHARACTER LENGTH CODE (5 BITS)
013520 012705 000013      MOV    #13, R5      ;LINE 13 WILL BE TESTED
013524 012767 105400 002626      MOV    #13*400+100000, RDATA
                                ;SET EXPECTED LINE NUMBER
                                ;AND VALID DATA FLAG
                                ;EXPECTED DATA
                                ;4 CHARACTER LENGTHS
                                ;WILL BE TESTED
                                ;FIRST CHARACTER LENGTH =5 BITS..
                                ;LINE SPEED =9600 BAUD
                                ;40 CHARACTERS AT 5 BITS
                                ;SELECT LINE 13
013532 012700 000004      MOV    #4, R0
013536 012701 033500      MOV    #33500, R1
013542 012767 177740 002612      MOV    #-40, BYTCNT
013550 010577 002502      1$:    MOV    R5, @DHSCR
013554 016702 002602      MOV    BYTCNT, R2
013560 005402      NEG     R2

```

```

013562 010177 002474      MOV      R1, @DHLPR      ;SET LINE SPEED AND
                                ;CHARACTER LENGTH
013566 012777 016364 002470      MOV      @TBUF, @DHBA      ;ADDRESS OF TRANSMITTER
                                ;DATA BUFFER
013574 016777 002562 002464      MOV      BYTCNT, @DHBC      ;400 (OCTAL) BYTES
                                ;WILL BE TRANSMITTED
013602 012777 004000 002460      MOV      #4000, @DHBAR      ;START TRANSMITTER
013610 105777 002442      2$:      TSTB      @DHSCR      ;WAIT FOR DATA TO BE RECEIVED
013614 100375      BPL      2$
013616 017702 002436      MOV      @DHNR, R3      ;GET RECEIVED DATA
013622 020367 002532      CMP      R3, RDATA      ;COMPER EXPECTED AND RECEIVED DATA
013626 001407      BEQ      3$
013630 005077 002434      CLR      @DHBAR      ;STOP TRANSMITTER
013634      HLT      2      ;DATA ERROR
013634 104002      EMT      2
013636 104410      SCOPE1
013640 012777 004000 002422      MOV      #4000, @DHBAR      ;CHECK FOR LOOP AT CURRENT SPEED
013646 105267 002506      3$:      INCB      RDATA      ;RESTART TRANSMITTER
013652 005302      DEC      R2      ;UPDATA EXPECTED DATA
013654 001355      BNE      2$
013656 105067 002476      CLRB      RDATA      ;INITIALIZE EXPECTED
                                ;RECEIVED DATA
                                ;UPDATA CHARACTER LENGTH
013662 005201      INC      R1
013664 005204      INC      R4
013666 006367 002470      ASL      BYTCNT
013672 005300      DEC      R0
013674 001325      BNE      1$
013676 104400      4$:      SCOPE
                                LINE=LINE+1
                                BITX=BITX+BITX
013700 010000      SDATA3 \LINE, \BITX

                                ;SINGLE LINE DATA TEST
                                ;TRANSMIT A BLOCK OF 400 (OCTAL) CHARACTERS ON LINE 14
                                ;LINE SPEED IS 9600 BAUD
                                ;CHARACTER LENGTH WILL START AT 5 BITS AND BE INCREMENTED
                                ;TO 8 BITS
                                ;A BLOCK OF 400 CHARACTERS WILL BE TRANSMITTED
                                ;AT EACH CHARACTER LENGTH

013700      TS \XN, 1, 4$, 1$
013700 012767 000340 164070      T55:      MOV      #340, PS      ;DISABLE ALL INTERRUPTS
013706 012767 000001 002410      MOV      #1, ICOUNT      ;SET UP FOR 1 ITERATIONS
013714 012767 014116 002376      MOV      #4$, ESCAPE      ;SET UP TO ESCAPE TO NEXT TEST
                                .IF NB <1$>
013722 012767 013770 002372      MOV      #1$, FREEZ1      ;SET UP TO LOOP WITH DATA      ; 3
                                .ENDC
                                XN=XN+1
013730 012777 004000 002320      MOV      @BIT11, @DHSCR      ;MASTER CLEAR INTERFACE
013736 005004      CLR      R4      ;FIRST CHARACTER LENGTH CODE (5 BITS)
013740 012705 000014      MOV      #14, R5      ;LINE 14 WILL BE TESTED
013744 012767 106000 002406      MOV      #14*400+100000, RDATA
                                ;SET EXPECTED LINE NUMBER
                                ;AND VALID DATA FLAG
                                ;EXPECTED DATA
                                ;4CHARACTER LENGTHS
                                ;WILL BE TESTED

013752 012700 000004      MOV      #4, R0

```

```

013756 012701 033500      MOV      #33500,R1      ;FIRST CHARACTER LENGTH =5 BITS.,
                                ;LINE SPEED =9600 BAUD
013762 012767 177740 002372      MOV      #-40,BYTCNT      ;40 CHARACTERS AT 5 BITS
013770 010577 002262      1$:      MOV      R5,@DHSCR      ;SELECT LINE 14
013774 016702 002362      MOV      BYTCNT,R2
014000 005402      NEG      R2
014002 010177 002254      MOV      R1,@DHLPR      ;SET LINE SPEED AND
                                ;CHARACTER LENGTH
014006 012777 016364 002250      MOV      #TBUF,@DHBA      ;ADDRESS OF TRANSMITTER
                                ;DATA BUFFER
014014 016777 002342 002244      MOV      BYTCNT,@DHBC      ;400 (OCTAL) BYTES
                                ;WILL BE TRANSMITTED
014022 012777 010000 002240      MOV      #10000,@DHBAR      ;START TRANSMITTER
014030 105777 002222      2$:      TSTB      @DHSCR      ;WAIT FOR DATA TO BE RECEIVED
014034 100375      BPL      2$
014036 017703 002216      MOV      @DHNRC,R3      ;GET RECEIVED DATA
014042 020367 002312      CMP      R3,RDATA      ;COMPER EXPECTED AND RECEIVED DATA
014046 001407      BEQ      3$
014050 005077 002214      CLR      @DHBAR      ;STOP TRANSMITTER
014054      HLT      2      ;DATA ERROR
014054 104002      EMT      2
014056 104410      SCOPE1
014060 012777 010000 002202      MOV      #10000,@DHBAR      ;CHECK FOR LOOP AT CURRENT SPEED
014066 105267 002266      3$:      INCB      RDATA      ;RESTART TRANSMITTER
014072 005302      DEC      R2      ;UPDATA EXPECTED DATA
014074 001355      BNE      2$
014076 105067 002256      CLR      RDATA
                                ;INITIALIZE EXPECTED
                                ;RECEIVED DATA
                                ;UPDATA CHARACTER LENGTH
014102 005201      INC      R1
014104 005204      INC      R4
014106 006367 002250      ASL      BYTCNT
014112 005300      DEC      R0
014114 001325      BNE      1$
014116 104400      4$:      SCOPE
                                LINE=LINE+1
                                BITX=BITX+BITX
                                SDATA3 \LINE,\BITX
014120      ;SINGLE LINE DATA TEST
                                ;TRANSMIT A BLOCK OF 400 (OCTAL) CHARACTERS ON LINE 15
                                ;LINE SPEED IS 9600 BAUD
                                ;CHARACTER LENGTH WILL START AT 5 BITS AND BE INCREMENTED
                                ;TO 8 BITS
                                ;A BLOCK OF 400 CHARACTERS WILL BE TRANSMITTED
                                ;AT EACH CHARACTER LENGTH

014120      TS \XN,1,4$,1$
014120 012767 000340 163650      T56:      MOV      #340,PS      ;DISABLE ALL INTERRUPTS
014126 012767 000001 002170      MOV      #1,ICOUNT      ;SET UP FOR 1 ITERATIONS
014134 012767 014336 002156      MOV      #4$,ESCAPE      ;SET UP TO ESCAPE TO NEXT TEST
                                .IF NB <1$>
014142 012767 014210 002152      MOV      #1$,FREEZ1      ;SET UP TO LOOP WITH DATA      ; 3
                                .ENDC
                                XN=XN+1
014150 000057      MOV      #BIT11,@DHSCR      ;MASTER CLEAR INTERFACE
014156 005004      CLR      R4      ;FIRST CHARACTER LENGTH CODE (5 BITS)
014160 012705 000015      MOV      #15,R5      ;LINE 15 WILL BE TESTED

```

Address	Offset	Value	Label	Operation	Register/Value	Comment	
014164	012767	106400	002166	MOV	#15*400+100000,RDATA	;SET EXPECTED LINE NUMBER ;AND VALID DATA FLAG	
014172	012700	000004		MOV	#4,R0	;EXPECTED DATA ;4CHARACTER LENGTHS	
014176	012701	033500		MOV	#33500,R1	;WILL BE TESTED ;FIRST CHARACTER LENGTH =5 BITS..	
014202	012767	177740	002152	MOV	#-40,BYTCNT	;LINE SPEED =9600 BAUD	
014210	010577	002042	1\$:	MOV	R5,@DHSCR	;40 CHARACTERS AT 5 BITS	
014214	016702	002142		MOV	BYTCNT,R2	;SELECT LINE 15	
014220	005402			NEG	R2		
014222	010177	002034		MOV	R1,@DHLPR	;SET LINE SPEED AND ;CHARACTER LENGTH	
014226	012777	016364	002030	MOV	#TBUF,@DHBA	;ADDRESS OF TRANSMITTER ;DATA BUFFER	
014234	016777	002122	002024	MOV	BYTCNT,@DHBC	;400 (OCTAL) BYTES ;WILL BE TRANSMITTED	
014242	012777	020000	002020	MOV	#20000,@DHBAR	;START TRANSMITTER	
014250	105777	002002	2\$:	TSTB	@DHSCR	;WAIT FOR DATA TO BE RECEIVED	
014254	100375			RPL	2\$		
014256	017703	001776		MOV	@DHNR,R3	;GET RECEIVED DATA	
014262	020367	002072		CMP	R3,RDATA	;COMPER EXPECTED AND RECEIVED DATA	
014266	001407			BEQ	3\$		
014270	005077	001774		CLR	@DHBAR	;STOP TRANSMITTER	
014274				HLT	2	;DATA ERROR	
014274	104002			EMT	2		
014276	104410			SCOPE1		;CHECK FOR LOOP AT CURRENT SPEED	
014300	012777	020000	001762	MOV	#20000,@DHBAR	;RESTART TRANSMITTER	
014306	105267	002046	3\$:	INCB	RDATA	;UPDATA EXPECTED DATA	
014312	005302			DEC	R2		
014314	001355			BNE	2\$		
014316	105067	002036		CLRB	RDATA	;INITIALIZE EXPECTED ;RECEIVED DATA	
014322	005201			INC	R1	;UPDATA CHARACTER LENGTH	
014324	005204			INC	R4		
014326	006367	002030		ASL	BYTCNT		
014332	005300			DEC	R0		
014334	001325			BNE	1\$		
014336	104400		4\$:	SCOPE			
	000016			LINE=LINE+1			
	040000			BITX=BITX+BITX			
014340				SDATA3	\LINE,\BITX		
						;SINGLE LINE DATA TEST ;TRANSMIT A BLOCK OF 400 (OCTAL) CHARACTERS ON LINE 16 ;LINE SPEED IS 9600 BAUD ;CHARACTER LENGTH WILL START AT 5 BITS AND BE INCREMENTED ;TO 8 BITS ;A BLOCK OF 400 CHARACTERS WILL BE TRANSMITTED ;AT EACH CHARACTER LENGTH	
014340				TS	\XN,1,4\$,1\$		
014340	012767	000340	163430	T57:	MOV	#340,PS	;DISABLE ALL INTERRUPTS
014346	012767	000001	001750		MOV	#1,ICOUNT	;SET UP FOR 1 ITERATIONS
014354	012767	014556	001736		MOV	#4\$,ESCAPE	;SET UP TO ESCAPE TO NEXT TEST
				.IF NB	<1\$>		

```

014362 012767 014430 001732      MOV    #1$,FREEZ1      ;SET UP TO LOOP WITH DATA      ; 3
                                .ENDC
                                XN=XN+1
014370 012777 004000 001660      MOV    @BIT11,@DHSCR      ;MASTER CLEAR INTERFACE
014376 005004                      CLR    R4      ;FIRST CHARACTER LENGTH CODE (5 BITS)
014400 0127C5 000016                      MOV    #16,R5      ;LINE 16 WILL BE TESTED
014404 012767 107000 001746      MOV    #16*400+100000,RDATA      ;SET EXPECTED LINE NUMBER
                                ;AND VALID DATA FLAG
                                ;EXPECTED DATA
                                ;4CHARACTER LENGTHS
                                ;WILL BE TESTED
                                ;FIRST CHARACTER LENGTH =5 BITS,,
                                ;LINE SPEED =9600 BAUD
                                ;40 CHARACTERS AT 5 BITS
                                ;SELECT LINE 16

014412 012700 000004                      MOV    #4,R0
014416 012701 033500                      MOV    #33500,R1
                                ;SET LINE SPEED AND
                                ;CHARACTER LENGTH
                                ;ADDRESS OF TRANSMITTER
                                ;DATA BUFFER
                                ;400 (OCTAL) BYTES
                                ;WILL BE TRANSMITTED
                                ;START TRANSMITTER
                                ;WAIT FOR DATA TO BE RECEIVED

014422 012767 177740 001732      MOV    # 40,BYTCNT
014430 010577 001622      1$:      MOV    R5,@DHSCR
014434 016702 001722      MOV    BYTCNT,R2
014440 005402                      NEG    R2
014442 010177 001614      MOV    R1,@DHLPR      ;GET RECEIVED DATA
                                ;COMPER EXPECTED AND RECEIVED DATA

014446 012777 016364 001610      MOV    #TBUF,@DHBA
014454 016777 001702 001604      MOV    BYTCNT,@DHBC
                                ;STOP TRANSMITTER
                                ;DATA ERROR

014462 012777 040000 001600      MOV    #40000,@DHBAR
014470 105777 001562      2$:      TSTB    @DHSCR
014474 100375                      BPL     2$
014476 017703 001556      MOV    @DHNRC,R3
014502 020367 001652      CMP     R3,RDATA
014506 001407                      BEQ     3$
014510 005077 001554      CLR     @DHBAR
014514                      HLT     2
014514                      EMT     2
                                ;CHECK FOR LOOP AT CURRENT SPEED
                                ;RESTART TRANSMITTER
                                ;UPDATA EXPECTED DATA

014516 104410                      SCOPE1
014520 012777 040000 001542      MOV    #40000,@DHBAR
014526 105267 001626      3$:      INCB    RDATA
014532 005302                      DEC     R2
014534 001355                      BNE     2$
014536 105067 001616      CLRB    RDATA
                                ;INITIALIZE EXPECTED
                                ;RECEIVED DATA
                                ;UPDATA CHARACTER LENGTH

014542 005201                      INC     R1
014544 005204                      INC     R4
014546 006367 001610      ASL     BYTCNT
014552 005300                      DEC     R0
014554 001325                      BNE     1$
014556 104400      4$:      SCOPE
                                LINE=LINE+1
                                BITX=BITX+BITX
                                SDATA3 \LINE,\BITX

```

```

;SINGLE LINE DATA TEST
;TRANSMIT A BLOCK OF 400 (OCTAL) CHARACTERS ON LINE 17
;LINE SPEED IS 9600 BAUD
;CHARACTER LENGTH WILL START AT 5 BITS AND BE INCREMENTED
;TO 8 BITS
;A BLOCK OF 400 CHARACTERS WILL BE TRANSMITTED
;AT EACH CHARACTER LENGTH

```



```

014560      TS \XN,1,4$,1$
014560 012767 000340 163210 T60:  MOV  #340,PS      ;DISABLE ALL INTERRUPTS
014566 012767 000001 00153C      MOV  #1,ICOUNT    ;SET UP FOR 1 ITERATIONS
014574 012767 014776 001516      MOV  #4$,ESCAPE    ;SET UP TO ESCAPE TO NEXT TEST

014602 012767 014650 001512      .IF NB  <1$>
                                MOV  #1$,FREEZ1      ;SET UP TO LOOP WITH DATA      ; 3
                                .ENDC
                                XN=XN+1

014610      000061
014616 012777 004000 001440      MOV  #9IT11,@DHSCR    ;MASTER CLEAR INTERFACE
014620 012705 000017      CLR  F4      ;FIRST CHARACTER LENGTH CODE (5 BITS)
014624 012767 107400 001526      MOV  #17,R5      ;LINE 17 WILL BE TESTED
                                MOV  #17*400+100000,RDATA
                                ;SET EXPECTED LINE NUMBER
                                ;AND VALID DATA FLAG
                                ;EXPECTED DATA
                                ;4 CHARACTER LENGTHS
                                ;WILL BE TESTED
                                ;FIRST CHARACTER LENGTH =5 BITS,,
                                ;LINE SPEED =9600 BAUD
                                ;40 CHARACTERS AT 5 BITS
                                ;SELECT LINE 17

014632 012700 000004      MOV  #4,R0
                                ;SET LINE SPEED AND
                                ;CHARACTER LENGTH
                                ;ADDRESS OF TRANSMITTER
                                ;DATA BUFFER
                                ;400 (OCTAL) BYTES
                                ;WILL BE TRANSMITTED
                                ;START TRANSMITTER
                                ;WAIT FOR DATA TO BE RECEIVED

014636 012701 033500      MOV  #33500,R1
                                ;GET RECEIVED DATA
                                ;COMPER EXPECTED AND RECEIVED DATA

014642 012767 177740 001512      MOV  #-40,BYTCNT
014650 010577 001402      1$:  MOV  R5,@DHSCR
014654 016702 001502      MOV  BYTCNT,R2
014660 005402      NEG  R2
014662 010177 001374      MOV  R1,@DHLPR
                                ;STOP TRANSMITTER
                                ;DATA ERROR

014666 012777 016364 001370      MOV  #TBUF,@DHBA
                                ;CHECK FOR LOOP AT CURRENT SPEED
                                ;RESTART TRANSMITTER
                                ;UPDATA EXPECTED DATA

014674 016777 001462 001364      MOV  BYTCNT,@DHBC
                                ;INITIALIZE EXPECTED
                                ;RECEIVED DATA
                                ;UPDATA CHARACTER LENGTH

014702 012777 100000 001360      MOV  #100000,@DHBAR
014710 105777 001342      2$:  TSTB  @DHSCR
014714 100375      BPL  2$
014716 017703 001336      MOV  @DHNR,R3
014722 020367 001432      CMP  R3,RDATA
014726 001407      BEQ  3$
014730 005077 001334      CLR  @DHBAR
014734      HLT  2
014734 104002      EMT  2
014736 104410      SCOPE1
014740 012777 100000 001322      MOV  #100000,@DHBAR
014746 105267 001406      3$:  INCB  RDATA
014752 005302      DEC  R2
014754 001355      BNE  2$
014756 105067 001376      CLRB  RDATA

014762 005201      INC  R1
014764 005204      INC  R4
014766 006367 001370      ASL  BYTCNT
014772 005300      DEC  R0
014774 001325      BNE  1$
014776 104400      4$:  SCOPE
                                LINE=LINE+1
                                BITX=BITX+BITX
                                XDATA=0

```

```

1
2 015000      .EOP      +/BEGIN/

                        ;END OF PASS
                        ;TYPE NAME OF TEST
                        ;UPDATE PASS COUNT
                        ;CHECK FOR EXIT TO ACT-11
                        ;RESTART TEST

015000  104401      EOP:      TYPE
015002  017347      MEPASS      ;TYPE NAME OF TEST
015004  005067      001344      CLR      LAST      ;CLEAR LAST ERROR PC
015010  005067      001274      CLR      ERRFLG     ;CLEAR ERROR FLAG
015014  005267      001272      INC      PASCNT     ;UPDATE PASS COUNT
015020  005767      163756      TST      LIGHTS     ; ARE WE USING LIGHTS?      ; 4
015024  001005      BNE      2$      ; BRANCH IF WE ARE      ; 6
015026  104401      TYPE      ; TYPE PASCOUNT MESSAGE      ; 5
015030  017362      PASTXT      ; 5
015032  104402      OCTASC      ; PRINT PASCOUNT      ; 4
015034  015072      PASARG      ; 4
015036  000403      BR      3$      ; CONTINUE      ; 4 ; 6
015040      2$:
015040  016767      001246      163734      MOV      PASCNT,LIGHTS      ;DISPLAY PASS COUNT      ; 4
015046      3$:
015046  013701      000042      MOV      @42,R1      ;CHECK FOR ACT-11 OR DDP      ; 4
015052  001405      BEQ      RESTRT      ;IF NOT, CONTINUE TESTING
015054  000005      RESET
015056  004711      LOGICAL:      JSR      PC,(R1)
015060  000240      NOP
015062  000240      NOP
015064  000240      NOP
015066  000167      164214      RESTRT: JMP      BEGIN
015072  000001      PASARG: .WORD      1      ; PARAMETERS TO PRINT PASCOUNT      ; 5
015074      006      002      .BYTE      6,2      ; 5
015076  016312      .WORD      PASCNT      ; 5
3 015100      .SCOPE

                        ;CHECK FOR LOOP ON CURRENT TEST      ; 3
                        ;CHECK FOR ITERATION SUPPRESSION

015100  032777      002000      163672      SCOPER: BIT      @SW10,@SWR      ; 4
015106  001030      BNE      4$
015110  032777      040000      163662      1$:      BIT      @SW14,@SWR      ; 4
015116  001021      BNE      3$
015120  032777      004000      163652      BIT      @SW11,@SWR      ; 4
015126  001006      BNE      2$
015130  005267      001172      INC      LPCNT
015134  026767      001166      001162      CMP      LPCNT,ICOUNT
015142  001007      BNE      3$
015144  005067      001156      2$:      CLR      LPCNT
015150  005067      001134      CLR      ERRFLG
015154  011667      001136      MOV      (SP),RETRN
015160  000002      RTI
015162  016716      001130      3$:      MOV      RETRN,(SP)
015166  000002      RTI
015170  005767      001114      4$:      TST      ERRFLG
015174  001745      BEQ      1$

```

015176 000762  
4 015200

BR 2\$  
.SCOP1

;CHECK FOR FREEZE ON CURRENT DATA

015200 032777 001000 163572 SCOP1R: BIT #SW09,@SWR  
015206 001402 BEQ 1\$ ; 4  
015210 016716 001106 MOV FREEZ1,(SP)  
015214 000002 1\$: RTI

1 015216

.ERROR

;ERROR HANDLER

```

015216 032777 020000 163554 ERRORS: BIT    #SW13,BSWR
015224 001055          BNE    HALTS
015226 021667 001122    CMP    (SP),LAST
015232 001404          BEQ    1$
015234 011667 001114    MOV    (SP),LAST
015240 005067 001044    CLR    ERRFLG
015244 104406          1$: SAV05P
015246 011605          MOV    (SP),R5
015250 162705 000002    SUB    #2,R5
015254 011504          MOV    (R5),R4
015256 006304          ASL    R4
015260 006304          ASL    R4
015262 042704 177001    BIC    #177001,R4
015266 062704 017502    ADD    #ERRTAB,R4
015272 012467 000040    MOV    (R4)+,ERRMSG
015276 011467 000052    MOV    (R4),DATABP
015302 005767 001002    TST    ERRFLG
015306 001403          BEQ    TYPMSG
015310 005767 000040    TST    DATABP
015314 001011          BNE    TYPDAT
015316 104401          TYPMSG: TYPE
015320 017257          MCRLF
015322 104402          OCTASC
015324 015422          ERTAB0
015326 012767 000001 000754 MOV    #1,ERRFLG
015334 104401          TYPE
015336 000000          ERRMSG: 0
015340 005767 000010    TYPDAT: TST    DATABP
015344 001404          BEQ    RESREG
015346 104401          TYPE
015350 017257          MCRLF
015352 104402          OCTASC
015354 000000          DATABP: 0
015356 104407          RESREG: RES05
015360 005777 163414    HALTS: TST    BSWR
015364 100005          BPL    EXITER
015366 010046          PUSHRO
015370 016600 000002    MOV    2(SP),R0
015374 000000          HALT
015376 012600          POPRO
015400 005267 000710    EXITER: INC    ERRCNT
015404 032777 002000 163366 BIT    #SW10,BSWR
015412 001402          BEQ    1$
015414 016716 000700    MOV    ESCAPE,(SP)
015420 000002          1$: RTI
015422 000001          ERTAB0: 1
015424 006          .BYTE 6,2
015426 016346          SAVPC

```

; 4

; 3

; 5

; 5

; 5

; 5

; 5

; 4

; 4

015430

.TRPSRV

;TRAP DISPATCH SERVICE  
;ARGUMENT OF TRAP IS EXTRACTED  
;AND USED AS OFFSET TO OBTAIN POINTER  
;TO SELECTED SUBROUTINE

; 3

015430 011646  
015432 162716 000002  
015436 017616 000000  
015442 006316  
015444 042716 177001  
015450 062716 017422  
015454 017616 000000  
015460 000136

RPSRV: MOV (SP),-(SP) ;GET PC OF RETURN  
SUB #2,(SP) ;=PC OF TRAP  
MOV @((SP),(SP) ;GET TRP  
TRPOK: ASL (SP) ;MULTIPLY TRAP ARG BY 2  
BIC #177001,(SP) ;CLEAR UNWANTED BITS  
ADD #TRPTAB,(SP) ;POINTER TO SUBROUTINE ADDRESS  
MOV @((SP),(SP) ;SUBROUTINE ADDRESS  
JMP @((SP)+ ;GO TO SUBROUTINE

2 015462

.SAVREG

;SAVE PC OF TEST THAT FAILED AND R0-R5

015462 016667 000004 000656 SV05P: MOV 4(SP),SAVPC

;SAVE R0-R5

015470 010567 000646  
015474 010467 000640  
015500 010367 000632  
015504 010267 000624  
015510 010167 000616  
015514 010067 000610  
015520 000002

SV05: MOV R5,SAVR5  
MOV R4,SAVR4  
MOV R3,SAVR3  
MOV R2,SAVR2  
MOV R1,SAVR1  
MOV R0,SAVR0  
RTI

; 3

3 015522

.RESREG

;RESTORE R0-R5

015522 016700 000602  
015526 016701 000600  
015532 016702 000576  
015536 016703 000574  
015542 016704 000572  
015546 016705 000570  
015552 000002

RS05: MOV SAVR0,R0  
MOV SAVR1,R1  
MOV SAVR2,R2  
MOV SAVR3,R3  
MOV SAVR4,R4  
MOV SAVR5,R5  
RTI

1 015554

.TYPER

;TELETYPE OUTPUT ROUTINE

015554	017605	000000		TYPER:	MOV	@(SP),R5	
015560	062716	000002			ADD	#2,(SP)	; 3
015564	105777	000462		1\$:	TSTB	@TPCSR	
015570	100375				BPL	1\$	
015572	105715				TSTB	(R5)	
015574	001001				BNE	2\$	
015576	000002				RTI		
015600	112577	000450		2\$:	MOVB	(R5)+,@TPDBR	
015604	000767				BR	1\$	
2 015606				.INSTRG			

;ASCII SIPPING INPUT ROUTINE

015606	017667	000000	000006	INSTRG:	MOV	@(SP),MSG	
015614	062716	000002			ADD	#2,(SP)	
015620	104401			INSTR1:	TYPE		
015622	000000			MSG:	0		
015624	012704	017444			MOV	#INBUF,R4	
015630	012703	000007			MOV	#7,R3	
015634	105777	000406		1\$:	TSTB	@TKCSR	
015640	100375				BPL	1\$	
015642	117714	000402			MOVB	@TKDBR,(R4)	
015646	142714	000200			BICB	#200,(R4)	
015652	122427	000015			CMPB	(R4)+,#15	
015656	001413				BEQ	INSTR2	
015660	117777	000364	000366		MOVB	@TKDBR,@TPDBR	
015666	105777	000360		2\$:	TSTB	@TPCSR	
015672	100375				BPL	2\$	
015674	005303				DEC	R3	
015676	001356				BNE	1\$	
015700	104401			INSTRE:	TYPE		
015702	017253				MQM		
015704	000745				BR	INSTR1	
015706	000002			INSTR2:	RTI		

1 015710

.PARAMS

;CONVERT ASCII STRING TO OCTAL

; 3

015710 011605  
 015712 012567 000146  
 015716 012567 000144  
 015722 012567 000142  
 015726 112567 000140  
 015732 112567 000135  
 015736 010516  
 015740 005005  
 015742 012704 017444  
 015746 122714 000015  
 015752 001420  
 015754 121427 000060  
 015760 002415  
 015762 121427 000067  
 015766 003012  
 015770 142714 000060  
 015774 152405  
 015776 122714 000015  
 016002 001406  
 016004 006305  
 016006 006305  
 016010 006305  
 016012 000760  
 016014 104404  
 016016 000750

PARAMS: MOV (SP),R5  
 MOV (R5)+,LOLIM  
 MOV (R5)+,HILIM  
 MOV (R5)+,DEVADR  
 MOVB (R5)+,LOBITS  
 MOVB (R5)+,ADRCNT  
 MOV R5,(SP)  
 PARAM1: CLR R5  
 MOV #INBUF,R4  
 CMPB #15,(R4)  
 BEQ PARERR  
 1\$: CMPB (R4),#60  
 BLT PARERR  
 CMPB (R4),#67  
 BGT PARERR  
 BICB #60,(R4)  
 BISB (R4)+,R5  
 CMPB #15,(R4)  
 BEQ LIMITS  
 ASL R5  
 ASL R5  
 ASL R5  
 BR 1\$  
 PARERR: INSTER  
 BR PARAM1

;TEST TO SEE IF NUMBER IS WITHIN LIMITS

016020 020567 000042  
 016024 101373  
 016026 020567 000032  
 016032 103770  
 016034 136705 000032  
 016040 001365

LIMITS: CMP R5,HILIM  
 BHI PARERR  
 CMP R5,LOLIM  
 BLO PARERR  
 BITB LOBITS,R5  
 BNE PARERR

; 3

;STORE NUMBER AT SPECIFIED ADDRESS

016042 016704 000022  
 016046 010524  
 016050 062705 000002  
 016054 105367 000013  
 016060 001372  
 016062 000002  
 016064 000000  
 016066 000000  
 016070 000000  
 016072 000000  
 016073

1\$: MOV DEVADR,R4  
 MOV R5,(R4)+  
 ADD #2,R5  
 DECB ADRCNT  
 BNE 1\$  
 RTI  
 LOLIM: 0  
 HILIM: 0  
 DEVADR: 0  
 LOBITS: 0  
 ADRCNT=LOBITS+1

016074

.OCTASC

;CONVERT OCTAL NUMBER TO ASCII AND OUTPUT TO TELEPRINTER

016074	017601	000000	OCTASN: MOV	0(SP),R1	
016100	062716	000002	ADD	#2,(SP)	; 5
016104	012167	000130	MOV	(R1)+,WRDCNT	
016110	112167	000126	1\$: MOV	(R1)+,CHRCNT	
016114	112167	000123	MOV	(R1)+,SPACNT	
016120	013167	000120	MOV	0(R1)+,BINWRD	; 3
016124	016704	000114	2\$: MOV	BINWRD,R4	
016130	116705	000106	MOV	CHRCNT,R5	
016134	012700	017456	MOV	#TEMP,R0	
016140	010403		3\$: MOV	R4,R3	
016142	042703	177770	BIC	#177770,R3	
016146	062703	000260	ADD	#260,R3	
016152	110320		MOVB	R3,(R0)+	
016154	006204		ASR	R4	
016156	006204		ASR	R4	
016160	006204		ASR	R4	
016162	005305		DEC	R5	
016164	001365		BNE	3\$	
016166	012703	017470	MOV	#MDATA,R3	
016172	114023		4\$: MOVB	-(R0),(R3)+	
016174	105367	000042	DECB	CHRCNT	
016200	001374		BNE	4\$	
016202	105767	000035	TSTB	SPACNT	
016206	001405		BEQ	6\$	
016210	112723	000240	5\$: MOVB	#240,(R3)+	
016214	105367	000023	DECB	SPACNT	
016220	001373		BNE	5\$	
016222	105013		6\$: CLRB	(R3)	
016224	104401		TYPE		
016226	017470		MDATA		
016230	005367	000004	DEC	WRDCNT	
016234	001325		BNE	1\$	
016236	000002		RTI		
016240	000000		WRDCNT: 0		
016242	000000		CHRCNT: 0		
	016243		SPACNT=CHRCNT+1		
016244	000000		BINWRD: 0		



```

016246      .POINT  + 'DHSCR,DHNRCDHLP, DHBA,DHBC,DHBAR,DHBCR,DHSSP,DHSLR,DHREVC,DHRLVL,DHTEVC,DHTLVL/
               ;INDIRECT POINTERS
               ; 3

016246 177560  TKCSR: 177560
016250 177562  TKDBR: 177562
016252 177564  TPCSR: 177564
016254 177566  TPDBR: 177566
               .IRP  A      <DHSCR,DHNRCDHLP, DHBA,DHBC,DHBAR,DHBCR,DHSSP,DHSLR,DHREVC,DHRLVL,DHTEVC,DH
TLVL>
               A: 0
               .ENDM
016256 000000  DHSCR: 0
016260 000000  DHNRCD: 0
016262 000000  DHLP: 0
016264 000000  DHBA: 0
016266 000000  DHBC: 0
016270 000000  DHBAR: 0
016272 000000  DHBCR: 0
016274 000000  DHSSP: 0
016276 000000  DHSLR: 0
016300 000000  DHREVC: 0
016302 000000  DHRLVL: 0
016304 000000  DHTEVC: 0
016306 000000  DHTLVL: 0
2 016310      .VARIA  + /TDATA,RDATA,BYTCNT/
               ;PROGRAM VARIABLES

016310 000000  ERRFLG: 0      ;ERROR FLAG
016312 000000  PASCNT: 0      ;PASS COUNT
016314 000000  ERRCNT: 0      ;ERROR COUNT
016316 000000  RETRN: 0       ;SCOPE RETURN ADDRESS FOR TEST LOOPING
016320 000000  ESCAPE: 0      ;ADDRESS FOR ERROR ESCAPE
016322 000000  FREEZ1: 0      ;DATA LOOPING RETURN ADDRESS
016324 000000  ICOUNT: 0      ;ITERATION COUNT FOR TEST IN PROGRESS
016326 000000  LPCNT: 0       ;NUMBER OF ITERATIONS THIS TEST
016330 000000  SAVR0: 0       ;R0 SAVE AREA
016332 000000  SAVR1: 0       ;R1 SAVE AREA
016334 000000  SAVR2: 0       ;R2 SAVE AREA
016336 000000  SAVR3: 0       ;R3 SAVE ARE
016340 000000  SAVR4: 0       ;R4 SAVE AREA
016342 000000  SAVR5: 0       ;R5 SAVE AREA
016344 000000  SAVSP: 0       ;STACK POINTER SAVE AREA
016346 000000  SAVPC: 0       ;CALLING ROUTINE SAVE AREA
016350 000000  INIFLG: 0      ;PROGRAM INITIALIZATION FLAG
016352 000000  STFLG: 0       ;PROGRAM START FLAG
016354 000000  LAST: 0        ;LAST ERROR PC
               .IRP  A      <TDATA,RDATA,BYTCNT>
               A: 0
               .ENDM
016356 000000  TDATA: 0
016360 000000  RDATA: 0
016362 000000  BYTCNT: 0

```

; 3

1	016364	000400	TBUF: .REPT 400
2			.BYTE XDATA
3			.NLIST
4			XDATA=XDATA+1
5			.LIST
6			.ENDR
	016364	000	.BYTE XDATA
		000001	XDATA=XDATA+1
	016365	001	.BYTE XDATA
		000002	XDATA=XDATA+1
	016366	002	.BYTE XDATA
		000003	XDATA=XDATA+1
	016367	003	.BYTE XDATA
		000004	XDATA=XDATA+1
	016370	004	.BYTE XDATA
		000005	XDATA=XDATA+1
	016371	005	.BYTE XDATA
		000006	XDATA=XDATA+1
	016372	006	.BYTE XDATA
		000007	XDATA=XDATA+1
	016373	007	.BYTE XDATA
		000010	XDATA=XDATA+1
	016374	010	.BYTE XDATA
		000011	XDATA=XDATA+1
	016375	011	.BYTE XDATA
		000012	XDATA=XDATA+1
	016376	012	.BYTE XDATA
		000013	XDATA=XDATA+1
	016377	013	.BYTE XDATA
		000014	XDATA=XDATA+1
	016400	014	.BYTE XDATA
		000015	XDATA=XDATA+1
	016401	015	.BYTE XDATA
		000016	XDATA=XDATA+1
	016402	016	.BYTE XDATA
		000017	XDATA=XDATA+1
	016403	017	.BYTE XDATA
		000020	XDATA=XDATA+1
	016404	020	.BYTE XDATA
		000021	XDATA=XDATA+1
	016405	021	.BYTE XDATA
		000022	XDATA=XDATA+1
	016406	022	.BYTE XDATA
		000023	XDATA=XDATA+1
	016407	023	.BYTE XDATA
		000024	XDATA=XDATA+1
	016410	024	.BYTE XDATA
		000025	XDATA=XDATA+1
	016411	025	.BYTE XDATA
		000026	XDATA=XDATA+1
	016412	026	.BYTE XDATA
		000027	XDATA=XDATA+1
	016413	027	.BYTE XDATA
		000030	XDATA=XDATA+1
	016414	030	.BYTE XDATA
		000031	XDATA=XDATA+1
	016415	031	.BYTE XDATA

	000032	XDATA=XDATA+1
016416	032	.BYTE XDATA
	000033	XDATA=XDATA+1
016417	033	.BYTE XDATA
	000034	XDATA=XDATA+1
016420	034	.BYTE XDATA
	000035	XDATA=XDATA+1
016421	035	.BYTE XDATA
	000036	XDATA=XDATA+1
016422	036	.BYTE XDATA
	000037	XDATA=XDATA+1
016423	037	.BYTE XDATA
	000040	XDATA=XDATA+1
016424	040	.BYTE XDATA
	000041	XDATA=XDATA+1
016425	041	.BYTE XDATA
	000042	XDATA=XDATA+1
016426	042	.BYTE XDATA
	000043	XDATA=XDATA+1
016427	043	.BYTE XDATA
	000044	XDATA=XDATA+1
016430	044	.BYTE XDATA
	000045	XDATA=XDATA+1
016431	045	.BYTE XDATA
	000046	XDATA=XDATA+1
016432	046	.BYTE XDATA
	000047	XDATA=XDATA+1
016433	047	.BYTE XDATA
	000050	XDATA=XDATA+1
016434	050	.BYTE XDATA
	000051	XDATA=XDATA+1
016435	051	.BYTE XDATA
	000052	XDATA=XDATA+1
016436	052	.BYTE XDATA
	000053	XDATA=XDATA+1
016437	053	.BYTE XDATA
	000054	XDATA=XDATA+1
016440	054	.BYTE XDATA
	000055	XDATA=XDATA+1
016441	055	.BYTE XDATA
	000056	XDATA=XDATA+1
016442	056	.BYTE XDATA
	000057	XDATA=XDATA+1
016443	057	.BYTE XDATA
	000060	XDATA=XDATA+1
016444	060	.BYTE XDATA
	000061	XDATA=XDATA+1
016445	061	.BYTE XDATA
	000062	XDATA=XDATA+1
016446	062	.BYTE XDATA
	000063	XDATA=XDATA+1
016447	063	.BYTE XDATA
	000064	XDATA=XDATA+1
016450	064	.BYTE XDATA
	000065	XDATA=XDATA+1
016451	065	.BYTE XDATA
	000066	XDATA=XDATA+1

016452	066	.BYTE XDATA
	000067	XDATA=XDATA+1
016453	067	.BYTE XDATA
	000070	XDATA=XDATA+1
016454	070	.BYTE XDATA
	000071	XDATA=XDATA+1
016455	071	.BYTE XDATA
	000072	XDATA=XDATA+1
016456	072	.BYTE XDATA
	000073	XDATA=XDATA+1
016457	073	.BYTE XDATA
	000074	XDATA=XDATA+1
016460	074	.BYTE XDATA
	000075	XDATA=XDATA+1
016461	075	.BYTE XDATA
	000076	XDATA=XDATA+1
016462	076	.BYTE XDATA
	000077	XDATA=XDATA+1
016463	077	.BYTE XDATA
	000100	XDATA=XDATA+1
016464	100	.BYTE XDATA
	000101	XDATA=XDATA+1
016465	101	.BYTE XDATA
	000102	XDATA=XDATA+1
016466	102	.BYTE XDATA
	000103	XDATA=XDATA+1
016467	103	.BYTE XDATA
	000104	XDATA=XDATA+1
016470	104	.BYTE XDATA
	000105	XDATA=XDATA+1
016471	105	.BYTE XDATA
	000106	XDATA=XDATA+1
016472	106	.BYTE XDATA
	000107	XDATA=XDATA+1
016473	107	.BYTE XDATA
	000110	XDATA=XDATA+1
016474	110	.BYTE XDATA
	000111	XDATA=XDATA+1
016475	111	.BYTE XDATA
	000112	XDATA=XDATA+1
016476	112	.BYTE XDATA
	000113	XDATA=XDATA+1
016477	113	.BYTE XDATA
	000114	XDATA=XDATA+1
016500	114	.BYTE XDATA
	000115	XDATA=XDATA+1
016501	115	.BYTE XDATA
	000116	XDATA=XDATA+1
016502	116	.BYTE XDATA
	000117	XDATA=XDATA+1
016503	117	.BYTE XDATA
	000120	XDATA=XDATA+1
016504	120	.BYTE XDATA
	000121	XDATA=XDATA+1
016505	121	.BYTE XDATA
	000122	XDATA=XDATA+1
016506	122	.BYTE XDATA

	000123	XDATA=XDATA+1
016507	123	.BYTE XDATA
	000124	XDATA=XDATA+1
016510	124	.BYTE XDATA
	000125	XDATA=XDATA+1
016511	125	.BYTE XDATA
	000126	XDATA=XDATA+1
016512	126	.BYTE XDATA
	000127	XDATA=XDATA+1
016513	127	.BYTE XDATA
	000130	XDATA=XDATA+1
016514	130	.BYTE XDATA
	000131	XDATA=XDATA+1
016515	131	.BYTE XDATA
	000132	XDATA=XDATA+1
016516	132	.BYTE XDATA
	000133	XDATA=XDATA+1
016517	133	.BYTE XDATA
	000134	XDATA=XDATA+1
016520	134	.BYTE XDATA
	000135	XDATA=XDATA+1
016521	135	.BYTE XDATA
	000136	XDATA=XDATA+1
016522	136	.BYTE XDATA
	000137	XDATA=XDATA+1
016523	137	.BYTE XDATA
	000140	XDATA=XDATA+1
016524	140	.BYTE XDATA
	000141	XDATA=XDATA+1
016525	141	.BYTE XDATA
	000142	XDATA=XDATA+1
016526	142	.BYTE XDATA
	000143	XDATA=XDATA+1
016527	143	.BYTE XDATA
	000144	XDATA=XDATA+1
016530	144	.BYTE XDATA
	000145	XDATA=XDATA+1
016531	145	.BYTE XDATA
	000146	XDATA=XDATA+1
016532	146	.BYTE XDATA
	000147	XDATA=XDATA+1
016533	147	.BYTE XDATA
	000150	XDATA=XDATA+1
016534	150	.BYTE XDATA
	000151	XDATA=XDATA+1
016535	151	.BYTE XDATA
	000152	XDATA=XDATA+1
016536	152	.BYTE XDATA
	000153	XDATA=XDATA+1
016537	153	.BYTE XDATA
	000154	XDATA=XDATA+1
016540	154	.BYTE XDATA
	000155	XDATA=XDATA+1
016541	155	.BYTE XDATA
	000156	XDATA=XDATA+1
016542	156	.BYTE XDATA
	000157	XDATA=XDATA+1

016543	157	.BYTE XDATA
	000160	XDATA=XDATA+1
016544	160	.BYTE XDATA
	000161	XDATA=XDATA+1
016545	161	.BYTE XDATA
	000162	XDATA=XDATA+1
016546	162	.BYTE XDATA
	000163	XDATA=XDATA+1
016547	163	.BYTE XDATA
	000164	XDATA=XDATA+1
016550	164	.BYTE XDATA
	000165	XDATA=XDATA+1
016551	165	.BYTE XDATA
	000166	XDATA=XDATA+1
016552	166	.BYTE XDATA
	000167	XDATA=XDATA+1
016553	167	.BYTE XDATA
	000170	XDATA=XDATA+1
016554	170	.BYTE XDATA
	000171	XDATA=XDATA+1
016555	171	.BYTE XDATA
	000172	XDATA=XDATA+1
016556	172	.BYTE XDATA
	000173	XDATA=XDATA+1
016557	173	.BYTE XDATA
	000174	XDATA=XDATA+1
016560	174	.BYTE XDATA
	000175	XDATA=XDATA+1
016561	175	.BYTE XDATA
	000176	XDATA=XDATA+1
016562	176	.BYTE XDATA
	000177	XDATA=XDATA+1
016563	177	.BYTE XDATA
	000200	XDATA=XDATA+1
016564	200	.BYTE XDATA
	000201	XDATA=XDATA+1
016565	201	.BYTE XDATA
	000202	XDATA=XDATA+1
016566	202	.BYTE XDATA
	000203	XDATA=XDATA+1
016567	203	.BYTE XDATA
	000204	XDATA=XDATA+1
016570	204	.BYTE XDATA
	000205	XDATA=XDATA+1
016571	205	.BYTE XDATA
	000206	XDATA=XDATA+1
016572	206	.BYTE XDATA
	000207	XDATA=XDATA+1
016573	207	.BYTE XDATA
	000210	XDATA=XDATA+1
016574	210	.BYTE XDATA
	000211	XDATA=XDATA+1
016575	211	.BYTE XDATA
	000212	XDATA=XDATA+1
016576	212	.BYTE XDATA
	000213	XDATA=XDATA+1
016577	213	.BYTE XDATA

	000214	XDATA=XDATA+1
016600	214	.BYTE XDATA
	000215	XDATA=XDATA+1
016601	215	.BYTE XDATA
	000216	XDATA=XDATA+1
016602	216	.BYTE XDATA
	000217	XDATA=XDATA+1
016603	217	.BYTE XDATA
	000220	XDATA=XDATA+1
016604	220	.BYTE XDATA
	000221	XDATA=XDATA+1
016605	221	.BYTE XDATA
	000222	XDATA=XDATA+1
016606	222	.BYTE XDATA
	000223	XDATA=XDATA+1
016607	223	.BYTE XDATA
	000224	XDATA=XDATA+1
016610	224	.BYTE XDATA
	000225	XDATA=XDATA+1
016611	225	.BYTE XDATA
	000226	XDATA=XDATA+1
016612	226	.BYTE XDATA
	000227	XDATA=XDATA+1
016613	227	.BYTE XDATA
	000230	XDATA=XDATA+1
016614	230	.BYTE XDATA
	000231	XDATA=XDATA+1
016615	231	.BYTE XDATA
	000232	XDATA=XDATA+1
016616	232	.BYTE XDATA
	000233	XDATA=XDATA+1
016617	233	.BYTE XDATA
	000234	XDATA=XDATA+1
016620	234	.BYTE XDATA
	000235	XDATA=XDATA+1
016621	235	.BYTE XDATA
	000236	XDATA=XDATA+1
016622	236	.BYTE XDATA
	000237	XDATA=XDATA+1
016623	237	.BYTE XDATA
	000240	XDATA=XDATA+1
016624	240	.BYTE XDATA
	000241	XDATA=XDATA+1
016625	241	.BYTE XDATA
	000242	XDATA=XDATA+1
016626	242	.BYTE XDATA
	000243	XDATA=XDATA+1
016627	243	.BYTE XDATA
	000244	XDATA=XDATA+1
016630	244	.BYTE XDATA
	000245	XDATA=XDATA+1
016631	245	.BYTE XDATA
	000246	XDATA=XDATA+1
016632	246	.BYTE XDATA
	000247	XDATA=XDATA+1
016633	247	.BYTE XDATA
	000250	XDATA=XDATA+1

016634	250	.BYTE XDATA
	000251	XDATA=XDATA+1
016635	251	.BYTE XDATA
	000252	XDATA=XDATA+1
016636	252	.BYTE XDATA
	000253	XDATA=XDATA+1
016637	253	.BYTE XDATA
	000254	XDATA=XDATA+1
016640	254	.BYTE XDATA
	000255	XDATA=XDATA+1
016641	255	.BYTE XDATA
	000256	XDATA=XDATA+1
016642	256	.BYTE XDATA
	000257	XDATA=XDATA+1
016643	257	.BYTE XDATA
	000260	XDATA=XDATA+1
016644	260	.BYTE XDATA
	000261	XDATA=XDATA+1
016645	261	.BYTE XDATA
	000262	XDATA=XDATA+1
016646	262	.BYTE XDATA
	000263	XDATA=XDATA+1
0 547	263	.BYTE XDATA
	000264	XDATA=XDATA+1
016650	264	.BYTE XDATA
	000265	XDATA=XDATA+1
016651	265	.BYTE XDATA
	000266	XDATA=XDATA+1
016652	266	.BYTE XDATA
	000267	XDATA=XDATA+1
016653	267	.BYTE XDATA
	000270	XDATA=XDATA+1
016654	270	.BYTE XDATA
	000271	XDATA=XDATA+1
016655	271	.BYTE XDATA
	000272	XDATA=XDATA+1
016656	272	.BYTE XDATA
	000273	XDATA=XDATA+1
016657	273	.BYTE XDATA
	000274	XDATA=XDATA+1
016660	274	.BYTE XDATA
	000275	XDATA=XDATA+1
016661	275	.BYTE XDATA
	000276	XDATA=XDATA+1
016662	276	.BYTE XDATA
	000277	XDATA=XDATA+1
016663	277	.BYTE XDATA
	000300	XDATA=XDATA+1
016664	300	.BYTE XDATA
	000301	XDATA=XDATA+1
016665	301	.BYTE XDATA
	000302	XDATA=XDATA+1
016666	302	.BYTE XDATA
	000303	XDATA=XDATA+1
016667	303	.BYTE XDATA
	000304	XDATA=XDATA+1
016670	304	.BYTE XDATA



	000305	XDATA=XDATA+1
016671	305	.BYTE XDATA
	000306	XDATA=XDATA+1
016672	306	.BYTE XDATA
	000307	XDATA=XDATA+1
016673	307	.BYTE XDATA
	000310	XDATA=XDATA+1
016674	310	.BYTE XDATA
	000311	XDATA=XDATA+1
016675	311	.BYTE XDATA
	000312	XDATA=XDATA+1
016676	312	.BYTE XDATA
	000313	XDATA=XDATA+1
016677	313	.BYTE XDATA
	000314	XDATA=XDATA+1
016700	314	.BYTE XDATA
	000315	XDATA=XDATA+1
016701	315	.BYTE XDATA
	000316	XDATA=XDATA+1
016702	316	.BYTE XDATA
	000317	XDATA=XDATA+1
016703	317	.BYTE XDATA
	000320	XDATA=XDATA+1
016704	320	.BYTE XDATA
	000321	XDATA=XDATA+1
016705	321	.BYTE XDATA
	000322	XDATA=XDATA+1
016706	322	.BYTE XDATA
	000323	XDATA=XDATA+1
016707	323	.BYTE XDATA
	000324	XDATA=XDATA+1
016710	324	.BYTE XDATA
	000325	XDATA=XDATA+1
016711	325	.BYTE XDATA
	000326	XDATA=XDATA+1
016712	326	.BYTE XDATA
	000327	XDATA=XDATA+1
016713	327	.BYTE XDATA
	000330	XDATA=XDATA+1
016714	330	.BYTE XDATA
	000331	XDATA=XDATA+1
016715	331	.BYTE XDATA
	000332	XDATA=XDATA+1
016716	332	.BYTE XDATA
	000333	XDATA=XDATA+1
016717	333	.BYTE XDATA
	000334	XDATA=XDATA+1
016720	334	.BYTE XDATA
	000335	XDATA=XDATA+1
016721	335	.BYTE XDATA
	000336	XDATA=XDATA+1
016722	336	.BYTE XDATA
	000337	XDATA=XDATA+1
016723	337	.BYTE XDATA
	000340	XDATA=XDATA+1
016724	340	.BYTE XDATA
	000341	XDATA=XDATA+1

016725	341	.BYTE XDATA
	000342	XDATA=XDATA+1
016726	342	.BYTE XDATA
	000343	XDATA=XDATA+1
016727	343	.BYTE XDATA
	000344	XDATA=XDATA+1
016730	344	.BYTE XDATA
	000345	XDATA=XDATA+1
016731	345	.BYTE XDATA
	000346	XDATA=XDATA+1
016732	346	.BYTE XDATA
	000347	XDATA=XDATA+1
016733	347	.BYTE XDATA
	000350	XDATA=XDATA+1
016734	350	.BYTE XDATA
	000351	XDATA=XDATA+1
016735	351	.BYTE XDATA
	000352	XDATA=XDATA+1
016736	352	.BYTE XDATA
	000353	XDATA=XDATA+1
016737	353	.BYTE XDATA
	000354	XDATA=XDATA+1
016740	354	.BYTE XDATA
	000355	XDATA=XDATA+1
016741	355	.BYTE XDATA
	000356	XDATA=XDATA+1
016742	356	.BYTE XDATA
	000357	XDATA=XDATA+1
016743	357	.BYTE XDATA
	000360	XDATA=XDATA+1
016744	360	.BYTE XDATA
	000361	XDATA=XDATA+1
016745	361	.BYTE XDATA
	000362	XDATA=XDATA+1
016746	362	.BYTE XDATA
	000363	XDATA=XDATA+1
016747	363	.BYTE XDATA
	000364	XDATA=XDATA+1
016750	364	.BYTE XDATA
	000365	XDATA=XDATA+1
016751	365	.BYTE XDATA
	000366	XDATA=XDATA+1
016752	366	.BYTE XDATA
	000367	XDATA=XDATA+1
016753	367	.BYTE XDATA
	000370	XDATA=XDATA+1
016754	370	.BYTE XDATA
	000371	XDATA=XDATA+1
016755	371	.BYTE XDATA
	000372	XDATA=XDATA+1
016756	372	.BYTE XDATA
	000373	XDATA=XDATA+1
016757	373	.BYTE XDATA
	000374	XDATA=XDATA+1
016760	374	.BYTE XDATA
	000375	XDATA=XDATA+1
016761	375	.BYTE XDATA

```

016762 000376          XDATA=XDATA+1
          376          .BYTE  XDATA
016763 000377          XDATA=XDATA+1
          377          .BYTE  XDATA
          000400        XDATA=XDATA+1
7          .EVEN
8 016764          .PFAIL
                                ;ENTER HERE ON POWER FAILURE

016764 010046          PFAIL:  MOV    R0,-(SP)          ;SAVE R0 R5 ON PROCESSOR STACK
016766 010146          MOV    R1,-(SP)
016770 010246          MOV    R2,-(SP)
016772 010346          MOV    R3,-(SP)
016774 010446          MOV    R4,-(SP)
016776 010546          MOV    R5,-(SP)
017000 016746 161020    MOV    24,-(SP)
017004 010667 177334    MOV    SP,SAVSP
017010 012767 017022 161006  MOV    @RESTART,24          ;SAVE STACK POINTER
017016 000000          HALT                                ;SET UP FOR POWER UP TRAP
017020 000777          BR      .                          ;HALT ON POWER DOWN NORMAL ; 3

                                ;PROCESSOR WILL TRAP HERE WHEN POWER IS RESTORED

017022 016706 177316    RESTAR: MOV    SAVSP,SP          ;RESTORE STACK POINTER
017026 012605          MOV    (SP)+,R5          ;RESTORE R0-R5
017030 012604          MOV    (SP)+,R4
017032 012603          MOV    (SP)+,R3
017034 012602          MOV    (SP)+,R2
017036 012601          MOV    (SP)+,R1
017040 012600          MOV    (SP)+,R0
017042 012767 016764 160754  MOV    @PFAIL,24          ;SET UP FOR POWER FAILURE
017050 012767 000340 160720  MOV    #340,PS
017056 012706 020164    MOV    @STACK,SP
017062 005067 000370    CLR     TEMP
017066 005267 000364    INC     TEMP
017072 001375          BNE     .-4
017074 104401          TYPE
017076 017257          MCRLF
017100 104402          OCTASC
017102 017124          PFTAB
017104 104401          TYPE
017106 017262          MPFAIL
017110 005067 177174    CLR     ERRFLG
017114 005067 177234    CLR     LAST
017120 000177 177172    JMP     @RETRN
017124 000001          PFTAB:  1
017126 000006 000002    6,2
017132 016316          RETRN

9 017134          .MSG  +/DH11 SINGLE LINE DATA TEST/,+/CZDMF-CO/
017134          015      012      012  MTITLE:  .ASCIZ  <15><12><12>/DH11 SINGLE LINE DATA TEST /<15><12>
017137          104      110      061
017142          061      040      123
017145          111      116      107
017150          114      105      040
017153          114      111      116
017156          105      040      104

```

017161	101	124	101	
017164	040	124	105	
017167	123	124	040	
017172	015	012	000	
017175	015	012	126	MVECTOR: .ASCIZ <15><12>/VECTOR ADDRESS- /
017200	105	103	124	
017203	117	122	040	
017206	101	104	104	
017211	122	105	123	
017214	123	055	000	
017217	015	012	103	MREGAD: .ASCIZ <15><12>/CONTROL REGISTER ADDRESS- /
017222	117	116	124	
017225	122	117	114	
017230	040	122	105	
017233	107	111	123	
017236	124	105	122	
017241	040	101	104	
017244	104	122	105	
017247	123	123	055	
017252	000			
017253	040	040	077	MQM: .ASCIZ / ? /
017256	000			
017257	015	012	000	MCRLF: .ASCIZ <15><12>
017262	040	040	120	MPFAIL: .ASCIZ / POWER FAILURE, PROGRAM RESTART AT TEST IN PROGRESS /
017265	117	127	105	
017270	122	040	106	
017273	101	111	114	
017276	125	122	105	
017301	054	040	120	
017304	122	117	107	
017307	122	101	115	
017312	040	122	105	
017315	123	124	101	
017320	122	124	040	
017323	101	124	040	
017326	124	105	123	
017331	124	040	111	
017334	116	040	120	
017337	122	117	107	
017342	122	105	123	
017345	123	000		
017347	015	012	103	MEPASS: .ASCIZ <15><12>/CZDHF-CO /
017352	132	104	110	
017355	106	055	103	
017360	060	000		
017362	015	012	120	PASTXT: .ASCIZ <15><12>/PASS COUNT = /
017365	101	123	123	
017370	040	103	117	
017373	125	116	124	
017376	040	075	040	
017401	000			
017402	015	012	122	MR: .ASCIZ <15><12>/R /
017405	000			
017406	015	012	124	MTSTPC: .ASCIZ <15><12>/TEST PC - /
017411	105	123	124	
017414	040	120	103	

: 5

017417 055 000

10

11 017422

.EVEN  
.EVEN  
.TRPTAB

;TABLE OF POINTERS FOR TRAP DECODING

017422 015100  
017424 015554  
017426 016074  
017430 015606  
017432 015700  
017434 015710  
017436 015462  
017440 015522  
017442 015200TRPTAB: SCOPER  
TYPER  
OCTASN  
INSTRG  
INSTRE  
PARAMS  
SV05P  
RS05  
SCOP1R

12 017444

.BUFFER

;BUFFERS FOR INPUT-OUTPUT

017444 000000  
017456 000000  
017470 000000INBUF: 0  
.=.+10  
TEMP: 0  
.=.+10017470 000000  
017502 017502MDATA: 0  
.=.+10  
.ERRTAB

13 017502

;TABLE OF POINTERS TO ERROR MESSAGES AND DATA

017502  
14 017502 017516  
15 017504 017702  
16 017506 017557  
17 017510 017720  
18 017512 017630  
19 017514 017742

ERRTAB:

EM1  
DT1  
EM2  
DT2  
EM3  
DT320 017516 104 101 124  
017521 101 040 105  
017524 122 122 117  
017527 122 015 012  
017532 105 130 120  
017535 040 040 040  
017540 040 040 122  
017543 105 103 040  
017546 040 040 040  
017551 040 114 111  
017554 116 105 000  
21 017557 104 101 124  
017562 101 040 105  
017565 122 122 117  
017570 122 015 012  
017573 105 130 120  
017576 040 040 040  
017601 040 040 122  
017604 105 103 040

EM1: .ASCIZ /DATA ERROR/&lt;15&gt;&lt;12&gt;/EXP REC LINE/

EM2: .ASCIZ /DATA ERROR/&lt;15&gt;&lt;12&gt;/EXP REC SPEED LINE/

	017607	040	040	040			
	017612	040	123	120			
	017615	105	105	104			
	017620	040	040	040			
	017623	114	111	116			
	017626	105	000				
22	017630	104	101	124	EM3:	.ASCIZ /DATA ERROR/<15><12>/EXP	REC LENGTH LINE/
	017633	101	040	105			
	017636	122	122	117			
	017641	122	015	012			
	017644	105	130	120			
	017647	040	040	040			
	017652	040	040	122			
	017655	105	103	040			
	017660	040	040	040			
	017663	040	114	105			
	017666	116	107	124			
	017671	110	040	040			
	017674	114	111	116			
	017677	105	000				
23					.EVEN		
24	017702	000003			DT1:	3	
25	017704	006	002		.BYTE	6,2	
26	017706	016356				TDATA	
27	017710	006	002		.BYTE	6,2	
28	017712	016340				SAVR4	
29	017714	002	000		.BYTE	2,0	
30	017716	016336				SAVR3	
31	017720	000004			DT2:	4	
32	017722	006	002		.BYTE	6,2	
33	017724	016360				RDATA	
34	017726	006	002		.BYTE	6,2	
35	017730	016336				SAVR3	
36	017732	002	005		.BYTE	2,5	
37	017734	016334				SAVR2	
38	017736	002	000		.BYTE	2,0	
39	017740	016342				SAVR5	
40	017742	000004			DT3:	4	
41	017744	006	002		.BYTE	6,2	
42	017746	016360				RDATA	
43	017750	006	002		.BYTE	6,2	
44	017752	016336				SAVR3	
45	017754	002	006		.BYTE	2,6	
46	017756	016340				SAVR4	
47	017760	002	000		.BYTE	2,0	
48	017762	016342				SAVR5	
49	017764				.ENDCOD		
	017764	000000			ENDCOD: 0		
50		000001			.END		

ADRCNT = 016073	EOP 015000	PARAM = 104405	SW00 = 000001	T24 005232
BEGIN 001306	ERRCNT 016314	PARAMS 015710	SW01 = 000002	T25 005430
BINWRD 016244	ERRFLG 016310	PARAM1 015740	SW02 = 000004	T26 005626
BITX = 000000	ERRMSG 015336	PARERR 016014	SW03 = 000010	T27 006024
BIT00 = 000001	ERRORS 015216	PASARG 015072	SW04 = 000020	T3 001704
BIT01 = 000002	ERRTAB 017502	PASCNT 016312	SW05 = 000040	T30 006222
BIT02 = 000004	ERTAB0 015422	PASTXT 017362	SW06 = 000100	T31 006420
BIT03 = 000010	ESCAPE 016320	PFAIL 016764	SW08 = 000400	T32 006616
BIT04 = 000020	EXITER 015400	PFTAB 017124	SW09 = 001000	T33 007014
BIT05 = 000040	FREEZ1 016322	POPRO = 012600	SW10 = 002000	T34 007212
BIT06 = 000100	HALTS 015360	POP1SP = 005726	SW11 = 004000	T35 007410
BIT07 = 000200	HILIM 016066	POP2SP = 022626	SW12 = 010000	T36 007606
BIT08 = 000400	ICOUNT 016324	PS = 1776	SW13 = 020000	T37 010004
BIT09 = 001000	INBUF 017444	PUSHRO = 010046	SW14 = 040000	T4 002046
BIT10 = 002000	INIFLG 016350	PUSH1S = 005746	SW15 = 100000	T40 010202
BIT11 = 004000	INSTER = 104404	PUSH2S = 024646	TBUF 016364	T41 010400
BIT12 = 010000	INSTR = 104403	RDATA 016360	TDATA 016356	T42 010620
BIT13 = 020000	INSTRE 015700	RESREG 015356	TEMP 017456	T43 011040
BIT14 = 040000	INSTRG 015606	RESTAR 017022	TKCSR 016246	T44 011260
BIT15 = 100000	INSTR1 015620	RESTR1 015066	TKDBR 016250	T45 011500
BYICNT 016362	INSTR2 015706	RES05 = 104407	TPCSR 016252	T46 011720
CHRCNT 016242	LAST 016354	RETRN 016316	TPDBR 016254	T47 012140
DATABP 015354	LIGHTS 001002	RS05 015522	TRPOK 015442	T5 002210
DEVADR 016070	LIMITS 016020	SAVPC 016346	TRPSRV 015430	T50 012360
DHBA 016264	LINE = 000020	SAVRO 016330	TRPTAB 017422	T51 012600
DHBAR 016270	LOBITS 016072	SAVR1 016332	TYPDAT 015540	T52 013020
DHBC 016266	LOGICA 015056	SAVR2 016334	TYPE = 104401	T53 013240
DHBCR 016272	LOLIM 016064	SAVR3 016336	TYPER 015554	T54 013460
DHLPR 016262	LPCNT 016326	SAVR4 016340	TYPMSG 015316	T55 013700
DHNRC 016260	MCRLF 017257	SAVR5 016342	T1 001400	T56 014120
DHRLVL 016302	MDATA 017470	SAVSP 016344	T10 002656	T57 014340
DHRVEC 016300	MEPASS 017347	SAV0SP = 104406	T11 003020	T6 002352
DHSCR 016256	MPFAIL 017262	SCOPE = 104400	T12 003162	T60 014560
DHSLR 016276	MQM 017253	SCOPE1 015100	T13 003324	T7 002514
DHSR 016274	MR 017402	SCOPE1 = 104410	T14 003466	VEC1 001164
DHTLVL 016306	MREGAD 017217	SCOPE1R 015200	T15 003630	VEC2 001174
DHTVEC 016304	MSG 015622	SPACNT = 016243	T16 003772	WRDCNT 016240
DT1 017702	MTITLE 017134	STACK = 020164	T17 004134	X = 000000
DT2 017720	MTSTPC 017406	START 001004	T2 001542	XBIT = 000001
DT3 017742	MVECTO 017175	STFLG 016352	T20 004276	XDATA = 000400
EM1 017516	N = 000001	SV05 015470	T21 004440	XLIN = 000000
EM2 017557	OCTASC = 104402	SV05P 015462	T22 004636	XN = 000061
EM3 017630	OCTASN 016074	SWR 001000	T23 005034	Y = 000011
ENDCOD 017764				

. ABS. 017766 000  
000000 001  
ERRORS DETECTED: 0

VIRTUAL MEMORY USED: 19200 WORDS ( 75 PAGES)  
DYNAMIC MEMORY AVAILABLE FOR 71 PAGES  
CZDHF.C.BIN,CZDHF.C.SEQ=CZDHF.C.DOC,DHMACA.MAC,CZDHF.C.P11