

MAR 1979
digital
MADE IN USA

RM02, RM03

FCTNL TST 2
CZRMDCO

AH-B001C-MC

COPYRIGHT 77-79
FICHE 2 OF 2

MAR 1979

digital

MADE IN USA

.REM \

IDENTIFICATION

PRODUCT CODE:	AC-B000C-MC
PRODUCT NAME:	CZRMDCO RM03/2 FCTNL TST 2
DATE CREATED:	FEB 1979
MAINTAINER:	DIAGNOSTIC GROUP
AUTHOR:	DOUG RIIKONEN

THE INFORMATION IN THIS DOCUMENT IS SUBJECT TO CHANGE WITHOUT NOTICE AND SHOULD NOT BE CONSTRUED AS A COMMITMENT BY DIGITAL EQUIPMENT CORPORATION. DIGITAL EQUIPMENT CORPORATION ASSUMES NO RESPONSIBILITY FOR ANY ERRORS THAT MAY APPEAR IN THIS MANUAL.

THE SOFTWARE DESCRIBED IN THIS DOCUMENT IS FURNISHED TO THE PURSHASER UNDER A LICENSE FOR USE ON A SINGLE COMPUTER SYSTEM AND CAN BE COPIED (WITH INCLUSION OF DIGITAL'S COPYRIGHT NOTICE) ONLY FOR USE IN SUCH SYSTEM, EXCEPT AS MAY OTHERWISE BE PROVIDED IN WRITING BY DIGITAL.

DIGITAL EQUIPMENT CORPORATION ASSUMES NO RESPONSIBILITY FOR THE USE OR RELIABILITY OF ITS SOFTWARE ON EQUIPMENT THAT IS NOT SUPPLIED BY DIGITAL.

COPYRIGHT (C) 1977,1979 DIGITAL EQUIPMENT CORPORATION

.PAGE

CONTENTS

1. INTRODUCTION
 1. ABSTRACT
 2. UNIT UNDER TEST
2. OPERATING REQUIREMENTS
 1. HARDWARE REQUIREMENTS
 2. MEDIA REQUIREMENTS
 3. PREREQUISITE DIAGNOSTIC PROGRAMS
3. OPERATING PROCEDURE
 1. LOADING
 2. SWITCH OPTIONS
 3. STARTING
 4. HALTING
 5. RESTARTING
4. OPERATOR INTERFACE
 1. PROGRAM I.D.
 2. CONSOLE DIALOGUE
 3. PROGRESS REPORTS
 4. PERFORMANCE REPORTS
 5. PROGRAM HALTS
 6. ERROR REPORTS
5. ENVIRONMENTAL SUPPORT
 1. PROCESSOR COMPATIBILITY

CZRMDCO RM03/2 FCTNL TST 2
CZRMDC.P11 12-DEC-78 08:24

MACY11 30A(1052) 04-JAN-79 11:23 PAGE 3

D 1

SEQ 0003

108

2. DUAL PORT CONFIGURATIONS

109
110
111
112
113
114
115
116
117
118
119
120
121
122
123
124

- 3. MEMORY PARITY HARDWARE
- 4. MEMORY MANAGEMENT HARDWARE
- 5. ACT,APT COMPATIBILITY
- 6. XXDP COMPATIBILITY
- 7. OPERATING SYSTEM COMPATIBILITY
- 6. TEST DESCRIPTION

1.0 INTRODUCTION

1.1 ABSTRACT

THE RM03 SUBSYSTEM FUNCTIONAL TEST IS A STAND ALONE PROGRAM WHICH USES FUNCTIONAL MEANS TO VERIFY THE OPERABILITY OF THE RM03 DISK SUBSYSTEM. IN PARTICULAR, THE PROGRAM SERVES THE FOLLOWING PURPOSES:

TO EXPLICITLY ESTABLISH CONFIDENCE IN THE BASIC OPERATIONS OF THE DISK DRIVE, INCLUDING MECHANICAL POSITIONING AND DATA TRANSFER OPERATIONS;

TO IMPLICITLY ESTABLISH CONFIDENCE IN THE DRIVE/ADAPTER ELECTRICAL INTERFACE;

TO VERIFY THE FUNCTIONALITY OF THE RM03 SUBSYSTEM, INCLUDING THE MASSBUS CONTROLLER, MASSBUS ADAPTER AND THE DISK DRIVE.

THE TEST IS COMPRISED OF 3 PARTS, WHICH WOULD NORMALLY BE RUN IN SEQUENCE, STARTING WITH PART 1. BRIEFLY, PART 1 TESTS HOUSEKEEPING AND MECHANICAL POSITIONING OPERATIONS; PART 2 TESTS WRITE, READ AND WRITE CHECK OPERATIONS USING HEADER AND DATA; PART 3 TESTS WRITE, READ AND WRITE CHECK OPERATIONS USING DATA.

1.2 UNIT UNDER TEST

THE UNIT UNDER TEST (UUT) IS THE RM03 DISK SUBSYSTEM WHICH CONSISTS OF THE RHXX MASSBUS CONTROLLER, THE RM03 MASSBUS ADAPTER, AND THE STORAGE MODULE DISK DRIVE. NOTE THAT A DISK PACK IS REQUIRED FOR TESTING AND IS CONSIDERED AN INTEGRAL OF THE STORAGE MODULE DISK DRIVE.

2.0 OPERATING REQUIREMENTS

2.1 HARDWARE REQUIREMENTS

THE FOLLOWING MINIMUM HARDWARE CONFIGURATION, ASSUMED TO BE OPERATIONAL, IS REQUIRED TO LOAD AND EXECUTE THE RM03 SUBSYSTEM FUNCTIONAL TEST:

PDP-11 PROCESSOR
16K MEMORY
KW11-L OR KW11-P CLOCK
PROGRAM LOADING DEVICE
TERMINAL
RH11 OR RH70 CONTROLLER
UNIT UNDER TEST,

CZRMDCO RM03/2 FCYNL TST 2
CZRMDC.P11 12-DEC-78 08:24

MACY11 30A(1052) 04-JAN-79 11:23 ^{6 1}PAGE 6

SEQ 0006

181
182

WHERE THE UNIT UNDER TEST CONSISTS OF ONE TO EIGHT RM03 ADAPTERS, DISK
DRIVES AND DISK PACKS.

2.2 MEDIA REQUIREMENTS

EACH UNIT BEING TESTED MUST BE LOADED WITH A SCRATCH DISK PACK BEFORE TESTING BEGINS ON THAT UNIT. THE PACK MAY BE FORMATTED OR UNFORMATTED, BUT MUST NOT CONTAIN NEEDED INFORMATION BECAUSE THE PACK WILL BE WRITTEN DURING THE TEST.

NOTE

WHEN THE PROGRAM IS LOADED VIA THE RM03, DRIVE 0 IS NOT TESTED UNLESS THE OPERATOR SPECIFICALLY ENTERS THE DRIVE NUMBER DURING CONSOLE DIALOGUE.

2.3 PREREQUISITE DIAGNOSTIC PROGRAMS

RM03 DISKLESS DIAGNOSTIC, CZRMJ-B

3.0 OPERATING PROCEDURE

3.1 LOADING

THE PROGRAM MAY BE LOADED BY EITHER OF THE FOLLOWING MEDIA:

. PAPER TAPE, USING THE STANDARD PAPER TAPE LOADING PROCEDURE;

.XXDP MEDIA, USING THE APPROPRIATE LOADING DEVICE.

NOTE

WHEN THE PROGRAM IS LOADED VIA THE RM03, DRIVE 0 IS NOT TESTED UNLESS THE OPERATOR SPECIFICALLY ENTERS THE DRIVE NUMBER DURING CONSOLE DIALOGUE.

3.2 SWITCH OPTIONS

THE FOLLOWING SWITCH OPTIONS ARE PROVIDED TO ENHANCE THE UTILITY OF THE PROGRAM.

CZRMDCO RMC3/2 FCTNL TST 2
CZRMDC.P11 12-DEC-78 08:24

MACY11 30A(1052) 04-JAN-79 11:23 ¹ ₁ PAGE 8

SEQ 0008

239
240

SW15 HALT ON ERROR
SW14 LOOP ON TEST (CURRENTLY BEING EXECUTED)

PAGE 5

SW13 INHIBIT ERROR TIMEOUTS
SW12 UNUSED
SW11 INHIBIT TEST ITERATIONS
SW10 BELL ON ERROR
SW09 LOOP ON ERROR
SW08 LOOP ON TEST IN SW07-00

THE LOW ORDER 8 SWITCHES (SW07-SW00), ARE USED IN CONJUNCTION WITH SW08 TO SPECIFY THE OCTAL NUMBER OF THE TEST WHICH THE PROGRAM WILL LOOP ON.

3.3 STARTING

THE PROGRAM STARTS AT LOCATION 200, WHICH PROVIDES WORST CASE TEST CONDITIONS IF RUNNING IN AN AUTOMATIC ENVIRONMENT. IF RUNNING IN A STAND-ALONE ENVIRONMENT, THE PROGRAM USES CONSOLE DIALOGUE TO ALLOW THE OPERATOR TO CONTROL TEST CONDITIONS.

3.4 HALTING

THE PROGRAM CAN BE HALTED BY TYPING CONTROL C FROM THE CONSOLE.

3.5 RESTARTING

THE PROGRAM CAN BE RESTARTED AT ADDRESS 200.

4.0 OPERATOR INTERFACE

4.1 PROGRAM ID

THE PROGRAM TYPES ITS TITLE AND MAINDEC NUMBER THE FIRST TIME IT IS STARTED AFTER BEING LOADED. PROGRAM IDENTIFICATION DOES NOT OCCUR IF THE PROGRAM IS RESTARTED.

4.2 CONSOLE DIALOGUE

WHEN THE PROGRAM IS RUNNING IN STAND ALONE MODE, IT ENTERS A CONSOLE DIALOGUE SEQUENCE AFTER TYPING THE PROGRAM I.D..

THE FIRST QUESTION TYPED OUT IS: "TYPE HELP TEXT (Y OR N)??". IF THE OPERATOR RESPONDS WITH A Y, THE PROGRAM WILL TYPE A BRIEF HELP MESSAGE WHICH WILL LIST SWITCH OPTIONS, ETC.

THE SECOND QUESTION TYPED OUT IS, "CHANGE RM03 UNIBUS ADDRESS OR VECTOR ADDRESS (Y OR N)??". IF THE UNIBUS ADDRESS OF THE RM03 IS NON STANDARD, THE OPERATOR SHOULD RESPOND Y, THEN ANSWER SUBSEQUENT QUESTIONS TO SPECIFY THE UNIBUS ADDRESS, VECTOR ADDRESS AND INTERRUPT PRIORITY. IF THE OPERATOR DOES NOT RESPOND WITH A Y, THE PROGRAM SKIPS TO THE THIRD QUESTION.

THE THIRD QUESTION TYPED OUT IS, "TYPE (A) TO TEST ALL DEVICES, OR TYPE DEVICE NUMBER(S). TERMINATE INPUT WITH CARRIAGE RETURN". IF THE OPERATOR TYPES A, ALL POSSIBLE DEVICES ARE TESTED. OTHERWISE, THE OPERATOR CAN TYPE THE NUMBER(S) OF THE DEVICE(S) HE WANTS TESTED, AND TERMINATE HIS INPUT WITH A CARRIAGE RETURN.

IF THE PROGRAM IS RESTARTED, THE FIRST QUESTION TYPED IS, "USE SAME DEVICES (Y OR N)??". IF THE OPERATOR TYPES Y, THE TEST IS RESTARTED USING THE SAME DEVICES AS THE LAST TIME, OTHERWISE, THE TEST RESTARTS THE DIALOGUE AS IF THE PROGRAM WERE STARTED FOR THE FIRST TIME.

4.3 PROGRESS REPORTS

AN END OF PASS REPORT OCCURS EACH TIME THE PROGRAM IS EXECUTED FOR ALL DEVICES IN THE TEST QUE. THE END OF PASS REPORT INCLUDES A MESSAGE AND AN ERROR SUMMARY.

4.4 PERFORMANCE REPORT

NO PERFORMANCE REPORTS ARE GIVEN DURING THE EXECUTION OF THE PROGRAM.

4.5 PROGRAM HALTS

THERE ARE NO SCHEDULED HALTS DURING THE EXECUTION OF THE PROGRAM. PROCESSOR HALTS ARE DUE TO THE TRAP CATCHER.

4.6 ERROR REPORTS

THE FIRST LINE OF THE ERROR REPORT CONTAINS THE NUMBER OF THE UNIT BEING TESTED, THE TEST NUMBER, THE ERROR NUMBER AND THE VALUE OF THE PROGRAM COUNTER WHERE THE ERROR WAS CALLED. THIS LINE IS FOLLOWED BY THE ERROR MESSAGE: ONE OR MORE LINES OF TEXT WHICH GIVE A BRIEF, YET COMPREHENSIVE DESCRIPTION OF THE ERROR. THE ERROR MESSAGE IS NORMALLY FOLLOWED BY ONE OR MORE PAIRS OF LINES CONTAINING DATA HEADERS AND DATA PERTINENT TO THE ERROR, INCLUDING EXPECTED AND ACTUAL TEST RESULTS.

5.0 ENVIRONMENTAL SUPPORT

5.1 PROCESSOR COMPATIBILITY

THE RM03 SUBSYSTEM FUNCTIONAL TEST IS EXECUTABLE ON ANY PDP-11 PROCESSOR, PROVIDING PREVIOUSLY MENTIONED HARDWARE REQUIREMENTS ARE MET, AND PROVIDING THAT DATA THROUGHOUT THE SYSTEM IS SUFFICIENT TO SUSTAIN DATA TRANSFER OPERATIONS

5.2 DUAL PORT CONFIGURATIONS

THE RM03 SUBSYSTEM FUNCTIONAL TEST DOES NOT SPECIFICALLY TEST DUAL PORT LOGIC IN THE RM03 ADAPTER BUT IS EXECUTABLE ON RM03 SUBSYSTEMS HAVING THE DUAL PORT OPTION PROVIDING THE DUAL PORT SWITCH IS SET TO THE APPROPRIATE PORT (A OR B).

5.3 MEMORY PARITY HARDWARE

MEMORY PARITY HARDWARE IS NOT USED DURING THE EXECUTION OF THE RM03 SUBSYSTEM FUNCTIONAL TEST.

5.4 MEMORY MANAGEMENT HARDWARE

MEMORY MANAGEMENT HARDWARE IS NOT USED DURING THE RM03 SUBSYSTEM FUNCTIONAL TEST. CAPABILITIES OF THE MASSBUS CONTROLLER

5.5 ACT11, APT11 COMPATIBILITY

THE RM03 SUBSYSTEM FUNCTIONAL TEST IS COMPATIBLE WITH ACT11 AND APT11 IN BOTH DUMP AND AUTOMATIC MODES. FURTHER, THE PROGRAM WILL EXECUTE A QUICK PASS DURING THE FIRST PASS IN SUPPORT OF QUICK VERIFY MODE.

5.6 XXDP COMPATIBILITY

THE RM03 SUBSYSTEM FUNCTIONAL TEST IS COMPATIBLE WITH XXDP IN DUMP AND CHAIN MODES, AND PROVIDES MEDIA PROTECTION IN THE CASE WHERE THE RM03 IS THE XXDP LOADING DEVICE.

404
405
406
407
408
409

PAGE 8

5.7 OPERATING SYSTEM COMPATIBILITY

THE PROGRAM IS NOT COMPATIBLE WITH ANY SOFTWARE OPERATING SYSTEM.

6.0 TEST DESCRIPTION

CONTROLLER ACCESS TEST

PURPOSE:

TO VERIFY THAT THE UNIBUS ADDRESS OF THE RM03 SUBSYSTEM IS CORRECT, AS DEFINED AT LOCATION \$BASE.

PROCEDURE:

THE TEST TRIES TO ACCESS ALL MASSBUS CONTROLLER REGISTERS USING THE \$BASE ADDRESS. REGISTER CONTENTS ARE IGNORED DURING THE TEST, AND THE TEST FAILS IF A BUS TIMEOUT OCCURS FOR ANY REGISTER TRANSFER.

IF THE TEST FAILS AND THE PROGRAM IS RUNNING IN A STAND ALONE ENVIRONMENT, I.E., LOCATION 204, THE PROGRAM WILL JUMP TO LOCATION 204 WHICH ALLOWS THE OPERATOR TO CHANGE THE \$BASE ADDRESS VIA CONSOLE DIALOGUE. OTHERWISE, THE PROGRAM ESCAPES TO THE END OF PASS HANDLER.

DEVICE AVAILABLE TEST

PURPOSE:

TO VERIFY THAT THE UNIT UNDER TEST IS AVAILABLE FOR TESTING, AND IS NOT LOCKED OR PROGRAMMED TO THE ALTERNATE PORT.

PROCEDURE:

THIS TEST SELECTS THE DEVICE AND READS CONTROL STATUS REGISTERS 1 AND 2 TO VERIFY THAT THE SELECTED DEVICE IS AVAILABLE FOR TESTING, AS INDICATED BY DATA BITS 11 OF RMCS1 AND NEED STATUS, BIT 12 OF RMCS2. THE RESULTS OF THE TEST CAN VARY AS FOLLOWS:

.NONEXISTANT DEVICE - THE DEVICE IS NONEXISTENT OR IS LOCKED ON THE ALTERNATE PORT AND IS THEREFORE NOT AVAILABLE FOR TESTING;

.DEVICE NOT AVAILABLE - THE DEVICE EXISTS BUT IS SEIZED BY THE ALTERNATE PORT AND IS NOT AVAILABLE FOR TESTING;

.BUS TIMEOUT - THE MASSBUS CONTROLLER FAILED TO DETECT A

CZRMCO RM03/2 FCTNL TST 2
CZRMOC.P11 12-DEC-78 08:24

MACV11 30A(1052) 04-JAN-79 11:23 ² PAGE 14

SEQ 0014

466

NONEXISTENT DEVICE;

PAGE 10

.DEVICE AVAILABLE - THE DEVICE IS AVAILABLE FOR TESTING.

THE PROGRAM JUMPS TO THE SUBPASS HANDLER WHICH SELECTS THE
NEXT DRIVE TO BE TESTED IF THE DEVICE IS NOT AVAILABLE.

DRIVE TYPE TEST

PURPOSE:

TO VERIFY THAT THE UNIT UNDER TEST IS AN RMO3 SINGLE PORT OR
DUAL PORT SUBSYSTEM.

PROCEDURE:

THIS TEST READS THE DRIVE TYPE REGISTER, RMDT, OF THE
SELECTED DEVICE AND VERIFIES THAT THE DEVICE IS A SINGLE PORT OR
DUAL PORT RMO3 SUBSYSTEM. IF THE SELECTED DEVICE IS NOT AN RMO3,
THE PROGRAM JUMPS TO THE SUBPASS HANDLER WHICH WILL SELECT THE
NEXT DEVICE FOR TESTING.

WRITE/READ HEADER AND DATA (FORMAT) TESTS

PURPOSE:

TO TEST WRITE HEADER AND DATA AND READ HEADER AND DATA
FUNCTIONALITY OF THE RMO3 SUBSYSTEM USING A SET OF VARIABLES
WHICH INCLUDE WORD COUNT, HEAD MOTION, HEAD SWITCHING AND ERROR
CONDITIONS.

PROCEDURE:

ALTHOUGH EACH TEST EXERCISES A DIFFERENT VARIABLE, THE
GENERAL PROCEDURE OF EACH TEST IS THE SAME. THE DRIVE IS
INITIALIZED AND RECALIBRATED IF 'PIP' OR 'SKI' ARE ACTIVE SO THAT
THERE ARE NO ERRORS WHEN A TEST BEGINS. FOLLOWING THAT, THE TEST
PERFORMS ANY EXPLICIT SEEKS REQUIRED FOR THE CONDITIONS OF THE
TEST. REGISTERS ARE PRESET AND THE WRITE HEADER AND DATA COMMAND
IS EXECUTED. WHEN THE WRITE COMMAND IS COMPLETE, THE TEST STORES
ALL SUBSYSTEM STATUS AND CHECKS FOR PRIMARY ERRORS WHICH PRECLUDE
OTHER STATUS CHECKS. IF THERE ARE NO PRIMARY ERRORS, THE TEST
VERIFIES THE RESULTS OF THE WRITE COMMAND AND THEN CHECKS FOR
SECONDARY ERRORS. LOOP ADDRESSES ARE MODIFIED FOLLOWING THE
SUCCESSFUL COMPLETION OF THE WRITE COMMAND IN ORDER TO SHORTEN
EXECUTION TIMES AND ENHANCE SCOPING LOOPS, THEN THE PROGRAM
EXECUTES THE READ HEADER AND DATA PORTION OF THE TEST, VERIFYING

523
524
525
526
527
528
529
530
531
532
533
534
535
536
537

THE SAME TYPE OF ERRORS AS IN THE WRITE COMMAND.

NOTE THAT THE SECTOR USED DURING A TEST MAY DIFFER FROM THE
PROGRAM LISTING BECAUSE THE PROGRAM SUBSTITUTES A GOOD SECTOR IF
THE ONE SELECTED IS LISTED IN THE BAD BLOCK TABLE OF THE LAST
TRACK. UNLESS SPECIFIED OTHERWISE, ALL TESTS ARE IN 16 BIT (32
SECTOR) FORMAT.

FORMAT ZEROS - 18

PAGE 29

THE TEST SEEKS TO CYLINDER 0, THEN WRITES HEADER AND DATA ON SECTOR 0 IN 18 BIT FORMAT. THE HEADER AND DATA FIELDS ARE ALL ZEROS, CAUSING THE DEVICE TO USE NORMAL WRITE GATE. THE HEADER AND DATA ARE READ AND COMPARED WITH THE WRITE BUFFER. THE INITIAL SEEK POSITIONS THE HEAD SUCH THAT THERE IS NO IMPLIED SEEK.

FORMAT ZEROS - 16

THIS TEST IS THE SAME AS THE PREVIOUS TEST, EXCEPT THAT DATA IS WRITTEN IN 16 BIT FORMAT.

ZERO FILL TEST

THE TEST EXECUTES A SEEK TO CYLINDER 0 TO INSURE THAT THERE IS NO HEAD MOTION DURING DATA TRANSFER. THIS IS FOLLOWED BY A WRITE HEADER AND DATA COMMAND WITH THE WORD COUNT EQUAL TO THE SIZE OF THE HEADER WHICH CAUSES THE RM70 TO ZERO FILL THE DATA FIELD. THE READ HEADER AND DATA COMMAND THAT FOLLOWS READS A FULL SECTOR AND VERIFIES THAT DATA WAS ZERO FILLED.

FORMAT CHECK ZEROS

THE TEST WRITES HEADER AND AN ALL ZEROS DATA FIELD, THEN PERFORMS A WRITE CHECK HEADER AND DATA COMMAND AND VERIFIES THERE ARE NO ERRORS.

FORMAT CHECK ZEROS W/ WCE ERROR

THE TEST WRITES HEADER AND AN ALL ZEROS DATA FIELD. AFTER COMPLEMENTING THE LAST WORD OF THE WRITE BUFFER, THE TEST PERFORMS A WRITE CHECK HEADER AND DATA COMMAND AND VERIFIES THAT THE CORRECT WRITE CHECK ERROR IS DETECTED.

593
594
595
596
597
598
599
600
601
602
603
604
605
606
607
608
609
610
611
612
613
614
615
616
617
618
619
620
621
622
623
624
625
626
627
628
629
630
631
632
633
634
635
636
637
638
639
640
641
642
643
644
645
646
647
648

FORMAT ONES

THE TEST WRITES HEADER AND AN ALL ONES DATA FIELD, THEN READS THE HEADER AND DATA, VERIFYING THE READ BUFFER WITH THE WRITE BUFFER. THE ALL ONES FIELD IS A CONSTANT FREQUENCY, AND THE DRIVE SHOULD USE NORMAL WRITE GATE.

FORMAT CHECK ONES

THE TEST FORMATS AN ALL ONES DATA FIELD, THE PERFORMS A WRITE CHECK HEADER AND DATA COMMAND, VERIFYING THAT THERE ARE NO ERRORS.

FORMAT CHECK ONES W/ WCE ERROR

THE TEST FORMATS AN ALL ONES DATA FIELD, THEN COMPLEMENTS THE LAST WORD OF THE WRITE BUFFER. A WRITE CHECK HEADER AND DATA COMMAND IS EXECUTED, AND THE TEST VERIFIES THAT THE CORRECT WRITE CHECK ERROR IS DETECTED.

FORMAT MULTIPLE SECTORS

THE TEST SEEKS TO CYLINDER 0 TO INSURE THERE IS NO HEAD MOTION DURING DATA TRANSFER. THE WRITE HEADER AND DATA COMMAND FOLLOWS, WITH THE WORD COUNT EQUAL TO MULTIPLE SECTORS. THE WORD COUNT DURING THE READ HEADER AND DATA PORTION OF THE TEST IS SET FOR ALL OF THE FIRST SECTOR AND THE HEADER OF THE SECOND SECTOR.

FORMAT WITH HEAD SWITCHING

THE TEST SEEKS TO CYLINDER 0 TO INSURE THERE IS NO HEAD MOTION DURING DATA TRANSFER. THE WRITE HEADER AND DATA COMMAND STARTS WITH CYLINDER 0, TRACK 0, SECTOR 31. THE WORD COUNT IS EQUAL TO MULTIPLE SECTORS WHICH CAUSES THE SUBSYSTEM TO SWITCH

CZRMDCO RM03/2 FCTNL TST 2
CZRMDC.P11 12-DEC-78 08:24

MACY11 30A(1052) 04-JAN-79 11:23 ^{6 2}PAGE 19

SEQ 0019

649
650

FROM TRACK 0 TO TRACK 1 AFTER THE FIRST SECTOR IS WRITTEN. THE
READ HEADER AND DATA COMMAND USES THE SAME WORD COUNT AND

651
652
653
654
655
656
657
658
659
660
661
662
663
664
665
666
667
668
669
670
671
672
673
674
675
676
677
678
679
680
681
682
683
684
685
686
687
688
689
690
691
692
693
694
695
696
697
698
699
700
701
702
703
704

STARTING SECTOR.

FORMAT WITH IMPLIED SEEK

THIS TEST SEEKS TO THE LAST CYLINDER PRIOR TO WRITING HEADER AND DATA ON CYLINDER 0. THE EXPLICIT SEEK INSURES THAT THERE WILL BE MAXIMUM HEAD MOTION DURING THE IMPLIED SEEK OF THE WRITE COMMAND. THE SAME OPERATION, INCLUDING THE EXPLICIT SEEK IS REPEATED FOR READ HEADER AND DATA.

FORMAT WITH MIDTRANSFER SEEK

THIS TEST WRITES MULTIPLE SECTORS STARTING WITH CYLINDER 0, TRACK 4, SECTOR 31, CAUSING A MIDTRANSFER SEEK AFTER THE FIRST SECTOR IS WRITTEN. THE SAME SECTORS ARE READ WITH READ HEADER AND DATA COMMAND.

FORMAT EACH SECTOR ADDRESS

HEADERS AND DATA OF EACH SECTOR ON CYLINDER 0, TRACK 0 ARE FORMATTED AND READ WITH THE PROGRAM VERIFYING HEADERS AND DATA.

FORMAT EACH TRACK ADDRESS

THIS TEST FORMATS SECTOR 0 OF EACH TRACK ON CYLINDER 0 AND READS EACH SECTOR WITH THE PROGRAM VERIFYING HEADERS AND DATA.

FORMAT PRIME CYLINDERS

THIS TEST FORMATS AND READS SECTOR 0, TRACK 0 ON EACH PRIME CYLINDER, I.E., CYLINDERS 1,2,4,8,....,512.

PAGE 32

705
706
707
708
709
710
711
712
713
714
715
716
717
718
719
720
721
722
723
724
725
726
727
728
729
730
731
732
733
734
735
736
737
738
739
740
741
742
743
744
745
746
747
748
749
750
751
752
753
754
755
756
757
758

FORMAT LAST SECTOR

THIS TEST READS HEADER AND DATA ON THE LAST SECTOR, I.E.,
CYLINDER 822, TRACK 4, SECTOR 31, AND VERIFIES THAT LBT STATUS
SETS.

FOR W/ AOE ERROR

THIS TEST READS MULTIPLE SECTORS STARTING WITH THE LAST
SECTOR AND VERIFIES THAT AOE STATUS SETS.

FORMAT INVALID SECTOR ADDRESS

THIS TEST USES AN ILLEGAL SECTOR ADDRESS AND VERIFIES THAT
IAE STATUS SETS.

FORMAT INVALID TRACK ADDRESS

THIS TEST USES AN ILLEGAL TRACK ADDRESS AND VERIFIES THAT
IAE STATUS SETS.

FORMAT INVALID CYLINDER ADDRESS

THIS TEST USES AN ILLEGAL CYLINDER ADDRESS AND VERIFIES THAT
IAE STATUS SETS.

FORMAT AT OFFSET

THE PROGRAM SETS OFFSET MODE AND EXECUTES A WRITE HEADER AND
DATA COMMAND, VERIFYING THAT OFFSET MODE IS RESET BY THE WRITE
COMMAND.

759
760
761
762
763
764
765
766
767
768
769
770
771
772
773
774
775
776
777
778
779
780
781
782
783
784
785
786
787
788
789
790
791
792
793
794
795
796
797

IVC FORMAT TEST

VOLUME VALID IS RESET BY SETTING AND RESETTNG DIAGNOSTIC MODE. THE TEST THEN EXECUTES A WRITE HEADER AND DATA COMMAND AND VERIFIES THAT INVALID COMMAND STATUS SETS. THE TEST IS REPEATED FOR READ HEADER AND DATA COMMAND.

FORMAT ERROR TEST(18 AND 16)

A SINGLE SECTOR IS FORMATTED WITH THE OFFSET REGISTER SET FOR 16 BIT FORMAT AFTER WHICH THE SAME SECTOR IS READ IN 18 BIT FORMAT WITH THE PROGRAM VERIFYING THAT FORMAT ERROR STATUS IS SET. THE SAME PROCEDURE IS REPEATED WITH THE SECTOR WRITTEN IN 18 BIT FORMAT AND READ IN 16 BIT FORMAT.

FORMAT HCE (FIRST AND SECOND HEADER WORDS)

THESE TWO TESTS WRITE AN INCORRECT HEADER THEN READ THE HEADER AND VERIFY THAT THE CORRECT HEADER ERROR IS DETECTED. THE TESTS SETUP THE CORRECT HEADER, THEN COMPLEMENT BIT 0 AND USE THE MODIFIED BUFFER TO WRITE THE HEADER. THE PROCESS IS REPEATED UNTIL EACH BIT POSITION HAS BEEN SEPARATELY TESTED.

CZRMDCO RM03/2 FCTNL TST 2
CZRMDC.P11 12-DEC-78 08:24

MACY11 30A(1052) 04-JAN-79 11:23 ^{K 2} PAGE 23

SEQ 0023

798

\


```
799 ;PROGRAM REVISION #001
800
801 .TITLE CZRMDCO RM03/2 FCTNL TST 2
802 ;*COPYRIGHT (C) 1977
803 ;*DIGITAL EQUIPMENT CORP.
804 ;*MAYNARD, MASS. 01754
805 ;*
806 ;*PROGRAM BY DOUG RIIKONEN
807 ;*
808 ;*THIS PROGRAM WAS ASSEMBLED USING THE PDP-11 MAINDEC SYSMAC
809 ;*PACKAGE (MAINDEC- S-LQAC-C3), JAN 19, 1977.
810 ;*
811 000001 $TN=1
812 .SBTTL OPERATIONAL SWITCH SETTINGS
813 ;*
814 ;* SWITCH USE
815 ;* -----
816 ;* 15 HALT ON ERROR
817 ;* 14 LOOP ON TEST
818 ;* 13 INHIBIT ERROR TYPEOUTS
819 ;* 12 ENABLE EXTENDED STATUS
820 ;* 11 INHIBIT ITERATIONS
821 ;* 10 BELL ON ERROR
822 ;* 9 LOOP ON ERROR
823 ;* 8 LOOP ON TEST IN SWR<7:0>
824 ;* 7 TN128
825 ;* 6 TN64
826 ;* 5 TN32
827 ;* 4 TN16
828 ;* 3 TN8
829 ;* 2 TN4
830 ;* 1 TN2
831 ;* 0 TN1
832 .SBTTL BASIC DEFINITIONS
833 ;*
834 ;*INITIAL ADDRESS OF THE STACK POINTER *** 1100 ***
835 001100 STACK= 1100
836 .EQUIV EMT,ERROR ;;BASIC DEFINITION OF ERROR CALL
837 .EQUIV IOT,SCOPE ;;BASIC DEFINITION OF SCOPE CALL
838 ;*
839 ;*MISCELLANEOUS DEFINITIONS
840 ;*
841 ;* HT= 11 ;;CODE FOR HORIZONTAL TAB
842 ;* F= 12 ;;CODE FOR LINE FEED
843 ;* = 15 ;;CODE FOR CARRIAGE RETURN
844 ;* CRLF= 200 ;;CODE FOR CARRIAGE RETURN-LINE FEED
845 ;* PS= 177776 ;;PROCESSOR STATUS WORD
846 ;* .EQUIV PS,PSW
847 ;* STKLMT= 177774 ;;STACK LIMIT REGISTER
848 ;* PIRQ= 177772 ;;PROGRAM INTERRUPT REQUEST REGISTER
849 ;* DSWR= 177570 ;;HARDWARE SWITCH REGISTER
850 ;* DDISP= 177570 ;;HARDWARE DISPLAY REGISTER
851 ;*
852 ;*GENERAL PURPOSE REGISTER DEFINITIONS
853 000000 R0= %0 ;;GENERAL REGISTER
854 000001 R1= %1 ;;GENERAL REGISTER
855 000002 R2= %2 ;;GENERAL REGISTER
```

855	000003	R3=	%3	:: L REGISTER
856	000004	R4=	%4	:: REGISTER
857	000005	R5=	%5	:: GENERAL REGISTER
858	000006	R6=	%6	:: GENERAL REGISTER
859	000007	R7=	%7	:: GENERAL REGISTER
860	00C006	SP=	%6	:: STACK POINTER
861	000007	PC=	%7	:: PROGRAM COUNTER

863		; *PRIORITY LEVEL DEFINITIONS		
864	000000	PR0=	0	:: PRIORITY LEVEL 0
865	000040	PR1=	40	:: PRIORITY LEVEL 1
866	000100	PR2=	100	:: PRIORITY LEVEL 2
867	000140	PR3=	140	:: PRIORITY LEVEL 3
868	000200	PR4=	200	:: PRIORITY LEVEL 4
869	000240	PR5=	240	:: PRIORITY LEVEL 5
870	000300	PR6=	300	:: PRIORITY LEVEL 6
871	000340	PR7=	340	:: PRIORITY LEVEL 7

873		; *"SWITCH REGISTER" SWITCH DEFINITIONS		
874	100000	SW15=	100000	
875	040000	SW14=	40000	
876	020000	SW13=	20000	
877	010000	SW12=	10000	
878	004000	SW11=	4000	
879	002000	SW10=	2000	
880	001000	SW9=	1000	
881	000400	SW8=	400	
882	000200	SW7=	200	
883	000100	SW6=	100	
884	000040	SW5=	40	
885	000020	SW4=	20	
886	000010	SW3=	10	
887	000004	SW2=	4	
888	000002	SW1=	2	
889	000001	SW0=	1	
890		.EQUIV	SW15, SW9	
891		.EQUIV	SW14, SW8	
892		.EQUIV	SW13, SW7	
893		.EQUIV	SW12, SW6	
894		.EQUIV	SW11, SW5	
895		.EQUIV	SW10, SW4	
896		.EQUIV	SW9, SW3	
897		.EQUIV	SW8, SW2	
898		.EQUIV	SW7, SW1	
899		.EQUIV	SW6, SW0	

901		; DATA BIT DEFINITIONS (BIT00 TO BIT15)		
902	100000	BIT15=	100000	
903	040000	BIT14=	40000	
904	020000	BIT13=	20000	
905	010000	BIT12=	10000	
906	004000	BIT11=	4000	
907	002000	BIT10=	2000	
908	001000	BIT09=	1000	
909	000400	BIT08=	400	
910	000200	BIT07=	200	

```
911      000100      BIT06= 100
912      000040      BIT05= 40
913      000020      BIT04= 20
914      000010      BIT03= 10
915      000004      BIT02= 4
916      000002      BIT01= 2
917      000001      BIT00= 1
918      .EQUIV BIT09,BIT9
919      .EQUIV BIT08,BIT8
920      .EQUIV BIT07,BIT7
921      .EQUIV BIT06,BIT6
922      .EQUIV BIT05,BIT5
923      .EQUIV BIT04,BIT4
924      .EQUIV BIT03,BIT3
925      .EQUIV BIT02,BIT2
926      .EQUIV BIT01,BIT1
927      .EQUIV BIT00,BIT0
928
929      ;*BASIC "CPU" TRAP VECTOR ADDRESSES
930      000004      TRFVEC= 4      ;;TIME OUT AND OTHER ERRORS
931      000010      RESVEC= 10     ;;RESERVED AND ILLEGAL INSTRUCTIONS
932      000014      TBITVEC=14     ;;T BIT
933      000014      TRTVEC= 14     ;;TRACE TRAP
934      000014      BPTVEC= 14     ;;BREAKPOINT TRAP (BPT)
935      000020      IOTVEC= 20     ;;INPUT/OUTPUT TRAP (IOT) **SCOPE**
936      000024      PWRVEC= 24     ;;POWER FAIL
937      000030      EMTVEC= 30     ;;EMULATOR TRAP (EMT) **ERROR**
938      000034      TRAPVEC=34     ;;"TRAP" TRAP
939      000060      TKVEC= 60      ;;TTY KEYBOARD VECTOR
940      000064      TPVEC= 64      ;;TTY PRINTER VECTOR
941      000240      PIRQVEC=240    ;;PROGRAM INTERRUPT REQUEST VECTOR
942
943      .SBTTL RM03 REGISTER BIT DEFINITIONS
944
945      ;RMCS1 CONTROL STATUS REGISTER
946
947      004000      DVA      =      BIT11      ;DEVICE AVAILABLE-READ ONLY
948      000040      F4       =      BIT05      ;FUNCTION CODE
949      000020      F3       =      BIT04      ;FUNCTION CODE
950      000010      F2       =      BIT03      ;FUNCTION CODE
951      000004      F1       =      BIT02      ;FUNCTION CODE
952      000002      F0       =      BIT01      ;FUNCTION CODE
953      000001      GO       =      BIT00      ;GO BIT
954      000077      FNCMSK   =      000077    ;FUNCTION CODE MASK
955
956      ;FUNCTION CODE (BITS 01-05 OF RMCS1)
957
958      000000      NOP       =      000000    ;NOP COMMAND
959      000002      ILF02     =      000002    ;ILLEGAL COMMAND
960      000004      SEEK      =      000004    ;SEEK COMMAND
961      000006      RECAL     =      000006    ;RECALIBRATE COMMAND
962      000010      DRVCLR    =      000010    ;DRIVE CLEAR COMMAND
963      000012      RLEAS     =      000012    ;RELEASE COMMAND
964      000014      OFFSEI    =      000014    ;OFFSET COMMAND
965      000016      RTC       =      000016    ;RETURN TO CENTERLINE COMMAND
966      000020      RJP       =      000020    ;READ IN PRESET COMMAND
```

967	000022	PAKACK	=	000022	;PAK ACKNOWLEDGE COMMAND
968	000022	PACACK	=	PAKACK	
969	000024	ILF24	=	000024	;ILLEGAL COMMAND
970	000026	ILF26	=	000026	;ILLEGAL COMMAND
971	000030	SEARCH	=	000030	;SEARCH COMMAND
972	000030	ILF30	=	000030	;ILLEGAL COMMAND
973	000032	ILF32	=	000032	;ILLEGAL COMMAND
974	000034	ILF34	=	000034	;ILLEGAL COMMAND
975	000036	ILF36	=	000036	;ILLEGAL COMMAND
976	000040	ILF40	=	000040	;ILLEGAL COMMAND
977	000042	ILF42	=	000042	;ILLEGAL COMMAND
978	000044	ILF44	=	000044	;ILLEGAL COMMAND
979	000046	ILF46	=	000046	;ILLEGAL COMMAND
980	000050	WCD	=	000050	;WRITE CHECK DATA COMMAND
981	000052	WCH	=	000052	;WRITE CHECK HEADER AND DATA
982	000054	ILF54	=	000054	;ILLEGAL COMMAND
983	000056	ILF56	=	000056	;ILLEGAL COMMAND
984	000060	WD	=	000060	;WRITE DATA COMMAND
985	000062	WH	=	000062	;WRITE HEADER AND DATA COMMAND
986	000064	ILF64	=	000064	;ILLEGAL COMMAND
987	000066	ILF66	=	000066	;ILLEGAL COMMAND
988	000070	RD	=	000070	;READ DATA COMMAND
989	000072	RH	=	000072	;READ HEADER AND DATA COMMAND
990	000074	ILF74	=	000074	;ILLEGAL COMMAND
991	000076	ILF76	=	000076	;ILLEGAL COMMAND
992					
993		;RMDA		DISK ADDRESS REGISTER	
994					
995	002000	TA4	=	BIT10	;TRACK ADDRESS 4
996	001000	TA2	=	BIT09	;TRACK ADDRESS 2
997	000400	TA1	=	BIT08	;TRACK ADDRESS 1
998	000020	SA16	=	BIT04	;SECTOR ADDRESS 16
999	000010	SA8	=	BIT03	;SECTOR ADDRESS 8
1000	000004	SA4	=	BIT02	;SECTOR ADDRESS 4
1001	000002	SA2	=	BIT01	;SECTOR ADDRESS 2
1002	000001	SA1	=	BIT00	;SECTOR ADDRESS 1
1003					
1004		;TRACK,SECTOR MASKS			
1005					
1006	003400	TADMSK	=	003400	;TRACK ADDRESS MASK
1007	000037	SADMSK	=	000037	;SECTOR ADDRESS MASK
1008					
1009		;RMDS		DRIVE STATUS REGISTER	
1010					
1011	100000	ATA	=	BIT15	;ATTENTION ACTIVE
1012	040000	ERR	=	BIT14	;COMPOSITE ERROR
1013	020000	PIP	=	BIT13	;POSITIONING IN PROGRESS
1014	010000	MOL	=	BIT12	;MEDIUM ON LINE
1015	004000	WRL	=	BIT11	;WRITE LOCK
1016	002000	LBT	=	BIT10	;LAST BLOCK TRANSFERRED
1017	001000	PGM	=	BIT09	;PROGRAMMABLE
1018	000400	DPR	=	BIT08	;DRIVE PRESENT
1019	000200	DRY	=	BIT07	;DRIVE READY
1020	000100	VV	=	BIT06	;VOLUME VALID
1021	000001	OM	=	BIT00	;OFFSET MODE ACTIVE
1022					

```

1023      ;RMER1  ERROR REGISTER #1
1024
1025      100000      DCK      =      BIT15      ;DATA CHECK ERROR
1026      040000      UNS      =      BIT14      ;DRIVE UNSAFE
1027      020000      OPI      =      BIT13      ;OPERATION INCOMPLETE
1028      010000      DTE      =      BIT12      ;DRIVE TIMING ERROR
1029      004000      WLE      =      BIT11      ;WRITE LOCK ERROR
1030      002000      IAE      =      BIT10      ;INVALID ADDRESS ERROR
1031      001000      AOE      =      BIT09      ;ADDRESS OVERFLOW ERROR
1032      000400      HCRC     =      BIT08      ;HEADER CRC ERROR
1033      000200      HCE      =      BIT07      ;HEADER COMPARE ERROR
1034      000100      ECH      =      BIT06      ;ECC 'HARD' ERROR
1035      000040      WCF      =      BIT05      ;WRITE CLOCK FAILURE
1036      000020      FER      =      BIT04      ;FORMAT ERROR
1037      000010      PAR      =      BIT03      ;PARITY ERROR
1038      000004      RMR      =      BIT02      ;REGISTER MODIFICATION REFUSED
1039      000002      ILR      =      BIT01      ;ILLEGAL REGISTER
1040      000001      ILF      =      BIT00      ;ILLEGAL FUNCTION
1041
1042      115760      NDTMSK    =      DCK!DTE!WLE!IAE!HCRC!HCE!ECH!WCF!FER
1043      ;'NDTMSK' IS USED TO MASK ERROR REGISTER 1 DURING NON - DATA
1044      ;COMMANDS, I.E., HOUSEKEEPING AND POSITIONING COMMANDS
1045
1046      ;RMAS  ATTENTION SUMMARY REGISTER
1047
1048      000377      ATNMSK    =      377      ;MASK FOR ATTENTION BITS
1049
1050      ;RMLA  LOOK AHEAD REGISTER
1051
1052      002000      SC4      =      BIT10      ;SECTOR COUNT = 16
1053      001000      SC3      =      BIT09      ;SECTOR COUNT = 8
1054      000400      SC2      =      BIT08      ;SECTOR COUNT = 4
1055      000200      SC1      =      BIT07      ;SECTOR COUNT = 2
1056      000100      SC0      =      BIT06      ;SECTOR COUNT = 1
1057
1058      003700      SCTMSK    =      003700    ;SECTOR COUNT MASK
1059
1060      ;RMMR  MAINTENANCE REGISTER
1061
1062      ;      WRITE ONLY BITS
1063
1064      100000      DBCK      =      BIT15      ;DEBUG CLOCK
1065      040000      DBEN      =      BIT14      ;DEBUG CLOCK ENABLE
1066      020000      DEBL      =      BIT13      ;DIAGNOSTIC END OF BLOCK
1067      010000      DTO      =      BIT12      ;DIAGNOSTIC TIMEOUT
1068      004000      MCLK      =      BIT11      ;MAINTENANCE CLOCK
1069      002000      MRD      =      BIT10      ;READ DATA
1070      001000      MUR      =      BIT09      ;UNIT READY
1071      000400      MOC      =      BIT08      ;ON CYLINDER
1072      000200      MSER      =      BIT07      ;SEEK ERROR
1073      000100      MDF      =      BIT06      ;DRIVE FAULT
1074      000040      MS      =      BIT05      ;SECTOR PULSE
1075      000010      MWP      =      BIT03      ;WRITE PROTECT
1076      000004      MI      =      BIT02      ;INDEX PULSE
1077      000002      MSC      =      BIT01      ;SECTOR COMPARE
1078      000001      DMD      =      BIT00      ;DIAGNOSTIC MODE

```

```

1079
1080
1081
1082      100000
1083      040000
1084      020000
1085      010000
1086      004000
1087      002000
1088      001000
1089      000400
1090      000200
1091      000100
1092      000040
1093      000020
1094      000010
1095      000004
1096      000002
1097      000001
1098
1099
1100
1101      100000
1102      040000
1103      020000
1104      004000
1105
1106      020024
1107      024024
1108
1109
1110
1111      010000
1112      004000
1113      002000
1114      000200
1115
1116
1117
1118      001777
1119
1120
1121
1122
1123      100000
1124      040000
1125      020000
1126      010000
1127      004000
1128      002000
1129      001000
1130      000400
1131      000200
1132      000100
1133      000040
1134      000020

;      READ ONLY BITS
OCC      =      BIT15      ;OCCUPIED
RG        =      BIT14      ;RUN AND GO
EBL       =      BIT13      ;END OF BLOCK
REX       =      BIT12      ;EXCEPTION
ESRC      =      BIT11      ;ENABLE SEARCH
PLFS      =      BIT10      ;LOOKING FOR SYNC
ECRC      =      BIT09      ;ENABLE CRC OUT
PDA       =      BIT08      ;DATA AREA
PHA       =      BIT07      ;HEADER AREA
CONT      =      BIT06      ;CONTINUE
WC        =      BIT05      ;WORD CLOCK
EECC      =      BIT04      ;ENABLE ECC OUT
MWD       =      BIT03      ;WRITE DATA BIT
LS        =      BIT02      ;LAST SECTOR
LST       =      BIT01      ;LAST SECTOR AND TRACK
DMD       =      BIT00      ;DIAGNOSTIC MODE

;RMDT  DRIVE TYPE REGISTER
NSA       =      BIT15      ;NOT SECTOR ADDRESSED=0
TAP       =      BIT14      ;TAPE DRIVE = 0
MOH       =      BIT13      ;MOVING HEAD = 1
DRQ       =      BIT11      ;DRIVE REQUEST REQUIRED

SNGPRT    =      020024      ;SINGLE PORT DRIVE TYPE
DULPRT    =      024024      ;DUAL PORT DRIVE TYPE

;RMOF  OFFSET REGISTER
FMT16     =      BIT12      ;16 BIT WORD FORMAT
ECI       =      BIT11      ;ECC INHIBIT
HCI       =      BIT10      ;HEADER COMPARE INHIBIT
OFD       =      BIT07      ;OFFSET FORWARD

;RMDC  DESIRED CYLINDER ADDRESS REGISTER
CYLSK     =      1777      ;MASK FOR CYLINDER ADDRESS

;RMR2  MAINTENANCE REGISTER #2

;      READ ONLY BITS
RQA       =      BIT15      ;PORT A REQUEST
RQB       =      BIT14      ;PORT B REQUEST
TAG       =      BIT13      ;TAG CONTROL
TST       =      BIT12      ;COMMAND SEQUENCE TEST BIT
CC        =      BIT11      ;CONTROL OR CYLINDER TAG
CH        =      BIT10      ;CONTROL OR HEAD TAG
BB09      =      BIT09      ;TAG BUS
BB08      =      BIT08      ;TAG BUS
BB07      =      BIT07      ;TAG BUS
BB06      =      BIT06      ;TAG BUS
BB05      =      BIT05      ;TAG BUS
BB04      =      BIT04      ;TAG BUS

```



```

1135      000010      BB03      =      BIT03      ;TAG BUS
1136      000004      BB02      =      BIT02      ;TAG BUS
1137      000002      BB01      =      BIT01      ;TAG BUS
1138      000001      BB00      =      BIT00      ;TAG BUS
1139
1140
1141      ;RMER2  ERROR REGISTER 2
1142
1143      100000      BSE      =      BIT15      ;BAD SECTOR ERROR
1144      040000      SKI      =      BIT14      ;SEEK INCOMPLETE
1145      020000      OPE      =      BIT13      ;OPERATOR PLUG ERROR
1146      010000      IVC      =      BIT12      ;INVALID COMMAND ERROR
1147      004000      LSC      =      BIT11      ;LOSS OF SYSTEM CLOCK
1148      002000      LBC      =      BIT10      ;LOSS OF BIT CLOCK
1149      000200      DVC      =      BIT07      ;DEVICE CHECK
1150      000010      DPE      =      BIT03      ;DATA PARITY ERROR
1151
1152      .SBTTL  PROGRAM MNEMONICS
1153
1154      100000      MSE      =      BIT15      ;MANUFACTURING DETECTED SECTOR ERROR
1155      040000      USE      =      BIT14      ;USER DETECTED SECTOR ERROR
1156
1157      .SBTTL  RM03 REGISTER INDEX VALUES
1158
1159      000000      RMCSI    =      00      ;CONTROL STATUS REGISTER
1160      000006      RMDA    =      06      ;DISK ADDRESS REGISTER
1161      000012      RMDS    =      12      ;DRIVE STATUS REGISTER
1162      000014      RMER1   =      14      ;ERROR REGISTER 1
1163      000016      RMAS    =      16      ;ATTENTION SUMMARY REGISTER
1164      000020      RMLA    =      20      ;LOOK AHEAD REGISTER
1165      000024      RMMR1   =      24      ;MAINTENANCE REGISTER
1166      000026      RMDT    =      26      ;DRIVE TYPE REGISTER
1167      000030      RMSN    =      30      ;SERIAL NUMBER REGISTER
1168      000032      RMOF    =      32      ;OFFSET REGISTER
1169      000034      RMDC    =      34      ;DESIRED CYLINDER REGISTER
1170      000036      RMCC    =      36      ;CURRENT CYLINDER REGISTER
1171      000040      RMMR2   =      40      ;MAINTENANCE REGISTER 2
1172      000042      RMER2   =      42      ;ERROR REGISTER 2
1173      000044      RMEC1   =      44      ;ECC POSITION REGISTER
1174      000046      RMEC2   =      46      ;ECC PATTERN REGISTER
1175      000050      ILRG50  =      50      ;ILLEGAL REGISTER 50
1176      000052      ILRG52  =      52      ;ILLEGAL REGISTER 52
1177      000054      ILRG54  =      54      ;ILLEGAL REGISTER 54
1178      000056      ILRG56  =      56      ;ILLEGAL REGISTER 56
1179      000060      ILRG60  =      60      ;ILLEGAL REGISTER 60
1180      000062      ILRG62  =      62      ;ILLEGAL REGISTER 62
1181      000064      ILRG64  =      64      ;ILLEGAL REGISTER 64
1182      000066      ILRG66  =      66      ;ILLEGAL REGISTER 66
1183      000070      ILRG70  =      70      ;ILLEGAL REGISTER 70
1184      000072      ILRG72  =      72      ;ILLEGAL REGISTER 72
1185      000074      ILRG74  =      74      ;ILLEGAL REGISTER 74
1186      000076      ILRG76  =      76      ;ILLEGAL REGISTER 76
1187
1188
1189      000077      IDXMSK   =      77      ;MASK FOR REGISTER INDEX NUMBER
1190

```

```
1191 .SBTTL RM CONTROLLER REGISTER BIT DEFINITIONS
1192
1193 ;RMCS1 CONTROL STATUS REGISTER #1
1194
1195 100000 SC = BIT15 ;SPECIAL CONDITION-READ ONLY
1196 040000 TRE = BIT14 ;TRANSFER ERROR
1197 020000 MCPE = BIT13 ;MASSBUS CONTROL BUS PARITY
1198 ;ERROR-READ ONLY
1199 002000 PSEL = BIT10 ;PORT B SELECT
1200 001000 A17 = BIT09 ;ADDRESS EXTENSION
1201 000400 A16 = BIT08 ;ADDRESS EXTENSION
1202 000200 RDY = BIT07 ;READY-READ ONLY
1203 000100 IE = BIT06 ;INTERRUPT ENABLE
1204
1205 ;RMCS2 RM CONTROL STATUS REGISTER #2
1206
1207 100000 DLT = BIT15 ;DATA LATE-READ ONLY
1208 040000 WCE = BIT14 ;WRITE CHECK ERROR-READ ONLY
1209 020000 UPE = BIT13 ;UNIBUS PARITY ERROR
1210 010000 NED = BIT12 ;NONEXISTANT DRIVE-READ ONLY
1211 004000 NEM = BIT11 ;NONEXISTANT MEMORY-READ ONLY
1212 002000 PGE = BIT10 ;PROGRAM ERROR-READ ONLY
1213 001000 MXF = BIT09 ;MISSED TRANSFER
1214 000400 MDPE = BIT08 ;MASSBUS DATA BUS PARITY
1215 ;ERROR-READ ONLY
1216 000200 OR = BIT07 ;OUTPUT READY-READ ONLY
1217 000100 IR = BIT06 ;INPUT READY-READ ONLY
1218 000040 CLR = BIT05 ;CONTROLLER CLEAR
1219 000020 PAT = BIT04 ;PARITY TEST
1220 000010 BAI = BIT03 ;UNIBUS ADDRESS INCREMENT
1221 ;INHIBIT
1222 000004 U2 = BIT02 ;UNIT SELECT
1223 000002 U1 = BIT01 ;UNIT SELECT
1224 000001 U0 = BIT00 ;UNIT SELECT
1225
1226 ;UNIT SELECT MASK
1227 000007 UNTMSK = 7 ;UNIT SELECT MASK
1228
1229 ;RMCS3 RM70 CONTROL STATUS REGISTER #3
1230 100000 APE = BIT15 ;ADDRESS PARITY ERROR
1231 040000 DPEHI = BIT14 ;DATA PARITY ERROR HIGH WORD
1232 020000 DPELO = BIT13 ;DATA PARITY ERROR LOW WORD
1233 010000 WCEHI = BIT12 ;WRITE CHECK ERROR HIGH WORD
1234 004000 WCELO = BIT11 ;WRITE CHECK ERROR LOW WORD
1235 002000 DBL = BIT10 ;DOUBLE WORD TRANSFER
1236 000100 IE = BIT06 ;INTERRUPT ENABLE
1237 000010 IPCK3 = BIT03 ;INVERT PARITY CHECK
1238 000004 IPCK2 = BIT02 ;INVERT PARITY CHECK
1239 000002 IPCK1 = BIT01 ;INVERT PARITY CHECK
1240 000001 IPCK0 = BIT00 ;INVERT PARITY CHECK
1241 .SBTTL RM CONTROLLER REGISTER INDEX VALUES
1242
1243 000000 RMCS1 = 00 ;CONTROL, STATUS REGISTER
1244 000002 RMWC = 02 ;WORD COUNT REGISTER
1245 000004 RMBA = 04 ;BUS ADDRESS REGISTER
1246 000010 RMCS2 = 10 ;CONTROLLER STATUS REGISTER
```



```

1247      000022      RMDB      =      22      ;DATA BUFFER
1248      000050      RMBAE      =      50      ;BUS ADDRESS EXTENSION
1249      000052      RMCS3      =      52      ;CONTROL STATUS REGISTER #3
1250
1251      176700      ABASE      -      176700      ;UNIBUS ADDRESS
1252      120254      AVECT1      =      120254      ;UNIBUS VECTOR ADDRESS AND PRIORITY
1253
1254
1255      .SBTTL  TRAP CATCHER
1256
1257      000000      .=0
1258      ;*ALL UNUSED LOCATIONS FROM 4 - 776 CONTAIN A ".+2,HALT"
1259      ;*SEQUENCE TO CATCH ILLEGAL TRAPS AND INTERRUPTS
1260      ;*LOCATION 0 CONTAINS 0 TO CATCH IMPROPERLY LOADED VECTORS
1261      000174      .=174
1262      000174      000000      DISPREG: .WORD 0      ;;SOFTWARE DISPLAY REGISTER
1263      000176      000000      SWREG:   .WORD 0      ;;SOFTWARE SWITCH REGISTER
1264
1265
1266      .SBTTL  ACT11 HOOKS
1267
1268      ;*****
1269      ;HOOKS REQUIRED BY ACT11
1270      000200      $SVPC=.      ;SAVE PC
1271      000046      .=46
1272      000046      033156      $ENDAD      ;;1)SET LOC.46 TO ADDRESS OF $ENDAD IN .SEOP
1273      000052      .=52
1274      000052      000000      .WORD 0      ;;2)SET LOC.52 TO ZERO
1275      000200      .=$SVPC      ;; RESTORE PC
1276
1277      .SBTTL  STARTING ADDRESS
1278
1279      ;THE PROGRAM STARTS AT LOCATION 200
1280      000200      000200      =      200
1281      000200      000137      005324      JMP      START      ;JUMP TO START OF PROGRAM
1282
1283      001100      .=1100
1284      .SBTTL  APT PARAMETER BLOCK
1285
1286      ;*****
1287      ;SET LOCATIONS 24 AND 44 AS REQUIRED FOR APT
1288      ;*****
1289      001100      001100      $X=.      ;;SAVE CURRENT LOCATION
1290      000024      000024      .=24      ;;SET POWER FAIL TO POINT TO START OF PROGRAM
1291      000024      000200      200      ;;FOR APT START UP
1292      000044      000044      .=44      ;;POINT TO APT INDIRECT ADDRESS PNTR.
1293      000044      001100      $APTHDR      ;;POINT TO APT HEADER BLOCK
1294      001100      001100      .=$X      ;;RESET LOCATION COUNTER
1295
1296      ;*****
1297      ;SETUP APT PARAMETER BLOCK AS DEFINED IN THE APT-PDP11 DIAGNOSTIC
1298      ;INTERFACE SPEC.
1299
1300      001100      001100      000000      $APTHD:
1301      001102      001222      $HIBTS: .WORD 0      ;;TWO HIGH BITS OF 18 BIT MAILBOX ADDR.
1302      001104      000001      $MBADR: .WORD $MAIL      ;;ADDRESS OF APT MAILBOX (BITS 0-15)
      $STM:   .WORD 1      ;;RUN TIM OF LONGEST TEST

```

CZRMDCO RM03/2 FCTNL TST 2
CZRMDC.P11 12-DEC-78 08:24

MACY11 30A(1052) 04-JAN-79 11:23 PAGE 33
APT PARAMETER BLOCK

SEQ 0033

1303	001106	000002	SPASTM: .WORD	2	::RUN TIME IN SECS. OF 1ST PASS ON 1 UNIT (QUICK VERIFY)
1304	001110	000002	SUNITM: .WORD	2	::ADDITIONAL RUN TIME (SECS) OF A PASS FOR EACH ADDITIONAL UNIT
1305	001112	000042	.WORD		SETEND-SMAIL/2 ::LENGTH MAILBOX-ETABLE(WORDS)
1306	001114		TAGADR =	.	

```
1307 .SBTTL COMMON TAGS
1308
1309 ::*****
1310 ::*THIS TABLE CONTAINS VARIOUS COMMON STORAGE LOCATIONS
1311 ::*USED IN THE PROGRAM.
1312
1313 001114 .=TAGADR
1314 001114 $CMTAG: ::START OF COMMON TAGS
1315 001114 000000 $TSTNM: .WORD 0 ::CONTAINS THE TEST NUMBER
1316 001116 000 $ERFLG: .BYTE 0 ::CONTAINS ERROR FLAG
1317 001117 000 $ICNT: .WORD 0 ::CONTAINS SUBTEST ITERATION COUNT
1318 001120 000000 $LPADR: .WORD 0 ::CONTAINS SCOPE LOOP ADDRESS
1319 001122 000000 $LPERR: .WORD 0 ::CONTAINS SCOPE RETURN FOR ERRORS
1320 001124 000000 $ERTTL: .WORD 0 ::CONTAINS TOTAL ERRORS DETECTED
1321 001126 000000 $ITEMB: .BYTE 0 ::CONTAINS ITEM CONTROL BYTE
1322 001130 000 $ERMAX: .BYTE 1 ::CONTAINS MAX. ERRORS PER TEST
1323 001131 001 $ERRPC: .WORD 0 ::CONTAINS PC OF LAST ERROR INSTRUCTION
1324 001132 000000 $GDADR: .WORD 0 ::CONTAINS ADDRESS OF 'GOOD' DATA
1325 001134 000000 $BDADR: .WORD 0 ::CONTAINS ADDRESS OF 'BAD' DATA
1326 001136 000000 $GDDAT: .WORD 0 ::CONTAINS 'GOOD' DATA
1327 001140 000000 $BDDAT: .WORD 0 ::CONTAINS 'BAD' DATA
1328 001142 000000 .WORD 0 ::RESERVED--NOT TO BE USED
1329 001144 000000 .WORD 0
1330 001146 000000 .WORD 0
1331 001150 000 $AUTOB: .BYTE 0 ::AUTOMATIC MODE INDICATOR
1332 001151 000 $INTAG: .BYTE 0 ::INTERRUPT MODE INDICATOR
1333 001152 000000 .WORD 0
1334 001154 177570 $SWR: .WORD DSWR ::ADDRESS OF SWITCH REGISTER
1335 001156 177570 $DISPLAY: .WORD DDISP ::ADDRESS OF DISPLAY REGISTER
1336 001160 177560 $TKS: 177560 ::TTY KBD STATUS
1337 001162 177562 $TKB: 177562 ::TTY KBD BUFFER
1338 001164 177564 $TPS: 177564 ::TTY PRINTER STATUS REG. ADDRESS
1339 001166 177566 $TPB: 177566 ::TTY PRINTER BUFFER REG. ADDRESS
1340 001170 000 $NULL: .BYTE 0 ::CONTAINS NULL CHARACTER FOR FILLS
1341 001171 002 $FILLS: .BYTE 2 ::CONTAINS # OF FILLER CHARACTERS REQUIRED
1342 001172 012 $FILLC: .BYTE 12 ::INSERT FILL CHARS. AFTER A 'LINE FEED'
1343 001173 000 $TPFLG: .BYTE 0 ::'TERMINAL AVAILABLE' FLAG (BIT<07>=0=YES)
1344 001174 000000 $TMP0: .WORD 0 ::USER DEFINED
1345 001176 000000 $TMP1: .WORD 0 ::USER DEFINED
1346 001200 000000 $TMP2: .WORD 0 ::USER DEFINED
1347 001202 000000 $TMP3: .WORD 0 ::USER DEFINED
1348 001204 000000 $TMP4: .WORD 0 ::USER DEFINED
1349 001206 000000 $TIMES: 0 ::MAX. NUMBER OF ITERATIONS
1350 001210 000000 $ESCAPE: 0 ::ESCAPE ON ERROR ADDRESS
1351 001212 177607 000377 $BELL: .ASCIIZ <207><377><377> ::CODE FOR BELL
1352 001216 077 $QUES: .ASCII /?/ ::QUESTION MARK
1353 001217 015 $CRLF: .ASCII <15> ::CARRIAGE RETURN
1354 001220 000012 $LF: .ASCIIZ <12> ::LINE FEED
1355 ::*****
1356 .SBTTL APT MAILBOX-ETABLE
1357
1358 ::*****
1359 .NLIST ME
1360
1361
1362
```

```
1363 .EVEN
1364 001222 $MAIL: ;APT MAILBOX
1365 001222 000000 $MSGTY: .WORD AMSGTY ;MESSAGE TYPE CODE
1366 001224 000000 $FATAL: .WORD AFATAL ;FATAL ERROR NUMBER
1367 001226 000000 $TESTN: .WORD ATESTN ;TEST NUMBER
1368 001230 000000 $PASS: .WORD APASS ;PASS COUNT
1369 001232 000000 $DEVCT: .WORD ADEVCT ;DEVICE COUNT
1370 001234 000000 $UNIT: .WORD AUNIT ;I/O UNIT NUMBER
1371 001236 000000 $MSGAD: .WORD AMSGAD ;MESSAGE ADDRESS
1372 001240 000000 $MSGLG: .WORD AMSGLG ;MESSAGE LENGTH
1373 001242 $ETABLE: ;APT ENVIRONMENT TABLE
1374 001242 000 $ENV: .BYTE AENV ;ENVIRONMENT BYTE
1375 001243 000 $ENVN: .BYTE AENVN ;ENVIRONMENT MODE BITS
1376 001244 000000 $SWREG: .WORD ASWREG ;APT SWITCH REGISTER
1377 001246 000000 $USWR: .WORD AUSWR ;USER SWITCHES
1378 001250 000000 $CPUOP: .WORD ACPUOP ;CPU TYPE,OPTIONS
1379 ;*
1380 ;* 11/04=01,11/05=02,11/20=03,11/40=04,11/45=05
1381 ;* 11/70=06,PDQ=07,Q=10
1382 ;* BIT 10=REAL TIME CLOCK
1383 ;* BIT 9=FLOATING POINT PROCESSOR
1384 ;* BIT 8=MEMORY MANAGEMENT
1385 001252 000 $MAMS1: .BYTE AMAMS1 ;HIGH ADDRESS,M.S. BYTE
1386 001253 000 $MTYP1: .BYTE AMTYP1 ;MEM. TYPE,BLK#1
1387 ;* MEM. TYPE BYTE -- (HIGH BYTE)
1388 ;* 900 NSEC CORE=001
1389 ;* 300 NSEC BIPOLAR=002
1390 ;* 500 NSEC MOS=003
1391 001254 000000 $MADR1: .WORD AMADR1 ;HIGH ADDRESS,BLK#1
1392 ;* MEM.LAST ADDR.=3 BYTES,THIS WORD AND LOW OF "TYPE" ABOVE
1393 001256 000 $MAMS2: .BYTE AMAMS2 ;HIGH ADDRESS,M.S. BYTE
1394 001257 000 $MTYP2: .BYTE AMTYP2 ;MEM. TYPE,BLK#2
1395 001260 000000 $MADR2: .WORD AMADR2 ;MEM.LAST ADDRESS,BLK#2
1396 001262 000 $MAMS3: .BYTE AMAMS3 ;HIGH ADDRESS,M.S. BYTE
1397 001263 000 $MTYP3: .BYTE AMTYP3 ;MEM. TYPE,BLK#3
1398 001264 000000 $MADR3: .WORD AMADR3 ;MEM.LAST ADDRESS,BLK#3
1399 001266 000 $MAMS4: .BYTE AMAMS4 ;HIGH ADDRESS,M.S. BYTE
1400 001267 000 $MTYP4: .BYTE AMTYP4 ;MEM. TYPE,BLK#4
1401 001270 000000 $MADR4: .WORD AMADR4 ;MEM.LAST ADDRESS,BLK#4
1402 001272 120254 $VECT1: .WORD AVECT1 ;INTERRUPT VECTOR#1,BUS PRIORITY#1
1403 001274 000000 $VECT2: .WORD AVECT2 ;INTERRUPT VECTOR#2BUS PRIORITY#2
1404 001276 176700 $BASE: .WORD ABASE ;BASE ADDRESS OF EQUIPMENT UNDER TEST
1405 001300 000000 $DEVN: .WORD ADEVN ;DEVICE MAP
1406 001302 000000 $CDW1: .WORD ACDW1 ;CONTROLLER DESCRIPTION WORD#1
1407 001304 000000 $CDW2: .WORD ACDW2 ;CONTROLLER DESCRIPTION WORD#2
1408 001306 000000 $DDW0: .WORD ADDW0 ;DEVICE DESCRIPTOR WORD#0
1409 001310 000000 $DDW1: .WORD ADDW1 ;DEVICE DESCRIPTOR WORD#1
1410 001312 000000 $DDW2: .WORD ADDW2 ;DEVICE DESCRIPTOR WORD#2
1411 001314 000000 $DDW3: .WORD ADDW3 ;DEVICE DESCRIPTOR WORD#3
1412 001316 000000 $DDW4: .WORD ADDW4 ;DEVICE DESCRIPTOR WORD#4
1413 001320 000000 $DDW5: .WORD ADDW5 ;DEVICE DESCRIPTOR WORD#5
1414 001322 000000 $DDW6: .WORD ADDW6 ;DEVICE DESCRIPTOR WORD#6
1415 001324 000000 $DDW7: .WORD ADDW7 ;DEVICE DESCRIPTOR WORD#7
1416 001326 $ETEND:
1417 .MEXIT
1418 001326 000000 CTLFG: .WORD 0 ;CONTROL-C FLAG
```

```

1419
1420 ;THE REGISTER INPUT BUFFER IS USED FOR
1421 ;STORING DRIVE STATUS
1422
1423 001330 GETBUF:
1424
1425 ;REGISTER INPUT BUFFER
1426 001330 000000 RMCS11: .WORD ;CONTROL,STATUS REGISTER
1427 001332 000000 RMWC1: .WORD ;WORD COUNT REGISTER
1428 001334 000000 RMB1: .WORD ;BUS ADDRESS REGISTER
1429 001336 000000 RMDA1: .WORD ;DISK ADDRESS REGISTER
1430 001340 000000 RMCS21: .WORD ;CONTROLLER STATUS REGISTER
1431 001342 000000 RMDS1: .WORD ;DRIVE STATUS REGISTER
1432 001344 000000 RMER11: .WORD ;ERROR REGISTER 1
1433 001346 000000 RMA1: .WORD ;ATTENTION SUMMARY REGISTER
1434 001350 000000 RMLA1: .WORD ;LOOK AHEAD REGISTER
1435 001352 000000 RMDB1: .WORD ;DATA BUFFER
1436 001354 000000 RMMR11: .WORD ;MAINTENANCE REGISTER #1
1437 001356 000000 RMDT1: .WORD ;DRIVE TYPE REGISTER
1438 001360 000000 RMSN1: .WORD ;SERIAL NUMBER REGISTER
1439 001362 000000 RMOF1: .WORD ;OFFSET REGISTER
1440 001364 000000 RMDC1: .WORD ;DESIRED CYLINDER REGISTER
1441 001366 000000 RMCC1: .WORD ;CURRENT CYLINDER REGISTER
1442 001370 000000 RMMR21: .WORD ;MAINTENANCE REGISTER #2
1443 001372 000000 RMER21: .WORD ;ERROR REGISTER 2
1444 001374 000000 RMEC11: .WORD ;ECC POSITION REGISTER
1445 001376 000000 RMEC21: .WORD ;ECC PATTERN REGISTER
1446
1447 ;THE REGISTER OUTPUT BUFFER IS USED FOR
1448 ;ASSEMBLING DATA GOING TO REGISTER
1449
1450 001400 PUTBUF:
1451
1452 ;REGISTER OUTPUT BUFFER
1453 001400 000000 RMCS10: .WORD ;CONTROL,STATUS REGISTER
1454 001402 000000 RMWC0: .WORD ;WORD COUNT REGISTER
1455 001404 000000 RMB0: .WORD ;BUS ADDRESS REGISTER
1456 001406 000000 RMDA0: .WORD ;DISK ADDRESS REGISTER
1457 001410 000000 RMCS20: .WORD ;CONTROLLER STATUS REGISTER
1458 001412 000000 RMDS0: .WORD ;DRIVE STATUS REGISTER
1459 001414 000000 RMER10: .WORD ;ERROR REGISTER 1
1460 001416 000000 RMA0: .WORD ;ATTENTION SUMMARY REGISTER
1461 001420 000000 RMLA0: .WORD ;LOOK AHEAD REGISTER
1462 001422 000000 RMDB0: .WORD ;DATA BUFFER
1463 001424 000000 RMMR10: .WORD ;MAINTENANCE REGISTER #1
1464 001426 000000 RMDT0: .WORD ;DRIVE TYPE REGISTER
1465 001430 000000 RMSN0: .WORD ;SERIAL NUMBER REGISTER
1466 001432 000000 RMOF0: .WORD ;OFFSET REGISTER
1467 001434 000000 RMDC0: .WORD ;DESIRED CYLINDER REGISTER
1468 001436 000000 RMCC0: .WORD ;CURRENT CYLINDER REGISTER
1469 001440 000000 RMMR20: .WORD ;MAINTENANCE REGISTER #2
1470 001442 000000 RMER20: .WORD ;ERROR REGISTER 2
1471 001444 000000 RMEC10: .WORD ;ECC POSITION REGISTER
1472 001446 000000 RMEC20: .WORD ;ECC PATTERN REGISTER
1473
1474 ;EACH WORD OF THE TEST QUE CONTAINS THE DEVICE NUMBER IN

```

```
1475 ;THE LOW BYTE AND THE ATTENTION BIT IN THE HIGH BYTE. A ZERO
1476 ;WORD IS A BLANK AND REPRESENTS THE END OF THE QUE.
1477
1478 001450 000012 TSTQUE: .BLKW 10. ;TEST QUE
1479
1480 ;MEDIA ENABLE IS SET IF THE BAD SECTOR FILES HAVE BEEN RECOVERED
1481 ;FOR THE UNIT UNDER TEST, OTHERWISE IT IS ZERO.
1482 001474 000000 MEDENB: .WORD ;MEDIA ENABLE
1483
1484 ;LOCATIONS "ASNDC" AND "ASNDC" CONTAIN THE CYLINDER, TRACK AND SECTOR
1485 ;ADDRESS ASSIGNED BY THE BAD SECTOR MODULE.
1486 001476 000000 ASNDC: .WORD ;ASSIGNED DESIRED CYLINDER
1487 001500 000000 ASNDA: .WORD ;ASSIGNED TRACK, AND SECTOR
1488 001502 000000 CLKADR: .WORD ;UNIBUS ADDRESS OF KW11 CLOCK
1489 001504 000000 CLKVCT: .WORD ;VECTOR ADDRESS OF KW11 CLOCK
1490
1491 ;THE GET INDEX TABLE CONTAINS A BYTE LIST OF REGISTERS WHICH
1492 ;ARE READ BY THE GET SUBROUTINE. THE LIST IS TERMINATED BY
1493 ;A NEGATIVE BYTE.
1494 001506 000027 GETINX: .BLKB 23. ;GET INDEX TABLE
1495
1496 ;THE PUT INDEX TABLE ICONTAINS / BYTE LIST OF REGISTERS WHICH
1497 ;ARE WRITTEN BY THE PUT SUBROUTINE. THE LIST IS TERMINATED BY
1498 ;A NEGATIVE BYTE.
1499 001535 000027 PUTINX: .BLKB 23. ;PUT INDEX TABLE
1500
1501 ;PUT TAGS HERE
1502
```


1503
1504
1505
1506
1507
1508
1509
1510
1511
1512
1513
1514
1515
1516
1517
1518
1519

001564

.SBTTL ERROR POINTER TABLE

;*THIS TABLE CONTAINS THE INFORMATION FOR EACH ERROR THAT CAN OCCUR.
;*THE INFORMATION IS OBTAINED BY USING THE INDEX NUMBER FOUND IN
;*LOCATION \$ITEMB. THIS NUMBER INDICATES WHICH ITEM IN THE TABLE IS PERTINENT.
;*NOTE1: IF \$ITEMB IS 0 THE ONLY PERTINENT DATA IS (\$ERRPC).
;*NOTE2: EACH ITEM IN THE TABLE CONTAINS 4 POINTERS EXPLAINED AS FOLLOWS:

;* EM	::POINTS TO THE ERROR MESSAGE
;* DH	::POINTS TO THE DATA HEADER
;* DT	::POINTS TO THE DATA
;* DF	::POINTS TO THE DATA FORMAT

\$ERRTB:

1520			:ERROR 1	WRONG UNIT SELECTED
1521	001564	065430	EMT1	
1522	001566	071522	EHT1	
1523	001570	071646	EDT1	
1524	001572	071736	EFT1	
1525				
1526				
1527			:ERROR 2	DEVICE WENT UNAVAILABLE
1528	001574	065434	EMT2	
1529	001576	071522	EHT1	
1530	001600	071646	EDT1	
1531	001602	071736	EFT1	
1532				
1533				
1534			:ERROR 3	DEVICE WENT NONEXISTENT
1535	001604	065442	EMT3	
1536	001606	071522	EHT1	
1537	001610	071646	EDT1	
1538	001612	071736	EFT1	
1539				
1540				
1541			:ERROR 4	CONTROLLER NOT READY
1542	001614	065450	EMT4	
1543	001616	071522	EHT1	
1544	001620	071646	EDT1	
1545	001622	071736	EFT1	
1546				
1547				
1548			:E' JR 5	DRIVE NOT READY AND GO NOT RESET
1549	001624	065456	EMT5	
1550	001626	071522	EHT1	
1551	001630	071646	EDT1	
1552	001632	071736	EFT1	
1553				
1554				
1555			:ERROR 6	UNEXPECTED VALUE FOR "ATA" STATUS
1556	001634	065464	EMT6	
1557	001636	071522	EHT1	
1558	001640	071646	EDT1	
1559	001642	071736	EFT1	
1560				
1561				
1562			:ERROR 7	BUS TIMEOUT TRYING TO READ OR WRITE REGISTER
1563	001644	065472	EMT7	
1564	001646	000000	0	
1565	001650	000000	0	
1566	001652	000000	0	
1567				
1568				
1569			:ERROR 10	DRIVE NOT READY BUT GO IS RESET
1570	001654	065500	EMT10	
1571	001656	071522	EHT1	
1572	001660	071646	EDT1	
1573	001662	071736	EFT1	
1574				
1575				

1576			;ERROR 11	GO NOT RESET BUT DRIVE IS READY
1577	001664	065504	EMT11	
1578	001666	071522	EHT1	
1579	001670	071646	EDT1	
1580	001672	071736	EFT1	
1581				
1582				
1583			;ERROR 12	INCORRECT FUNCTION CODE
1584	001674	065510	EMT12	
1585	001676	071522	EHT1	
1586	001700	071646	EDT1	
1587	001702	071736	EFT1	
1588				
1589				
1590			;ERROR 13	PARITY ERROR READING REMOTE REGISTERS
1591	001704	065516	EMT13	
1592	001706	071522	EHT1	
1593	001710	071646	EDT1	
1594	001712	071736	EFT1	
1595				
1596				
1597			;ERROR 14	TRANSFER ERROR IS INCORRECT
1598	001714	065530	EMT14	
1599	001716	071522	EHT1	
1600	001720	071646	EDT1	
1601	001722	071736	EFT1	
1602				
1603				
1604			;ERROR 15	INCORRECT WORD COUNT
1605	001724	065536	EMT15	
1606	001726	071522	EHT1	
1607	001730	071646	EDT1	
1608	001732	071736	EFT1	
1609				
1610				
1611			;ERROR 16	INCORRECT BUS ADDRESS
1612	001734	065544	EMT16	
1613	001736	071522	EHT1	
1614	001740	071646	EDT1	
1615	001742	071736	EFT1	
1616				
1617				
1618			;ERROR 17	INCORRECT LBT STATUS
1619	001744	065554	EMT17	
1620	001746	071522	EHT1	
1621	001750	071646	EDT1	
1622	001752	071736	EFT1	
1623				
1624				
1625			;ERROR 20	INCORRECT AOE
1626	001754	065564	EMT20	
1627	001756	071522	EHT1	
1628	001760	071646	EDT1	
1629	001762	071736	EFT1	
1630				
1631				

1632			;ERROR 21	INCORRECT DISK ADDRESS
1633	001764	065574	EMT21	
1634	001766	071522	EMT1	
1635	001770	071646	EDT1	
1636	001772	071736	EFT1	
1637				
1638				
1639			;ERROR 22	INCORRECT CYLINDER ADDRESS
1640	001774	065604	EMT22	
1641	001776	071522	EMT1	
1642	002000	071646	EDT1	
1643	002002	071736	EFT1	
1644				
1645				
1646			;ERROR 23	INCORRECT WLE STATUS
1647	002004	065614	EMT23	
1648	002006	071522	EMT1	
1649	002010	071646	EDT1	
1650	002012	071736	EFT1	
1651				
1652				
1653			;ERROR 24	INCORRECT UPE STATUS
1654	002014	065624	EMT24	
1655	002016	071522	EMT1	
1656	002020	071646	EDT1	
1657	002022	071736	EFT1	
1658				
1659				
1660			;ERROR 25	INCORRECT WCF STATUS
1661	002024	065634	EMT25	
1662	002026	071522	EMT1	
1663	002030	071646	EDT1	
1664	002032	071736	EFT1	
1665				
1666				
1667			;ERROR 26	INCORRECT WCE STATUS
1668	002034	065644	EMT26	
1669	002036	071522	EMT1	
1670	002040	071646	EDT1	
1671	002042	071736	EFT1	
1672				
1673				
1674			;ERROR 27	INCORRECT MDPE STATUS
1675	002044	065654	EMT27	
1676	002046	071522	EMT1	
1677	002050	071646	EDT1	
1678	002052	071736	EFT1	
1679				
1680				
1681			;ERROR 30	INCORRECT DCK STATUS
1682	002054	065664	EMT30	
1683	002056	071522	EMT1	
1684	002060	071646	EDT1	
1685	002062	071736	EFT1	
1686				
1687				

1688			;ERROR 31	INCORRECT ECM STATUS
1689	002064	065674	EMT31	
1690	002066	071522	EMT1	
1691	002070	071646	EDT1	
1692	002072	071736	EFT1	
1693				
1694				
1695			;ERROR 32	DLT SHOULD NOT BE SET
1696	002074	065704	EMT32	
1697	002076	071522	EMT1	
1698	002100	071646	EDT1	
1699	002102	071736	EFT1	
1700				
1701				
1702			;ERROR 33	MXF SHOULD NOT BE SET
1703	002104	065714	EMT33	
1704	002106	071522	EMT1	
1705	002110	071646	EDT1	
1706	002112	071736	EFT1	
1707				
1708				
1709			;ERROR 34	DTE SHOULD NOT BE SET
1710	002114	065724	EMT34	
1711	002116	071522	EMT1	
1712	002120	071646	EDT1	
1713	002122	071736	EFT1	
1714				
1715				
1716			;ERROR 35	INCORRECT HCRC STATUS
1717	002124	065734	EMT35	
1718	002126	071522	EMT1	
1719	002130	071646	EDT1	
1720	002132	071736	EFT1	
1721				
1722				
1723			;ERROR 36	INCORRECT HCE STATUS
1724	002134	065744	EMT36	
1725	002136	071522	EMT1	
1726	002140	071646	EDT1	
1727	002142	071736	EFT1	
1728				
1729				
1730			;ERROR 37	INCORRECT FER STATUS
1731	002144	065754	EMT37	
1732	002146	071522	EMT1	
1733	002150	071646	EDT1	
1734	002152	071736	EFT1	
1735				
1736				
1737			;ERROR 40	DPE SHOULD NOT BE SET (NOT A DATA COMMAND)
1738	002154	065764	EMT40	
1739	002156	071522	EMT1	
1740	002160	071646	EDT1	
1741	002162	071736	EFT1	
1742				
1743				

1744			:ERROR	41	LOST 'MOL' DURING PACK ACKNOWLEDGE
1745	002164	065772		EMT41	
1746	002166	071522		EHT1	
1747	002170	071646		EDT1	
1748	002172	071736		EFT1	
1749					
1750					
1751			:ERROR	42	UNSAFE ERROR DURING PACK ACKNOWLEDGE
1752	002174	066002		EMT42	
1753	002176	071522		EHT1	
1754	002200	071646		EDT1	
1755	002202	071736		EFT1	
1756					
1757					
1758			:ERROR	43	'OPI' ERROR DURING PACK ACKNOWLEDGE
1759	002204	066014		EMT43	
1760	002206	071522		EHT1	
1761	002210	071646		EDT1	
1762	002212	071736		EFT1	
1763					
1764					
1765			:ERROR	44	'RMR' ERROR DURING PACK ACKNOWLEDGE
1766	002214	066024		EMT44	
1767	002216	071522		EHT1	
1768	002220	071646		EDT1	
1769	002222	071736		EFT1	
1770					
1771					
1772			:ERROR	45	'ILR' ERROR DURING PACK ACKNOWLEDGE
1773	002224	066034		EMT45	
1774	002226	071522		EHT1	
1775	002230	071646		EDT1	
1776	002232	071736		EFT1	
1777					
1778					
1779			:ERROR	46	'ILF' ERROR DURING PACK ACKNOWLEDGE
1780	002234	066044		EMT46	
1781	002236	071522		EHT1	
1782	002240	071646		EDT1	
1783	002242	071736		EFT1	
1784					
1785					
1786			:ERROR	47	COMPOSITE ERROR STATUS IS INCORRECT
1787	002244	066054		EMT47	
1788	002246	071522		EHT1	
1789	002250	071646		EDT1	
1790	002252	071736		EFT1	
1791					
1792					
1793			:ERROR	50	PARITY ERROR WRITING REMOTE REGISTERS
1794	002254	066062		EMT50	
1795	002256	071522		EHT1	
1796	002260	071646		EDT1	
1797	002262	071736		EFT1	
1798					
1799					

1800			:ERROR 51	INCORRECT IAE STATUS DURING SEEK COMMAND
1801	002264	066072	EMT51	
1802	002266	071522	EMT1	
1803	002270	071646	EDT1	
1804	002272	071736	EFT1	
1805				
1806				
1807			:ERROR 52	OPI ERROR DURING SEEK - MEDIUM IS NOT ON LINE
1808	002274	066104	EMT52	
1809	002276	071522	EMT1	
1810	002300	071646	EDT1	
1811	002302	071736	EFT1	
1812				
1813				
1814			:ERROR 53	OPI ERROR DURING SEEK - MEDIUM IS ON LINE, ASSUME
1815			:	ON CYLINDER LATCH DIDN'T RESET
1816	002304	066122	EMT53	
1817	002306	071522	EMT1	
1818	002310	071646	EDT1	
1819	002312	071736	EFT1	
1820				
1821				
1822			:ERROR 54	SEEK INCOMPLETE ERROR DURING SEEK COMMAND
1823	002314	066140	EMT54	
1824	002316	071522	EMT1	
1825	002320	071646	EDT1	
1826	002322	071736	EFT1	
1827				
1828				
1829			:ERROR 55	DEVICE CHECK DURING SEEK COMMAND
1830	002324	066150	EMT55	
1831	002326	071522	EMT1	
1832	002330	071646	EDT1	
1833	002332	071736	EFT1	
1834				
1835				
1836			:ERROR 56	PIP IS STILL SET AFTER SEEK - SKI IS RESET
1837	002334	066162	EMT56	
1838	002336	071522	EMT1	
1839	002340	071646	EDT1	
1840	002342	071736	EFT1	
1841				
1842				
1843			:ERROR 57	ATA DID NOT SET DURING SEEK COMMAND
1844	002344	066200	EMT57	
1845	002346	071522	EMT1	
1846	002350	071646	EDT1	
1847	002352	071736	EFT1	
1848				
1849				
1850			:ERROR 60	IVC ERROR DURING SEEK COMMAND - LOST
1851			:	VOLUME VALID
1852	002354	066210	EMT60	
1853	002356	071522	EMT1	
1854	002360	071646	EDT1	
1855	002362	071736	EFT1	

1856				
1857				
1858			;ERROR 61	ERRONEOUS IVC ERROR DURING SEEK COMMAND -
1859			:	VOLUME VALID IS STIL SET
1860	002364	066226		
1861	002366	071522	EMT61	
1862	002370	071646	EMT1	
1863	002372	071736	EDT1	
1864			EFT1	
1865				
1866			;ERROR 62	MOL IS ZERO, BUT OPI WAS NOT
1867			:	REPORTED DURING SFEK COMMAND
1868	002374	066246		
1869	002376	071522	EMT62	
1870	002400	071646	EMT1	
1871	002402	071736	EDT1	
1872			EFT1	
1873				
1874			;ERROR 63	UNUSED
1875	002404	000000	0	
1876	002406	000000	0	
1877	002410	000000	0	
1878	002412	000000	0	
1879				
1880				
1881			;ERROR 64	DRIVE DID NOT DETECT "IVC" ERROR DURING SEEK
1882	002414	066264	EMT64	
1883	002416	071522	EMT1	
1884	002420	071646	EDT1	
1885	002422	071736	EFT1	
1886				
1887				
1888			;ERROR 65	DRIVE EXECUTED A SEEK WITH ERROR SET
1889	002424	066304	EMT65	
1890	002426	071522	EMT1	
1891	002430	071646	EDT1	
1892	002432	071736	EFT1	
1893				
1894				
1895			;ERROR 66	UNEXPECTED ERROR SET IN RMER1
1896	002434	066324	EMT66	
1897	002436	071522	EMT1	
1898	002440	071646	EDT1	
1899	002442	071736	EFT1	
1900				
1901				
1902			;ERROR 67	UNEXPECTED ERROR SET IN RMER2
1903	002444	066336	EMT67	
1904	002446	071522	EMT1	
1905	002450	071646	EDT1	
1906	002452	071736	EFT1	
1907				
1908				
1909			;ERROR 70	ERRONEOUS "IAE" ERROR DURING RECALIBRATE
1910	002454	066350	EMT70	
1911	002456	071522	EMT1	

1912	002460	071646	EDT1	
1913	002462	071736	EDT1	
1914				
1915				
1916			;ERROR 71	"ILF" ERROR DURING RECALIBRATE
1917	002464	066360	EDT1	
1918	002466	071522	EDT1	
1919	002470	071646	EDT1	
1920	002472	071736	EDT1	
1921				
1922				
1923			;ERROR 72	"OPI" ERROR DURING RECALIBRATE DUE TO "MOL" = 0
1924	002474	066370	EDT1	
1925	002476	071522	EDT1	
1926	002500	071646	EDT1	
1927	002502	071736	EDT1	
1928				
1929				
1930			;ERROR 73	"OPI" ERROR DURING RECALIBRATE BECAUSE ON
1931				CYLINDER DIDNT DROP
1932	002504	066406	EDT1	
1933	002506	071522	EDT1	
1934	002510	071646	EDT1	
1935	002512	071736	EDT1	
1936				
1937				
1938			;ERROR 74	"IVC" ERROR DURING RECALIBRATE - "VV" = 0
1939	002514	066424	EDT1	
1940	002516	071522	EDT1	
1941	002520	071646	EDT1	
1942	002522	071736	EDT1	
1943				
1944				
1945			;ERROR 75	ERRONEOUS "IVC" ERROR DURING RECALIBRATE - "VV" = 1
1946	002524	066434	EDT1	
1947	002526	071522	EDT1	
1948	002530	071646	EDT1	
1949	002532	071736	EDT1	
1950				
1951				
1952			;ERROR 76	"SKI" ERROR DURING RECALIBRATE
1953	002534	066454	EDT1	
1954	002536	071522	EDT1	
1955	002540	071646	EDT1	
1956	002542	071736	EDT1	
1957				
1958				
1959			;ERROR 77	"DVC" OCCURRED DURING RECALIBRATE
1960	002544	066464	EDT1	
1961	002546	071522	EDT1	
1962	002550	071646	EDT1	
1963	002552	071736	EDT1	
1964				
1965				
1966			;ERROR 100	LOST "MC" DURING RECALIBRATE - "OPI" = 0
1967	002554	066476	EDT100	

1968	002556	071522			
1969	002560	071646		EMT1	
1970	002562	071736		EDT1	
1971				EFT1	
1972					
1973			;ERROR	101	LOST "VV" DURING RECALIBRATE - "IVC" = 0
1974	002564	066514		EMT101	
1975	002566	071522		EMT1	
1976	002570	071646		EDT1	
1977	002572	071736		EFT1	
1978					
1979					
1980			;ERROR	102	"ATA" DID NOT SET DURING RECALIBRATE
1981	002574	066532		EMT102	
1982	002576	071522		EMT1	
1983	002600	071646		EDT1	
1984	002602	071736		EFT1	
1985					
1986					
1987			;ERROR	103	"OM" DID NOT RESET DURING RECALIBRATE
1988	002604	066542		EMT103	
1989	002606	071522		EMT1	
1990	002610	071646		EDT1	
1991	002612	071736		EFT1	
1992					
1993					
1994			;ERROR	104	"PIP" IS STILL SET AFTER RECALIBRATE
1995	002614	066554		EMT104	
1996	002616	071522		EMT1	
1997	002620	071646		EDT1	
1998	002622	071736		EFT1	
1999					
2000					
2001			;ERROR	105	UNEXPECTED "ILR" ERROR DURING RECALIBRATE
2002	002624	066572		EMT105	
2003	002626	071522		EMT1	
2004	002630	071646		EDT1	
2005	002632	071736		EFT1	
2006					
2007					
2008			;ERROR	106	UNEXPECTED "RMR" ERROR DURING RECALIBRATE
2009	002634	066602		EMT106	
2010	002636	071522		EMT1	
2011	002640	071646		EDT1	
2012	002642	071736		EFT1	
2013					
2014					
2015			;ERROR	107	"UNS" ERROR DURING RECALIBRATE - AC POWER IS LOW
2016	002644	066612		EMT107	
2017	002646	071522		EMT1	
2018	002650	071646		EDT1	
2019	002652	071736		EFT1	
2020					
2021					
2022			;ERROR	110	CANNOT ACCESS MASSBUS CONTROLLER VIA UNIBUS
2023	002654	066632		EMT110	

2024	002656	071544	EMT110	
2025	002660	071664	EDT110	
2026	002662	071754	EFT110	
2027				
2028				
2029			;ERROR	111 NONEXISTENT DEVICE
2030	002664	066644	EMT111	
2031	002666	071550	EMT111	
2032	002670	071666	EDT111	
2033	002672	071756	EFT111	
2034				
2035				
2036			;ERROR	112 DEVICE NOT AVAILABLE
2037	002674	066652	EMT112	
2038	002676	071550	EMT111	
2039	002700	071666	EDT111	
2040	002702	071756	EFT111	
2041				
2042				
2043			;ERROR	113 BUS TIMEOUT-NED STATUS FAILURE
2044	002704	066660	EMT113	
2045	002706	000000	0	
2046	002710	000000	0	
2047	002712	000000	0	
2048				
2049				
2050			;ERROR	114 DEVICE NOT AN RM03
2051	002714	066674	EMT114	
2052	002716	071554	EMT114	
2053	002720	071670	EDT114	
2054	002722	071760	EFT114	
2055				
2056				
2057			;ERROR	115 RMCS1 NOT INITIALIZED BY UNIBUS
2058	002724	066702	EMT115	
2059	002726	071522	EMT1	
2060	002730	071646	EDT1	
2061	002732	071736	EFT1	
2062				
2063				
2064			;ERROR	116 RMBA NOT INITIALIZED BY UNIBUS
2065	002734	066712	EMT116	
2066	002736	071522	EMT1	
2067	002740	071646	EDT1	
2068	002742	071736	EFT1	
2069				
2070				
2071			;ERROR	117 RMCS2 NOT INITIALIZED BY UNIBUS
2072	002744	066722	EMT117	
2073	002746	071522	EMT1	
2074	002750	071646	EDT1	
2075	002752	071736	EFT1	
2076				
2077				
2078			;ERROR	120 RMER1 NOT INITIALIZED BY UNIBUS
2079	002754	066732	EMT120	

2080	002756	071522		EMT1	
2081	002760	071646		EDT1	
2082	002762	071736		EFT1	
2083					
2084					
2085			;ERROR	121	RMA5 NOT INITIALIZED BY UNIBUS
2086	002764	066742		EMT121	
2087	002766	071522		EMT1	
2088	002770	071646		EDT1	
2089	002772	071736		EFT1	
2090					
2091					
2092			;ERROR	122	RMMR1 NOT INITIALIZED BY UNIBUS
2093	002774	066752		EMT122	
2094	002776	071522		EMT1	
2095	003000	071646		EDT1	
2096	003002	071736		EFT1	
2097					
2098					
2099			;ERROR	123	RMDS NOT INITIALIZED BY UNIBUS
2100	003004	066762		EMT123	
2101	003006	071522		EMT1	
2102	003010	071646		EDT1	
2103	003012	071736		EFT1	
2104					
2105					
2106			;ERROR	124	RMEC2 NOT INITIALIZED BY UNIBUS
2107	003014	066772		EMT124	
2108	003016	071522		EMT1	
2109	003020	071646		EDT1	
2110	003022	071736		EFT1	
2111					
2112					
2113			;ERROR	125	RMMR2 NOT INITIALIZED BY UNIBUS
2114	003024	067002		EMT125	
2115	003026	071522		EMT1	
2116	003030	071646		EDT1	
2117	003032	071736		EFT1	
2118					
2119					
2120			;ERROR	126	RMCS1 NOT CLEARED BY CONTROLLER CLEAR
2121	003034	067012		EMT126	
2122	003036	071522		EMT1	
2123	003040	071646		EDT1	
2124	003042	071736		EFT1	
2125					
2126					
2127			;ERROR	127	RMBA NOT CLEARED BY CONTROLLER CLEAR
2128	003044	067024		EMT127	
2129	003046	071522		EMT1	
2130	003050	071646		EDT1	
2131	003052	071736		EFT1	
2132					
2133					
2134			;ERROR	130	RMCS2 NOT CLEARED BY CONTROLLER CLEAR
2135	003054	067036		EMT130	

2136	003056	071522		EHT1	
2137	003060	071646		EDT1	
2138	003062	071736		EFT1	
2139					
2140					
2141			;ERROR	131	RMER1 NOT CLEARED BY CONTROLLER CLEAR
2142	003064	067050		EMT131	
2143	003066	071522		EHT1	
2144	003070	071646		EDT1	
2145	003072	071736		EFT1	
2146					
2147					
2148			;ERROR	132	RMAS NOT CLEARED BY CONTROLLER CLEAR
2149	003074	067062		EMT132	
2150	003076	071522		EHT1	
2151	003100	071646		EDT1	
2152	003102	071736		EFT1	
2153					
2154					
2155			;ERROR	133	RMMR1 NOT CLEARED BY CONTROLLER CLEAR
2156	003104	067074		EMT133	
2157	003106	071522		EHT1	
2158	003110	071646		EDT1	
2159	003112	071736		EFT1	
2160					
2161					
2162			;ERROR	134	RMDS NOT CLEARED BY CONTROLLER CLEAR
2163	003114	067106		EMT134	
2164	003116	071522		EHT1	
2165	003120	071646		EDT1	
2166	003122	071736		EFT1	
2167					
2168					
2169			;ERROR	135	RMEC2 NOT CLEARED BY CONTROLLER CLEAR
2170	003124	067120		EMT135	
2171	003126	071522		EHT1	
2172	003130	071646		EDT1	
2173	003132	071736		EFT1	
2174					
2175					
2176			;ERROR	136	RMMR2 NOT CLEARED BY CONTROLLER CLEAR
2177	003134	067132		EMT136	
2178	003136	071522		EHT1	
2179	003140	071646		EDT1	
2180	003142	071736		EFT1	
2181					
2182					
2183			;ERROR	137	RMCS1 NOT CLEARED BY ERROR CLEAR
2184	003144	067144		EMT137	
2185	003146	071522		EHT1	
2186	003150	071646		EDT1	
2187	003152	071736		EFT1	
2188					
2189					
2190			;ERROR	140	RMCS2 NOT CLEARED BY ERROR CLEAR
2191	003154	067154		EMT140	

2192	003156	071522		EMT1	
2193	003160	071646		EDT1	
2194	003162	071736		EFT1	
2195					
2196					
2197			;ERROR	141	RMCS1 NOT CLEARED BY DRIVE CLEAR
2198	003164	067164		EMT141	
2199	003166	071522		EMT1	
2200	003170	071646		EDT1	
2201	003172	071736		EFT1	
2202					
2203					
2204			;ERROR	142	RMDS NOT CLEARED BY DRIVE CLEAR
2205	003174	067174		EMT142	
2206	003176	071522		EMT1	
2207	003200	071646		EDT1	
2208	003202	071736		EFT1	
2209					
2210					
2211			;ERROR	143	RMER1 NOT CLEARED BY DRIVE CLEAR
2212	003204	067204		EMT143	
2213	003206	071522		EMT1	
2214	003210	071646		EDT1	
2215	003212	071736		EFT1	
2216					
2217					
2218			;ERROR	144	RMA5 NOT CLEARED BY DRIVE CLEAR
2219	003214	067214		EMT144	
2220	003216	071522		EMT1	
2221	003220	071646		EDT1	
2222	003222	071736		EFT1	
2223					
2224					
2225			;ERROR	145	RMMR1 NOT CLEARED BY DRIVE CLEAR
2226	003224	067224		EMT145	
2227	003226	071522		EMT1	
2228	003230	071646		EDT1	
2229	003232	071736		EFT1	
2230					
2231					
2232			;ERROR	146	RMMR2 NOT CLEARED BY DRIVE CLEAR
2233	003234	067234		EMT146	
2234	003236	071522		EMT1	
2235	003240	071646		EDT1	
2236	003242	071736		EFT1	
2237					
2238					
2239			;ERROR	147	RMER2 NOT CLEARED BY DRIVE CLEAR
2240	003244	067244		EMT147	
2241	003246	071522		EMT1	
2242	003250	071646		EDT1	
2243	003252	071736		EFT1	
2244					
2245					
2246			;ERROR	150	RMEC2 NOT CLEARED BY DRIVE CLEAR
2247	003254	067254		EMT150	

2248	003256	071522		EMT1	
2249	003260	071646		EDT1	
2250	003262	071736		EFT1	
2251					
2252					
2253			;ERROR	151	MEDIUM NOT ON LINE
2254	003264	067264		EMT151	
2255	003266	071522		EMT1	
2256	003270	071646		EDT1	
2257	003272	071736		EFT1	
2258					
2259					
2260			;ERROR	152	DRIVE FAULT
2261	003274	067276		EMT152	
2262	003276	071522		EMT1	
2263	003300	071646		EDT1	
2264	003302	071736		EFT1	
2265					
2266					
2267			;ERROR	153	UNSAFE SHOULD BE SET BECAUSE DVC IS SET
2268	003304	067310		EMT153	
2269	003306	071522		EMT1	
2270	003310	071646		EDT1	
2271	003312	071736		EFT1	
2272					
2273					
2274			;ERROR	154	UNSAFE SHOULD NOT BE SET, AC IS LOW
2275	003314	067326		EMT154	
2276	003316	071522		EMT1	
2277	003320	071646		EDT1	
2278	003322	071736		EFT1	
2279					
2280					
2281			;ERROR	155	VOLUME VALID NOT SET BY PACK ACK
2282	003324	067344		EMT155	
2283	003326	071522		EMT1	
2284	003330	071646		EDT1	
2285	003332	071736		EFT1	
2286					
2287					
2288			;ERROR	156	OFFSET MODE NOT SET BY OFFSET COMMAND
2289	003334	067356		EMT156	
2290	003336	071522		EMT1	
2291	003340	071646		EDT1	
2292	003342	071736		EFT1	
2293					
2294					
2295			;ERROR	157	OFFSET MODE NOT RESET BY RTC COMMAND
2296	003344	067370		EMT157	
2297	003346	071522		EMT1	
2298	003350	071646		EDT1	
2299	003352	071736		EFT1	
2300					
2301					
2302			;ERROR	160	RMOF NOT RESET BY RIP COMMAND
2303	003354	067402		EMT160	

2304	003356	071522	EMT1	
2305	003360	071646	EDT1	
2306	003362	071736	EFT1	
2307				
2308				
2309			:ERROR 161	RMDA NOT RESET BY RIP COMMAND
2310	003364	067412	EMT161	
2311	003366	071522	EMT1	
2312	003370	071646	EDT1	
2313	003372	071736	EFT1	
2314				
2315				
2316			:ERROR 162	RMDC NOT RESET BY RIP COMMAND
2317	003374	067424	EMT162	
2318	003376	071522	EMT1	
2319	003400	071646	EDT1	
2320	003402	071736	EFT1	
2321				
2322				
2323			:ERROR 163	DATA WAS ECC CORRECTED BUT DOES NOT COMPARE WITH
2324			:	WRITE BUFFER
2325	003404	071316	EMT336	
2326	003406	071604	EMT336	
2327	003410	071702	EDT336	
2328	003412	071772	EFT336	
2329				
2330				
2331			:ERROR 164	OPI SHOULD NOT BE SET
2332	003414	067446	EMT164	
2333	003416	071522	EMT1	
2334	003420	071646	EDT1	
2335	003422	071736	EFT1	
2336				
2337				
2338			:ERROR 165	IVC SHOULD NOT BE SET
2339	003424	067454	EMT165	
2340	003426	071522	EMT1	
2341	003430	071646	EDT1	
2342	003432	071736	EFT1	
2343				
2344				
2345			:ERROR 166	IAE SHOULD NOT BE SET
2346	003434	067462	EMT166	
2347	003436	071522	EMT1	
2348	003440	071646	EDT1	
2349	003442	071736	EFT1	
2350				
2351				
2352			:ERROR 167	NEM SHOULD NOT BE SET
2353	003444	067470	EMT167	
2354	003446	071522	EMT1	
2355	003450	071646	EDT1	
2356	003452	071736	EFT1	
2357				
2358				
2359			:ERROR 170	UNUSED

2360	003454	000000	0	
2361	003456	000000	0	
2362	003460	000000	0	
2363	003462	000000	0	
2364				
2365				
2366			:ERROR 171	"ATA" NOT SET DURING RETURN TO CENTERLINE
2367	003464	067506	EMT171	
2368	003466	071522	EHT1	
2369	003470	071646	EDT1	
2370	003472	071736	EFT1	
2371				
2372				
2373			:ERROR 172	"ATA" NOT SET BY OFFSET COMMAND
2374	003474	067516	EMT172	
2375	003476	071522	EHT1	
2376	003500	071646	EDT1	
2377	003502	071736	EFT1	
2378				
2379				
2380			:ERROR 173	RMER2 NOT INITIALIZED BY UNIBUS INIT
2381	003504	067526	EMT173	
2382	003506	071522	EHT1	
2383	003510	071646	EDT1	
2384	003512	071736	EFT1	
2385				
2386				
2387			:ERROR 174	RMER2 NOT INITIALIZED BY CONTROLLER CLEAR
2388	003514	067536	EMT174	
2389	003516	071522	EHT1	
2390	003520	071646	EDT1	
2391	003522	071736	EFT1	
2392				
2393				
2394			:ERROR 175	SELECTED DEVICE IS IN WRITE PROTECT
2395	003524	067550	EMT175	
2396	003526	071522	EHT1	
2397	003530	071646	EDT1	
2398	003532	071736	EFT1	
2399				
2400				
2401			:ERROR 176	CANNOT SET DIAGNOSTIC MODE
2402	003534	067556	EMT176	
2403	003536	071522	EHT1	
2404	003540	071646	EDT1	
2405	003542	071736	EFT1	
2406				
2407				
2408			:ERROR 177	INCORRECT "MOL" STATUS DURING DIAGNOSTIC MODE
2409	003544	067564	EMT177	
2410	003546	071522	EHT1	
2411	003550	071646	EDT1	
2412	003552	071736	EFT1	
2413				
2414				
2415			:ERROR 200	INCORRECT "PIP" STATUS DURING DIAGNOSTIC MODE

2416	003554	067576	EMT200	
2417	003556	071522	EMT1	
2418	003560	071646	EDT1	
2419	003562	071736	EFT1	
2420				
2421				
2422			:ERROR 201	INCORRECT 'WRL' STATUS DURING DIAGNOSTIC MODE
2423	003564	067610	EMT201	
2424	003566	071522	EMT1	
2425	003570	071646	EDT1	
2426	003572	071736	EFT1	
2427				
2428				
2429			:ERROR 202	INCORRECT 'SKI' STATUS DURING DIAGNOSTIC MODE
2430	003574	067622	EMT202	
2431	003576	071522	EMT1	
2432	003600	071646	EDT1	
2433	003602	071736	EFT1	
2434				
2435				
2436			:ERROR 203	INCORRECT 'DVC' STATUS DURING DIAGNOSTIC MODE
2437	003604	067634	EMT203	
2438	003606	071522	EMT1	
2439	003610	071646	EDT1	
2440	003612	071736	EFT1	
2441				
2442				
2443			:ERROR 204	'VV' WAS NOT RESET BY MAINTENANCE UNIT READY
2444	003614	067646	EMT204	
2445	003616	071522	EMT1	
2446	003620	071646	EDT1	
2447	003622	071736	EFT1	
2448				
2449				
2450			:ERROR 205	SELECTED DEVICE HAS A PERSISTENT 'SKI' ERROR
2451	003624	067664	EMT205	
2452	003626	071522	EMT1	
2453	003630	071646	EDT1	
2454	003632	071736	EFT1	
2455				
2456				
2457			:ERROR 206	'LBC' DID NOT SET DURING DIAGNOSTIC MODE
2458	003634	067674	EMT206	
2459	003636	071522	EMT1	
2460	003640	071646	EDT1	
2461	003642	071736	EFT1	
2462				
2463				
2464			:ERROR 207	UNEXPECTED LOSS OF 'MOL' - MEDIUM IS OFF LINE
2465	003644	067704	EMT207	
2466	003646	071522	EMT1	
2467	003650	071646	EDT1	
2468	003652	071736	EFT1	
2469				
2470				
2471			:ERROR 210	UNEXPECTED LOSS OF VOLUME VALID - 'VV' = 0

2472	003654	067716		EMT210	
2473	003656	071522		EMT1	
2474	003660	071646		EDT1	
2475	003662	071736		EFT1	
2476					
2477					
2478			;ERROR	211	UNEXPECTED MECHANICAL MOTION - 'PIP' = 1
2479	003664	067724		EMT211	
2480	003666	071522		EMT1	
2481	003670	071646		EDT1	
2482	003672	071736		EFT1	
2483					
2484					
2485			;ERROR	212	UNEXPECTED DEVICE FAULT - 'DVC' = 1
2486	003674	067740		EMT212	
2487	003676	071522		EMT1	
2488	003700	071646		EDT1	
2489	003702	071736		EFT1	
2490					
2491					
2492			;ERROR	213	UNEXPECTED SEEK INCOMPLETE ERROR - 'SKI' = 1
2493	003704	067754		EMT213	
2494	003706	071522		EMT1	
2495	003710	071646		EDT1	
2496	003712	071736		EFT1	
2497					
2498					
2499			;ERROR	214	DRIVE EXECUTED A RECALIBRATE WITH ERROR SET
2500	003714	067764		EMT214	
2501	003716	071534		EMT2	
2502	003720	071656		EDT2	
2503	003722	071746		EFT2	
2504					
2505					
2506			;ERROR	215	DRIVE DID NOT DETECT 'IVC' ERROR DURING RECALIBRATE
2507	003724	070004		EMT215	
2508	003726	071534		EMT2	
2509	003730	071656		EDT2	
2510	003732	071746		EFT2	
2511					
2512					
2513			;ERROR	216	INCORRECT 'IVC' STATUS
2514	003734	070016		EMT216	
2515	003736	071522		EMT1	
2516	003740	071646		EDT1	
2517	003742	071736		EFT1	
2518					
2519					
2520			;ERROR	217	INCORRECT 'IAE' STATUS
2521	003744	070026		EMT217	
2522	003746	071522		EMT1	
2523	003750	071646		EDT1	
2524	003752	071736		EFT1	
2525					
2526					
2527			;ERROR	220	INCORRECT 'WLE' STATUS

2528	003754	070036		EMT220	
2529	003756	071522		EMT1	
2530	003760	071646		EDT1	
2531	003762	071736		EFT1	
2532					
2533					
2534			;ERROR	221	INCORRECT 'OPI' STATUS
2535	003764	070046		EMT221	
2536	003766	071522		EMT1	
2537	003770	071646		EDT1	
2538	003772	071736		EFT1	
2539					
2540					
2541			;ERROR	222	RM03 DID NOT DETECT RMR ERROR
2542	003774	070056		EMT222	
2543	003776	071522		EMT1	
2544	004000	071646		EDT1	
2545	004002	071736		EFT1	
2546					
2547					
2548			;ERROR	223	RM03 DID NOT DETECT PARITY ERROR ON MASSE IS CONTROL BUS
2549	004004	070066		EMT223	
2550	004006	071560		EMT223	
2551	004010	071672		EDT223	
2552	004012	071762		EFT223	
2553					
2554					
2555			;ERROR	224	UNUSED
2556	004014	000000		0	
2557	004016	000000		0	
2558	004020	000000		0	
2559	004022	000000		0	
2560					
2561					
2562			;ERROR	225	UNUSED
2563	004024	000000		0	
2564	004026	000000		0	
2565	004030	000000		0	
2566	004032	000000		0	
2567					
2568					
2569			;ERROR	226	UNUSED
2570	004034	000000		0	
2571	004036	000000		0	
2572	004040	000000		0	
2573	004042	000000		0	
2574					
2575					
2576			;ERROR	227	UNUSED
2577	004044	000000		0	
2578	004046	000000		0	
2579	004050	000000		0	
2580	004052	000000		0	
2581					
2582					
2583			;ERROR	230	UNUSED

2584	004054	000000	0	
2585	004056	000000	0	
2586	004060	000000	0	
2587	004062	000000	0	
2588				
2589				
2590			;ERROR 231	UNUSED
2591	004064	000000	0	
2592	004066	000000	0	
2593	004070	000000	0	
2594	004072	000000	0	
2595				
2596				
2597			;ERROR 232	UNUSED
2598	004074	000000	0	
2599	004076	000000	0	
2600	004100	000000	0	
2601	004102	000000	0	
2602				
2603				
2604			;ERROR 233	UNUSED
2605	004104	000000	0	
2606	004106	000000	0	
2607	004110	000000	0	
2608	004112	000000	0	
2609				
2610				
2611			;ERROR 234	UNUSED
2612	004114	000000	0	
2613	004116	000000	0	
2614	004120	000000	0	
2615	004122	000000	0	
2616				
2617				
2618			;ERROR 235	UNUSED
2619	004124	000000	0	
2620	004126	000000	0	
2621	004130	000000	0	
2622	004132	000000	0	
2623				
2624				
2625			;ERROR 236	UNUSED
2626	004134	000000	0	
2627	004136	000000	0	
2628	004140	000000	0	
2629	004142	000000	0	
2630				
2631				
2632			;ERROR 237	UNUSED
2633	004144	000000	0	
2634	004146	000000	0	
2635	004150	000000	0	
2636	004152	000000	0	
2637				
2638				
2639			;ERROR 240	UNUSED

2640	004154	000000	0	
2641	004156	000000	0	
2642	004160	000000	0	
2643	004162	000000	0	
2644				
2645				
2646			;ERROR 241	UNUSED
2647	004164	000000	0	
2648	004166	000000	0	
2649	004170	000000	0	
2650	004172	000000	0	
2651				
2652				
2653			;ERROR 242	UNUSED
2654	004174	000000	0	
2655	004176	000000	0	
2656	004200	000000	0	
2657	004202	000000	0	
2658				
2659				
2660			;ERROR 243	UNUSED
2661	004204	000000	0	
2662	004206	000000	0	
2663	004210	000000	0	
2664	004212	000000	0	
2665				
2666				
2667			;ERROR 244	UNUSED
2668	004214	000000	0	
2669	004216	000000	0	
2670	004220	000000	0	
2671	004222	000000	0	
2672				
2673				
2674			;ERROR 245	UNUSED
2675	004224	000000	0	
2676	004226	000000	0	
2677	004230	000000	0	
2678	004232	000000	0	
2679				
2680				
2681			;ERROR 246	'ATA' NOT RESET BY GO WHEN 'ERR' = 0
2682	004234	070142	EMT246	
2683	004236	071522	EHT1	
2684	004240	071646	EDT1	
2685	004242	071736	EFT1	
2686				
2687				
2688			;ERROR 247	'ATA' NOT RESET BY WRITING RMAS
2689	004244	070152	EMT247	
2690	004246	071522	EHT1	
2691	004250	071646	EDT1	
2692	004252	071736	EFT1	
2693				
2694				
2695			;ERROR 250	'ATA' WAS RESET BY GO WHEN 'ERR' = 1

2696	004254	070164		EMT250	
2697	004256	071522		EMT1	
2698	004260	071646		EDT1	
2699	004262	071736		EFT1	
2700					
2701					
2702			:ERROR	251	PROGRAM INTERRUPT WAS NOT GENERATED
2703	004264	070200		EMT251	
2704	004266	071534		EMT2	
2705	004270	071656		EDT2	
2706	004272	071746		EFT2	
2707					
2708					
2709			:ERROR	252	PROGRAM INTERRUPT SHOULD NOT HAVE BEEN GENERATED
2710	004274	070206		EMT252	
2711	004276	071534		EMT2	
2712	004300	071656		EDT2	
2713	004302	071746		EFT2	
2714					
2715					
2716			:ERROR	253	OFFSET MODE WAS NOT RESET BY WRITING RMDC
2717	004304	070214		EMT253	
2718	004306	071522		EMT1	
2719	004310	071646		EDT1	
2720	004312	071736		EFT1	
2721					
2722					
2723			:ERROR	254	INCORRECT "ILF" STATUS
2724	004314	070232		EMT254	
2725	004316	071522		EMT1	
2726	004320	071646		EDT1	
2727	004322	071736		EFT1	
2728					
2729					
2730			:ERROR	255	INCORRECT "ATA" STATUS
2731	004324	070242		EMT255	
2732	004326	071522		EMT1	
2733	004330	071646		EDT1	
2734	004332	071736		EFT1	
2735					
2736					
2737			:ERROR	256	INCORRECT "ILR" STATUS
2738	004334	070252		EMT256	
2739	004336	071572		EMT256	
2740	004340	071672		EDT223	
2741	004342	071762		EFT223	
2742					
2743					
2744			:ERROR	257	INVALID IAE STATUS DURING SEARCH COMMAND
2745	004344	070262		EMT257	
2746	004346	071522		EMT1	
2747	004350	071646		EDT1	
2748	004352	071736		EFT1	
2749					
2750					
2751			:ERROR	260	"IVC" WAS NOT DETECTED DURING SEARCH COMMAND

2752	004354	070274		EMT260	
2753	004356	071522		EMT1	
2754	004360	071646		EDT1	
2755	004362	071736		EFT1	
2756					
2757					
2758			;ERROR	261	DRIVE EXECUTED SEARCH WITH ERROR SET
2759	004364	070306		EMT261	
2760	004366	071522		EMT1	
2761	004370	071646		EDT1	
2762	004372	071736		EFT1	
2763					
2764					
2765			;ERROR	262	"LBC" ERROR NOT SET DURING DIAGNOSTIC MODE
2766	004374	070326		EMT262	
2767	004376	071522		EMT1	
2768	004400	071646		EDT1	
2769	004402	071736		EFT1	
2770					
2771					
2772			;ERROR	263	"SKI" ERROR DURING SEARCH COMMAND
2773	004404	070336		EMT263	
2774	004406	071522		EMT1	
2775	004410	071646		EDT1	
2776	004412	071736		EFT1	
2777					
2778					
2779			;ERROR	264	"IVC" ERROR DURING SEARCH - LOST VOLUME VALID
2780	004414	070346		EMT264	
2781	004416	071522		EMT1	
2782	004420	071646		EDT1	
2783	004422	071736		EFT1	
2784					
2785					
2786			;ERROR	265	ERRONEOUS IVC ERROR DURING SEARCH - VOLUME IS VALID
2787	004424	070366		EMT265	
2788	004426	071522		EMT1	
2789	004430	071646		EDT1	
2790	004432	071736		EFT1	
2791					
2792					
2793			;ERROR	266	DEVICE FAULT (DVC) DURING SEARCH
2794	004434	070406		EMT266	
2795	004436	071522		EMT1	
2796	004440	071646		EDT1	
2797	004442	071736		EFT1	
2798					
2799					
2800			;ERROR	267	SKI SHOULD HAVE BEEN SET BECAUSE CYLINDER ADDRESS IS TOO LARGE
2801			:		
2802	004444	070420		EMT267	
2803	004446	071522		EMT1	
2804	004450	071646		EDT1	
2805	004452	071736		EFT1	
2806					
2807					

2808			:ERROR 270	OPI ERROR DURING SEARCH BECAUSE MOL = 0
2809	004454	070436	EMT270	
2810	004456	071522	EDT1	
2811	004460	071646	EFT1	
2812	004462	071736		
2813				
2814				
2815			:ERROR 271	OPI ERROR DURING SEARCH BECAUSE ON CYLINDER
2816			:	DIDN'T DROP
2817	004464	070452	EMT271	
2818	004466	071522	EDT1	
2819	004470	071646	EFT1	
2820	004472	071736		
2821				
2822				
2823			:ERROR 272	LOST MOL DURING SEARCH, OPI IS NOT SET
2824	004474	070470	EMT272	
2825	004476	071522	EDT1	
2826	004500	071646	EFT1	
2827	004502	071736		
2828				
2829				
2830			:ERROR 273	PIP STIL SET AFTER SEARCH
2831	004504	070506	EMT273	
2832	004506	071522	EDT1	
2833	004510	071646	EFT1	
2834	004512	071736		
2835				
2836				
2837			:ERROR 274	PARITY ERROR OCCURRED WHILE WRITING REMOTE
2838			:	REGISTERS BUT MXF DID NOT SET
2839	004514	070524	EMT274	
2840	004516	071522	EDT1	
2841	004520	071646	EFT1	
2842	004522	071736		
2843				
2844				
2845			:ERROR 275	MXF ERROR - COMPOSITE ERROR OCCURRED BEFORE DATA
2846			:	COMMAND STARTED
2847	004524	070542	EMT275	
2848	004526	071522	EDT1	
2849	004530	071646	EFT1	
2850	004532	071736		
2851				
2852				
2853			:ERROR 276	'OPI' ERROR DURING DATA TRANSFER BECAUSE 'MOL' WAS
2854			:	ZERO
2855	004534	070554	EMT276	
2856	004536	071522	EDT1	
2857	004540	071646	EFT1	
2858	004542	071736		
2859				
2860				
2861			:ERROR 277	'OPI' ERROR DURING DATA TRANSFER BECAUSE 1) ON
2862			:	CYLINDER DIDN'T DROP OR 2) SEARCH TIMED OUT OR
2863			:	3) RUN TIMED OUT

2864	004544	070570	EMT277	
2865	004546	071522	EHT1	
2866	004550	071646	EDT1	
2867	004552	071736	EFT1	
2868				
2869				
2870			;ERROR 300	"IVC" ERROR DURING DATA TRANSFER BECAUSE VOLUME
2871			:	WAS NOT VALID
2872	004554	070606	EMT300	
2873	004556	071522	EHT1	
2874	004560	071646	EDT1	
2875	004562	071736	EFT1	
2876				
2877				
2878			;ERROR 301	ERRONEOUS "IVC" ERROR DURING DATA TRANSFER - VOLUME
2879			:	IS VALID
2880	004564	070626	EMT301	
2881	004566	071522	EHT1	
2882	004570	071646	EDT1	
2883	004572	071736	EFT1	
2884				
2885				
2886			;ERROR 302	"ILR" ERROR DURING DATA TRANSFER
2887	004574	070650	EMT302	
2888	004576	071522	EHT1	
2889	004600	071646	EDT1	
2890	004602	071736	EFT1	
2891				
2892				
2893			;ERROR 303	"ILF" ERROR DURING DATA TRANSFER
2894	004604	070662	EMT303	
2895	004606	071522	EHT1	
2896	004610	071646	EDT1	
2897	004612	071736	EFT1	
2898				
2899				
2900			;ERROR 304	"RMR" ERROR DURING DATA TRANSFER
2901	004614	070674	EMT304	
2902	004616	071522	EHT1	
2903	004620	071646	EDT1	
2904	004622	071736	EFT1	
2905				
2906				
2907			;ERROR 305	INCORRECT "IAE" STATUS DURING DATA TRANSFER
2908	004624	070706	EMT305	
2909	004626	071522	EHT1	
2910	004630	071646	EDT1	
2911	004632	071736	EFT1	
2912				
2913				
2914			;ERROR 306	"SKI" ERROR DURING DATA TRANSFER
2915	004634	070720	EMT306	
2916	004636	071522	EHT1	
2917	004640	071646	EDT1	
2918	004642	071736	EFT1	
2919				

2920				
2921			;ERROR	307 DRIVE DID NOT DETECT SKI ERROR DUE TO CYLINDER
2922	004644	070730		EMT307
2923	004646	071522		EHT1
2924	004650	071646		EDT1
2925	004652	071736		EFT1
2926				
2927				
2928			;ERROR	310 DEVICE FAULT DURING DATA TRANSFER
2929	004654	070750		EMT310
2930	004656	071522		EHT1
2931	004660	071646		EDT1
2932	004662	071736		EFT1
2933				
2934				
2935			;ERROR	311 LOSS OF BIT CLOCK DURING DATA TRANSFER
2936	004664	070762		EMT311
2937	004666	071522		EHT1
2938	004670	071646		EDT1
2939	004672	071736		EFT1
2940				
2941				
2942			;ERROR	312 LOSS OF SYSTEM CLOCK DURING DATA TRANSFER
2943	004674	070774		EMT312
2944	004676	071522		EHT1
2945	004700	071646		EDT1
2946	004702	071736		EFT1
2947				
2948				
2949			;ERROR	313 UNSAFE ERROR DURING DATA TRANSFER (DVC = 0)
2950	004704	071006		EMT313
2951	004706	071522		EHT1
2952	004710	071646		EDT1
2953	004712	071736		EFT1
2954				
2955				
2956			;ERROR	314 DRIVE TIMING ERROR DURING DATA TRANSFER
2957	004714	071026		EMT314
2958	004716	071522		EHT1
2959	004720	071646		EDT1
2960	004722	071736		EFT1
2961				
2962				
2963			;ERROR	315 WRITE LOCK ERROR
2964	004724	071040		EMT315
2965	004726	071522		EHT1
2966	004730	071646		EDT1
2967	004732	071736		EFT1
2968				
2969				
2970			;ERROR	316 ERRONEOUS WRITE LOCK ERROR
2971	004734	071052		EMT316
2972	004736	071522		EHT1
2973	004740	071646		EDT1
2974	004742	071736		EFT1
2975				

2976				
2977			:ERROR	317 HEADER CRC ERROR DURING DATA TRANSFER
2978	004744	071064		EMT317
2979	004746	071522		EHT1
2980	004750	071646		EDT1
2981	004752	071736		EFT1
2982				
2983				
2984			:ERROR	320 FORMAT ERROR DURING DATA TRANSFER
2985	GJ4754	071074		EMT320
2986	004756	071522		EHT1
2987	004760	071646		EDT1
2988	004762	071736		EFT1
2989				
2990				
2991			:ERROR	321 HEADER COMPARE ERROR DURING DATA TRANSFER
2992	004764	071104		EMT321
2993	004766	071522		EHT1
2994	004770	071646		EDT1
2995	004772	071736		EFT1
2996				
2997				
2998			:ERROR	322 HEADER ERRORS SHOULD NOT BE SET
2999	004774	071114		EMT322
3000	004776	071522		EHT1
3001	005000	071646		EDT1
3002	005002	071736		EFT1
3003				
3004				
3005			:ERROR	323 DATA CHECK ERROR DURING DATA TRANSFER
3006	005004	071122		EMT323
3007	005006	071522		EHT1
3008	005010	071646		EDT1
3009	005012	071736		EFT1
3010				
3011				
3012			:ERROR	324 CORRECTABLE DATA CHECK ERROR DURING DATA TRANSFER
3013	005014	071132		EMT324
3014	005016	071522		EHT1
3015	005020	071646		EDT1
3016	005022	071736		EFT1
3017				
3018				
3019			:ERROR	325 UNCORRECTABLE DATA CHECK ERROR DURING DATA TRANSFER
3020	005024	071144		EMT325
3021	005026	071522		EHT1
3022	005030	071646		EDT1
3023	005032	071736		EFT1
3024				
3025				
3026			:ERROR	326 DATA PARITY ERROR DURING READ COMMAND
3027	005034	071156		EMT326
3028	005036	071522		EHT1
3029	005040	071646		EDT1
3030	005042	071736		EFT1
3031				

3032				
3033			:ERROR	327 OFFSET MODE NOT RESET BY WRITE COMMAND
3034	005044	071174		EMT327
3035	005046	071522		EHT1
3036	005050	071646		EDT1
3037	005052	071736		EFT1
3038				
3039				
3040			:ERROR	330 DATA PARITY ERROR DURING WRITE COMMAND
3041	005054	071206		EMT330
3042	005056	071522		EHT1
3043	005060	071646		EDT1
3044	005062	071736		EFT1
3045				
3046				
3047			:ERROR	331 WRITE CLOCK FAILURE DURING WRITE COMMAND
3048	005064	071216		EMT331
3049	005066	071522		EHT1
3050	005070	071646		EDT1
3051	005072	071736		EFT1
3052				
3053				
3054			:ERROR	332 DATA LATE ERROR DURING DATA TRANSFER
3055	005074	071230		EMT332
3056	005076	071522		EHT1
3057	005100	071646		EDT1
3058	005102	071736		EFT1
3059				
3060				
3061			:ERROR	333 PIP STIL SET AFTER DATA TRANSFER - SKI = 0
3062	005104	071242		EMT333
3063	005106	071522		EHT1
3064	005110	071646		EDT1
3065	005112	071736		EFT1
3066				
3067				
3068			:ERROR	334 LOST MOL DURING DATA TRANSFER - OPI = 0
3069	005114	071260		EMT334
3070	005116	071522		EHT1
3071	005120	071646		EDT1
3072	005122	071736		EFT1
3073				
3074				
3075			:ERROR	335 LOST VOLUME VALID DURING DATA TRANSFER - IVC = 0
3076	005124	071276		EMT335
3077	005126	071522		EHT1
3078	005130	071646		EDT1
3079	005132	071736		EFT1
3080				
3081				
3082			:ERROR	336 DATA READ DOES NOT COMPARE WITH DATA WRITTEN
3083	005134	071316		EMT336
3084	005136	071604		EHT336
3085	005140	071702		EDT336
3086	005142	071772		EFT336
3087				

3088				
3089			:ERROR	337 WRITE CHECK ERROR NOT DETECTED
3090	005144	071326		EMT337
3091	005146	071616		EHT337
3092	005150	071712		EDT337
3093	005152	072002		EFT337
3094				
3095				
3096			:ERROR	340 WRITE CHECK ERROR AT UNEXPECTED ADDRESS
3097	005154	071336		EMT340
3098	005156	071604		EHT336
3099	005160	071702		EDT336
3100	005162	071772		EFT336
3101				
3102				
3103			:ERROR	341 INCORRECT DATA DURING WRITE CHECK ERROR
3104	005164	071350		EMT341
3105	005166	071604		EHT336
3106	005170	071702		EDT336
3107	005172	071772		EFT336
3108				
3109				
3110			:ERROR	342 "IVC" ERROR NOT DETECTED DURING DATA TRANSFER
3111	005174	071356		EMT342
3112	005176	071522		EHT1
3113	005200	071646		EDT1
3114	005202	071736		EFT1
3115				
3116				
3117			:ERROR	343 "FER" NOT DETECTED DURING DATA TRANSFER
3118	005204	071370		EMT343
3119	005206	071522		EHT1
3120	005210	071646		EDT1
3121	005212	071736		EFT1
3122				
3123				
3124			:ERROR	344 "HCE" NOT DETECTED DURING DATA TRANSFER
3125	005214	071402		EMT344
3126	005216	071630		EHT344
3127	005220	071722		EDT344
3128	005222	072012		EFT344
3129				
3130				
3131			:ERROR	345 "BSE" NOT DETECTED DURING DATA TRANSFER
3132	005224	071414		EMT345
3133	005226	071522		EHT1
3134	005230	071646		EDT1
3135	005232	071736		EFT1
3136				
3137				
3138			:ERROR	346 HEADER ERROR WAS DETECTED W/ HCI SET
3139	005234	071424		EMT346
3140	005236	071522		EHT1
3141	005240	071646		EDT1
3142	005242	071736		EFT1
3143				

```

3144
3145      ;ERROR 347      DATA TRANSFER NOT ABORTED W/ COMP ERROR SET
3146      005244      071440      EMT347
3147      005246      071522      EHT1
3148      005250      071646      EDT1
3149      005252      071736      EFT1
3150
3151
3152      ;ERROR 350      LOST VOLUME VALID DURING SEARCH - "IVC" = 0
3153      005254      071452      EMT350
3154      005256      071522      EHT1
3155      005260      071646      EDT1
3156      005262      071736      EFT1
3157
3158
3159      ;ERROR 351      "ATA" DID NOT SET DURING SEARCH
3160      005264      071470      EMT351
3161      005266      071522      EHT1
3162      005270      071646      EDT1
3163      005272      071736      EFT1
3164
3165
3166      ;ERROR 352      PROGRAM TIMEOUT WHILE TESTING RMLA
3167      005274      071500      EMT352
3168      005276      000000      0
3169      005300      000000      0
3170      005302      000000      0
3171
3172
3173      ;ERROR 353      LOOK AHEAD TEST FAILS
3174      005304      071504      EMT353
3175      005306      071642      EHT353
3176      005310      071734      EDT353
3177      005312      072022      EFT353
3178
3179
3180      ;ERROR 354      BSE SHOULD NOT BE SET
3181      005314      071514      EMT354
3182      005316      071522      EHT1
3183      005320      071646      EDT1
3184      005322      071736      EFT1
3185
3186
3187      ;PUT ERROR TABLE HERE
3188      ;SBTTL ERROR TABLE USAGE
3189
3190      ;THE ERROR TABLE ABOVE CONSISTS OF FOUR WORD ENTRIES FOR EACH ERROR
3191      ;NUMBER, I.E.,
3192      :
3193      :      EMT - ERROR MESSAGE TABLE ADDRESS
3194      :      EHT - ERROR HEADER TABLE ADDRESS
3195      :      EDT - ERROR DATA TABLE ADDRESS
3196      :      EFT - ERROR FORMAT TABLE ADDRESS
3197      :
3198      ;THE EMT ENTRY IS THE ADDRESS OF THE TABLE OF ERROR MESSAGE STRINGS
3199      ;FOR THE PARTICULAR ERROR. EACH ERROR MESSAGE TABLE LISTS THE ADDRESS

```

3200 :OF ONE OR MORE ERROR MESSAGE STRINGS WHICH ARE TO BE FORMATTED AND
3201 :TYPED BY THE ERROR TYPE SUBROUTINE. IF THE EMT ENTRY IS ZERO, THERE IS
3202 :NO MESSAGE TO BE TYPED FOR THE ERROR.
3203 :
3204 :SIMILARLY, THE EHT, EDT, AND EFT ENTRIES ARE ADDRESSES OF TABLES
3205 :OF HEADER, DATA AND FORMAT INFORMATION FOR A GIVEN ERROR. EACH ENTRY
3206 :IN THE ERROR HEADER TABLE MAY OR MAY NOT HAVE AN ASSOCIATED LINE OF
3207 :DATA, HOWEVER, EACH DATA LINE MUST HAVE AN ASSOCIATED FORMAT AND
3208 :HEADER. THAT IS, A HEADER LINE MAY BE PRINTED WITHOUT ANY DATA,
3209 :BUT A DATA LINE IS NOT PRINTED WITHOUT A HEADER, AND EACH DATA LINE
3210 :MUST ALSO HAVE A FORMAT.
3211 :
3212 :IN SUMMARY,
3213 :
3214 :EACH NONZERO ENTRY IS THE ADDRESS OF A TABLE.
3215 :EACH TABLE IS A LIST OF ADDRESSES WHICH DEFINES THE LOCATIONS
3216 :OF MESSAGE STRINGS, HEADERS, DATA OR FORMAT.
3217 :
3218 :


```
3219 .SBTTL START OF PROGRAM
3220
3221
3222 005324 START:
3223
3224 ;CLEAR AND SETUP FOR TEST EXECUTION
3225 005324 000240 NOP
3226 005326 000005 RESET ;INITIALIZE THE SYSTEM
3227 005330 013746 000300 MOV PR6,-(SP) ;PUT NEW PS ON STACK
3228 005334 012746 005342 MOV #64$,-(SP) ;PUT NEW PC ON STACK
3229 005340 000002 RTI ;POP NEW PC AND PS
3230 005342
3231
3232 .SBTTL INITIALIZE THE COMMON TAGS
3233 ;:CLEAR THE COMMON TAGS ($CMTAG) AREA
3234 005342 012706 001114 MOV #CMTAG,R6 ;:FIRST LOCATION TO BE CLEARED
3235 005346 005026 CLR (R6)+ ;:CLEAR MEMORY LOCATION
3236 005350 022706 001154 CMP #SWR,R6 ;:DONE?
3237 005354 001374 BNE .-6 ;:LOOP BACK IF NO
3238 005356 012706 001100 MOV #STACK,SP ;:SETUP THE STACK POINTER
3239 ;:INITIALIZE A FEW VECTORS
3240 005362 012737 060556 000020 MOV #SCOPE,@IOTVEC ;:IOT VECTOR FOR SCOPE ROUTINE
3241 005370 012737 000340 000022 MOV #340,@IOTVEC+2 ;:LEVEL 7
3242 005376 012737 061166 000030 MOV #ERROR,@EMTVEC ;:EMT VECTOR FOR ERROR ROUTINE
3243 005404 012737 000340 000032 MOV #340,@EMTVEC+2 ;:LEVEL 7
3244 005412 012737 062726 000034 MOV #TRAP,@TRAPVEC ;:TRAP VECTOR FOR TRAP CALLS
3245 005420 012737 000340 000036 MOV #340,@TRAPVEC+2 ;:LEVEL 7
3246 005426 012737 063034 000024 MOV #SPWRDN,@PWRVEC ;:POWER FAILURE VECTOR
3247 005434 012737 000340 000026 MOV #340,@PWRVEC+2 ;:LEVEL 7
3248 005442 013737 033022 033014 MOV $ENDCT,$EOPCT ;:SETUP END-OF-PROGRAM COUNTER
3249 005450 005037 001206 CLR $TIMES ;:INITIALIZE NUMBER OF ITERATIONS
3250 005454 005037 001210 CLR $ESCAPE ;:CLEAR THE ESCAPE ON ERROR ADDRESS
3251 005460 112737 000001 001131 MOVB #1,$ERMAX ;:ALLOW ONE ERROR PER TEST
3252 005466 012737 005466 001122 MOV #.,$LPADR ;:INITIALIZE THE LOOP ADDRESS FOR SCOPE
3253 005474 012737 005474 001124 MOV #.,$LPERR ;:SETUP THE ERROR LOOP ADDRESS
3254 ;:SIZE FOR A HARDWARE SWITCH REGISTER. IF NOT FOUND OR IT IS
3255 ;:EQUAL TO A "-1", SETUP FOR A SOFTWARE SWITCH REGISTER.
3256 005502 015746 000004 MOV @ERRVEC,-(SP) ;:SAVE ERROR VECTOR
3257 005506 012737 005542 000004 MOV #65$,@ERRVEC ;:SET UP ERROR VECTOR
3258 005514 012737 177570 001154 MOV #DSWR,$WR ;:SETUP FOR A HARDWARE SWICH REGISTER
3259 005522 012737 177570 001156 MOV #DDISP,DISPLAY ;:AND A HARDWARE DISPLAY REGISTER
3260 005530 022777 177777 173416 CMP #-1,@SWR ;:TRY TO REFERENCE HARDWARE SWR
3261 005536 001012 BNE 67$ ;:BRANCH IF NO TIMEOUT TRAP OCCURRED
3262 ;:AND THE HARDWARE SWR IS NOT = -1
3263 005540 000403 BR 66$ ;:BRANCH IF NO TIMEOUT
3264 005542 012716 005550 65$: MOV #66$, (SP) ;:SET UP FOR TRAP RETURN
3265 005546 000002 RTI
3266 005550 012737 000176 001154 66$: MOV #SWREG,SWR ;:POINT TO SOFTWARE SWR
3267 005556 012737 000174 001156 MOV #DISPREG,DISPLAY
3268 005564 012637 000004 67$: MOV (SP)+,@ERRVEC ;:RESTORE ERROR VECTOR
3269
3270 005570 005037 001230 CLR $PASS ;:CLEAR PASS COUNT
3271 005574 132737 000200 001243 BITB #APTSIZE,$ENVM ;:TEST USER SIZE UNDER APT
3272 005602 001403 BEQ 68$ ;:YES,USE NON-APT SWITCH
3273 005604 012737 001244 001154 , MOV #SSWREG,SWR ;:NO,USE APT SWITCH REGISTER
3274 005612 68$:
```

```
3275 .SBTTL TYPE PROGRAM NAME
3276 ;;TYPE THE NAME OF THE PROGRAM IF FIRST PASS
3277 005612 005227 177777 INC #1 ;;FIRST TIME?
3278 005616 001061 BNE 69$ ;;BRANCH IF NO
3279 005620 022737 033156 000042 CMP #SENDAD,@#42 ;;ACT-11?
3280 005626 001455 BEQ 69$ ;;BRANCH IF YES
3281 005630 104401 005676 TYPE ,70$ ;;TYPE ASCII STRING
3282 .SBTTL GET VALUE FOR SOFTWARE SWITCH REGISTER
3283 005634 005737 000042 TST @#42 ;;ARE WE RUNNING UNDER XXDP/ACT?
3284 005640 001012 BNE 71$ ;;BRANCH IF YES
3285 005642 123727 001242 000001 CMPB $ENV,#1 ;;ARE WE RUNNING UNDER APT?
3286 005650 001406 BEQ 71$ ;;BRANCH IF YES
3287 005652 023727 001154 000176 CMP SWR,#SWREG ;;SOFTWARE SWITCH REG SELECTED?
3288 005660 001005 BNE 72$ ;;BRANCH IF NO
3289 005662 104407 GTSWR ;;GET SOFT-SWR SETTINGS
3290 005664 000403 BR 72$
3291 005666 112737 000001 001150 71$: MOVB #1,$AUTOB ;;SET AUTO-MODE INDICATOR
3292 005674 72$:
3293 005674 000432 BR 69$ ;;GET OVER THE ASCII
3294 ;;70$: .ASCII <CRLF>@CZRMDB - RM03/RM02 SUBSYS FUNCTIONAL TEST,PART 2 @<CRLF>
3295 005762 69$:
3296
3297
3298 ;FIND OUT IF PROGRAM IS RUNNING IN STANDALONE MODE
3299 005762 122737 000077 000041 CMPB #77,@#41 ;LOAD FROM XXDP MEDIM ?
3300 005770 001003 BNE 5$ ;BRANCH IF NOT
3301 005772 104401 064560 TYPE ,XDPMG ;TYPE THE MESSAGE
3302 005776 000000 HALT
3303 006000 5$:
3304 006000 005737 000042 TST 42 ;IS LOC 42 ZERO ??
3305 006004 001003 BNE 10$ ;NO - NOT IN STANDALONE
3306 006006 105737 001242 TSTB $ENV ;IS APT ENVIRONMENT ZERO ??
3307 006012 001454 BEQ STANDALONE ;YES - PROGRAM IN STANDALONE
3308 006014 10$:
3309
3310 ;PROGRAM NOT RUNNING IN STANDALONE - SEE IF SIZING IS ALLOWED
3311 006014 132737 000200 001243 XSIZ: BITB #BIT7,$ENVM ;SIZING ALLOWED ??
3312 006022 001046 BNE 20$ ;NO
3313 006024 012737 000377 001300 MOV #377,$DEVH ;YES - SET DEVICE MAP FOR ALL DEVICES
3314 006032 005037 001300 CLR $DEVH ;CLEAR THE BIT MAP
3315 006036 005001 CLR R1 ;START FROM THE DRIVE 0
3316 006040 012704 000001 MOV #BIT0,R4 ;BIT MAP
3317 006044 013700 001276 MOV $BASE,R0 ;LOAD BASE ADDRESS
3318 006050 012760 000040 000010 15$: MOV #CLR,RMCS2(R0) ;MASS BUS CLEAR
3319 006056 010160 000010 MOV R1,RMCS2(R0) ;LOAD THE DRIVE ADDRESS
3320 006062 016003 000010 MOV RMCS2(R0),R3 ;READ DRIVE STATUS TO SEE NED BIT
3321 006066 032703 010000 BIT #NED,R3 ;NED BIT SET ?
3322 006072 001010 BNE 16$ ;BRANCH IF SO
3323 006074 016003 000000 MOV RMCS1(R0),R3 ;CHECK THE DVA BIT
3324 006100 032703 004000 BIT #DVA,R3 ;DRIVE AVAILABLE ?
3325 006104 001403 BEQ 16$ ;BRANCH IF NOT
3326 006106 050437 001300 BIS R4,$DEVH ;SET THE BIT MAP
3327 006112 000405 BR 17$ ;NOT TYPE THE NONE-EXIST MSG
3328 006114 16$:
3329 006114 104401 064645 TYPE ,NOTEX ;NOT EXIST DRIVE
3330 006120 010146 MOV R1,-(SP) ;DRIVE NUMBER
```


3331	006122	104403			
3332	006124	006			
3333	006125	000			
3334	006126	005201	17\$:	INC R1	; INCREMENT THE DRIVE ADDRESS
3335	006130	006304		ASL R4	; SET UP BIT MAP
3336	006132	022701		CMP #7,R1	; ALL DRIVE CHECKED ?
3337	006136	103344		BHIS 15\$	; BRANCH IF NOT
3338	006140		20\$:		
3339					
3340					
3341	006140	000137	006772	; GO TO COMMON START CODE	
				JMP CMNSTART	

```
3342 006144
3343 006144 004737 061376
3344
3345
3346 006150 005327 000001
3347 006154 100024
3348
3349
3350
3351 006156 104401 064067
3352 006162 104411
3353 006164 012637 001176
3354 006170 104401 001176
3355 006174 123727 001176 000131
3356 006202 001002
3357 006204 000137 007124
3358 006210 123727 001176 000116
3359 006216 001420
3360 006220 104401 063577
3361 006224 000754
3362 006226
3363
3364
3365 006226 104401 063601
3366 006232 104411
3367 006234 012637 001176
3368 006240 104401 001176
3369 006244 123727 001176 000131
3370 006252 001002
3371 006254 104401 103564
3372 006260
3373
3374
3375 006260 104401 063770
3376 006264 104411
3377 006266 012637 001176
3378 006272 104401 001176
3379 006276 104411
3380 006300 005726
3381 006302 123727 001176 000131
3382 006310 001137
3383 006312
3384
3385
3386 006312 104401 064126
3387 006316 013746 001276
3388 006322 104402
3389 006324 104401 063570
3390 006330 104413
3391 006332 012637 001176
3392 006336 001412
3393 006340 022737 160000 001176
3394 006346 101403
3395 006350 104401 064153
3396 006354 000756
3397 006356 013737 001176 001276

STANDALONE:
JSR PC,$TKINT ;INITIALIZE CONSOLE

;SEE IF THIS IS THE FIRST START AFTER PROGRAM WAS LOADED
DEC #1 ;FIRST START ??
BPL 10$ ;YES !!

;SEE IF THE USER WANTS TO KEEP SAME DEVICES FOR TESTING
5$: TYPE ,CNSLOO ;MAINTAIN PREVIOUS PARAMETERS??
RDCHR ;GET RESPONSE
MOV (SP)+,$TMP1 ;ECHO RESPONSE
TYPE , $TMP1
CMPB $TMP1,#'Y ;YES RESPONSE??
BNE 6$ ;NO!!
JMP READY ;KEEP PREVIOUS PARAMETERS
6$: CMPB $TMP1,#'N ;NO RESPONSE??
BEQ 20$ ;GET NEW PARAMETERS
TYPE ,QSTMWK ;NOT YES OR NO, TYPE '?'
BR 5$ ;RETRY

10$:

;SEE IF OPERATOR WANTS HELP FILE
TYPE ,HELPOST ;WANT HELP ??
RDCHR ;GET RESPONSE
MOV (SP)+,$TMP1 ;SAVE AND ECHO RESPONSE
TYPE , $TMP1
CMPB $TMP1,#'Y ;WAS IT A YES RESPONSE ??
BNE 20$ ;NO - DONT TYPE HELP
TYPE ,HELP ;YES - TYPE HELP TEXT

20$:

;SEE IF USER WANTS TO CHANGE RM03 UNIBUS ADDRESS
TYPE ,UBUSQST ;WANT TO CHANGE ADDRESS ??
RDCHR ;GET RESPONSE
MOV (SP)+,$TMP1 ;SAVE AND ECHO RESPONSE
TYPE , $TMP1
RDCHR ;READ ONE MORE CHARACTER
TST (SP)+ ;CLEAR OFF THE STACK
CMPB $TMP1,#'Y ;WAS IT A YES RESPONSE ??
BNE 30$ ;NO !!

30$:

;DIALOGUE TO CHANGE THE UNIBUS ADDRESS, AND INTERRUPT VECTOR
TYPE ,CNSLO1 ;TYPE CURRENT BUS ADDRESS
MOV $BASE,-(SP) ;;SAVE $BASE FOR TYPEOUT
TYPOC ;;GO TYPE--OCTAL ASCII(ALL DIGITS)
TYPE ,CLSPRN
RDOCT ;GET NEW BUS ADDRESS
MOV (SP)+,$TMP1 ;CARRIAGE RETURN??
BEQ 50$ ;YES-SKIP TO NEXT ENTRY
CMP #160000,$TMP1 ;BASE ADDRESS IN I/O PAGE??
BLOS 40$ ;YES
TYPE ,CNSLO2 ;TYPE WARNING MESSAGE
BR 30$ ;RETRY
MOV $TMP1,$BASE ;STORE NEW BUS ADDRESS

40$:
```

3398 006364 113737 001272 001176 50\$: MOV \$VECT1,\$TMP1 ;TYPE CURRENT VECTOR ADDRESS
3399 006372 105037 001177 CLRB \$TMP1+1
3400 006376 104401 064234 TYPE ,CNSLO3
3401 006402 013746 001176 MOV \$TMP1,-(SP) ;;SAVE \$TMP1 FOR TYPEOUT
3402 006406 104403 TYPOS ;;GO TYPE--OCTAL ASCII
3403 006410 003 .BYTE 3 ;;TYPE 3 DIGIT(S)
3404 006411 000 .BYTE 0 ;;SUPPRESS LEADING ZEROS
3405 006412 104401 063570 TYPE ,CLSPRN
3406 006416 104413 RDOCT ;GET NEW VECTOR ADDRESS
3407 006420 012637 001176 MOV (SP)+,\$TMP1 ;CARRIAGE RETURN?
3408 006424 001412 BEQ 70\$;YES-SKIP TO NEXT ENTRY
3409 006426 022737 001000 001176 CMP #1000,\$TMP1 ;VECTOR ADDRESS < 1000??
3410 006434 101003 BHI 60\$;YES!!
3411 006436 104401 064264 TYPE ,CNSLO4 ;TYPE WARNING MESSAGE
3412 006442 000750 BR 50\$;RETRY
3413 006444 113737 001176 001272 60\$: MOV \$TMP1,\$VECT1 ;STORE NEW VECTOR ADDRESS
3414 006452 113737 001173 001176 70\$: MOV \$VECT1+1,\$TMP1 ;TYPE CURRENT PRIORITY
3415 006460 006237 001176 ASR \$TMP1
3416 006464 006237 001176 ASR \$TMP1
3417 006470 006237 001176 ASR \$TMP1
3418 006474 006237 001176 ASR \$TMP1
3419 006500 006237 001176 ASR \$TMP1
3420 006504 105037 001177 CLRB \$TMP1+1
3421 006510 104401 064340 TYPE ,CNSLO5
3422 006514 013746 001176 MOV \$TMP1,-(SP) ;;SAVE \$TMP1 FOR TYPEOUT
3423 006520 104403 TYPOS ;;GO TYPE--OCTAL ASCII
3424 006522 001 .BYTE 1 ;;TYPE 1 DIGIT(S)
3425 006523 000 .BYTE 0 ;;SUPPRESS LEADING ZEROS
3426 006524 104401 063570 TYPE ,CLSPRN
3427 006530 104413 RDOCT ;GET NEW PRIORITY
3428 006532 012637 001176 MOV (SP)+,\$TMP1 ;CARRIAGE RETURN??
3429 006536 001424 BEQ 90\$;YES-SKIP TO NEXT ENTRY
3430 006540 023727 001176 000007 CMP \$TMP1,#7 ;LEGAL PRIORITY??
3431 006546 002403 BLT 80\$;YES!!
3432 006550 104401 064374 TYPE ,CNSLO6 ;TYPE WARNING MESSAGE
3433 006554 000736 BR 70\$;RETRY
3434 006556 80\$: ;STORE NEW PRIORITY
3435 006556 006337 001176 ASL \$TMP1
3436 006562 006337 001176 ASL \$TMP1
3437 006566 006337 001176 ASL \$TMP1
3438 006572 006337 001176 ASL \$TMP1
3439 006576 006337 001176 ASL \$TMP1
3440 006602 113737 001176 001273 MOV \$TMP1,\$VECT1+1
3441 006610 90\$:
3442
3443 ;DIALOGUE TO INPUT DEVICE NUMBERS
3444 006610 005037 001300 CLR \$DEVN ;CLEAR DEVICE MAP
3445 006614 104401 064421 TYPE ,CNSLO7 ;TYPE INPUT INSTRUCTIONS
3446 006620 104401 063573 TYPE ,PROMPT ;TYPE PROMPTING CHARACTER
3447 006624 104411 RDCHR ;GET RESPONSE
3448 006626 012637 001176 MOV (SP)+,\$TMP1 ;ECHO RESPONSE
3449 006632 104401 001176 TYPE , \$TMP1
3450 006636 023727 001176 000101 CMP \$TMP1,#'A ;TEST ALL DRIVES??
3451 006644 001021 BNE 110\$;NO
3452 006646 000137 006014 JMP XSIZ ;AUTO SIZE
3453 006652 012737 000377 001300 MOV #377,\$DEVN ;TEST ALL DEVICES

CZRMDCO RM03/2 FCTNL TST 2
CZRMDC.P11 12-DEC-78 08:24

MACY11 30A(1052) 04-JAN-79 11:23 PAGE 75
GET VALUE FOR SOFTWARE SWITCH REGISTER

SEQ 0075

```
3454 006660 000444  
3455 006662 104401 063573 100$: BR 140$ ;SKIP TO NEXT ENTRY  
3456 006666 104411 ;TYPE ,PROMPT ;TYPE PROMPTING CHARACTER  
3457 006670 012637 001176 RDCHR ;GET RESPONSE  
3458 006674 104401 001176 MOV (SP)+,$TMP1 ;ECHO RESPONSE  
3459 006700 023727 001176 000015 TYPE $TMP1 ;CARRIAGE RETURN??  
3460 006706 001431 BEQ 140$  
3461 006710 023727 001176 000060 110$: CMP $TMP1,#'0 ;NUMBER < 0??  
3462 006716 002404 BLT 120$ ;YES!!  
3463 006720 023727 001176 000067 CMP $TMP1,#'7 ;NUMBER > 7??  
3464 006726 003403 BLE 130$ ;NO!!  
3465 006730 104401 063577 120$: TYPE ,QSTMRK ;TYPE '?'  
3466 006734 000752 BR 100$ ;RETRY  
3467 006736 013701 001176 130$: MOV $TMP1,R1 ;R1=DRIVE NUMBER  
3468 006742 042701 177770 BIC #'C7,R1  
3469 006746 116102 064772 MOVB ATNTBL(R1),R2 ;DECODE DEVICE NUMBER  
3470 006752 042702 177400 BIC #'C377,R2 ;CLEAR UNUSED BITS  
3471 006756 050237 001300 BIS R2,$DEVM ;SET DEVICE # IN MAP  
3472 006762 122737 000377 001300 CMPB #'377,$DEVM ;DONE ??  
3473 006770 101334 BHI 100$ ;NO  
3474 006772 140$:  
3475
```

```

3476 006772 CMNSTART:
3477
3478 ;ASSEMBLE TEST QUE FROM DEVICE MAP
3479 006772 013700 001300      MOV      $DEVN,R0      ;R0 = DEVICE MAP
3480 006776 012701 001452      MOV      #TSTQUE+2,R1    ;R1 = ADDRESS OF FIRST ENTRY IN QUE
3481 007002 010137 001450      MOV      R1,TSTQUE      ;INITIALIZE ENTRY POINTER
3482 007006 012702 000001      MOV      #1,R2        ;R2 = DEVICE POINTER
3483 007012 005003              CLR      R3          ;R3 = DEVICE NUMBER
3484 007014 030200      10$:    BIT      R2,R0        ;IS THIS DEVICE IN MAP ??
3485 007016 001406              BEQ      20$          ;NO !!
3486 007020 010311              MOV      R3,(R1)       ;YES - ENTER DEVICE NUMBER IN QUE
3487 007022 116361 064772 000001  MOVB    ATNTBL(R3),1(R1) ;ENTER ATTENTION BIT IN QUE
3488 007030 062701 000002      ADD      #2,R1        ;ADVANCE ENTRY POINTER
3489 007034 006302      20$:    ASL      R2          ;ADVANCE DEVICE POINTER
3490 007036 105702      TSTB     R2          ;DONE ALL DEVICES ??
3491 007040 001402      BEQ      25$          ;YES
3492 007042 005203      INC      R3          ;ADVANCE DEVICE NUMBER
3493 007044 000763      BR       10$          ;ENTER NEXT DEVICE
3494 007046 005011      25$:    CLR      (R1)        ;TERMINATE TEST QUE
3495
3496 ;SIZE FOR CLOCK
3497 007050 004737 040204      JSR      PC,SIZCLK      ;SEE IF CLOCK PRESENT
3498 007054 000403      BR       40$          ;YES - CLOCK IS PRESENT
3499 007056 104000      30$:    ERROR    ;NO CLOCK
3500 007060 000000      HALT
3501 007062 000775      BR       30$
3502 007064
3503 .SBTTL GET VALUE FOR SOFTWARE SWITCH REGISTER
3504 007064 005737 000642      TST      @#42        ;;ARE WE RUNNING UNDER XXDP/ACT?
3505 007070 001012      BNE      64$          ;;BRANCH IF YES
3506 007072 123727 001242 000001  CMPB    $ENV,#1        ;;ARE WE RUNNING UNDER APT?
3507 007100 001406      BEQ      64$          ;;BRANCH IF YES
3508 007102 023727 001154 000176  CMP      SWR,#SWREG    ;;SOFTWARE SWITCH REG SELECTED?
3509 007110 001005      BNE      65$          ;;BRANCH IF NO
3510 007112 104407      GTSWR              ;;GET SOFT-SWR SETTINGS
3511 007114 000403      BR       65$
3512 007116 112737 000001 001150  64$:    MOVB    #1,$AUTOB    ;;SET AUTO-MODE INDICATOR
3513 007124      65$:
3514 007124 000240      READY:  NOP              ;READY TO START TEST
3515 007126 005037 001326      CLR      CTLFG        ;CLEAR THE CONTROL-C FLAG
3516 007132 004737 061376      JSR      PC,$TKINT    ;INITIALIZE TTY
3517 007136 013746 000300      MOV      PR6,-(SP)    ;;PUT NEW PS ON STACK
3518 007142 012746 007150      MOV      #64$,-(SP)    ;;PUT NEW PC ON STACK
3519 007146 000002      RTI              ;;POP NEW PC AND PS
3520 007150
3521 007150 117737 172274 001234  64$:    MOVB    @TSTQUE,$UNIT ;LOAD UNIT NUMBER
3522 007156 005037 001474      CLR      MEDENB      ;CLEAR MEDIA ENABLE

```

```
3523 .....
3524 :*TEST 1 CONTROLLER ACCESS TEST
3525 .....
3526 TST1:
3527 007162 000240 NOP ;START OF TEST
3528 007164 012737 007200 001122 MOV #1$,SLPADR
3529 007172 012737 007200 001124 MOV #1$,SLPERR
3530 007200 1$:
3531 007200 012706 001100 MOV #STACK,SP ;INITIALIZE STACK POINTER
3532 007204 013700 001276 MOV $BASE,R0 ;R0=UNIBUS ADDRESS
3533 007210 013701 001450 MOV TSTQUE,R1 ;(R1) = DEVICE BEING TESTED
3534 007214 012737 000001 001226 MOV #1,$TESTN ;SET TEST NUMBER IN APT MAIL BOX
3535 007222 005001 CLR R1
3536 007224 013746 000004 MOV ERRVEC,-(SP) ;PUSH ERRVEC ON STACK
3537 007230 013746 000006 MOV ERRVEC+2,-(SP) ;PUSH ERRVEC+2 ON STACK
3538 007234 012737 007326 000004 MOV #3$,ERRVEC
3539 007242 012737 000300 000006 MOV #PR6,ERRVEC+2
3540
3541 007250 110160 000001 MOV B R1,RMCS1+1(R0) ;MOVE HI BYTE TO RMCS1
3542 007254 010160 000002 MOV R1,RMWC(R0) ;MOVE WORD COUNT REGISTER
3543 007260 016002 000002 MOV RMWC(R0),R2
3544 007264 010160 000004 MOV R1,RMBA(R0) ;MOVE BUS ADDRESS REGISTER
3545 007270 016002 000004 MOV RMBA(R0),R2
3546 007274 010160 000010 MOV R1,RMCS2(R0) ;MOVE CONTROL STATUS REGISTER
3547 007300 016002 000010 MOV RMCS2(R0),R2
3548 007304 010160 000022 MOV R1,RMDB(R0) ;MOVE DATA BUFFER
3549 007310 016002 000022 MOV RMDB(R0),R2
3550 007314 012637 000006 MOV (SP)+,ERRVEC+2 ;POP STACK INTO ERRVEC+2
3551 007320 012637 000004 MOV (SP)+,ERRVEC ;POP STACK INTO ERRVEC
3552 007324 000415 BR 7$ ;NO BUS TIMEOUT OCCURRED
3553
3554 007326 022626 3$: CMP (SP)+,(SP)+ ;ADJUST STACK
3555 007330 012637 000006 MOV (SP)+,ERRVEC+2 ;POP STACK INTO ERRVEC+2
3556 007334 012637 000004 MOV (SP)+,ERRVEC ;POP STACK INTO ERRVEC
3557 007340 104110 ERROR 110 ;CANNOT ACCESS MASSBUS CONTROLLER
3558 007342 005737 000042 TST 42 ;STAND ALONE MODE??
3559 007346 001002 BNE 5$ ;NO!!
3560 007350 000137 005324 JMP START ;YES-GO GET $BASE
3561 007354 000137 032766 5$: JMP $EOP ;GO TO END OF PASS HANDLER
3562 007360 7$:
3563
3564 .....
3565 :*TEST 2 DEVICE AVAILABLE TEST
3566 .....
3567 TST2:
3568 007360 SCOPE ;SCOPE CALL
3569 007360 000004 NOP ;START OF TEST
3570 007362 000240 MOV #STACK,SP ;INITIALIZE STACK POINTER
3571 007364 012706 001100 MOV $BASE,R0 ;R0=UNIBUS ADDRESS
3572 007370 013700 001276 MOV TSTQUE,R1 ;(R1) = DEVICE BEING TESTED
3573 007374 013701 001450 MOV #2,$TESTN ;SET TEST NUMBER IN APT MAIL BOX
3574 007400 012737 000002 001226
3575
3576 007406 004737 046660 JSR PC,CNTCLR
3577 007412 000404 BR 2$ ;GO TO 2$ IF NO ERROR
3578 007414 000240 NOP ;RETURN HERE IF ERROR
```



```

3579 007416 104000          ERROR          ;ERROR NUMBER DEFINED BY SUB
3580 007420 000137 007540    2$:      JMP      7$          ;GO TO 7$ IF ERROR WAS FOUND
3581 007424                MOV      ERRVEC, -(SP)      ;:PUSH ERRVEC ON STACK
3582 007424 013746 000004    MOV      ERRVEC+2, -(SP)    ;:PUSH ERRVEC+2 ON STACK
3583 007430 013746 000006    MOV      #5$,ERRVEC
3584 007434 012737 007524 000004    MOV      PR6,ERRVEC+2
3585 007442 013737 000300 000006    MOV      RMCS1(R0),STMP1 ;GET DVA STATUS
3586                                MOV      RMCS2(R0),STMP0 ;GET NED STATUS
3587 007450 016037 000000 001176    MOV      (SP)+,ERRVEC+2      ;:POP STACK INTO ERRVEC+2
3588 007456 016037 000010 001174    MOV      (SP)+,ERRVEC      ;:POP STACK INTO ERRVEC
3589 007464 012637 000006    BIT      #NED,STMP0      ;NONEXISTENT DEVICE??
3590 007470 012637 000004    BEQ      3$          ;NO!!
3591 007474 032737 010000 001174    ERROR    111      ;NONEXISTENT DEVICE
3592 007502 001402          BR      7$
3593 007504 104111          BIT      #DVA,STMP1      ;DEVICE AVAILABLE??
3594 007506 000414          BNE      9$          ;YES!!
3595 007510 032737 004000 001176 3$:      ERROR    112      ;DEVICE NOT AVAILABLE
3596 007516 001012          BR      7$
3597 007520 104112
3598 007522 000406
3599
3600 007524 022626          5$:      CMP      (SP)+,(SP)+      ;ADJUST STACK
3601 007526 012637 000006    MOV      (SP)+,ERRVEC+2      ;:POP STACK INTO ERRVEC+2
3602 007532 012637 000004    MOV      (SP)+,ERRVEC      ;:POP STACK INTO ERRVEC
3603 007536 104113          ERROR    113      ;BUS TIMEOUT (04 TRAP)
3604 007540 000137 032732    7$:      JMP      $EOSP
3605
3606 007544          9$:
3607
3608          ;*****
3609          ;*TEST 3      DRIVE TYPE TEST
3610          ;*****
3611          ;*****
3612          TST3:
3613 007544 000004          SCOPE          ;SCOPE CALL
3614 007546 000240          NOP          ;START OF TEST
3615 007550 012706 001100    MOV      #STACK,SP      ;INITIALIZE STACK POINTER
3616 007554 013700 001276    MOV      $BASE,R0      ;R0=UNIBUS ADDRESS
3617 007560 013701 001450    MOV      TSTQUE,R1      ;(R1) = DEVICE BEING TESTED
3618 007564 012737 000003 001226    MOV      #3,$TESTN      ;:SET TEST NUMBER IN APT MAIL BOX
3619
3620 007572 004737 046660    JSR      PC,CNTCLR
3621 007576 000404          BR      2$          ;GO TO 2$ IF NO ERROR
3622 007600 000240          NOP          ;RETURN HERE IF ERROR
3623 007602 104000          ERROR          ;ERROR NUMBER DEFINED BY SUB
3624 007604 000137 007722    JMP      4$          ;GO TO 4$ IF ERROR WAS FOUND
3625 007610          2$:
3626 007610 112737 000026 001506    MOVB      #RMDT,GETINX      ;SETUP GET INDEX TABLE
3627 007616 112737 000200 001507    MOVB      #200,GETINX+1
3628 007624 012737 007726 001356    MOV      #5$,RMDT1      ;RMDT INPUT BUFFER = 5$
3629 007632 004737 037516    JSR      PC,GET      ;GO GET DRIVE TYPE
3630 007636 000402          BR      3$          ;GO TO 3$ IF NO ERROR
3631 007640 000240          NOP          ;RETURN HERE IF ERROR
3632 007642 104000          ERROR          ;ERROR NUMBER SPECIFIED BY GET
3633 007644 022737 020024 001356 3$:      CMP      #SNGPRT,RMDT1      ;SINGLE PORT RM03??
3634 007652 001425          BEQ      5$          ;YES!!

```

```
3635 007654 022737 024024 001356      CMP      #DULPRT,RMDT1      ;DUAL PORT RM03??
3636 007662 001421                      BEQ      S8                      ;YES!!
3637 007664 022737 020025 001356      CMP      #SNGPRT!BIT0,RMDT1
3638 007672 001415                      BEQ      S8
3639 007674 022737 024025 001356      CMP      #DULPRT!BIT0,RMDT1
3640 007702 001411                      BEQ      S8
3641 007704 012737 020024 001176      MOV      #SNGPRT,$TMP1
3642 007712 012737 024024 001200      MOV      #DULPRT,$TMP2
3643 007720 104114                      ERROR    114                      ;NOT AN RM03
3644 007722 000137 032732      4$:      JMP      $EOSP                      ;GO TO SUBPASS HANDLER.
3645
3646 007726      5$:
3647      ;*****
3648      ;*TEST 4          FORMAT ZEROS - 18
3649      ;*****
3650 007726      TST4:
3651 007726 000004                      SCOPE                      ;SCOPE CALL
3652 007730 000240                      NOP                      ;START OF TEST
3653 007732 012706 001100      MOV      #STACK,SP      ;INITIALIZE STACK POINTER
3654 007736 013700 001276      MOV      $BASE,R0      ;R0=UNIBUS ADDRESS
3655 007742 013701 001450      MOV      TSTQUE,R1      ;(R1) = DEVICE BEING TESTED
3656 007746 012737 000004 001226      MOV      #4,$TESTN      ;SET TEST NUMBER IN APT MAIL BOX
3657 007754
3658
3659      ;SETUP PARAMETERS FOR GENERATING DATA BUFFER
3660 007754 012737 000000 001434      MOV      #0,RMDCO      ;CYLINDER = 0
3661 007762 012737 000000 001406      MOV      #0,RMDAO      ;TRACK = SECTOR = 0
3662 007770 012737 000000 001432      MOV      #0,RMOFO      ;18 BIT FORMAT
3663 007776 012737 177376 001402      MOV      #<^C<2+256.>+1>,RMWCO      ;2 + 256 WORDS
3664 010004 012737 103564 001404      MOV      #BUFONE,RMBAO      ;DATA BUFFER ADDRESS
3665 010012 012737 000062 001400      MOV      #WH,RMCS10      ;WRITE HEADER AND DATA
3666 010020 012737 065104 001174      MOV      #ZEROS,$TMP0      ;USE ALL ZEROS DATA PATTERN
3667 010026 012737 000001 001176      MOV      #1,$TMP1
3668 010034 004737 036620      JSR      PC,GENBUF      ;GO GENERATE DATA BUFFER
3669 010040
3670
3671      ;PREPARE DEVICE FOR DATA TRANSFER
3672 010040 004737 034000      JSR      PC,TSTPRP      ;PREPARE DEVICE FOR TEST
3673 010044 154130      .WORD    154130      ;TASK DESCRIPTOR
3674 010046 000404      BR      30$      ;GO TO 30$ IF NO ERROR
3675 010050 000240      NOP                      ;RETURN HERE IF ERROR
3676 010052 104000      ERROR    ;ERROR # DEFINED BY TSTPRP SUBROUTINE
3677 010054 000137 010526      JMP      180$      ;GO TO 180$ IF ERROR WAS FOUND
3678 010060
3679
3680      30$:
3681      ;SETUP PARAMETERS AND EXECUTE SEEK TO GET DRIVE ON CYLINDER
3682 010060 012737 000005 001400      MOV      #SEEK!GO,RMCS10      ;CHANGE COMMAND TO SEEK
3683 010066 012702 001535      MOV      #PUTINX,R2      ;WRITE REGISTER INDEX TABLE
3684 010072 112722 000006      MOV      #RMDA,(R2)+
3685 010076 112722 000034      MOV      #RMDC,(R2)+
3686 010102 112722 000032      MOV      #RMOF,(R2)+
3687 010106 112722 000000      MOV      #RMCS1,(R2)+
3688 010112 112722 000200      MOV      #200,(R2)+
3689 010116 004737 037766      JSR      PC,PUT      ;GO WRITE REGISTERS VIA PUT SUB
3690 010122 000404      BR      40$      ;GO TO 40$ IF NO ERROR
3690 010124 000240      NOP                      ;RETURN HERE IF ERROR
```



```
3691 010126 104000          ERROR          ;ERROR DEFINED BY PUT SUB
3692 010130 000137 010526    JMP      180$    ;GO TO 180$ IF ERROR WAS FOUND
3693 010134
3694
3695          ;SETUP FOR READING STATUS AND THEN WAIT FOR SEEK TO COMPLETE
3696 010134 004737 037432    JSR      PC,GETSTS      ;SETUP FOR STATUS
3697 010140 004737 040326    JSR      PC,TIMOUT      ;WAIT FOR SEEK TO COMPLETE
3698 010144
3699
3700          ;GO READ SEEK STATUS
3701 010144 004737 037516    JSR      PC,GET      ;GO READ REGISTERS VIA GET SUB
3702 010150 000404          BR      60$      ;GO TO 60$ IF NO ERROR
3703 010152 000240          NOP          ;RETURN HERE IF ERROR
3704 010154 104000          ERROR        ;ERROR DEFINED BY GET SUB
3705 010156 000137 010526    JMP      180$    ;GO TO 180$ IF ERROR WAS FOUND
3706 010162
3707
3708          ;VERIFY THE RESULTS OF THE SEEK COMMAND
3709 010162 004737 045420    JSR      PC,SEKSTS      ;GO VERIFY RESULTS OF SEEK OPERATION
3710 010166 000405          BR      70$      ;GO TO 70$ IF NO ERROR
3711 010170 000240          NOP          ;RETURN HERE IF ERROR
3712 010172 104000          ERROR        ;ERROR # DEFINED BY SEKSTS SUBROUTINE
3713 010174 004736          JSR      PC,@(SP)+      ;GO BACK FOR MORE ERROR CHECKS
3714 010176 000137 010526    JMP      180$    ;GO TO 180$ IF ERROR WAS FOUND
3715 010202
3716
3717          ;SETUP AND EXECUTE WRITE HEADER AND DATA COMMAND
3718 010202 012737 000063 001400    MOV      #WH!GO,RMCS10      ;LOAD WRITE HEADER AND DATA
3719 010210 012702 001540          MOV      #PUTINX+3,R2      ;EXTEND REGISTER INDEX TABLE
3720 010214 112722 000002          MOV      #RMWC,(R2)+
3721 010220 112722 000004          MOV      #RMBA,(R2)+
3722 010224 112722 000000          MOV      #RMCS1,(R2)+
3723 010230 112722 000200          MOV      #200,(R2)+
3724 010234 004737 037766    JSR      PC,PUT      ;GO WRITE REGISTERS VIA PUT SUB
3725 010240 000404          BR      80$      ;GO TO 80$ IF NO ERROR
3726 010242 000240          NOP          ;RETURN HERE IF ERROR
3727 010244 104000          ERROR        ;ERROR DEFINED BY PUT SUB
3728 010246 000137 010526    JMP      180$    ;GO TO 180$ IF ERROR WAS FOUND
3729 010252
3730
3731          ;WAIT FOR WRITE COMMAND TO COMPLETE AND READ STATUS
3732 010252 004737 040326    JSR      PC,TIMOUT      ;WAIT FOR COMMAND TO COMPLETE
3733 010256 004737 037516    JSR      PC,GET      ;GO READ REGISTERS VIA GET SUB
3734 010262 000404          BR      90$      ;GO TO 90$ IF NO ERROR
3735 010264 000240          NOP          ;RETURN HERE IF ERROR
3736 010266 104000          ERROR        ;ERROR DEFINED BY GET SUB
3737 010270 000137 010526    JMP      180$    ;GO TO 180$ IF ERROR WAS FOUND
3738 010274
3739
3740          ;VERIFY RESULTS OF WRITE COMMAND
3741 010274 004737 040512    JSR      PC,PRIERR      ;GO CHECK FOR PRIMARY ERRORS
3742 010300 000405          BR      100$     ;GO TO 100$ IF NO ERROR
3743 010302 000240          NOP          ;RETURN HERE IF ERROR
3744 010304 104000          ERROR        ;ERROR # DEFINED BY PRIERR SUBROUTINE
3745 010306 004736          JSR      PC,@(SP)+      ;GO BACK FOR MORE ERROR CHECKS
3746 010310 000137 010526    JMP      180$    ;GO TO 180$ IF ERROR WAS FOUND
```

```
3747 010314 100$:
3748 010314 004737 053016 JSR PC,DTASTS ;GO VERIFY RESULTS OF DATA TRANSFER
3749 010320 000405 BR 110$ ;GO TO 110$ IF NO ERROR
3750 010322 000240 NOP ;RETURN HERE IF ERROR
3751 010324 104000 ERROR ;ERROR # DEFINED BY DTASTS SUBROUTINE
3752 010326 004736 JSR PC,@(SP)+ ;GO BACK FOR MORE ERROR CHECKS
3753 010330 000137 010526 JMP 180$ ;GO TO 180$ IF ERROR WAS FOUND
3754 010334 110$:
3755 010334 004737 041344 JSR PC,SECERR ;GO CHECK FOR SECONDARY ERRORS
3756 010340 000405 BR 120$ ;GO TO 120$ IF NO ERROR
3757 010342 000240 NOP ;RETURN HERE IF ERROR
3758 010344 104000 ERROR ;ERROR # DEFINED BY SECERR SUBROUTINE
3759 010346 004736 JSR PC,@(SP)+ ;GO BACK FOR MORE ERROR CHECKS
3760 010350 000137 010526 JMP 180$ ;GO TO 180$ IF ERROR WAS FOUND
3761 010354 120$:
3762
3763
3764 ;READ HEADER AND DATA FOR SECTOR JUST WRITTEN
3765 010354 012737 000073 001400 MOV #RH!GO,RMC$10 ;READ HEADER & DATA COMMAND
3766 010362 012737 104570 001404 MOV #BUFTWO,RMBAO ;CHANGE BUS ADDRESS
3767 010370 004737 037766 JSR PC,PUT ;GO WRITE REGISTERS VIA PUT SUB
3768 010374 000404 BR 130$ ;GO TO 130$ IF NO ERROR
3769 010376 000240 NOP ;RETURN HERE IF ERROR
3770 010400 104000 ERROR ;ERROR DEFINED BY PUT SUB
3771 010402 000137 010526 JMP 180$ ;GO TO 180$ IF ERROR WAS FOUND
3772 010406 130$:
3773
3774 ;WAIT FOR READ TO COMPLETE AND GET STATUS
3775 010406 004737 040326 JSR PC,TIMOUT ;WAIT FOR READ TO COMPLETE
3776 010412 004737 037516 JSR PC,GET ;GO READ REGISTERS VIA GET SUB
3777 010416 000404 BR 140$ ;GO TO 140$ IF NO ERROR
3778 010420 000240 NOP ;RETURN HERE IF ERROR
3779 010422 104000 ERROR ;ERROR DEFINED BY GET SUB
3780 010424 000137 010526 JMP 180$ ;GO TO 180$ IF ERROR WAS FOUND
3781 010430 140$:
3782
3783 ;VERIFY THE RESULTS OF READ OPERATION
3784 010430 004737 040512 JSR PC,PRIERR ;GO CHECK FOR PRIMARY ERRORS
3785 010434 000405 BR 150$ ;GO TO 150$ IF NO ERROR
3786 010436 000240 NOP ;RETURN HERE IF ERROR
3787 010440 104000 ERROR ;ERROR # DEFINED BY PRIERR SUBROUTINE
3788 010442 004736 JSR PC,@(SP)+ ;GO BACK FOR MORE ERROR CHECKS
3789 010444 000137 010526 JMP 180$ ;GO TO 180$ IF ERROR WAS FOUND
3790 010450 150$:
3791 010450 004737 053016 JSR PC,DTASTS ;GO VERIFY RESULTS OF DATA TRANSFER
3792 010454 000405 BR 160$ ;GO TO 160$ IF NO ERROR
3793 010456 000240 NOP ;RETURN HERE IF ERROR
3794 010460 104000 ERROR ;ERROR # DEFINED BY DTASTS SUBROUTINE
3795 010462 004736 JSR PC,@(SP)+ ;GO BACK FOR MORE ERROR CHECKS
3796 010464 000137 010526 JMP 180$ ;GO TO 180$ IF ERROR WAS FOUND
3797 010470 160$:
3798 010470 004737 041344 JSR PC,SECERR ;GO CHECK FOR SECONDARY ERRORS
3799 010474 000405 BR 170$ ;GO TO 170$ IF NO ERROR
3800 010476 000240 NOP ;RETURN HERE IF ERROR
3801 010500 104000 ERROR ;ERROR # DEFINED BY SECERR SUBROUTINE
3802 010502 004736 JSR PC,@(SP)+ ;GO BACK FOR MORE ERROR CHECKS
```

```

3803 010504 000137 010526      JMP      180$                ;GO TO 180$ IF ERROR WAS FOUND
3804 010510
3805
3806      ;VERIFY DATA
3807 010510 004737 037064      JSR      PC,CMPBUF      ;GO COMPARE WRITE, READ DATA BUFFERS
3808 010514 103564              .WORD    BUFO1E      ;STARTING ADDRESS OF WRITE BUFFER
3809 010516 104570              .WORD    BUFTWO     ;STARTING ADDRESS OF READ BUFFER
3810 010520 000402              BR       180$        ;GO TO 180$ IF NO ERROR
3811 010522 000240              NOP                     ;RETURN HERE IF ERROR
3812 010524 104000              ERROR          ;ERROR # DEFINED BY CMPBUF SUBROUTINE
3813 010526
3814
3815      ;*****
3816      ;*TEST 5          FORMAT ZEROS - 16
3817      ;*****
3818 010526
3819 010526 000004              SCOPE          ;SCOPE CALL
3820 010530 000240              NOP            ;START OF TEST
3821 010532 012706 001100      MOV      #STACK,SP  ;INITIALIZE STACK POINTER
3822 010536 013700 001276      MOV      $BASE,R0   ;R0=UNIBUS ADDRESS
3823 010542 013701 001450      MOV      TSTQUE,R1  ;(R1) = DEVICE BEING TESTED
3824 010546 012737 000005 001226  MOV      #5,$TESTN ;SET TEST NUMBER IN APT MAIL BOX
3825 010554
3826
3827      ;SETUP PARAMETERS FOR GENERATING DATA BUFFER
3828 010554 012737 000000 001434  MOV      #0,RMDCO      ;CYLINDER = 0
3829 010562 012737 000000 001406  MOV      #0,RMDAO      ;TRACK = SECTOR = 0
3830 010570 012737 010000 001432  MOV      #FMT16,RMOFO    ;16 BIT FORMAT
3831 010576 012737 177376 001402  MOV      #<^C<2+256.>+1>,RMWCO ;2 + 256 WORDS
3832 010604 012737 103564 001404  MOV      #BUFO1E,RMBAO    ;DATA BUFFER ADDRESS
3833 010612 012737 000062 001400  MOV      #WH,RMCS10    ;WRITE HEADER AND DATA
3834 010620 012737 065104 001174  MOV      #ZEROS,$TMP0    ;USE ALL ZEROS DATA PATTERN
3835 010626 012737 000001 001176  MOV      #1,$TMP1
3836 010634 004737 036620      JSR      PC,GENBUF      ;GO GENERATE DATA BUFFER
3837 010640
3838
3839      ;PREPARE DEVICE FOR DATA TRANSFER
3840 010640 004737 034000      JSR      PC,TSTPRP      ;PREPARE DEVICE FOR TEST
3841 010644 154130              .WORD    154130 ;TASK DESCRIPTOR
3842 010646 000404              BR       30$          ;GO TO 30$ IF NO ERROR
3843 010650 000240              NOP                     ;RETURN HERE IF ERROR
3844 010652 104000              ERROR          ;ERROR # DEFINED BY TSTPRP SUBROUTINE
3845 010654 000137 011326      JMP      180$        ;GO TO 180$ IF ERROR WAS FOUND
3846 010660
3847
3848      ;SETUP PARAMETERS AND EXECUTE SEEK TO GET DRIVE ON CYLINDER
3849 010660 012737 000005 001400  MOV      #SEEK!GO,RMCS10 ;CHANGE COMMAND TO SEEK
3850 010666 012702 001535      MOV      #PUTINX,R2      ;WRITE REGISTER INDEX TABLE
3851 010672 112722 000006      MOV      #RMDA,(R2)+
3852 010676 112722 000034      MOV      #RMDC,(R2)+
3853 010702 112722 000032      MOV      #RMOF,(R2)+
3854 010706 112722 000000      MOV      #RMCS1,(R2)+
3855 010712 112722 000200      MOV      #200,(R2)+
3856 010716 004737 037766      JSR      PC,PUT      ;GO WRITE REGISTERS VIA PUT SUB
3857 010722 000404              BR       40$          ;GO TO 40$ IF NO ERROR
3858 010724 000240              NOP                     ;RETURN HERE IF ERROR

```

```
3859 010726 104000          ERROR          ;ERROR DEFINED BY PUT SUB
3860 010730 000137 011326    JMP      180$    ;GO TO 180$ IF ERROR WAS FOUND
3861 010734          40$:
3862
3863          ;SETUP FOR READING STATUS AND THEN WAIT FOR SEEK TO COMPLETE
3864 010734 004737 037432    JSR      PC,GETSTS          ;SETUP FOR STATUS
3865 010740 004737 040326    JSR      PC,TIMOUT          ;WAIT FOR SEEK TO COMPLETE
3866 010744          50$:
3867
3868          ;GO READ SEEK STATUS
3869 010744 004737 037516    JSR      PC,GET          ;GO READ REGISTERS VIA GET SUB
3870 010750 000404          BR      60$    ;GO TO 60$ IF NO ERROR
3871 010752 000240          NOP          ;RETURN HERE IF ERROR
3872 010754 104000          ERROR          ;ERROR DEFINED BY GET SUB
3873 010756 000137 011326    JMP      180$    ;GO TO 180$ IF ERROR WAS FOUND
3874 010762          60$:
3875
3876          ;VERIFY THE RESULTS OF THE SEEK COMMAND
3877 010762 004737 045420    JSR      PC,SEKSTS          ;GO VERIFY RESULTS OF SEEK OPERATION
3878 010766 000405          BR      70$    ;GO TO 70$ IF NO ERROR
3879 010770 000240          NOP          ;RETURN HERE IF ERROR
3880 010772 104000          ERROR          ;ERROR # DEFINED BY SEKSTS SUBROUTINE
3881 010774 004736          JSR      PC,@(SP)+          ;GO BACK FOR MORE ERROR CHECKS
3882 010776 000137 011326    JMP      180$    ;GO TO 180$ IF ERROR WAS FOUND
3883 011002          70$:
3884
3885          ;SETUP AND EXECUTE WRITE HEADER AND DATA COMMAND
3886 011002 012737 000063 001400 MOV      #WH!GO,RMCS10          ;LOAD WRITE HEADER AND DATA
3887 011010 012702 001540    MOV      #PUTINX+3,R2          ;EXTEND REGISTER INDEX TABLE
3888 011014 112722 000002    MOV      #RMWC,(R2)+
3889 011020 112722 000004    MOV      #RMBA,(R2)+
3890 011024 112722 000000    MOV      #RMCS1,(R2)+
3891 011030 112722 000200    MOV      #200,(R2)+
3892 011034 004737 037766    JSR      PC,PUT          ;GO WRITE REGISTERS VIA PUT SUB
3893 011040 000404          BR      80$    ;GO TO 80$ IF NO ERROR
3894 011042 000240          NOP          ;RETURN HERE IF ERROR
3895 011044 104000          ERROR          ;ERROR DEFINED BY PUT SUB
3896 011046 000137 011326    JMP      180$    ;GO TO 180$ IF ERROR WAS FOUND
3897 011052          80$:
3898
3899          ;WAIT FOR WRITE COMMAND TO COMPLETE AND READ STATUS
3900 011052 004737 040326    JSR      PC,TIMOUT          ;WAIT FOR COMMAND TO COMPLETE
3901 011056 004737 037516    JSR      PC,GET          ;GO READ REGISTERS VIA GET SUB
3902 011062 000404          BR      90$    ;GO TO 90$ IF NO ERROR
3903 011064 000240          NOP          ;RETURN HERE IF ERROR
3904 011066 104000          ERROR          ;ERROR DEFINED BY GET SUB
3905 011070 000137 011326    JMP      180$    ;GO TO 180$ IF ERROR WAS FOUND
3906 011074          90$:
3907
3908          ;VERIFY RESULTS OF WRITE COMMAND
3909 011074 004737 040512    JSR      PC,PRIERR          ;GO CHECK FOR PRIMARY ERRORS
3910 011100 000405          BR      100$          ;GO TO 100$ IF NO ERROR
3911 011102 000240          NOP          ;RETURN HERE IF ERROR
3912 011104 104000          ERROR          ;ERROR # DEFINED BY PRIERR SUBROUTINE
3913 011106 004736          JSR      PC,@(SP)+          ;GO BACK FOR MORE ERROR CHECKS
3914 011110 000137 011326    JMP      180$    ;GO TO 180$ IF ERROR WAS FOUND
```

```
3915 011114      100$:
3916 011114 004737 053016      JSR    PC,DTASTS      ;GO VERIFY RESULTS OF DATA TRANSFER
3917 011120 000405              BR      110$      ;GO TO 110$ IF NO ERROR
3918 011122 000240              NOP              ;RETURN HERE IF ERROR
3919 011124 104000              ERROR           ;ERROR # DEFINED BY DTASTS SUBROUTINE
3920 011126 004736              JSR    PC,@(SP)+  ;GO BACK FOR MORE ERROR CHECKS
3921 011130 000137 011326      JMP      180$      ;GO TO 180$ IF ERROR WAS FOUND
3922 011134      110$:
3923 011134 004737 041344      JSR    PC,SECERR     ;GO CHECK FOR SECONDARY ERRORS
3924 011140 000405              BR      120$      ;GO TO 120$ IF NO ERROR
3925 011142 000240              NOP              ;RETURN HERE IF ERROR
3926 011144 104000              ERROR           ;ERROR # DEFINED BY SECERR SUBROUTINE
3927 011146 004736              JSR    PC,@(SP)+  ;GO BACK FOR MORE ERROR CHECKS
3928 011150 000137 011326      JMP      180$      ;GO TO 180$ IF ERROR WAS FOUND
3929 011154      120$:
3930
3931
3932      ;READ HEADER AND DATA FOR SECTOR JUST WRITTEN
3933 011154 012737 000073 001400  MOV     #RH!GO,RMC$IO      ;READ HEADER & DATA COMMAND
3934 011162 012737 104570 001404  MOV     #BUFTWO,RMBAO     ;CHANGE BUS ADDRESS
3935 011170 004737 037766              JSR    PC,PUT      ;GO WRITE REGISTERS VIA PUT SUB
3936 011174 000404              BR      130$      ;GO TO 130$ IF NO ERROR
3937 011176 000240              NOP              ;RETURN HERE IF ERROR
3938 011200 104000              ERROR           ;ERROR DEFINED BY PUT SUB
3939 011202 000137 011326      JMP      180$      ;GO TO 180$ IF ERROR WAS FOUND
3940 011206      130$:
3941
3942      ;WAIT FOR READ TO COMPLETE AND GET STATUS
3943 011206 004737 040326      JSR    PC,TIMOUT     ;WAIT FOR READ TO COMPLETE
3944 011212 004737 037516      JSR    PC,GET      ;GO READ REGISTERS VIA GET SUB
3945 011216 000404              BR      140$      ;GO TO 140$ IF NO ERROR
3946 011220 000240              NOP              ;RETURN HERE IF ERROR
3947 011222 104000              ERROR           ;ERROR DEFINED BY GET SUB
3948 011224 000137 011326      JMP      180$      ;GO TO 180$ IF ERROR WAS FOUND
3949 011230      140$:
3950
3951      ;VERIFY THE RESULTS OF READ OPERATION
3952 011230 004737 040512      JSR    PC,PRIERR     ;GO CHECK FOR PRIMARY ERRORS
3953 011234 000405              BR      150$      ;GO TO 150$ IF NO ERROR
3954 011236 000240              NOP              ;RETURN HERE IF ERROR
3955 011240 104000              ERROR           ;ERROR # DEFINED BY PRIERR SUBROUTINE
3956 011242 004736              JSR    PC,@(SP)+  ;GO BACK FOR MORE ERROR CHECKS
3957 011244 000137 011326      JMP      180$      ;GO TO 180$ IF ERROR WAS FOUND
3958 011250      150$:
3959 011250 004737 053016      JSR    PC,DTASTS     ;GO VERIFY RESULTS OF DATA TRANSFER
3960 011254 000405              BR      160$      ;GO TO 160$ IF NO ERROR
3961 011256 000240              NOP              ;RETURN HERE IF ERROR
3962 011260 104000              ERROR           ;ERROR # DEFINED BY DTASTS SUBROUTINE
3963 011262 004736              JSR    PC,@(SP)+  ;GO BACK FOR MORE ERROR CHECKS
3964 011264 000137 011326      JMP      180$      ;GO TO 180$ IF ERROR WAS FOUND
3965 011270      160$:
3966 011270 004737 041344      JSR    PC,SECERR     ;GO CHECK FOR SECONDARY ERRORS
3967 011274 000405              BR      170$      ;GO TO 170$ IF NO ERROR
3968 011276 000240              NOP              ;RETURN HERE IF ERROR
3969 011300 104000              ERROR           ;ERROR # DEFINED BY SECERR SUBROUTINE
3970 011302 004736              JSR    PC,@(SP)+  ;GO BACK FOR MORE ERROR CHECKS
```

```
3971 011304 000137 011326          JMP      180$          ;GO TO 180$ IF ERROR WAS FOUND
3972 011310
3973
3974          ;VERIFY DATA
3975 011310 004737 037064          JSR      PC,CMPBUF      ;GO COMPARE WRITE, READ DATA BUFFERS
3976 011314 103564          .WORD    BUFO1E      ;STARTING ADDRESS OF WRITE BUFFER
3977 011316 104570          .WORD    BUFTWO     ;STARTING ADDRESS OF READ BUFFER
3978 011320 000402          BR        180$          ;GO TO 180$ IF NO ERROR
3979 011322 000240          NOP
3980 011324 104000          ERROR      ;RETURN HERE IF ERROR
3981 011326          ;ERROR # DEFINED BY CMPBUF SUBROUTINE
3982
3983
3984          ;*****
3985          ;*TEST 6          ZERO FILL TEST
3986          ;*****
3987 011326 000004          TSTB:
3988 011330 000240          SCOPE          ;SCOPE CALL
3989 011332 012706 001100          NOP          ;START OF TEST
3990 011336 013700 001276          MOV      #STACK,SP      ;INITIALIZE STACK POINTER
3991 011342 013701 001450          MOV      $BASE,R0      ;R0=UNIBUS ADDRESS
3992 011346 012737 000006 001226  MOV      TSTQUE,R1      ; (R1) = DEVICE BEING TESTED
3993 011354          MOV      #6,$TESTN      ;SET TEST NUMBER IN APT MAIL BOX
3994
3995          ;SETUP PARAMETERS FOR GENERATING DATA BUFFER
3996 011354 012737 000000 001434  MOV      #0,RMDCO      ;CYLINDER = 0
3997 011362 012737 000000 001406  MOV      #0,RMDAO      ;TRACK = SECTOR = 0
3998 011370 012737 010000 001432  MOV      #FMT16,RMOFO      ;16 BIT FORMAT
3999 011376 012737 177376 001402  MOV      #<^C<2+256.>+1>,RMWFO      ;2 + 256 WORDS
4000 011404 012737 103564 001404  MOV      #BUFO1E,RMBAO      ;DATA BUFFER ADDRESS
4001 011412 012737 000062 001400  MOV      #WH,RMCS10      ;WRITE HEADER AND DATA
4002 011420 012737 065104 001174  MOV      #ZEROS,$TMP0      ;USE ALL ZEROS DATA PATTERN
4003 011426 012737 000001 001176  MOV      #1,$TMP1
4004 011434 004737 036620          JSR      PC,GENBUF      ;GO GENERATE DATA BUFFER
4005 011440
4006
4007          ;PREPARE DEVICE FOR DATA TRANSFER
4008 011440 004737 034000          JSR      PC,TSTPRP      ;PREPARE DEVICE FOR TEST
4009 011444 154130          .WORD    154130      ;TASK DESCRIPTOR
4010 011446 000404          BR        30$          ;GO TO 30$ IF NO ERROR
4011 011450 000240          NOP          ;RETURN HERE IF ERROR
4012 011452 104000          ERROR      ;ERROR # DEFINED BY TSTPRP SUBROUTINE
4013 011454 000137 012142          JMP      180$          ;GO TO 180$ IF ERROR WAS FOUND
4014 011460
4015
4016          ;SETUP PARAMETERS AND EXECUTE SEEK TO GET DRIVE ON CYLINDER
4017 011460 012737 000005 001400  MOV      #SEEK!GO,RMCS10      ;CHANGE COMMAND TO SEEK
4018 011466 012702 001535          MOV      #PUTINX,R2      ;WRITE REGISTER INDEX TABLE
4019 011472 112722 000006          MOV      #RMDA,(R2)+
4020 011476 112722 000034          MOV      #RMDC,(R2)+
4021 011502 112722 000032          MOV      #RMOF,(R2)+
4022 011506 112722 000000          MOV      #RMCS1,(R2)+
4023 011512 112722 000200          MOV      #200,(R2)+
4024 011516 004737 037766          JSR      PC,PUT      ;GO WRITE REGISTERS VIA PUT SUB
4025 011522 000404          BR        40$          ;GO TO 40$ IF NO ERROR
4026 011524 000240          NOP          ;RETURN HERE IF ERROR
```



```
4027 011526 104000          ERROR          ;ERROR DEFINED BY PUT SUB
4028 011530 000137 012142    JMP      180$    ;GO TO 180$ IF ERROR WAS FOUND
4029 011534
4030
4031          ;SETUP FOR READING STATUS AND THEN WAIT FOR SEEK TO COMPLETE
4032 011534 004737 037432    JSR      PC,GETSTS      ;SETUP FOR STATUS
4033 011540 004737 040326    JSR      PC,TIMOUT      ;WAIT FOR SEEK TO COMPLETE
4034 011544
4035
4036          ;GO READ SEEK STATUS
4037 011544 004737 037516    JSR      PC,GET      ;GO READ REGISTERS VIA GET SUB
4038 011550 000404          BR      60$      ;GO TO 60$ IF NO ERROR
4039 011552 000240          NOP              ;RETURN HERE IF ERROR
4040 011554 104000          ERROR          ;ERROR DEFINED BY GET SUB
4041 011556 000137 012142    JMP      180$    ;GO TO 180$ IF ERROR WAS FOUND
4042 011562
4043
4044          ;VERIFY THE RESULTS OF THE SEEK COMMAND
4045 011562 004737 045420    JSR      PC,SEKSTS      ;GO VERIFY RESULTS OF SEEK OPERATION
4046 011566 000405          BR      70$      ;GO TO 70$ IF NO ERROR
4047 011570 000240          NOP              ;RETURN HERE IF ERROR
4048 011572 104000          ERROR          ;ERROR # DEFINED BY SEKSTS SUBROUTINE
4049 011574 004736          JSR      PC,@(SP)+      ;GO BACK FOR MORE ERROR CHECKS
4050 011576 000137 012142    JMP      180$    ;GO TO 180$ IF ERROR WAS FOUND
4051 011602
4052
4053          ;SETUP AND EXECUTE WRITE HEADER AND DATA COMMAND
4054 011602 012737 177776 001402    MOV      #<^C2+1>,RMWCO      ;FORMAT PARTIAL SECTOR
4055 011610 012737 000063 001400    MOV      #WH!GO,RMCS10      ;LOAD WRITE HEADER AND DATA
4056 011616 012702 001540          MOV      #PUTINX+3,R2      ;EXTEND REGISTER INDEX TABLE
4057 011622 112722 000002          MOVB     #RMWC,(R2)+
4058 011626 112722 000004          MOVB     #RMBA,(R2)+
4059 011632 112722 000000          MOVB     #RMCS1,(R2)+
4060 011636 112722 000200          MOVB     #200,(R2)+
4061 011642 004737 037766    JSR      PC,PUT      ;GO WRITE REGISTERS VIA PUT SUB
4062 011646 000404          BR      80$      ;GO TO 80$ IF NO ERROR
4063 011650 000240          NOP              ;RETURN HERE IF ERROR
4064 011652 104000          ERROR          ;ERROR DEFINED BY PUT SUB
4065 011654 000137 012142    JMP      180$    ;GO TO 180$ IF ERROR WAS FOUND
4066 011660
4067
4068          ;WAIT FOR WRITE COMMAND TO COMPLETE AND READ STATUS
4069 011660 004737 040326    JSR      PC,TIMOUT      ;WAIT FOR COMMAND TO COMPLETE
4070 011664 004737 037516    JSR      PC,GET      ;GO READ REGISTERS VIA GET SUB
4071 011670 000404          BR      90$      ;GO TO 90$ IF NO ERROR
4072 011672 000240          NOP              ;RETURN HERE IF ERROR
4073 011674 104000          ERROR          ;ERROR DEFINED BY GET SUB
4074 011676 000137 012142    JMP      180$    ;GO TO 180$ IF ERROR WAS FOUND
4075 011702
4076
4077          ;VERIFY RESULTS OF WRITE COMMAND
4078 011702 004737 040512    JSR      PC,PRIERR      ;GO CHECK FOR PRIMARY ERRORS
4079 011706 000405          BR      100$     ;GO TO 100$ IF NO ERROR
4080 011710 000240          NOP              ;RETURN HERE IF ERROR
4081 011712 104000          ERROR          ;ERROR # DEFINED BY PRIERR SUBROUTINE
4082 011714 004736          JSR      PC,@(SP)+      ;GO BACK FOR MORE ERROR CHECKS
```

4083 011716 000137 012142 JMP 180\$;GO TO 180\$ IF ERROR WAS FOUND
4084 011722 100\$: JSR PC,DTASTS ;GO VERIFY RESULTS OF DATA TRANSFER
4085 011722 004737 053016 BR 110\$;GO TO 110\$ IF NO ERROR
4086 011726 000405 NOP ;RETURN HERE IF ERROR
4087 011730 000240 ERROR ;ERROR # DEFINED BY DTASTS SUBROUTINE
4088 011732 104000 JSR PC,@(SP)+ ;GO BACK FOR MORE ERROR CHECKS
4089 011734 004736 JMP 180\$;GO TO 180\$ IF ERROR WAS FOUND
4090 011736 000137 012142 110\$: JSR PC,SECERR ;GO CHECK FOR SECONDARY ERRORS
4091 011742 004737 041344 BR 120\$;GO TO 120\$ IF NO ERROR
4092 011742 000405 NOP ;RETURN HERE IF ERROR
4093 011746 000240 ERROR ;ERROR # DEFINED BY SECERR SUBROUTINE
4094 011750 004736 JSR PC,@(SP)+ ;GO BACK FOR MORE ERROR CHECKS
4095 011752 104000 JMP 180\$;GO TO 180\$ IF ERROR WAS FOUND
4096 011754 004736 120\$: JSR PC,SECERR ;GO CHECK FOR SECONDARY ERRORS
4097 011756 000137 012142 BR 120\$;GO TO 120\$ IF NO ERROR
4098 011762 000240 ERROR ;ERROR # DEFINED BY SECERR SUBROUTINE
4099 011762 004736 JMP 180\$;GO TO 180\$ IF ERROR WAS FOUND
4100
4101 ;READ HEADER AND DATA FOR SECTOR JUST WRITTEN
4102 011762 012737 177376 001402 MOV #<^C<2+256.>+1>,RMWCO ;READ A FULL SECTOR
4103 011770 012737 000073 001400 MOV #RH!GO,RMCSTO ;READ HEADER & DATA COMMAND
4104 011776 012737 104570 001404 MOV #BUFTWO,RMBAO ;CHANGE BUS ADDRESS
4105 012004 004737 037766 JSR PC,PUT ;GO WRITE REGISTERS VIA PUT SUB
4106 012010 000404 BR 130\$;GO TO 130\$ IF NO ERROR
4107 012012 000240 NOP ;RETURN HERE IF ERROR
4108 012014 104000 ERROR ;ERROR DEFINED BY PUT SUB
4109 012016 000137 012142 JMP 180\$;GO TO 180\$ IF ERROR WAS FOUND
4110 012022 130\$:
4111
4112 ;WAIT FOR READ TO COMPLETE AND GET STATUS
4113 012022 004737 040326 JSR PC,TIMOUT ;WAIT FOR READ TO COMPLETE
4114 012026 004737 037516 JSR PC,GET ;GO READ REGISTERS VIA GET SUB
4115 012032 000404 BR 140\$;GO TO 140\$ IF NO ERROR
4116 012034 000240 NOP ;RETURN HERE IF ERROR
4117 012036 104000 ERROR ;ERROR DEFINED BY GET SUB
4118 012040 000137 012142 JMP 180\$;GO TO 180\$ IF ERROR WAS FOUND
4119 012044 140\$:
4120
4121 ;VERIFY THE RESULTS OF READ OPERATION
4122 012044 004737 040512 JSR PC,PRIERR ;GO CHECK FOR PRIMARY ERRORS
4123 012050 000405 BR 150\$;GO TO 150\$ IF NO ERROR
4124 012052 000240 NOP ;RETURN HERE IF ERROR
4125 012054 104000 ERROR ;ERROR # DEFINED BY PRIERR SUBROUTINE
4126 012056 004736 JSR PC,@(SP)+ ;GO BACK FOR MORE ERROR CHECKS
4127 012060 000137 012142 JMP 180\$;GO TO 180\$ IF ERROR WAS FOUND
4128 012064 150\$:
4129 012064 004737 053016 JSR PC,DTASTS ;GO VERIFY RESULTS OF DATA TRANSFER
4130 012070 000405 BR 160\$;GO TO 160\$ IF NO ERROR
4131 012072 000240 NOP ;RETURN HERE IF ERROR
4132 012074 104000 ERROR ;ERROR # DEFINED BY DTASTS SUBROUTINE
4133 012076 004736 JSR PC,@(SP)+ ;GO BACK FOR MORE ERROR CHECKS
4134 012100 000137 012142 JMP 180\$;GO TO 180\$ IF ERROR WAS FOUND
4135 012104 160\$:
4136 012104 004737 041344 JSR PC,SECERR ;GO CHECK FOR SECONDARY ERRORS
4137 012110 000405 BR 170\$;GO TO 170\$ IF NO ERROR
4138 012112 000240 NOP ;RETURN HERE IF ERROR


```
4139 012114 104000          ERROR          ;ERROR # DEFINED BY SECERR SUBROUTINE
4140 012116 004736          JSR      PC,2(SP)+ ;GO BACK FOR MORE ERROR CHECKS
4141 012120 000137 012142    JMP      180$    ;GO TO 180$ IF ERROR WAS FOUND
4142 012124
4143
4144          ;VERIFY DATA
4145 012124 004737 037064    JSR      PC,CMPBUF ;GO COMPARE WRITE, READ DATA BUFFERS
4146 012130 103564          .WORD    BUFO1E   ;STARTING ADDRESS OF WRITE BUFFER
4147 012132 104570          .WORD    BUFTWO  ;STARTING ADDRESS OF READ BUFFER
4148 012134 000402          BR        180$    ;GO TO 180$ IF NO ERROR
4149 012136 000240          NOP
4150 012140 104000          ERROR          ;RETURN HERE IF ERROR
4151 012142          ;ERROR # DEFINED BY CMPBUF SUBROUTINE
4152
4153          ;*****
4154          ;*TEST 7          FORMAT CHECK ZEROS - 16
4155          ;*****
4156          TST7:
4157 012142 000004          SCOPE          ;SCOPE CALL
4158 012144 000240          NOP          ;START OF TEST
4159 012146 012706 001100    MOV      #STACK,SP ;INITIALIZE STACK POINTER
4160 012152 013700 001276    MOV      $BASE,R0  ;R0=UNIBUS ADDRESS
4161 012156 013701 001450    MOV      TSTQUE,R1 ; (R1) = DEVICE BEING TESTED
4162 012162 012737 000007 001226    MOV      #7,$TESTN ;SET TEST NUMBER IN APT MAIL BOX
4163 012170
4164
4165          ;SETUP PARAMETERS FOR GENERATING DATA BUFFER
4166 012170 012737 000000 001434    MOV      #0,RMDCO          ;CYLINDER = 0
4167 012176 012737 000000 001406    MOV      #0,RMDAO          ;TRACK = SECTOR = 0
4168 012200 012737 010000 001432    MOV      #FMT16,RMOFO        ;16 BIT FORMAT
4169 012212 012737 177376 001402    MOV      #<^C<2+256.>+1>,RMWCO ;2 + 256 WORDS
4170 012220 012737 103564 001404    MOV      #BUFO1E,RMBAO      ;DATA BUFFER ADDRESS
4171 012226 012737 000062 001400    MOV      #WH,RMCS10       ;WRITE HEADER AND DATA
4172 012234 012737 065104 001174    MOV      #ZEROS,$TMP0     ;USE ALL ZEROS DATA PATTERN
4173 012242 012737 000001 001176    MOV      #1,$TMP1
4174 012250 004737 036620          JSR      PC,GENBUF          ;GO GENERATE DATA BUFFER
4175 012254
4176
4177          ;PREPARE DEVICE FOR DATA TRANSFER
4178 012254 004737 034000    JSR      PC,TSTPRP      ;PREPARE DEVICE FOR TEST
4179 012260 154130          .WORD    154130 ;TASK DESCRIPTOR
4180 012262 000404          BR        30$          ;GO TO 30$ IF NO ERROR
4181 012264 000240          NOP          ;RETURN HERE IF ERROR
4182 012266 104000          ERROR          ;ERROR # DEFINED BY TSTPRP SUBROUTINE
4183 012270 000137 012716    JMP      260$        ;GO TO 260$ IF ERROR WAS FOUND
4184 012274
4185
4186          ;SETUP PARAMETERS AND EXECUTE SEEK TO GET DRIVE ON CYLINDER
4187 012274 012737 000005 001400    MOV      #SEEK!GO,RMCS10      ;CHANGE COMMAND TO SEEK
4188 012302 012702 001535          MOV      #PUTINX,R2          ;WRITE REGISTER INDEX TABLE
4189 012306 112722 000006          MOVB     #RMDA,(R2)+
4190 012312 112722 000034          MOVB     #RMDC,(R2)+
4191 012316 112722 000032          MOVB     #RMOF,(R2)+
4192 012322 112722 000000          MOVB     #RMCS1,(R2)+
4193 012326 112722 000200          MOVB     #200,(R2)+
4194 012332 004737 037766          JSR      PC,PUT          ;GO WRITE REGISTERS VIA PUT SUB
```

```
4195 012336 000404          BR      40$      ;GO TO 40$ IF NO ERROR
4196 012340 000240          NOP                      ;RETURN HERE IF ERROR
4197 012342 104000          ERROR                ;ERROR DEFINED BY PUT SUB
4198 012344 000137 012716   JMP      260$      ;GO TO 260$ IF ERROR WAS FOUND
4199 012350
4200
4201          ;SETUP FOR READING STATUS AND THEN WAIT FOR SEEK TO COMPLETE
4202 012350 004737 037432   JSR      PC,GETSTS      ;SETUP FOR STATUS
4203 012354 004737 040326   JSR      PC,TIMOUT      ;WAIT FOR SEEK TO COMPLETE
4204 012360
4205
4206          ;GO READ SEEK STATUS
4207 012360 004737 037516   JSR      PC,GET      ;GO READ REGISTERS VIA GET SUB
4208 012364 000404          BR      60$      ;GO TO 60$ IF NO ERROR
4209 012366 000240          NOP                      ;RETURN HERE IF ERROR
4210 012370 104000          ERROR                ;ERROR DEFINED BY GET SUB
4211 012372 000137 012716   JMP      260$      ;GO TO 260$ IF ERROR WAS FOUND
4212 012376
4213
4214          ;VERIFY THE RESULTS OF THE SEEK COMMAND
4215 012376 004737 045420   JSR      PC,SEKSTS      ;GO VERIFY RESULTS OF SEEK OPERATION
4216 012402 000405          BR      70$      ;GO TO 70$ IF NO ERROR
4217 012404 000240          NOP                      ;RETURN HERE IF ERROR
4218 012406 104000          ERROR                ;ERROR # DEFINED BY SEKSTS SUBROUTINE
4219 012410 004736          JSR      PC,@(SP)+      ;GO BACK FOR MORE ERROR CHECKS
4220 012412 000137 012716   JMP      260$      ;GO TO 260$ IF ERROR WAS FOUND
4221 012416
4222
4223          ;SETUP AND EXECUTE WRITE HEADER AND DATA COMMAND
4224 012416 012737 000063 001400 MOV     #WH!GO,RMCS10      ;LOAD WRITE HEADER AND DATA
4225 012424 012702 001540 MOV     #PUTINX+3,R2      ;EXTEND REGISTER INDEX TABLE
4226 012430 112722 000002 MOV     #RMWC,(R2)+
4227 012434 112722 000004 MOV     #RMBA,(R2)+
4228 012440 112722 000000 MOV     #RMCS1,(R2)+
4229 012444 112722 000200 MOV     #200,(R2)+
4230 012450 004737 037766   JSR      PC,PUT      ;GO WRITE REGISTERS VIA PUT SUB
4231 012454 000404          BR      80$      ;GO TO 80$ IF NO ERROR
4232 012456 000240          NOP                      ;RETURN HERE IF ERROR
4233 012460 104000          ERROR                ;ERROR DEFINED BY PUT SUB
4234 012462 000137 012716   JMP      260$      ;GO TO 260$ IF ERROR WAS FOUND
4235 012466
4236
4237          ;WAIT FOR WRITE COMMAND TO COMPLETE AND READ STATUS
4238 012466 004737 040326   JSR      PC,TIMOUT      ;WAIT FOR COMMAND TO COMPLETE
4239 012472 004737 037516   JSR      PC,GET      ;GO READ REGISTERS VIA GET SUB
4240 012476 000404          BR      90$      ;GO TO 90$ IF NO ERROR
4241 012500 000240          NOP                      ;RETURN HERE IF ERROR
4242 012502 104000          ERROR                ;ERROR DEFINED BY GET SUB
4243 012504 000137 012716   JMP      260$      ;GO TO 260$ IF ERROR WAS FOUND
4244 012510
4245
4246          ;VERIFY RESULTS OF WRITE COMMAND
4247 012510 004737 040512   JSR      PC,PRIERR      ;GO CHECK FOR PRIMARY ERRORS
4248 012514 000405          BR      100$      ;GO TO 100$ IF NO ERROR
4249 012516 000240          NOP                      ;RETURN HERE IF ERROR
4250 012520 104000          ERROR                ;ERROR # DEFINED BY PRIERR SUBROUTINE
```

```

4251 012522 004736      JSR    PC,@(SP)+      ;GO BACK FOR MORE ERROR CHECKS
4252 012524 000137 012716    JMP    260$      ;GO TO 260$ IF ERROR WAS FOUND
4253 012530      100$:      JSR    PC,DTASTS      ;GO VERIFY RESULTS OF DATA TRANSFER
4254 012530 004737 053016    BR    110$      ;GO TO 110$ IF NO ERROR
4255 012534 000405      NOP      ;RETURN HERE IF ERROR
4256 012536 000240      ERROR     ;ERROR # DEFINED BY DTASTS SUBROUTINE
4257 012540 104000      JSR    PC,@(SP)+      ;GO BACK FOR MORE ERROR CHECKS
4258 012542 004736      JMP    260$      ;GO TO 260$ IF ERROR WAS FOUND
4259 012544 000137 012716    110$:      JSR    PC,SECERR      ;GO CHECK FOR SECONDARY ERRORS
4260 012550      BR    120$      ;GO TO 120$ IF NO ERROR
4261 012550 004737 041344    NOP      ;RETURN HERE IF ERROR
4262 012554 000405      ERROR     ;ERROR # DEFINED BY SECERR SUBROUTINE
4263 012556 000240      JSR    PC,@(SP)+      ;GO BACK FOR MORE ERROR CHECKS
4264 012560 104000      JMP    260$      ;GO TO 260$ IF ERROR WAS FOUND
4265 012562 004736      120$:      JSR    PC,SECERR      ;GO CHECK FOR SECONDARY ERRORS
4266 012564 000137 012716    BR    120$      ;GO TO 120$ IF NO ERROR
4267 012570      NOP      ;RETURN HERE IF ERROR
4268      ERROR     ;ERROR # DEFINED BY SECERR SUBROUTINE
4269      JSR    PC,@(SP)+      ;GO BACK FOR MORE ERROR CHECKS
4270      JMP    260$      ;GO TO 260$ IF ERROR WAS FOUND
4271 012570 012737 000053 001400 ;WRITE CHECK HEADER AND DATA FOR SECTOR JUST WRITTEN
4272 012576 004737 037766      MOV    #WCH!GO,RMC$10      ;WRITE CHECK COMMAND
4273 012602 000404      JSR    PC,PUT      ;GO WRITE REGISTERS VIA PUT SUB
4274 012604 000240      BR    130$      ;GO TO 130$ IF NO ERROR
4275 012606 104000      NOP      ;RETURN HERE IF ERROR
4276 012610 000137 012716    ERROR     ;ERROR DEFINED BY PUT SUB
4277 012614      JMP    260$      ;GO TO 260$ IF ERROR WAS FOUND
4278      130$:
4279      ;WAIT FOR WRITE CHECK TO COMPLETE AND GET STATUS
4280 012614 004737 040326      JSR    PC,TIMOUT      ;WAIT FOR READ TO COMPLETE
4281 012620 004737 037516      JSR    PC,GET      ;GO READ REGISTERS VIA GET SUB
4282 012624 000404      BR    140$      ;GO TO 140$ IF NO ERROR
4283 012626 000240      NOP      ;RETURN HERE IF ERROR
4284 012630 104000      ERROR     ;ERROR DEFINED BY GET SUB
4285 012632 000137 012716    JMP    260$      ;GO TO 260$ IF ERROR WAS FOUND
4286 012636      140$:
4287
4288      ;VERIFY THE RESULTS OF WRITE CHECK OPERATION
4289 012636 004737 040512      JSR    PC,PRIERR      ;GO CHECK FOR PRIMARY ERRORS
4290 012642 000405      BR    150$      ;GO TO 150$ IF NO ERROR
4291 012644 000240      NOP      ;RETURN HERE IF ERROR
4292 012646 104000      ERROR     ;ERROR # DEFINED BY PRIERR SUBROUTINE
4293 012650 004736      JSR    PC,@(SP)+      ;GO BACK FOR MORE ERROR CHECKS
4294 012652 000137 012716    JMP    260$      ;GO TO 260$ IF ERROR WAS FOUND
4295 012656      150$:
4296 012656 004737 053016      JSR    PC,DTASTS      ;GO VERIFY RESULTS OF DATA TRANSFER
4297 012662 000405      BR    160$      ;GO TO 160$ IF NO ERROR
4298 012664 000240      NOP      ;RETURN HERE IF ERROR
4299 012666 104000      ERROR     ;ERROR # DEFINED BY DTASTS SUBROUTINE
4300 012670 004736      JSR    PC,@(SP)+      ;GO BACK FOR MORE ERROR CHECKS
4301 012672 000137 012716    JMP    260$      ;GO TO 260$ IF ERROR WAS FOUND
4302 012676      160$:
4303 012676 004737 041344      JSR    PC,SECERR      ;GO CHECK FOR SECONDARY ERRORS
4304 012702 000405      BR    170$      ;GO TO 170$ IF NO ERROR
4305 012704 000240      NOP      ;RETURN HERE IF ERROR
4306 012706 104000      ERROR     ;ERROR # DEFINED BY SECERR SUBROUTINE
```

```
4307 012710 004736 JSR PC,2(SP)+ ;GO BACK FOR MORE ERROR CHECKS
4308 012712 000137 012716 JMP 260$ ;GO TO 260$ IF ERROR WAS FOUND
4309 012716 170$:
4310
4311 012716 260$:
4312
4313 ;*****
4314 ;*TEST 10 FORMAT CHECK ZEROS W/ WCE ERROR
4315 ;*****
4316 012716 TST10:
4317 012716 000004 SCOPE ;SCOPE CALL
4318 012720 000240 NOP ;START OF TEST
4319 012722 012706 001100 MOV #STACK,SP ;INITIALIZE STACK POINTER
4320 012726 013700 001276 MOV $BASE,R0 ;R0=UNIBUS ADDRESS
4321 012732 013701 001450 MOV TSTQUE,R1 ;(R1) = DEVICE BEING TESTED
4322 012736 012737 000010 001226 MOV #10,$TESTN ;SET TEST NUMBER IN APT MAIL BOX
4323 012744 10$:
4324
4325 ;SETUP PARAMETERS FOR GENERATING DATA BUFFER
4326 012744 012737 000000 001434 MOV #0,RMDCO ;CYLINDER = 0
4327 012752 012737 000000 001406 MOV #0,RMDAO ;TRACK = SECTOR = 0
4328 012760 012737 010000 001432 MOV #FMT16,RMOFO ;16 BIT FORMAT
4329 012766 012737 177376 001402 MOV #<^C<2+256.>+1>,RMWCO ;2 + 256 WORDS
4330 012774 012737 103564 001404 MOV #BUFONE,RMBAC ;DATA BUFFER ADDRESS
4331 013002 012737 000062 001400 MOV #WH,RMCS10 ;WRITE HEADER AND DATA
4332 013010 012737 065104 001174 MOV #ZEROS,$TMP0 ;USE ALL ONES DATA PATTERN
4333 013016 012737 000001 001176 MOV #1,$TMP1
4334 013024 004737 036620 JSR PC,GENBUF ;GO GENERATE DATA BUFFER
4335 013030 20$:
4336
4337 ;PREPARE DEVICE FOR DATA TRANSFER
4338 013030 004737 034000 JSR PC,TSTPRP ;PREPARE DEVICE FOR TEST
4339 013034 154130 .WORD 154130 ;TASK DESCRIPTOR
4340 013036 000404 BR 30$ ;GO TO 30$ IF NO ERROR
4341 013040 000240 NOP ;RETURN HERE IF ERROR
4342 013042 104000 ERROR ;ERROR # DEFINED BY TSTPRP SUBROUTINE
4343 013044 000137 013636 JMP 260$ ;GO TO 260$ IF ERROR WAS FOUND
4344 013050 30$:
4345
4346 ;SETUP PARAMETERS AND EXECUTE SEEK TO GET DRIVE ON CYLINDER
4347 013050 012737 000005 001400 MOV #SEEK!GO,RMCS10 ;CHANGE COMMAND TO SEEK
4348 013056 012702 001535 MOV #PUTINX,R2 ;WRITE REGISTER INDEX TABLE
4349 013062 112722 000006 MOV #RMDA,(R2)+
4350 013066 112722 000034 MOV #RMDC,(R2)+
4351 013072 112722 000032 MOV #RMOF,(R2)+
4352 013076 112722 000000 MOV #RMCS1,(R2)+
4353 013102 112722 000200 MOV #200,(R2)+
4354 013106 004737 037766 JSR PC,PUT ;GO WRITE REGISTERS VIA PUT SUB
4355 013112 000404 BR 40$ ;GO TO 40$ IF NO ERROR
4356 013114 000240 NOP ;RETURN HERE IF ERROR
4357 013116 104000 ERROR ;ERROR DEFINED BY PUT SUB
4358 013120 000137 013636 JMP 260$ ;GO TO 260$ IF ERROR WAS FOUND
4359 013124 40$:
4360
4361 ;SETUP FOR READING STATUS AND THEN WAIT FOR SEEK TO COMPLETE
4362 013124 004737 037432 JSR PC,GETSTS ;SETUP FOR STATUS
```

CZRMDCO RM03/2 FCTML TST 2
CZRMDC.P11 12-DEC-78 08:24

MACV11 30A(1052) 04-JAN-79 11:23 PAGE 92
T10 FORMAT CHECK ZEROS W/ WCE ERROR

SEQ 0092

```
4363 013130 004737 040326          JSR    PC, TIMEOUT          ;WAIT FOR SEEK TO COMPLETE
4364 013134          50$:
4365          ;GO READ SEEK STATUS
4366          JSR    PC, GET          ;GO READ REGISTERS VIA GET SUB
4367 013134 004737 037516          BR    60$          ;GO TO 60$ IF NO ERROR
4368 013140 000404          NOP          ;RETURN HERE IF ERROR
4369 013142 000240          ERROR          ;ERROR DEFINED BY GET SUB
4370 013144 104000          JMP    260$          ;GO TO 260$ IF ERROR WAS FOUND
4371 013146 000137 013636          60$:
4372 013152          ;VERIFY THE RESULTS OF THE SEEK COMMAND
4373          JSR    PC, SEKSTS          ;GO VERIFY RESULTS OF SEEK OPERATION
4374          BR    70$          ;GO TO 70$ IF NO ERROR
4375 013152 004737 045420          NOP          ;RETURN HERE IF ERROR
4376 013156 000405          ERROR          ;ERROR # DEFINED BY SEKSTS SUBROUTINE
4377 013160 000240          JSR    PC, @ (SP)+          ;GO BACK FOR MORE ERROR CHECKS
4378 013162 104000          JMP    260$          ;GO TO 260$ IF ERROR WAS FOUND
4379 013164 004736          70$:
4380 013166 000137 013636          ;SETUP AND EXECUTE WRITE HEADER AND DATA COMMAND
4381 013172          MOV    #WH!GO, RMCS10          ;LOAD WRITE HEADER AND DATA
4382
4383
4384 013172 012737 000063 001400
```

```

4385 013200 012702 001540      MOV      #PUTINX+3,R2      ;EXTEND REGISTER INDEX TABLE
4386 013204 112722 000002      MOV      #RMC,(R2)+
4387 013210 112722 000004      MOV      #RMB,(R2)+
4388 013214 112722 000000      MOV      #RMC$1,(R2)+
4389 013220 112722 000200      MOV      #200,(R2)+
4390 013224 004737 037766      JSR      PC,PUT      ;GO WRITE REGISTERS VIA PUT SUB
4391 013230 000404      BR      80$      ;GO TO 80$ IF NO ERROR
4392 013232 000240      NOP      ;RETURN HERE IF ERROR
4393 013234 104000      ERROR     ;ERROR DEFINED BY PUT SUB
4394 013236 000137 013636      JMP      260$     ;GO TO 260$ IF ERROR WAS FOUND
4395 013242
4396
4397      ;WAIT FOR WRITE COMMAND TO COMPLETE AND READ STATUS
4398 013242 004737 040326      JSR      PC,TIMOUT     ;WAIT FOR COMMAND TO COMPLETE
4399 013246 004737 037516      JSR      PC,GET      ;GO READ REGISTERS VIA GET SUB
4400 013252 000404      BR      90$      ;GO TO 90$ IF NO ERROR
4401 013254 000240      NOP      ;RETURN HERE IF ERROR
4402 013256 104000      ERROR     ;ERROR DEFINED BY GET SUB
4403 013260 000137 013636      JMP      260$     ;GO TO 260$ IF ERROR WAS FOUND
4404 013264
4405
4406      ;VERIFY RESULTS OF WRITE COMMAND
4407 013264 004737 040512      JSR      PC,PRIERR     ;GO CHECK FOR PRIMARY ERRORS
4408 013270 000405      BR      100$     ;GO TO 100$ IF NO ERROR
4409 013272 000240      NOP      ;RETURN HERE IF ERROR
4410 013274 104000      ERROR     ;ERROR # DEFINED BY PRIERR SUBROUTINE
4411 013276 004736      JSR      PC,@(SP)+    ;GO BACK FOR MORE ERROR CHECKS
4412 013300 000137 013636      JMP      260$     ;GO TO 260$ IF ERROR WAS FOUND
4413 013304
4414 013304 004737 053016      JSR      PC,DASTS     ;GO VERIFY RESULTS OF DATA TRANSFER
4415 013310 000405      BR      110$     ;GO TO 110$ IF NO ERROR
4416 013312 000240      NOP      ;RETURN HERE IF ERROR
4417 013314 104000      ERROR     ;ERROR # DEFINED BY DASTS SUBROUTINE
4418 013316 004736      JSR      PC,@(SP)+    ;GO BACK FOR MORE ERROR CHECKS
4419 013320 000137 013636      JMP      260$     ;GO TO 260$ IF ERROR WAS FOUND
4420 013324
4421 013324 004737 041344      JSR      PC,SECERR     ;GO CHECK FOR SECONDARY ERRORS
4422 013330 000405      BR      120$     ;GO TO 120$ IF NO ERROR
4423 013332 000240      NOP      ;RETURN HERE IF ERROR
4424 013334 104000      ERROR     ;ERROR # DEFINED BY SECERR SUBROUTINE
4425 013336 004736      JSR      PC,@(SP)+    ;GO BACK FOR MORE ERROR CHECKS
4426 013340 000137 013636      JMP      260$     ;GO TO 260$ IF ERROR WAS FOUND
4427 013344
4428
4429      ;ALTER DATA BUFFER
4430 013344 005137 104566      COM      BU$TWO-2      ;COMPLEMENT LAST DATA WORD
4431
4432
4433      ;SETUP AND WRITE CHECK HEADER AND DATA COMMAND
4434 013350 012737 000053 001400      MOV      #WCH!GO,RMC$10    ;LOAD COMMAND
4435 013356 004737 037766      JSR      PC,PUT      ;GO WRITE REGISTERS VIA PUT SUB
4436 013362 000404      BR      180$     ;GO TO 180$ IF NO ERROR
4437 013364 000240      NOP      ;RETURN HERE IF ERROR
4438 013366 104000      ERROR     ;ERROR DEFINED BY PUT SUB
4439 013370 000137 013636      JMP      260$     ;GO TO 260$ IF ERROR WAS FOUND
4440 013374
4441
```


CZRMDCO RM03/2 FCTNL TST 2
CZRMDC.P11 12-DEC-78 08:24

MACY11 30A(1052) 04-JAN-79 11:23 PAGE 94
T10 FORMAT CHECK ZEROS W/ WCE ERROR

SEQ 0094

```
4441
4442
4443 013374 004737 040326
4444 013400 004737 037516
4445 013404 000404
4446 013406 000240
4447 013410 104000
4448 013412 000137 013636
4449 013416
4450
4451
4452 013416 004737 040512
4453 013422 000405
4454 013424 000240
4455 013426 104000
4456 013430 004736
4457 013432 000137 013636
4458 013436
4459

;WAIT FOR WRITE CHECK COMMAND TO COMPLETE AND READ STATUS
JSR PC, TIMEOUT ;WAIT FOR COMMAND TO COMPLETE
JSR PC, GET ;GO READ REGISTERS VIA GET SUB
BR 190$ ;GO TO 190$ IF NO ERROR
NOP ;RETURN HERE IF ERROR
ERROR ;ERROR DEFINED BY GET SUB
JMP 260$ ;GO TO 260$ IF ERROR WAS FOUND

190$:

;CHECK FOR PRIMARY ERRORS
JSR PC, PRIERR ;GO CHECK FOR PRIMARY ERRORS
BR 200$ ;GO TO 200$ IF NO ERROR
NOP ;RETURN HERE IF ERROR
ERROR ;ERROR # DEFINED BY PRIERR SUBROUTINE
JSR PC, @ (SP)+ ;GO BACK FOR MORE ERROR CHECKS
JMP 260$ ;GO TO 260$ IF ERROR WAS FOUND

200$:
```

```
4460 ;MAKE SURE THE WRITE CHECK ERROR WAS DETECTED
4461 013436 032737 040000 001340 BIT #WCE,RMCS21 ;IS WRITE CHECK ERROR SET??
4462 013444 001023 BNE 210$ ;YES!!
4463 013446 004737 053016 JSR PC,DTASTS ;GO VERIFY RESULTS OF DATA TRANSFER
4464 013452 000405 BR 205$ ;GO TO 205$ IF NO ERROR
4465 013454 000240 NOP ;RETURN HERE IF ERROR
4466 013456 104000 ERROR ;ERROR # DEFINED BY DTASTS SUBROUTINE
4467 013460 004736 JSR PC,@(SP)+ ;GO BACK FOR MORE ERROR CHECKS
4468 013462 000137 013636 JMP 260$ ;GO TO 260$ IF ERROR WAS FOUND
4469 013466 013737 001340 001140 205$: MOV RMCS21,$GDDAT ;LOAD EXPECTED STATUS
4470 013474 052737 040000 001140 BIS #WCE,$GDDAT
4471 013502 013737 001340 001142 MOV RMCS21,$BDDAT ;LOAD RECEIVED STATUS
4472 013510 104337 ERROR 337 ;WRITE CHECK ERROR NOT DETECTED
4473 013512 000451 BR 260$
4474 013514 210$:
4475
4476 ;VERIFY THE ADDRESS OF THE WRITE CHECK ERROR
4477 013514 012737 104566 001134 MOV #BUFTWO-2,$GDADR ;LOAD EXPECTED ADDRESS
4478 013522 013737 001334 001136 MOV RMBA1,$BDADR ;LOAD RECEIVED ADDRESS
4479 013530 162737 000002 001136 SUB #2,$BDADR ;DECREMENT RECEIVED ADDRESS
4480
4481 ;GET WCE DATA AND VERIFY IT IS OK
4482 013536 112737 000022 001506 MOVB #RMDB,GETINX ;SETUP FOR READING RMDB
4483 013544 112737 000200 001507 MOVB #200,GETINX+1
4484 013552 004737 037516 JSR PC,GET ;GO READ REGISTERS VIA GET SUB
4485 013556 000404 BR 230$ ;GO TO 230$ IF NO ERROR
4486 013560 000240 NOP ;RETURN HERE IF ERROR
4487 013562 104000 ERROR ;ERROR DEFINED BY GET SUB
4488 013564 000137 013636 JMP 260$ ;GO TO 260$ IF ERROR WAS FOUND
4489 013570 013737 001352 001142 230$: MOV RMDB1,$BDDAT ;LOAD RECEIVED DATA WORD
4490 013576 013737 104566 001140 MOV BUFTWO-2,$GDDAT ;LOAD EXPECTED DATA WORD
4491 013604 005137 001140 COM $GDDAT
4492 013610 023737 001134 001136 CMP $GDADR,$BDADR ;IS ADDRESS OK??
4493 013616 001402 BEQ 220$ ;YES!!
4494 013620 104340 ERROR 340 ;ADDRESS OF WCE INCORRECT
4495 013622 000405 BR 260$
4496 013624 023737 001140 001142 220$: CMP $GDDAT,$BDDAT ;IS DATA WORD OK??
4497 013632 001401 BEQ 260$ ;YES!!
4498 013634 104341 ERROR 341 ;UNEXPECTED WCE DATA
4499 013636 260$:
4500
4501 ;*****
4502 ;*TEST 11 FORMAT ONES - 16
4503 ;*****
4504 TST11:
4505 013636 000004 SCOPE ;SCOPE CALL
4506 013640 000240 NOP ;START OF TEST
4507 013642 012706 001100 MOV #STACK,SP ;INITIALIZE STACK POINTER
4508 013646 013700 001276 MOV $BASE,R0 ;R0=UNIBUS ADDRESS
4509 013652 013701 001450 MOV TSTQUE,R1 ;(R1) = DEVICE BEING TESTED
4510 013656 012737 000011 001226 MOV #11,$TESTN ;SET TEST NUMBER IN APT MAIL BOX
4511 013664 10$:
4512
4513 ;SETUP PARAMETERS FOR GENERATING DATA BUFFER
4514 013664 012737 000000 001434 MOV #0,RMDCO ;CYLINDER = 0
4515 013672 012737 000000 001406 MOV #0,RMDAO ;TRACK = SECTOR = 0
```



```
4516 013700 012737 010000 001432      MOV    #FMT16,RMOFO      ;16 BIT FORMAT
4517 013706 012737 177376 001402      MOV    #<^C<2+256.>+1>,RMWCO    ;2 + 256 WORDS
4518 013714 012737 103564 001404      MOV    #BUFONE,RMBAO      ;DATA BUFFER ADDRESS
4519 013722 012737 000062 001400      MOV    #WH,RMCS10      ;WRITE HEADER AND DATA
4520 013730 012737 065042 001174      MOV    #ONES,$TMP0      ;USE ALL ONES DATA PATTERN
4521 013736 012737 000001 001176      MOV    #1,$TMP1
4522 013744 004737 036620      JSR     PC,GENBUF        ;GO GENERATE DATA BUFFER
4523 013750
4524
4525      20$:
;PREPARE DEVICE FOR DATA TRANSFER
4526 013750 004737 034000      JSR     PC,TSTPRP      ;PREPARE DEVICE , TEST
4527 013754 154130      .WORD    154130      ;TASK DESCRIPTOR
4528 013756 000404      BR      30$          ;GO TO 30$ IF NO ERROR
4529 013760 000240      NOP
4530 013762 104000      ERROR    ;RETURN HERE IF ERROR
4531 013764 000137 014436      JMP     180$         ;ERROR # DEFINED BY TSTPRP SUBROUTINE
4532 013770
4533      30$:
;SETUP PARAMETERS AND EXECUTE SEEK TO GET DRIVE ON CYLINDER
4534
4535 013770 012737 000005 001400      MOV    #SEEK!GO,RMCS10    ;CHANGE COMMAND TO SEEK
4536 013776 012702 001535      MOV    #PUTINX,R2        ;WRITE REGISTER INDEX TABLE
4537 014002 112722 000006      MOV     #RMDA,(R2)+
4538 014006 112722 000034      MOV     #RMDC,(R2)+
4539 014012 112722 000032      MOV     #RMOF,(R2)+
4540 014016 112722 000000      MOV     #RMCS1,(R2)+
4541 014022 112722 000200      MOV     #200,(R2)+
4542 014026 004737 037766      JSR     PC,PUT          ;GO WRITE REGISTERS VIA PUT SUB
4543 014032 000404      BR      40$          ;GO TO 40$ IF NO ERROR
4544 014034 000240      NOP
4545 014036 104000      ERROR    ;RETURN HERE IF ERROR
4546 014040 000137 014436      JMP     180$         ;ERROR DEFINED BY PUT SUB
4547 014044
4548      40$:
;SETUP FOR READING STATUS AND THEN WAIT FOR SEEK TO COMPLETE
4549
4550 014044 004737 037432      JSR     PC,GETSTS      ;SETUP FOR STATUS
4551 014050 004737 040326      JSR     PC,TIMOUT      ;WAIT FOR SEEK TO COMPLETE
4552 014054
4553      50$:
;GO READ SEEK STATUS
4554
4555 014054 004737 037516      JSR     PC,GET          ;GO READ REGISTERS VIA GET SUB
4556 014060 000404      BR      60$          ;GO TO 60$ IF NO ERROR
4557 014062 000240      NOP
4558 014064 104000      ERROR    ;RETURN HERE IF ERROR
4559 014066 000137 014436      JMP     180$         ;ERROR DEFINED BY GET SUB
4560 014072
4561      60$:
;VERIFY THE RESULTS OF THE SEEK COMMAND
4562
4563 014072 004737 045420      JSR     PC,SEKSTS      ;GO VERIFY RESULTS OF SEEK OPERATION
4564 014076 000405      BR      70$          ;GO TO 70$ IF NO ERROR
4565 014100 000240      NOP
4566 014102 104000      ERROR    ;RETURN HERE IF ERROR
4567 014104 004736      JSR     PC,@(SP)+    ;ERROR # DEFINED BY SEKSTS SUBROUTINE
4568 014106 000137 014436      JMP     180$         ;GO BACK FOR MORE ERROR CHECKS
4569 014112
4570      70$:
;SETUP AND EXECUTE WRITE HEADER AND DATA COMMAND
4571
```

```

4572 014112 012737 000063 001400      MOV      #WH!GO,RMCS10      ;LOAD WRITE HEADER AND DATA
4573 014120 012702 001540      MOV      #PUTINX+3,R2      ;EXTEND REGISTER INDEX TABLE
4574 014124 112722 000002      MOV      #RMWC,(R2)+
4575 014130 112722 000004      MOV      #RMB A,(R2)+
4576 014134 112722 000000      MOV      #RMCS1,(R2)+
4577 014140 112722 000200      MOV      #200,(R2)+
4578 014144 004737 037766      JSR      PC,PUT      ;GO WRITE REGISTERS VIA PUT SUB
4579 014150 000404      BR      80$      ;GO TO 80$ IF NO ERROR
4580 014152 000240      NOP      ;RETURN HERE IF ERROR
4581 014154 104000      ERROR   ;ERROR DEFINED BY PUT SUB
4582 014156 000137 014436      JMP      180$      ;GO TO 180$ IF ERROR WAS FOUND
4583 014162
4584
4585      ;WAIT FOR WRITE COMMAND TO COMPLETE AND READ STATUS
4586 014162 004737 040326      JSR      PC,TIMOUT      ;WAIT FOR COMMAND TO COMPLETE
4587 014166 004737 037516      JSP      PC,GET      ;GO READ REGISTERS VIA GET SUB
4588 014172 000404      BR      90$      ;GO TO 90$ IF NO ERROR
4589 014174 000240      NOP      ;RETURN HERE IF ERROR
4590 014176 104000      ERROR   ;ERROR DEFINED BY GET SUB
4591 014200 000137 014436      JMP      180$      ;GO TO 180$ IF ERROR WAS FOUND
4592 014204
4593
4594      ;VERIFY RESULTS OF WRITE COMMAND
4595 014204 004737 040512      JSR      PC,PRIERR      ;GO CHECK FOR PRIMARY ERRORS
4596 014210 000405      BR      100$      ;GO TO 100$ IF NO ERROR
4597 014212 000240      NOP      ;RETURN HERE IF ERROR
4598 014214 104000      ERROR   ;ERROR # DEFINED BY PRIERR SUBROUTINE
4599 014216 004736      JSR      PC,@(SP)+      ;GO BACK FOR MORE ERROR CHECKS
4600 014220 000137 014436      JMP      180$      ;GO TO 180$ IF ERROR WAS FOUND
4601 014224
4602 014224 004737 053016      JSR      PC,DASTS      ;GO VERIFY RESULTS OF DATA TRANSFER
4603 014230 000405      BR      110$      ;GO TO 110$ IF NO ERROR
4604 014232 000240      NOP      ;RETURN HERE IF ERROR
4605 014234 104000      ERROR   ;ERROR # DEFINED BY DASTS SUBROUTINE
4606 014236 004736      JSR      PC,@(SP)+      ;GO BACK FOR MORE ERROR CHECKS
4607 014240 000137 014436      JMP      180$      ;GO TO 180$ IF ERROR WAS FOUND
4608 014244
4609 014244 004737 041344      JSR      PC,SECERR      ;GO CHECK FOR SECONDARY ERRORS
4610 014250 000405      BR      120$      ;GO TO 120$ IF NO ERROR
4611 014252 000240      NOP      ;RETURN HERE IF ERROR
4612 014254 104000      ERROR   ;ERROR # DEFINED BY SECERR SUBROUTINE
4613 014256 004736      JSR      PC,@(SP)+      ;GO BACK FOR MORE ERROR CHECKS
4614 014260 000137 014436      JMP      180$      ;GO TO 180$ IF ERROR WAS FOUND
4615 014264
4616
4617
4618      ;READ HEADER AND DATA FOR SECTOR JUST WRITTEN
4619 014264 012737 000073 001400      MOV      #RH!GO,RMCS10      ;READ HEADER & DATA COMMAND
4620 014272 012737 104570 001404      MOV      #BUFTWO,RMBA0      ;CHANGE BUS ADDRESS
4621 014300 004737 037766      JSR      PC,PUT      ;GO WRITE REGISTERS VIA PUT SUB
4622 014304 000404      BR      130$      ;GO TO 130$ IF NO ERROR
4623 014306 000240      NOP      ;RETURN HERE IF ERROR
4624 014310 104000      ERROR   ;ERROR DEFINED BY PUT SUB
4625 014312 000137 014436      JMP      180$      ;GO TO 180$ IF ERROR WAS FOUND
4626 014316
4627

```

```
4628 ;WAIT FOR READ TO COMPLETE AND GET STATUS
4629 014316 004737 040326 JSR PC,TIMOUT ;WAIT FOR READ TO COMPLETE
4630 014322 004737 037516 JSR PC,GET ;GO READ REGISTERS VIA GET SUB
4631 014326 000404 BR 140$ ;GO TO 140$ IF NO ERROR
4632 014330 000240 NOP ;RETURN HERE IF ERROR
4633 014332 104000 ERROR ;ERROR DEFINED BY GET SUB
4634 014334 000137 014436 JMP 180$ ;GO TO 180$ IF ERROR WAS FOUND
4635 014340
4636
4637 ;VERIFY THE RESULTS OF READ OPERATION
4638 014340 004737 040512 JSR PC,PRIERR ;GO CHECK FOR PRIMARY ERRORS
4639 014344 000405 BR 150$ ;GO TO 150$ IF NO ERROR
4640 014346 000240 NOP ;RETURN HERE IF EPROR
4641 014350 104000 ERROR ;ERROR # DEFINED BY PRIERR SUBROUTINE
4642 014352 004736 JSR PC,@(SP)+ ;GO BACK FOR MORE ERROR CHECKS
4643 014354 000137 014436 JMP 180$ ;GO TO 180$ IF ERROR WAS FOUND
4644 014360
4645 014360 004737 053016 JSR PC,DASTS ;GO VERIFY RESULTS OF DATA TRANSFER
4646 014364 000405 BR 160$ ;GO TO 160$ IF NO ERROR
4647 014366 000240 NOP ;RETURN HERE IF ERROR
4648 014370 104000 ERROR ;ERROR # DEFINED BY DASTS SUBROUTINE
4649 014372 004736 JSR PC,@(SP)+ ;GO BACK FOR MORE ERROR CHECKS
4650 014374 000137 014436 JMP 180$ ;GO TO 180$ IF ERROR WAS FOUND
4651 014400
4652 014400 004737 041344 JSR PC,SECERR ;GO CHECK FOR SECONDARY ERRORS
4653 014404 000405 BR 170$ ;GO TO 170$ IF NO ERROR
4654 014406 000240 NOP ;RETURN HERE IF ERROR
4655 014410 104000 ERROR ;ERROR # DEFINED BY SECERR SUBROUTINE
4656 014412 004736 JSR PC,@(SP)+ ;GO BACK FOR MORE EPROR CHECKS
4657 014414 000137 014436 JMP 180$ ;GO TO 180$ IF ERROR WAS FOUND
4658 014420
4659
4660 ;VERIFY DATA
4661 014420 004737 037064 JSR PC,CMPBUF ;GO COMPARE WRITE, READ DATA BUFFERS
4662 014424 103564 .WORD BUFONE ;STARTING ADDRESS OF WRITE BUFFER
4663 014426 104570 .WORD BUFTWO ;STARTING ADDRESS OF READ BUFFER
4664 014430 000402 BR 180$ ;GO TO 180$ IF NO ERROR
4665 014432 000240 NOP ;RETURN HERE IF ERROR
4666 014434 104000 ERROR ;ERROR # DEFINED BY CMPBUF SUBROUTINE
4667 014436
4668
4669 ;*****
4670 ;*TEST 12 FORMAT CHECK ONES - 16
4671 ;*****
4672 TST12:
4673 014436 000004 SCOPE ;SCOPE CALL
4674 014440 000240 NOP ;START OF TEST
4675 014442 012706 001100 MOV #STACK,SP ;INITIALIZE STACK POINTER
4676 014446 013700 001276 MOV $BASE,R0 ;R0=UNIBUS ADDRESS
4677 014452 013701 001450 MOV TSTQUE,R1 ;(R1) = DEVICE BEING TESTED
4678 014456 012737 000012 001226 MOV #12,$TESTN ;SET TEST NUMBER IN APT MAIL BOX
4679 014464
4680
4681 ;SETUP PARAMETERS FOR GENERATING DATA BUFFER
4682 014464 012737 000000 001434 MOV #0,RMDCO ;CYLINDER = 0
4683 014472 012737 000000 001406 MOV #0,RMDAO ;TRACK = SECTOR = 0
```

```

4684 014500 012737 010000 001432      MOV      #FMT16,RMOFO      ;16 BIT FORMAT
4685 014506 012737 177376 001402      MOV      #<^C<2+256.>+1>,RMWCO    ;2 + 256 WORDS
4686 014514 012737 103564 001404      MOV      #BUFONE,RMBAO      ;DATA BUFFER ADDRESS
4687 014522 012737 000062 001400      MOV      #WH,RMCS10      ;WRITE HEADER AND DATA
4688 014530 012737 065042 001174      MOV      #ONES,$TMP0      ;USE ALL ONES DATA PATTERN
4689 014536 012737 000001 001176      MOV      #1,$TMP1
4690 014544 004737 036620      JSR      PC,GENBUF      ;GO GENERATE DATA BUFFER
4691 014550
4692
4693      20$:
4694      ;PREPARE DEVICE FOR DATA TRANSFER
4695      JSR      PC,TSTPRP      ;PREPARE DEVICE FOR TEST
4696      .WORD    154130      ;TASK DESCRIPTOR
4697      BR       30$          ;GO TO 30$ IF NO ERROR
4698      NOP
4699      ERROR    ;RETURN HERE IF ERROR
4700      JMP      260$        ;ERROR # DEFINED BY TSTPRP SUBROUTINE
4701      30$:
4702      ;SETUP PARAMETERS AND EXECUTE SEEK TO GET DRIVE ON CYLINDER
4703      MOV      #SEEK!GO,RMCS10      ;CHANGE COMMAND TO SEEK
4704      MOV      #PUTINX,R2          ;WRITE REGISTER INDEX TABLE
4705      MOV      #RMDA,(R2)+
4706      MOV      #RMDC,(R2)+
4707      MOV      #RMOF,(R2)+
4708      MOV      #RMCS1,(R2)+
4709      MOV      #200,(R2)+
4710      JSR      PC,PUT          ;GO WRITE REGISTERS VIA PUT SUB
4711      BR       40$          ;GO TO 40$ IF NO ERROR
4712      NOP
4713      ERROR    ;RETURN HERE IF ERROR
4714      JMP      260$        ;ERROR DEFINED BY PUT SUB
4715      40$:
4716      ;SETUP FOR READING STATUS AND THEN WAIT FOR SEEK TO COMPLETE
4717      JSR      PC,GETSTS      ;SETUP FOR STATUS
4718      JSR      PC,TIMOUT      ;WAIT FOR SEEK TO COMPLETE
4719      50$:
4720      ;GO READ SEEK STATUS
4721      JSR      PC,GET          ;GO READ REGISTERS VIA GET SUB
4722      BR       60$          ;GO TO 60$ IF NO ERROR
4723      NOP
4724      ERROR    ;RETURN HERE IF ERROR
4725      JMP      260$        ;ERROR DEFINED BY GET SUB
4726      60$:
4727      ;VERIFY THE RESULTS OF THE SEEK COMMAND
4728      JSR      PC,SEKSTS      ;GO VERIFY RESULTS OF SEEK OPERATION
4729      BR       70$          ;GO TO 70$ IF NO ERROR
4730      NOP
4731      ERROR    ;RETURN HERE IF ERROR
4732      JSR      PC,@(SP)+      ;ERROR # DEFINED BY SEKSTS SUBROUTINE
4733      JMP      260$        ;GO BACK FOR MORE ERROR CHECKS
4734      70$:
4735      ;SETUP AND EXECUTE WRITE HEADER AND DATA COMMAND
4736
4737
4738
4739

```

4740 014712 012737 000063 001400 MOV #WH!GO,RMCS10 ;LOAD WRITE HEADER AND DATA
4741 014720 012702 001540 MOV #PUTINX+3,R2 ;EXTEND REGISTER INDEX TABLE
4742 014724 112722 000002 MOVB #RMWC,(R2)+
4743 014730 112722 000004 MOVB #RMBB,(R2)+
4744 014734 112722 000000 MOVB #RMCS1,(R2)+
4745 014740 112722 000200 MOVB #200,(R2)+
4746 014744 004737 037766 JSR PC,PUT ;GO WRITE REGISTERS VIA PUT SUB
4747 014750 000404 BR 80\$;GO TO 80\$ IF NO ERROR
4748 014752 000240 NOP ;RETURN HERE IF ERROR
4749 014754 104000 ERROR ;ERROR DEFINED BY PUT SUB
4750 014756 000137 015212 JMP 260\$;GO TO 260\$ IF ERROR WAS FOUND
4751 014762 80\$:
4752
4753 ;WAIT FOR WRITE COMMAND TO COMPLETE AND READ STATUS
4754 014762 004737 040326 JSR PC,TIMOUT ;WAIT FOR COMMAND TO COMPLETE
4755 014766 004737 037516 JSR PC,GET ;GO READ REGISTERS VIA GET SUB
4756 014772 000404 BR 90\$;GO TO 90\$ IF NO ERROR
4757 014774 000240 NOP ;RETURN HERE IF ERROR
4758 014776 104000 ERROR ;ERROR DEFINED BY GET SUB
4759 015000 000137 015212 JMP 260\$;GO TO 260\$ IF ERROR WAS FOUND
4760 015004 90\$:
4761
4762 ;VERIFY RESULTS OF WRITE COMMAND
4763 015004 004737 040512 JSR PC,PRIERR ;GO CHECK FOR PRIMARY ERRORS
4764 015010 000405 BR 100\$;GO TO 100\$ IF NO ERROR
4765 015012 000240 NOP ;RETURN HERE IF ERROR
4766 015014 104000 ERROR ;ERROR # DEFINED BY PRIERR SUBROUTINE
4767 015016 004736 JSR PC,@(SP)+ ;GO BACK FOR MORE ERROR CHECKS
4768 015020 000137 015212 JMP 260\$;GO TO 260\$ IF ERROR WAS FOUND
4769 015024 100\$:
4770 015024 004737 053016 JSR PC,DTASTS ;GO VERIFY RESULTS OF DATA TRANSFER
4771 015030 000405 BR 110\$;GO TO 110\$ IF NO ERROR
4772 015032 000240 NOP ;RETURN HERE IF ERROR
4773 015034 104000 ERROR ;ERROR # DEFINED BY DTASTS SUBROUTINE
4774 015036 004736 JSR PC,@(SP)+ ;GO BACK FOR MORE ERROR CHECKS
4775 015040 000137 015212 JMP 260\$;GO TO 260\$ IF ERROR WAS FOUND
4776 015044 110\$:
4777 015044 004737 041344 JSR PC,SECERR ;GO CHECK FOR SECONDARY ERRORS
4778 015050 000405 BR 120\$;GO TO 120\$ IF NO ERROR
4779 015052 000240 NOP ;RETURN HERE IF ERROR
4780 015054 104000 ERROR ;ERROR # DEFINED BY SECERR SUBROUTINE
4781 015056 004736 JSR PC,@(SP)+ ;GO BACK FOR MORE ERROR CHECKS
4782 015060 000137 015212 JMP 260\$;GO TO 260\$ IF ERROR WAS FOUND
4783 015064 120\$:
4784
4785
4786 ;WRITE CHECK HEADER AND DATA FOR SECTOR JUST WRITTEN
4787 015064 012737 000053 001400 MOV #WCH!GO,RMCS10 ;WRITE CHECK COMMAND
4788 015072 004737 037766 JSR PC,PUT ;GO WRITE REGISTERS VIA PUT SUB
4789 015076 000404 BR 130\$;GO TO 130\$ IF NO ERROR
4790 015100 000240 NOP ;RETURN HERE IF ERROR
4791 015102 104000 ERROR ;ERROR DEFINED BY PUT SUB
4792 015104 000137 015212 JMP 260\$;GO TO 260\$ IF ERROR WAS FOUND
4793 015110 130\$:
4794
4795 ;WAIT FOR WRITE CHECK TO COMPLETE AND GET STATUS

```
4796 015110 004737 040326      JSR    PC,TIMOUT      ;WAIT FOR READ TO COMPLETE
4797 015114 004737 037516      JSR    PC,GET        ;GO READ REGISTERS VIA GET SUB
4798 015120 000404              BR     140$          ;GO TO 140$ IF NO ERROR
4799 015122 000240              NOP                     ;RETURN HERE IF ERROR
4800 015124 104000              ERROR                   ;ERROR # DEFINED BY GET SUB
4801 015126 000137 015212      JMP     260$          ;GO TO 260$ IF ERROR WAS FOUND
4802 015132              140$:
4803
4804      ;VERIFY THE RESULTS OF WRITE CHECK OPERATION
4805 015132 004737 040512      JSR    PC,PRIERR      ;GO CHECK FOR PRIMARY ERRORS
4806 015136 000405              BR     150$          ;GO TO 150$ IF NO ERROR
4807 015140 000240              NOP                     ;RETURN HERE IF ERROR
4808 015142 104000              ERROR                   ;ERROR # DEFINED BY PRIERR SUBROUTINE
4809 015144 004736              JSR    PC,@(SP)+        ;GO BACK FOR MORE ERROR CHECKS
4810 015146 000137 015212      JMP     260$          ;GO TO 260$ IF ERROR WAS FOUND
4811 015152              150$:
4812 015152 004737 053016      JSR    PC,DASTS        ;GO VERIFY RESULTS OF DATA TRANSFER
4813 015156 000405              BR     160$          ;GO TO 160$ IF NO ERROR
4814 015160 000240              NOP                     ;RETURN HERE IF ERROR
4815 015162 104000              ERROR                   ;ERROR # DEFINED BY DASTS SUBROUTINE
4816 015164 004736              JSR    PC,@(SP)+        ;GO BACK FOR MORE ERROR CHECKS
4817 015166 000137 015212      JMP     260$          ;GO TO 260$ IF ERROR WAS FOUND
4818 015172              160$:
4819 015172 004737 041344      JSR    PC,SECERR      ;GO CHECK FOR SECONDARY ERRORS
4820 015176 000405              BR     170$          ;GO TO 170$ IF NO ERROR
4821 015200 000240              NOP                     ;RETURN HERE IF ERROR
4822 015202 104000              ERROR                   ;ERROR # DEFINED BY SECERR SUBROUTINE
4823 015204 004736              JSR    PC,@(SP)+        ;GO BACK FOR MORE ERROR CHECKS
4824 015206 000137 015212      JMP     260$          ;GO TO 260$ IF ERROR WAS FOUND
4825 015212              170$:
4826
4827 015212              260$:
4828
4829      ;*****
4830      ;*TEST 13      FORMAT CHECK ONES W/ WCE ERRORS
4831      ;*****
4832      TST13:
4833 015212 000004              SCOPE                  ;SCOPE CALL
4834 015214 000240              NOP                     ;START OF TEST
4835 015216 012706 001100      MOV     #STACK,SP        ;INITIALIZE STACK POINTER
4836 015222 013700 001276      MOV     $BASE,R0         ;R0=UNIBUS ADDRESS
4837 015226 013701 001450      MOV     TSTQUE,R1        ;(R1) = DEVICE BEING TESTED
4838 015232 012737 000013 001226  MOV     #13,$TESTN    ;SET TEST NUMBER IN APT MAIL BOX
4839 015240              10$:
4840
4841      ;SETUP PARAMETERS FOR GENERATING DATA BUFFER
4842 015240 012737 000000 001434  MOV     #0,RMDCO      ;CYLINDER = 0
4843 015246 012737 000000 001406  MOV     #0,RMDAO      ;TRACK = SECTOR = 0
4844 015254 012737 010000 001432  MOV     #FMT16,RMOFO    ;16 BIT FORMAT
4845 015262 012737 177376 001402  MOV     #<^C<2+256.>+1>,RMWCO ;2 + 256 WORDS
4846 015270 012737 103564 001404  MOV     #BUFONE,RMBAO   ;DATA BUFFER ADDRESS
4847 015276 012737 000062 001400  MOV     #WH,RMC$IO    ;WRITE HEADER AND DATA
4848 015304 012737 065042 001174  MOV     #ONES,$TMPO   ;USE ALL ONES DATA PATTERN
4849 015312 012737 000001 001176  MOV     #1,$TMP1
4850 015320 004737 036620              JSR    PC,GENBUF      ;GO GENERATE DATA BUFFER
4851 015324              20$:
```



```

4852
4853 ;PREPARE DEVICE FOR DATA TRANSFER
4854 015324 004737 034000 JSR PC,TSTPRP ;PREPARE DEVICE FOR TEST
4855 015330 154130 .WORD 154130 ;TASK DESCRIPTOR
4856 015332 000404 BR 30$ ;GO TO 30$ IF NO ERROR
4857 015334 000240 NOP ;RETURN HERE IF ERROR
4858 015336 104000 ERROR ;ERROR # DEFINED BY TSTPRP SUBROUTINE
4859 015340 000137 016130 JMP 260$ ;GO TO 260$ IF ERROR WAS FOUND
4860 015344
4861 30$:
4862 ;SETUP PARAMETERS AND EXECUTE SEEK TO GET DRIVE ON CYLINDER
4863 015344 012737 000005 001400 MOV #SEEK!GO,RMCS10 ;CHANGE COMMAND TO SEEK
4864 015352 012702 001535 MOV #PUTINX,R2 ;WRITE REGISTER INDEX TABLE
4865 015356 112722 000006 MOV #RMDA,(R2)+
4866 015362 112722 000034 MOV #RMDC,(R2)+
4867 015366 112722 000032 MOV #RMOF,(R2)+
4868 015372 112722 000000 MOV #RMCS1,(R2)+
4869 015376 112722 000200 MOV #200,(R2)+
4870 015402 004737 037766 JSR PC,PUT ;GO WRITE REGISTERS VIA PUT SUB
4871 015406 000404 BR 40$ ;GO TO 40$ IF NO ERROR
4872 015410 000240 NOP ;RETURN HERE IF ERROR
4873 015412 104000 ERROR ;ERROR DEFINED BY PUT SUB
4874 015414 000137 016130 JMP 260$ ;GO TO 260$ IF ERROR WAS FOUND
4875 015420
4876 40$:
4877 ;SETUP FOR READING STATUS AND THEN WAIT FOR SEEK TO COMPLETE
4878 015420 004737 037432 JSR PC,GETSTS ;SETUP FOR STATUS
4879 015424 004737 040326 JSR PC,TIMOUT ;WAIT FOR SEEK TO COMPLETE
4880 015430
4881 50$:
4882 ;GO READ SEEK STATUS
4883 015430 004737 037516 JSR PC,GET ;GO READ REGISTERS VIA GET SUB
4884 015434 000404 BR 60$ ;GO TO 60$ IF NO ERROR
4885 015436 000240 NOP ;RETURN HERE IF ERROR
4886 015440 104000 ERROR ;ERROR DEFINED BY GET SUB
4887 015442 000137 016130 JMP 260$ ;GO TO 260$ IF ERROR WAS FOUND
4888 015446
4889 60$:
4890 ;VERIFY THE RESULTS OF THE SEEK COMMAND
4891 015446 004737 045420 JSR PC,SEKSTS ;GO VERIFY RESULTS OF SEEK OPERATION
4892 015452 000405 BR 70$ ;GO TO 70$ IF NO ERROR
4893 015454 000240 NOP ;RETURN HERE IF ERROR
4894 015456 104000 ERROR ;ERROR # DEFINED BY SEKSTS SUBROUTINE
4895 015460 004736 JSR PC,@(SP)+ ;GO BACK FOR MORE ERROR CHECKS
4896 015462 000137 016130 JMP 260$ ;GO TO 260$ IF ERROR WAS FOUND
4897 015466
4898 70$:
4899 ;SETUP AND EXECUTE WRITE HEADER AND DATA COMMAND
4900 015466 012737 000063 001400 MOV #WH!GO,RMCS10 ;LOAD WRITE HEADER AND DATA
4901 015474 012702 001540 MOV #PUTINX+3,R2 ;EXTEND REGISTER INDEX TABLE
4902 015500 112722 000002 MOV #RMWC,(R2)+
4903 015504 112722 000004 MOV #RMBB,(R2)+
4904 015510 112722 000000 MOV #RMCS1,(R2)+
4905 015514 112722 000200 MOV #200,(R2)+
4906 015520 004737 037766 JSR PC,PUT ;GO WRITE REGISTERS VIA PUT SUB
4907 015524 000404 BR 80$ ;GO TO 80$ IF NO ERROR

```

```
4908 015526 000240      NOP      ;RETURN HERE IF ERROR
4909 015530 104000      ERROR     ;ERROR DEFINED BY PUT SUB
4910 015532 000137 016130      JMP 260$ ;GO TO 260$ IF ERROR WAS FOUND
4911 015536
4912
4913      ;WAIT FOR WRITE COMMAND TO COMPLETE AND READ STATUS
4914 015536 004737 040326      JSR PC,TIMOUT ;WAIT FOR COMMAND TO COMPLETE
4915 015542 004737 037516      JSR PC,GET ;GO READ REGISTERS VIA GET SUB
4916 015546 000404      BR 90$ ;GO TO 90$ IF NO ERROR
4917 015550 000240      NOP      ;RETURN HERE IF ERROR
4918 015552 104000      ERROR     ;ERROR DEFINED BY GET SUB
4919 015554 000137 016130      JMP 260$ ;GO TO 260$ IF ERROR WAS FOUND
4920 015560
4921
4922      ;VERIFY RESULTS OF WRITE COMMAND
4923 015560 004737 040512      JSR PC,PRIERR ;GO CHECK FOR PRIMARY ERRORS
4924 015564 000405      BR 100$ ;GO TO 100$ IF NO ERROR
4925 015566 000240      NOP      ;RETURN HERE IF ERROR
4926 015570 104000      ERROR     ;ERROR # DEFINED BY PRIERR SUBROUTINE
4927 015572 004736      JSR PC,@(SP)+ ;GO BACK FOR MORE ERROR CHECKS
4928 015574 000137 016130      JMP 260$ ;GO TO 260$ IF ERROR WAS FOUND
4929 015600
4930 015600 004737 053016      JSR PC,DIASTS ;GO VERIFY RESULTS OF DATA TRANSFER
4931 015604 000405      BR 110$ ;GO TO 110$ IF NO ERROR
4932 015606 000240      NOP      ;RETURN HERE IF ERROR
4933 015610 104000      ERROR     ;ERROR # DEFINED BY DIASTS SUBROUTINE
4934 015612 004736      JSR PC,@(SP)+ ;GO BACK FOR MORE ERROR CHECKS
4935 015614 000137 016130      JMP 260$ ;GO TO 260$ IF ERROR WAS FOUND
4936 015620
4937 015620 004737 041344      JSR PC,SECERR ;GO CHECK FOR SECONDARY ERRORS
4938 015624 000405      BR 120$ ;GO TO 120$ IF NO ERROR
4939 015626 000240      NOP      ;RETURN HERE IF ERROR
4940 015630 104000      ERROR     ;ERROR # DEFINED BY SECERR SUBROUTINE
4941 015632 004736      JSR PC,@(SP)+ ;GO BACK FOR MORE ERROR CHECKS
4942 015634 000137 016130      JMP 260$ ;GO TO 260$ IF ERROR WAS FOUND
4943 015640
4944
4945      ;ALTER DATA BUFFER
4946 015640 005137 104566      COM BUFTWO-2 ;COMPLEMENT DATA WORD
4947
4948
4949      ;SETUP AND WRITE CHECK HEADER AND DATA COMMAND
4950 015644 012737 000053 001400      MOV #WCH!GO,RMC$10 ;LOAD COMMAND
4951 015652 004737 037766      JSR PC,PUT ;GO WRITE REGISTERS VIA PUT SUB
4952 015656 000404      BR 180$ ;GO TO 180$ IF NO ERROR
4953 015660 000240      NOP      ;RETURN HERE IF ERROR
4954 015662 104000      ERROR     ;ERROR DEFINED BY PUT SUB
4955 015664 000137 016130      JMP 260$ ;GO TO 260$ IF ERROR WAS FOUND
4956 015670
4957
4958      ;WAIT FOR WRITE CHECK COMMAND TO COMPLETE AND READ STATUS
4959 015670 004737 040326      JSR PC,TIMOUT ;WAIT FOR COMMAND TO COMPLETE
4960 015674 004737 037516      JSR PC,GET ;GO READ REGISTERS VIA GET SUB
4961 015700 000404      BR 190$ ;GO TO 190$ IF NO ERROR
4962 015702 000240      NOP      ;RETURN HERE IF ERROR
4963 015704 104000      ERROR     ;ERROR DEFINED BY GET SUB
```



```

4964 015706 000137 016130      JMP      260$      ;GO TO 260$ IF ERROR WAS FOUND
4965 015712
4966
4967
4968 015712 004737 040512      ;CHECK FOR PRIMARY ERRORS
4969 015716 000405              JSR      PC,PRIERR      ;GO CHECK FOR PRIMARY ERRORS
4970 015720 000240              BR       200$      ;GO TO 200$ IF NO ERROR
4971 015722 104000              NOP
4972 015724 004736              ERROR      ;RETURN HERE IF ERROR
4973 015726 000137 016130      JSR      PC,@(SP)+      ;ERROR # DEFINED BY PRIERR SUBROUTINE
4974 015732              JMP      260$      ;GO BACK FOR MORE ERROR CHECKS
4975
4976
4977 015732 032737 040000 001340 200$:      ;MAKE SURE THE WRITE CHECK ERROR WAS DETECTED
4978 015740 001022              BIT      #WCE,RMC$21      ;IS WRITE CHECK ERROR SET??
4979 015742 004737 053016      BNE      210$      ;YES!!
4980 015746 000405              JSR      PC,DTASTS      ;GO VERIFY RESULTS OF DATA TRANSFER
4981 015750 000240              BR       205$      ;GO TO 205$ IF NO ERROR
4982 015752 104000              NOP
4983 015754 004736              ERROR      ;RETURN HERE IF ERROR
4984 015756 000137 016130      JSR      PC,@(SP)+      ;ERROR # DEFINED BY DTASTS SUBROUTINE
4985 015762 013737 001340 001140 205$:      JMP      260$      ;GO BACK FOR MORE ERROR CHECKS
4986 015770 052737 040000 001140      MOV      RMC$21,$GDDAT      ;GO TO 260$ IF ERROR WAS FOUND
4987 015776 013737 001340 001142      BIS      #WCE,$GDDAT      ;LOAD EXPECTED STATUS
4988 016004 104337              MOV      RMC$21,$BDDAT      ;LOAD RECEIVED STATUS
4989 016006              ERROR      337      ;WRITE CHECK ERROR NOT DETECTED
4990
4991
4992 016006 012737 104566 001134      210$:      ;VERIFY THE ADDRESS OF THE WRITE CHECK ERROR
4993 016014 013737 001334 001136      MOV      #BUFTWO-2,$GDADR      ;LOAD EXPECTED ADDRESS
4994 016022 162737 000002 001136      MOV      RMB$1,$BDADR      ;LOAD RECEIVED ADDRESS
4995
4996
4997 016030 112737 000022 001506      SUB      #2,$BDADR      ;DECREMENT RECEIVED ADDRESS
4998 016036 112737 000200 001507
4999 016044 004737 037516      ;GET WCE DATA AND VERIFY IT IS OK
5000 016050 000404              MOV      #RMDB,GETINX      ;SETUP FOR READING RMDB
5001 016052 000240              MOV      #200,GETINX+1
5002 016054 104000              JSR      PC,GET      ;GO READ REGISTERS VIA GET SUB
5003 016056 000137 016130      BR       230$      ;GO TO 230$ IF NO ERROR
5004 016062 013737 001352 001142      NOP
5005 016070 013737 104566 001140      ERROR      ;RETURN HERE IF ERROR
5006 016076 005137 001140      JSR      PC,GET      ;ERROR DEFINED BY GET SUB
5007 016102 023737 001134 001136      JMP      260$      ;GO TO 260$ IF ERROR WAS FOUND
5008 016110 001402      230$:      MOV      RMDB1,$BDDAT      ;LOAD RECEIVED DATA WORD
5009 016112 104340      MOV      BUFTWO-2,$GDDAT      ;LOAD EXPECTED DATA WORD
5010 016114 000405      COM      $GDDAT
5011 016116      CMP      $GDADR,$BDADR      ;IS ADDRESS OK??
5012 016116 023737 001140 001142      BEQ      220$      ;YES!!
5013 016124 001401      ERROR      340      ;ADDRESS OF WCE INCORRECT
5014 016126 104341      BR       260$
5015 016130      220$:      CMP      $GDDAT,$BDDAT      ;IS DATA WORD OK??
5016
5017      BEQ      260$      ;YES!!
5018      ERROR      341      ;UNEXPECTED WCE DATA
5019

```

```

*****
; *TEST 14      FORMAT MULTIPLE SECTORS
*****

```

```
5020 016130
5021 016130 000004
5022 016132 000240
5023 016134 012706 001100
5024 016140 013700 001276
5025 016144 013701 001450
5026 016150 012737 000014 001226
5027 016156
5028
5029
5030 016156 012737 000000 001434
5031 016164 012737 000000 001406
5032 016172 012737 010000 001432
5033 016200 012737 176774 001402
5034 016206 012737 103564 001404
5035 016214 012737 000062 001400
5036 016222 012737 065104 001174
5037- 016230 012737 000001 001176
5038 016236 004737 036620
5039 016242
5040
5041
5042 016242 004737 034000
5043 016246 154130
5044 016250 000404
5045 016252 000240
5046 016254 104000
5047 016256 000137 016704
5048 016262
5049
5050
5051 016262 012737 000005 001400
5052 016270 012702 001535
5053 016274 112722 000006
5054 016300 112722 000034
5055 016304 112722 000032
5056 016310 112722 000000
5057 016314 112722 000200
5058 016320 004737 037706
5059 016324 000404
5060 016326 000240
5061 016330 104000
5062 016332 000137 016704
5063 016336
5064
5065
5066 016336 004737 037432
5067 016342 004737 040326
5068 016346
5069
5070
5071 016346 004737 037516
5072 016352 000404
5073 016354 000240
5074 016356 104000
5075 016360 000137 016704

TST14:
SCOPE
NOP
MOV #STACK,SP
MOV $BASE,R0
MOV TSTQUE,R1
MOV #14,$TESTN

:SCOPE CALL
:START OF TEST
:INITIALIZE STACK POINTER
:RO=UN'BUS ADDRESS
:(R1) = DEVICE BEING TESTED
::SET TEST NUMBER IN APT MAIL BOX

10$:
;SETUP PARAMETERS FOR GENERATING DATA BUFFER
MOV #0,RMDCO
MOV #0,RMDAO
MOV #FMT16,RMOFO
MOV #<^C<<2+256.>*2>+1>,RMWCO
MOV #BUFONE,RMBAO
MOV #WH,RMCS10
MOV #ZEROS,$TMP0
MOV #1,$TMP1
JSR PC,GENBUF

:CYLINDER = 0
:TRACK = SECTOR = 0
:16 B11 FORMAT
:WORD COUNT FOR 2 SECTORS
:DATA BUFFER ADDRESS
:WRITE HEADER AND DATA
:USE ALL ZEROS DATA PATTERN
:GO GENERATE DATA BUFFER

20$:
;PREPARE DEVICE FOR DATA TRANSFER
JSR PC,TSTPRP
WORD 154130
BR 30$
NOP
ERROR
JMP 180$

:PREPARE DEVICE FOR TEST
:TASK DESCRIPTOR
:GO TO 30$ IF NO ERROR
:RETURN HERE IF ERROR
:ERROR # DEFINED BY TSTPRP SUBROUTINE
:GO TO 180$ IF ERROR WAS FOUND

30$:
;SETUP PARAMETERS AND EXECUTE SEEK TO GET DRIVE ON CYLINDER
MOV #SEEK!GO,RMCS10
MOV #PUTINX,R2
MOVB #RMDA,(R2)+
MOVB #RMDC,(R2)+
MOVB #RMOF,(R2)+
MOVB #RMCS1,(R2)+
MOVB #200,(R2)+
JSR PC,PUT
BR 40$
NOP
ERROR
JMP 180$

:CHANGE COMMAND TO SEEK
:WRITE REGISTER INDEX TABLE
:GO WRITE REGISTERS VIA PUT SUB
:GO TO 40$ IF NO ERROR
:RETURN HERE IF ERROR
:ERROR DEFINED BY PUT SUB
:GO TO 180$ IF ERROR WAS FOUND

40$:
;SETUP FOR READING STATUS AND THEN WAIT FOR SEEK TO COMPLETE
JSR PC,GETSTS
JSR PC,TIMOUT

:SETUP FOR STATUS
:WAIT FOR SEEK TO COMPLETE

50$:
;GO READ SEEK STATUS
JSR PC,GET
BR 60$
NOP
ERROR
JMP 180$

:GO READ REGISTERS VIA GET SUB
:GO TO 60$ IF NO ERROR
:RETURN HERE IF ERROR
:ERROR DEFINED BY GET SUB
:GO TO 180$ IF ERROR WAS FOUND
```

```
5076 016364
5077
5078
5079 016364 004737 045420
5080 016370 000405
5081 016372 000240
5082 016374 104000
5083 016376 004736
5084 016400 000137 016704
5085 016404
5086
5087
5088 016404 012737 000063 001400
5089 016412 012702 001540
5090 016416 112722 000002
5091 016422 112722 000004
5092 016426 112722 000000
5093 016432 112722 000200
5094 016436 004737 037766
5095 016442 000404
5096 016444 000240
5097 016446 104000
5098 016450 000137 016704
5099 016454
5100
5101
5102 016454 004737 040326
5103 016460 004737 037516
5104 016464 000404
5105 016466 000240
5106 016470 104000
5107 016472 000137 016704
5108 016476
5109
5110
5111 016476 004737 040512
5112 016502 000405
5113 016504 000240
5114 016506 104000
5115 016510 004736
5116 016512 000137 016704
5117 016516
5118 016516 004737 053016
5119 016522 000405
5120 016524 000240
5121 016526 104000
5122 016530 004736
5123 016532 000137 016704
5124 016536
5125 016536 004737 041344
5126 016542 000405
5127 016544 000240
5128 016546 104000
5129 016550 004736
5130 016552 000137 016704
5131 016556

60$:
;VERIFY THE RESULTS OF THE SEEK COMMAND
JSR PC,SEKSTS ;GO VERIFY RESULTS OF SEEK OPERATION
BR 70$ ;GO TO 70$ IF NO ERROR
NOP ;RETURN HERE IF ERROR
ERROR ;ERROR # DEFINED BY SEKSTS SUBROUTINE
JSR PC,@(SP)+ ;GO BACK FOR MORE ERROR CHECKS
JMP 180$ ;GO TO 180$ IF ERROR WAS FOUND

70$:
;SETUP AND EXECUTE WRITE HEADER AND DATA COMMAND
MOV #WH!GO,RMCS10 ;LOAD WRITE HEADER AND DATA
MOV #PUTINX+3,R2 ;EXTEND REGISTER INDEX TABLE
MOVB #RMWC,(R2)+
MOVB #RMBA,(R2)+
MOVB #RMCS1,(R2)+
MOVB #200,(R2)+
JSR PC,PUT ;GO WRITE REGISTERS VIA PUT SUB
BR 80$ ;GO TO 80$ IF NO ERROR
NOP ;RETURN HERE IF ERROR
ERROR ;ERROR DEFINED BY PUT SUB
JMP 180$ ;GO TO 180$ IF ERROR WAS FOUND

80$:
;WAIT FOR WRITE COMMAND TO COMPLETE AND READ STATUS
JSR PC,TIMOUT ;WAIT FOR COMMAND TO COMPLETE
JSR PC,GET ;GO READ REGISTERS VIA GET SUB
BR 90$ ;GO TO 90$ IF NO ERROR
NOP ;RETURN HERE IF ERROR
ERROR ;ERROR DEFINED BY GET SUB
JMP 180$ ;GO TO 180$ IF ERROR WAS FOUND

90$:
;VERIFY RESULTS OF WRITE COMMAND
JSR PC,PRIERR ;GO CHECK FOR PRIMARY ERRORS
BR 100$ ;GO TO 100$ IF NO ERROR
NOP ;RETURN HERE IF ERROR
ERROR ;ERROR # DEFINED BY PRIERR SUBROUTINE
JSR PC,@(SP)+ ;GO BACK FOR MORE ERROR CHECKS
JMP 180$ ;GO TO 180$ IF ERROR WAS FOUND

100$:
JSR PC,DASTS ;GO VERIFY RESULTS OF DATA TRANSFER
BR 110$ ;GO TO 110$ IF NO ERROR
NOP ;RETURN HERE IF ERROR
ERROR ;ERROR # DEFINED BY DASTS SUBROUTINE
JSR PC,@(SP)+ ;GO BACK FOR MORE ERROR CHECKS
JMP 180$ ;GO TO 180$ IF ERROR WAS FOUND

110$:
JSR PC,SECERR ;GO CHECK FOR SECONDARY ERRORS
BR 120$ ;GO TO 120$ IF NO ERROR
NOP ;RETURN HERE IF ERROR
ERROR ;ERROR # DEFINED BY SECERR SUBROUTINE
JSR PC,@(SP)+ ;GO BACK FOR MORE ERROR CHECKS
JMP 180$ ;GO TO 180$ IF ERROR WAS FOUND

120$:
```

```
5132
5133
5134 ;WRITE CHECK HEADER AND DATA FOR SECTORS JUST WRITTEN
5135 016556 012737 000053 001400 MOV #WCH!GO,RMCS10 ;READ HEADER & DATA COMMAND
5136 016564 004737 037766 JSR PC,PUT ;GO WRITE REGISTERS VIA PUT SUB
5137 016570 000404 BR 130$ ;GO TO 130$ IF NO ERROR
5138 016572 000240 NOP ;RETURN HERE IF ERROR
5139 016574 104000 ERROR ;ERROR DEFINED BY PUT SUB
5140 016576 000137 016704 JMP 180$ ;GO TO 180$ IF ERROR WAS FOUND
5141 016602 130$:
5142
5143 ;WAIT FOR WRITE CHECK TO COMPLETE AND GET STATUS
5144 016602 004737 040326 JSR PC,TIMOUT ;WAIT FOR WRITE CHECK TO FINISH
5145 016606 004737 037516 JSR PC,GET ;GO READ REGISTERS VIA GET SUB
5146 016612 000404 BR 140$ ;GO TO 140$ IF NO ERROR
5147 016614 000240 NOP ;RETURN HERE IF ERROR
5148 016616 104000 ERROR ;ERROR DEFINED BY GET SUB
5149 016620 000137 016704 JMP 180$ ;GO TO 180$ IF ERROR WAS FOUND
5150 016624 140$:
5151
5152 ;VERIFY THE RESULTS OF WRITE CHECK OPERATION
5153 016624 004737 040512 JSR PC,PRIERR ;GO CHECK FOR PRIMARY ERRORS
5154 016630 000405 BR 150$ ;GO TO 150$ IF NO ERROR
5155 016632 000240 NOP ;RETURN HERE IF ERROR
5156 016634 104000 ERROR ;ERROR # DEFINED BY PRIERR SUBROUTINE
5157 016636 004736 JSR PC,@(SP)+ ;GO BACK FOR MORE ERROR CHECKS
5158 016640 000137 016704 JMP 180$ ;GO TO 180$ IF ERROR WAS FOUND
5159 016644 150$:
5160 016644 004737 053016 JSR PC,DASTS ;GO VERIFY RESULTS OF DATA TRANSFER
5161 016650 000405 BR 160$ ;GO TO 160$ IF NO ERROR
5162 016652 000240 NOP ;RETURN HERE IF ERROR
5163 016654 104000 ERROR ;ERROR # DEFINED BY DASTS SUBROUTINE
5164 016656 004736 JSR PC,@(SP)+ ;GO BACK FOR MORE ERROR CHECKS
5165 016660 000137 016704 JMP 180$ ;GO TO 180$ IF ERROR WAS FOUND
5166 016664 160$:
5167 016664 004737 041344 JSR PC,SECERR ;GO CHECK FOR SECONDARY ERRORS
5168 016670 000405 BR 170$ ;GO TO 170$ IF NO ERROR
5169 016672 000240 NOP ;RETURN HERE IF ERROR
5170 016674 104000 ERROR ;ERROR # DEFINED BY SECERR SUBROUTINE
5171 016676 004736 JSR PC,@(SP)+ ;GO BACK FOR MORE ERROR CHECKS
5172 016700 000137 016704 JMP 180$ ;GO TO 180$ IF ERROR WAS FOUND
5173 016704 170$:
5174 016704 180$:
5175
5176 ;*****
5177 ;*TEST 15 FORMAT W/ HEAD SWITCHING
5178 ;*****
5179 016704 TST15:
5180 016704 000004 SCOPE ;SCOPE CALL
5181 016706 000240 NOP ;START OF TEST
5182 016710 012706 001100 MOV #STACK,SP ;INITIALIZE STACK POINTER
5183 016714 013700 001276 MOV $BASE,R0 ;R0=UNIBUS ADDRESS
5184 016720 013701 001450 MOV TSTQUE,R1 ;(R1) = DEVICE BEING TESTED
5185 016724 012737 000015 001226 MOV #15,$TESTN ;SET TEST NUMBER IN APT MAIL BOX
5186 016732 10$:
5187
```

```

5188 ;SETUP PARAMETERS FOR GENERATING DATA BUFFER
5189 016732 012737 000000 001434 MOV #0,RMDCO ;CYLINDER = 0
5190 016740 012737 000037 001406 MOV #31,RMDAO ;START AT LAST SECTOR
5191 016746 012737 010000 001432 MOV #FMT16,RMOFO ;16 BIT FORMAT
5192 016754 012737 176774 001402 MOV #<^C<<2+256.>*2>+1>,RMWCO;WORD COUNT FOR 2 SECTORS
5193 016762 012737 103564 001404 MOV #BUFONE,RMBAO ;DATA BUFFER ADDRESS
5194 016770 012737 000062 001400 MOV #WH,RMCS10 ;WRITE HEADER AND DATA
5195 016776 012737 065104 001174 MOV #ZEROS,$TMP0 ;USE ALL ZEROS DATA PATTERN
5196 017004 012737 000001 001176 MOV #1,$TMP1
5197 017012 004737 036620 JSR PC,GENBUF ;GO GENERATE DATA BUFFER
5198 017016
5199
5200 ;PREPARE DEVICE FOR DATA TRANSFER
5201 017016 004737 034000 JSR PC,TSTPRP ;PREPARE DEVICE FOR TEST
5202 017022 154130 .WORD 154130 ;TASK DESCRIPTOR
5203 017024 000404 BR 30$ ;GO TO 30$ IF NO ERROR
5204 017026 000240 NOP ;RETURN HERE IF ERROR
5205 017030 104000 ERROR ;ERROR # DEFINED BY TSTPRP SUBROUTINE
5206 017032 000137 017460 JMP 180$ ;GO TO 180$ IF ERROR WAS FOUND
5207 017036
5208
5209 ;SETUP PARAMETERS AND EXECUTE SEEK TO GET DRIVE ON CYLINDER
5210 017036 012737 000005 001400 MOV #SEEK!GO,RMCS10 ;CHANGE COMMAND TO SEEK
5211 017044 012702 001535 MOV #PUTINX,R2 ;WRITE REGISTER INDEX TABLE
5212 017050 112722 000006 MOV #RMDA,(R2)+
5213 017054 112722 000034 MOV #RMDC,(R2)+
5214 017060 112722 000032 MOV #RMOF,(R2)+
5215 017064 112722 000000 MOV #RMCS1,(R2)+
5216 017070 112722 000200 MOV #200,(R2)+
5217 017074 004737 037766 JSR PC,PUT ;GO WRITE REGISTERS VIA PUT SUB
5218 017100 000404 BR 40$ ;GO TO 40$ IF NO ERROR
5219 017102 000240 NOP ;RETURN HERE IF ERROR
5220 017104 104000 ERROR ;ERROR DEFINED BY PUT SUB
5221 017106 000137 017460 JMP 180$ ;GO TO 180$ IF ERROR WAS FOUND
5222 017112
5223
5224 ;SETUP FOR READING STATUS AND THEN WAIT FOR SEEK TO COMPLETE
5225 017112 004737 037432 JSR PC,GETSTS ;SETUP FOR STATUS
5226 017116 004737 040326 JSR PC,TIMOUT ;WAIT FOR SEEK TO COMPLETE
5227 017122
5228
5229 ;GO READ SEEK STATUS
5230 017122 004737 037516 JSR PC,GET ;GO READ REGISTERS VIA GET SUB
5231 017126 000404 BR 60$ ;GO TO 60$ IF NO ERROR
5232 017130 000240 NOP ;RETURN HERE IF ERROR
5233 017132 104000 ERROR ;ERROR DEFINED BY GET SUB
5234 017134 000137 017460 JMP 180$ ;GO TO 180$ IF ERROR WAS FOUND
5235 017140
5236
5237 ;VERIFY THE RESULTS OF THE SEEK COMMAND
5238 017140 004737 045420 JSR PC,SEKSTS ;GO VERIFY RESULTS OF SEEK OPERATION
5239 017144 000405 BR 70$ ;GO TO 70$ IF NO ERROR
5240 017146 000240 NOP ;RETURN HERE IF ERROR
5241 017150 104000 ERROR ;ERROR # DEFINED BY SEKSTS SUBROUTINE
5242 017152 004736 JSR PC,@(SP)+ ;GO BACK FOR MORE ERROR CHECKS
5243 017154 000137 017460 JMP 180$ ;GO TO 180$ IF ERROR WAS FOUND

```

```
5244 017160
5245
5246
5247 017160 012737 000063 001400 ;SETUP AND EXECUTE WRITE HEADER AND DATA COMMAND
5248 017166 012702 001540      MOV      #WH!GO,RMCS10      ;LOAD WRITE HEADER AND DATA
5249 017172 112722 000002      MOV      #PUTINX+3,R2      ;EXTEND REGISTER INDEX TABLE
5250 017176 112722 000004      MOV      #RMWC,(R2)+
5251 017202 112722 000000      MOV      #RMBA,(R2)+
5252 017206 112722 000200      MOV      #RMCS1,(R2)+
5253 017212 004737 037766      MOV      #200,(R2)+
5254 017216 000404      JSR      PC,PUT      ;GO WRITE REGISTERS VIA PUT SUB
5255 017220 000240      BR      80$      ;GO TO 80$ IF NO ERROR
5256 017222 104000      NOP      ;RETURN HERE IF ERROR
5257 017224 000137 017460      ERROR   ;ERROR DEFINED BY PUT SUB
5258 017230      JMP      180$      ;GO TO 180$ IF ERROR WAS FOUND
5259
5260
5261 017230 004737 040326      ;WAIT FOR WRITE COMMAND TO COMPLETE AND READ STATUS
5262 017234 004737 037516      JSR      PC,TIMOUT      ;WAIT FOR COMMAND TO COMPLETE
5263 017240 000404      JSR      PC,GET      ;GO READ REGISTERS VIA GET SUB
5264 017242 000240      BR      90$      ;GO TO 90$ IF NO ERROR
5265 017244 104000      NOP      ;RETURN HERE IF ERROR
5266 017246 000137 017460      ERROR   ;ERROR DEFINED BY GET SUB
5267 017252      JMP      180$      ;GO TO 180$ IF ERROR WAS FOUND
5268
5269
5270 017252 004737 040512      ;VERIFY RESULTS OF WRITE COMMAND
5271 017256 000405      JSR      PC,PRIERR      ;GO CHECK FOR PRIMARY ERRORS
5272 017260 000240      BR      100$      ;GO TO 100$ IF NO ERROR
5273 017262 104000      NOP      ;RETURN HERE IF ERROR
5274 017264 004736      ERROR   ;ERROR # DEFINED BY PRIERR SUBROUTINE
5275 017266 000137 017460      JSR      PC,@(SP)+      ;GO BACK FOR MORE ERROR CHECKS
5276 017272      JMP      180$      ;GO TO 180$ IF ERROR WAS FOUND
5277 017272 004737 053016      ;GO VERIFY RESULTS OF DATA TRANSFER
5278 017276 000405      JSR      PC,DASTS      ;GO TO 110$ IF NO ERROR
5279 017300 000240      BR      110$      ;RETURN HERE IF ERROR
5280 017302 104000      NOP      ;ERROR # DEFINED BY DASTS SUBROUTINE
5281 017304 004736      ERROR   ;GO BACK FOR MORE ERROR CHECKS
5282 017306 000137 017460      JSR      PC,@(SP)+      ;GO TO 180$ IF ERROR WAS FOUND
5283 017312      JMP      180$
5284 017312 004737 041344      ;GO CHECK FOR SECONDARY ERRORS
5285 017316 000405      JSR      PC,SECERR      ;GO TO 120$ IF NO ERROR
5286 017320 000240      BR      120$      ;RETURN HERE IF ERROR
5287 017322 104000      NOP      ;ERROR # DEFINED BY SECERR SUBROUTINE
5288 017324 004736      ERROR   ;GO BACK FOR MORE ERROR CHECKS
5289 017326 000137 017460      JSR      PC,@(SP)+      ;GO TO 180$ IF ERROR WAS FOUND
5290 017332      JMP      180$
5291
5292
5293
5294 017332 012737 000053 001400 ;WRITE CHECK HEADER AND DATA FOR SECTORS JUST WRITTEN
5295 017340 004737 037766      MOV      #WCH!GO,RMCS10      ;READ HEADER & DATA COMMAND
5296 017344 000404      JSR      PC,PUT      ;GO WRITE REGISTERS VIA PUT SUB
5297 017346 000240      BR      130$      ;GO TO 130$ IF NO ERROR
5298 017350 104000      NOP      ;RETURN HERE IF ERROR
5299 017352 000137 017460      ERROR   ;ERROR DEFINED BY PUT SUB
5299      JMP      180$      ;GO TO 180$ IF ERROR WAS FOUND
```



```

5300 017356      130$:
5301
5302      ;WAIT FOR WRITE CHECK TO COMPLETE AND GET STATUS
5303 017356 004737 040326      JSR PC,TIMOUT      ;WAIT FOR WRITE CHECK TO FINISH
5304 017362 004737 037516      JSR PC,GET      ;GO READ REGISTERS VIA GET SUB
5305 017366 000404      BR 140$      ;GO TO 140$ IF NO ERROR
5306 017370 000240      NOP      ;RETURN HERE IF ERROR
5307 017372 104000      ERROR      ;ERROR DEFINED BY GET SUB
5308 017374 000137 017460      JMP 180$      ;GO TO 180$ IF ERROR WAS FOUND
5309 017400
5310
5311      140$:
5312      ;VERIFY THE RESULTS OF WRITE CHECK OPERATION
5313 017400 004737 040512      JSR PC,PRIERR      ;GO CHECK FOR PRIMARY ERRORS
5314 017404 000405      BR 150$      ;GO TO 150$ IF NO ERROR
5315 017410 000240      NOP      ;RETURN HERE IF ERROR
5316 017412 104000      ERROR      ;ERROR # DEFINED BY PRIERR SUBROUTINE
5317 017414 000137 017460      JSR PC,@(SP)+      ;GO BACK FOR MORE ERROR CHECKS
5318 017420      JMP 180$      ;GO TO 180$ IF ERROR WAS FOUND
5319 017420 004737 053016      150$:
5320 017424 000405      JSR PC,DASTS      ;GO VERIFY RESULTS OF DATA TRANSFER
5321 017426 000240      BR 160$      ;GO TO 160$ IF NO ERROR
5322 017430 104000      NOP      ;RETURN HERE IF ERROR
5323 017432 004736      ERROR      ;ERROR # DEFINED BY DASTS SUBROUTINE
5324 017434 000137 017460      JSR PC,@(SP)+      ;GO BACK FOR MORE ERROR CHECKS
5325 017440      JMP 180$      ;GO TO 180$ IF ERROR WAS FOUND
5326 017440 004737 041344      160$:
5327 017444 000405      JSR PC,SECERR      ;GO CHECK FOR SECONDARY ERRORS
5328 017446 000240      BR 170$      ;GO TO 170$ IF NO ERROR
5329 017450 104000      NOP      ;RETURN HERE IF ERROR
5330 017452 004736      ERROR      ;ERROR # DEFINED BY SECERR SUBROUTINE
5331 017454 000137 017460      JSR PC,@(SP)+      ;GO BACK FOR MORE ERROR CHECKS
5332 017460      JMP 180$      ;GO TO 180$ IF ERROR WAS FOUND
5333 017460
5334
5335      170$:
5336      180$:
5337      ;*****
5338      ;*TEST 16      FORMAT W/ MID TRANSFER SEEK
5339      ;*****
5340      TST16:
5341      SCOPE      ;SCOPE CALL
5342      NOP      ;START OF TEST
5343      MOV #STACK,SP      ;INITIALIZE STACK POINTER
5344      MOV $BASE,R0      ;R0=UNIBUS ADDRESS
5345      MOV TSTQUE,R1      ;(R1) = DEVICE BEING TESTED
5346      MOV #16,$TESTN      ;SET TEST NUMBER IN APT MAIL BOX
5347
5348      10$:
5349      ;SETUP PARAMETERS FOR GENERATING DATA BUFFER
5350      MOV #0,RMDCO      ;CYLINDER = 0
5351      MOV #002037,RMDAO      ;START AT LAST TRACK & SECTOR
5352      MOV #FMT16,RMOFO      ;16 BIT FORMAT
5353      MOV #<^C<<2+256.>*2>+1>,RMWCO      ;WORD COUNT FOR 2 SECTORS
5354      MOV #BUFONE,RMBAO      ;DATA BUFFER ADDRESS
5355      MOV #WH,RMC$10      ;WRITE HEADER AND DATA
5356      MOV #ZEROS,$TMP0      ;USE ALL ZEROS DATA PATTERN
5357      MOV #1,$TMP1

```

```
5356 017566 004737 036620      JSR      PC,GENBUF      ;GO GENERATE DATA BUFFER
5357 017572      20$:
5358
5359      ;PREPARE DEVICE FOR DATA TRANSFER
5360 017572 004737 034000      JSR      PC,TSTPRP      ;PREPARE DEVICE FOR TEST
5361 017576      .WORD      154130 ;TASK DESCRIPTOR
5362 017600 000404      BR      30$      ;GO TO 30$ IF NO ERROR
5363 017602 000240      NOP      ;RETURN HERE IF ERROR
5364 017604 104000      ERROR     ;ERROR # DEFINED BY TSTPRP SUBROUTINE
5365 017606 000137 020234      JMP      180$      ;GO TO 180$ IF ERROR WAS FOUND
5366 017612      30$:
5367
5368      ;SETUP PARAMETERS AND EXECUTE SEEK TO GET DRIVE ON CYLINDER
5369 017612 012737 000005 001400 MOV      #SEEK!GO,RMCS10      ;CHANGE COMMAND TO SEEK
5370 017620 012702 001535      MOV      #PUTINX,R2      ;WRITE REGISTER INDEX TABLE
5371 017624 112722 000006      MOV      #RMDA,(R2)+
5372 017630 112722 000034      MOV      #RMDC,(R2)+
5373 017634 112722 000032      MOV      #RMOF,(R2)+
5374 017640 112722 000000      MOV      #RMCS1,(R2)+
5375 017644 112722 000200      MOV      #200,(R2)+
5376 017650 004737 037766      JSR      PC,PUT      ;GO WRITE REGISTERS VIA PUT SUB
5377 017654 000404      BR      40$      ;GO TO 40$ IF NO ERROR
5378 017656 000240      NOP      ;RETURN HERE IF ERROR
5379 017660 104000      ERROR     ;ERROR DEFINED BY PUT SUB
5380 017662 000137 020234      JMP      180$      ;GO TO 180$ IF ERROR WAS FOUND
5381 017666      40$:
5382
5383      ;SETUP FOR READING STATUS AND THEN WAIT FOR SEEK TO COMPLETE
5384 017666 004737 037432      JSR      PC,GETSTS      ;SETUP FOR STATUS
5385 017672 004737 040326      JSR      PC,TIMOUT      ;WAIT FOR SEEK TO COMPLETE
5386 017676      50$:
5387
5388      ;GO READ SEEK STATUS
5389 017676 004737 037516      JSR      PC,GET      ;GO READ REGISTERS VIA GET SUB
5390 017702 000404      BR      60$      ;GO TO 60$ IF NO ERROR
5391 017704 000240      NOP      ;RETURN HERE IF ERROR
5392 017706 104000      ERROR     ;ERROR DEFINED BY GET SUB
5393 017710 000137 020234      JMP      180$      ;GO TO 180$ IF ERROR WAS FOUND
5394 017714      60$:
5395
5396      ;VERIFY THE RESULTS OF THE SEEK COMMAND
5397 017714 004737 045420      JSR      PC,SEKSTS      ;GO VERIFY RESULTS OF SEEK OPERATION
5398 017720 000405      BR      70$      ;GO TO 70$ IF NO ERROR
5399 017722 000240      NOP      ;RETURN HERE IF ERROR
5400 017724 104000      ERROR     ;ERROR # DEFINED BY SEKSTS SUBROUTINE
5401 017726 004736      JSR      PC,@(SP)+      ;GO BACK FOR MORE ERROR CHECKS
5402 017730 000137 020234      JMP      180$      ;GO TO 180$ IF ERROR WAS FOUND
5403 017734      70$:
5404
5405      ;SETUP AND EXECUTE WRITE HEADER AND DATA COMMAND
5406 017734 012737 000063 001400 MOV      #WH!GO,RMCS10      ;LOAD WRITE HEADER AND DATA
5407 017742 012702 001540      MOV      #PUTINX+3,R2      ;EXTEND REGISTER INDEX TABLE
5408 017746 112722 000002      MOV      #RMWC,(R2)+
5409 017752 112722 000004      MOV      #RMBB,(R2)+
5410 017756 112722 000000      MOV      #RMCS1,(R2)+
5411 017762 112722 000200      MOV      #200,(R2)+
```


5412 017766 004737 037766 JSR PC,PUT ;GO WRITE REGISTERS VIA PUT SUB
5413 017772 000404 BR 80\$;GO TO 80\$ IF NO ERROR
5414 017774 000240 NOP ;RETURN HERE IF ERROR
5415 017776 104000 ERROR ;ERROR DEFINED BY PUT SUB
5416 020000 000137 020234 JMP 180\$;GO TO 180\$ IF ERROR WAS FOUND
5417 020004 80\$:
5418
5419 ;WAIT FOR WRITE COMMAND TO COMPLETE AND READ STATUS
5420 020004 004737 040326 JSR PC,TIMOUT ;WAIT FOR COMMAND TO COMPLETE
5421 020010 004737 037516 JSR PC,GET ;GO READ REGISTERS VIA GET SUB
5422 020014 000404 BR 90\$;GO TO 90\$ IF NO ERROR
5423 020016 000240 NOP ;RETURN HERE IF ERROR
5424 020020 104000 ERROR ;ERROR DEFINED BY GET SUB
5425 020022 000137 020234 JMP 180\$;GO TO 180\$ IF ERROR WAS FOUND
5426 020026 90\$:
5427
5428 ;VERIFY RESULTS OF WRITE COMMAND
5429 020026 004737 040512 JSR PC,PRIERR ;GO CHECK FOR PRIMARY ERRORS
5430 020032 000405 BR 100\$;GO TO 100\$ IF NO ERROR
5431 020034 000240 NOP ;RETURN HERE IF ERROR
5432 020036 104000 ERROR ;ERROR # DEFINED BY PRIERR SUBROUTINE
5433 020040 004736 JSR PC,@(SP)+ ;GO BACK FOR MORE ERROR CHECKS
5434 020042 000137 020234 JMP 180\$;GO TO 180\$ IF ERROR WAS FOUND
5435 020046 100\$:
5436 020046 004737 053016 JSR PC,DASTS ;GO VERIFY RESULTS OF DATA TRANSFER
5437 020052 000405 BR 110\$;GO TO 110\$ IF NO ERROR
5438 020054 000240 NOP ;RETURN HERE IF ERROR
5439 020056 104000 ERROR ;ERROR # DEFINED BY DASTS SUBROUTINE
5440 020060 004736 JSR PC,@(SP)+ ;GO BACK FOR MORE ERROR CHECKS
5441 020062 000137 020234 JMP 180\$;GO TO 180\$ IF ERROR WAS FOUND
5442 020066 110\$:
5443 020066 004737 041344 JSR PC,SECERR ;GO CHECK FOR SECONDARY ERRORS
5444 020072 000405 BR 120\$;GO TO 120\$ IF NO ERROR
5445 020074 000240 NOP ;RETURN HERE IF ERROR
5446 020076 104000 ERROR ;ERROR # DEFINED BY SECERR SUBROUTINE
5447 020100 004736 JSR PC,@(SP)+ ;GO BACK FOR MORE ERROR CHECKS
5448 020102 000137 020234 JMP 180\$;GO TO 180\$ IF ERROR WAS FOUND
5449 020106 120\$:
5450
5451
5452 ;WRITE CHECK HEADER AND DATA FOR SECTORS JUST WRITTEN
5453 020106 012737 000053 001400 MOV #WCH!GO,RMC\$10 ;READ HEADER & DATA COMMAND
5454 020114 004737 037766 JSR PC,PUT ;GO WRITE REGISTERS VIA PUT SUB
5455 020120 000404 BR 130\$;GO TO 130\$ IF NO ERROR
5456 020122 000240 NOP ;RETURN HERE IF ERROR
5457 020124 104000 ERROR ;ERROR DEFINED BY PUT SUB
5458 020126 000137 020234 JMP 180\$;GO TO 180\$ IF ERROR WAS FOUND
5459 020132 130\$:
5460
5461 ;WAIT FOR WRITE CHECK TO COMPLETE AND GET STATUS
5462 020132 004737 040326 JSR PC,TIMOUT ;WAIT FOR WRITE CHECK TO FINISH
5463 020136 004737 037516 JSR PC,GET ;GO READ REGISTERS VIA GET SUB
5464 020142 000404 BR 140\$;GO TO 140\$ IF NO ERROR
5465 020144 000240 NOP ;RETURN HERE IF ERROR
5466 020146 104000 ERROR ;ERROR DEFINED BY GET SUB
5467 020150 000137 020234 JMP 180\$;GO TO 180\$ IF ERROR WAS FOUND

```
5468 020154
5469
5470
5471 020154 004737 040512
5472 020160 000405
5473 020162 000240
5474 020164 104000
5475 020166 004736
5476 020170 000137 020234
5477 020174
5478 020174 004737 053016
5479 020200 000405
5480 020202 000240
5481 020204 104000
5482 020206 004736
5483 020210 000137 020234
5484 020214
5485 020214 004737 041344
5486 020220 000405
5487 020222 000240
5488 020224 104000
5489 020226 004736
5490 020230 000137 020234
5491 020234
5492 020234
5493
5494
5495
5496
5497 020234
5498 020234 000004
5499 020236 000240
5500 020240 012706 001100
5501 020244 013700 001276
5502 020250 013701 001450
5503 020254 012737 000017 001226
5504 020262
5505
5506
5507 020262 012737 000000 001434
5508 020270 012737 000000 001406
5509 020276 012737 010000 001432
5510 020304 012737 176774 001402
5511 020312 012737 103564 001404
5512 020320 012737 000062 001400
5513 020326 012737 065104 001174
5514 020334 012737 000001 001176
5515 020342 004737 036620
5516 020346
5517
5518
5519 020346 004737 034000
5520 020352 154130
5521 020354 000404
5522 020356 000240
5523 020360 104000

140$:
;VERIFY THE RESULTS OF WRITE CHECK OPERATION
JSR PC,PRIERR ;GO CHECK FOR PRIMARY ERRORS
BR 150$ ;GO TO 150$ IF NO ERROR
NOP ;RETURN HERE IF ERROR
ERROR ;ERROR # DEFINED BY PRIERR SUBROUTINE
JSR PC,@(SP)+ ;GO BACK FOR MORE ERROR CHECKS
JMP 180$ ;GO TO 180$ IF ERROR WAS FOUND

150$:
JSR PC,DASTS ;GO VERIFY RESULTS OF DATA TRANSFER
BR 160$ ;GO TO 160$ IF NO ERROR
NOP ;RETURN HERE IF ERROR
ERROR ;ERROR # DEFINED BY DASTS SUBROUTINE
JSR PC,@(SP)+ ;GO BACK FOR MORE ERROR CHECKS
JMP 180$ ;GO TO 180$ IF ERROR WAS FOUND

160$:
JSR PC,SECERR ;GO CHECK FOR SECONDARY ERRORS
BR 170$ ;GO TO 170$ IF NO ERROR
NOP ;RETURN HERE IF ERROR
ERROR ;ERROR # DEFINED BY SECERR SUBROUTINE
JSR PC,@(SP)+ ;GO BACK FOR MORE ERROR CHECKS
JMP 180$ ;GO TO 180$ IF ERROR WAS FOUND

170$:
180$:

;*****
;*TEST 17 FORMAT W/ IMPLIED SEEK
;*****
TST17:
SCOPE ;SCOPE CALL
NOP ;START OF TEST
MOV #STACK,SP ;INITIALIZE STACK POINTER
MOV $BASE,R0 ;R0=UNIBUS ADDRESS
MOV TSTQUE,R1 ;(R1) = DEVICE BEING TESTED
MOV #17,$TESTN ;;SET TEST NUMBER IN APT MAIL BOX

10$:
;SETUP PARAMETERS FOR GENERATING DATA BUFFER
MOV #0,RMDCO ;CYLINDER = 0
MOV #0,RMDAO ;TRACK = SECTOR = 0
MOV #FMT16,RMOFO ;16 BIT FORMAT
MOV #<^C<<2+256.>*2>+1>,RMWCO;WORD COUNT FOR 2 SECTORS
MOV #BUFONE,RMBAO ;DATA BUFFER ADDRESS
MOV #WH,RMC$10 ;WRITE HEADER AND DATA
MOV #ZEROS,$TMP0 ;USE ALL ZEROS DATA PATTERN
MOV #1,$TMP1
JSR PC,GENBUF ;GO GENERATE DATA BUFFER

20$:
;PREPARE DEVICE FOR DATA TRANSFER
JSR PC,TSTPRP ;PREPARE DEVICE FOR TEST
;WORD 154130 ;TASK DESCRIPTOR
BR 30$ ;GO TO 30$ IF NO ERROR
NOP ;RETURN HERE IF ERROR
ERROR ;ERROR # DEFINED BY TSTPRP SUBROUTINE

30$:
```

```
5524 020362 000137 021032          JMP      180$          ;GO TO 180$ IF ERROR WAS FOUND
5525 020366          30$:
5526
5527          ;SETUP PARAMETERS AND EXECUTE SEEK TO GET DRIVE OFF CYLINDER
5528 020366 013737 001434 021034      MOV      RMDCO,190$          ;SAVE CYLINDER ADDRESS
5529 020374 012737 001466 001434      MOV      #822.,RMDCO          ;SEEK TO LAST CYLINDER
5530 020402 012737 000005 001400      MOV      #SEEK!GO,RMCS10      ;CHANGE COMMAND TO SEEK
5531 020410 012702 001535              MOV      #PUTINX,R2          ;WRITE REGISTER INDEX TABLE
5532 020414 112722 000006              MOVB     #RMDA,(R2)+
5533 020420 112722 000034              MOVB     #RMDC,(R2)+
5534 020424 112722 000032              MOVB     #RMOF,(R2)+
5535 020430 112722 000000              MOVB     #RMCS1,(R2)+
5536 020434 112722 000200              MOVB     #200,(R2)+
5537 020440 004737 037766              JSR      PC,PUT          ;GO WRITE REGISTERS VIA PUT SUB
5538 020444 000404              BR      40$          ;GO TO 40$ IF NO ERROR
5539 020446 000240              NOP          ;RETURN HERE IF ERROR
5540 020450 104000              ERROR      ;ERROR DEFINED BY PUT SUB
5541 020452 000137 021032          JMP      180$          ;GO TO 180$ IF ERROR WAS FOUND
5542 020456          40$:
5543
5544          ;SETUP FOR READING STATUS AND THEN WAIT FOR SEEK TO COMPLETE
5545 020456 004737 037432              JSR      PC,GETSTS          ;SETUP FOR STATUS
5546 020462 004737 040326              JSR      PC,TIMOUT          ;WAIT FOR SEEK TO COMPLETE
5547 020466          50$:
5548
5549          ;GO READ SEEK STATUS
5550 020466 004737 037516              JSR      PC,GET          ;GO READ REGISTERS VIA GET SUB
5551 020472 000404              BR      60$          ;GO TO 60$ IF NO ERROR
5552 020474 000240              NOP          ;RETURN HERE IF ERROR
5553 020476 104000              ERROR      ;ERROR DEFINED BY GET SUB
5554 020500 000137 021032          JMP      180$          ;GO TO 180$ IF ERROR WAS FOUND
5555 020504          60$:
5556
5557          ;VERIFY THE RESULTS OF THE SEEK COMMAND
5558 020504 004737 045420              JSR      PC,SEKSTS          ;GO VERIFY RESULTS OF SEEK OPERATION
5559 020510 000405              BR      70$          ;GO TO 70$ IF NO ERROR
5560 020512 000240              NOP          ;RETURN HERE IF ERROR
5561 020514 104000              ERROR      ;ERROR # DEFINED BY SEKSTS SUBROUTINE
5562 020516 004736              JSR      PC,@(SP)+          ;GO BACK FOR MORE ERROR CHECKS
5563 020520 000137 021032          JMP      180$          ;GO TO 180$ IF ERROR WAS FOUND
5564 020524          70$:
5565
5566          ;SETUP AND EXECUTE WRITE HEADER AND DATA COMMAND
5567 020524 013737 021034 001434      MOV      190$,RMDCO          ;RESTORE DISK ADDRESS
5568 020532 012737 000063 001400      MOV      #WH!GO,RMCS10      ;LOAD WRITE HEADER AND DATA
5569 020540 012702 001540              MOV      #PUTINX+3,R2          ;EXTEND REGISTER INDEX TABLE
5570 020544 112722 000002              MOVB     #RMWC,(R2)+
5571 020550 112722 000004              MOVB     #RMBA,(R2)+
5572 020554 112722 000000              MOVB     #RMCS1,(R2)+
5573 020560 112722 000200              MOVB     #200,(R2)+
5574 020564 004737 037766              JSR      PC,PUT          ;GO WRITE REGISTERS VIA PUT SUB
5575 020570 000404              BR      80$          ;GO TO 80$ IF NO ERROR
5576 020572 000240              NOP          ;RETURN HERE IF ERROR
5577 020574 104000              ERROR      ;ERROR DEFINED BY PUT SUB
5578 020576 000137 021032          JMP      180$          ;GO TO 180$ IF ERROR WAS FOUND
5579 020602          80:
```

```
5580
5581      ;WAIT FOR WRITE COMMAND TO COMPLETE AND READ STATUS
5582      JSR      PC,TIMOUT      ;WAIT FOR COMMAND TO COMPLETE
5583      JSR      PC,GET          ;GO READ REGISTERS VIA GET SUB
5584      BR       90$            ;GO TO 90$ IF NO ERROR
5585      NOP                      ;RETURN HERE IF ERROR
5586      ERROR    ;ERROR DEFINED BY GET SUB
5587      JMP      180$           ;GO TO 180$ IF ERROR WAS FOUND
5588      90$:
5589
5590      ;VERIFY RESULTS OF WRITE COMMAND
5591      JSR      PC,PRIERR      ;GO CHECK FOR PRIMARY ERRORS
5592      BR       100$           ;GO TO 100$ IF NO ERROR
5593      NOP                      ;RETURN HERE IF ERROR
5594      ERROR    ;ERROR # DEFINED BY PRIERR SUBROUTINE
5595      JSR      PC,@(SP)+      ;GO BACK FOR MORE ERROR CHECKS
5596      JMP      180$           ;GO TO 180$ IF ERROR WAS FOUND
5597      100$:
5598      JSR      PC,DTASTS      ;GO VERIFY RESULTS OF DATA TRANSFER
5599      BR       110$           ;GO TO 110$ IF NO ERROR
5600      NOP                      ;RETURN HERE IF ERROR
5601      ERROR    ;ERROR # DEFINED BY DTASTS SUBROUTINE
5602      JSR      PC,@(SP)+      ;GO BACK FOR MORE ERROR CHECKS
5603      JMP      180$           ;GO TO 180$ IF ERROR WAS FOUND
5604      110$:
5605      JSR      PC,SECERR      ;GO CHECK FOR SECONDARY ERRORS
5606      BR       120$           ;GO TO 120$ IF NO ERROR
5607      NOP                      ;RETURN HERE IF ERROR
5608      ERROR    ;ERROR # DEFINED BY SECERR SUBROUTINE
5609      JSR      PC,@(SP)+      ;GO BACK FOR MORE ERROR CHECKS
5610      JMP      180$           ;GO TO 180$ IF ERROR WAS FOUND
5611      120$:
5612
5613
5614      ;WRITE CHECK HEADER AND DATA FOR SECTORS JUST WRITTEN
5615      MOV      #WCH!GO,RMCS10 ;READ HEADER & DATA COMMAND
5616      JSR      PC,PUT          ;GO WRITE REGISTERS VIA PUT SUB
5617      BR       130$           ;GO TO 130$ IF NO ERROR
5618      NOP                      ;RETURN HERE IF ERROR
5619      ERROR    ;ERROR DEFINED BY PUT SUB
5620      JMP      180$           ;GO TO 180$ IF ERROR WAS FOUND
5621      130$:
5622
5623      ;WAIT FOR WRITE CHECK TO COMPLETE AND GET STATUS
5624      JSR      PC,TIMOUT      ;WAIT FOR WRITE CHECK TO FINISH
5625      JSR      PC,GET          ;GO READ REGISTERS VIA GET SUB
5626      BR       140$           ;GO TO 140$ IF NO ERROR
5627      NOP                      ;RETURN HERE IF ERROR
5628      ERROR    ;ERROR DEFINED BY GET SUB
5629      JMP      180$           ;GO TO 180$ IF ERROR WAS FOUND
5630      140$:
5631
5632      ;VERIFY THE RESULTS OF WRITE CHECK OPERATION
5633      JSR      PC,PRIERR      ;GO CHECK FOR PRIMARY ERRORS
5634      BR       150$           ;GO TO 150$ IF NO ERROR
5635      NOP                      ;RETURN HERE IF ERROR
```

```
5636 020762 104000          ERROR          ;ERROR # DEFINED BY PRIERR SUBROUTINE
5637 020764 004736          JSR          PC,@(SP)+ ;GO BACK FOR MORE ERROR CHECKS
5638 020766 000137 021032    JMP          180$      ;GO TO 180$ IF ERROR WAS FOUND
5639 020772          150$:
5640 020772 004737 053016    JSR          PC,DASTS ;GO VERIFY RESULTS OF DATA TRANSFER
5641 020776 000405          BR          160$      ;GO TO 160$ IF NO ERROR
5642 021000 000240          NOP          ;RETURN HERE IF ERROR
5643 021002 104000          ERROR        ;ERROR # DEFINED BY DASTS SUBROUTINE
5644 021004 004736          JSR          PC,@(SP)+ ;GO BACK FOR MORE ERROR CHECKS
5645 021006 000137 021032    JMP          180$      ;GO TO 180$ IF ERROR WAS FOUND
5646 021012          160$:
5647 021012 004737 041344    JSR          PC,SECERR ;GO CHECK FOR SECONDARY ERRORS
5648 021016 000405          BR          170$      ;GO TO 170$ IF NO ERROR
5649 021020 000240          NOP          ;RETURN HERE IF ERROR
5650 021022 104000          ERROR        ;ERROR # DEFINED BY SECERR SUBROUTINE
5651 021024 004736          JSR          PC,@(SP)+ ;GO BACK FOR MORE ERROR CHECKS
5652 021026 000137 021032    JMP          180$      ;GO TO 180$ IF ERROR WAS FOUND
5653 021032          170$:
5654 021032          180$:
5655 021032 000401          BR          200$
5656 021034 000000          190$: .WORD          ;TEMPORARY STORAGE
5657 021036          200$:
5658
5659
5660 ;*****
5661 ;*TEST 20          FORMAT EACH SECTOR ADDRESS
5662 ;*****
5662 021036          TST20:
5663 021036 000004          SCOPE          ;SCOPE CALL
5664 021040 000240          NOP          ;START OF TEST
5665 021042 012706 001100    MOV          #STACK,SP ;INITIALIZE STACK POINTER
5666 021046 013700 001276    MOV          $BASE,R0 ;R0=UNIBUS ADDRESS
5667 021052 013701 001450    MOV          TSTQUE,R1 ;(R1) = DEVICE BEING TESTED
5668 021056 012737 000020 001226    MOV          #20,$TESTN ;SET TEST NUMBER IN APT MAIL BOX
5669 021064          10$:
5670
5671 ;SETUP PARAMETERS FOR GENERATING DATA BUFFER
5672 021064 012737 000000 001434    MOV          #0,RMDCO ;CYLINDER = 0
5673 021072 012737 000000 001406    MOV          #0,RMDAO ;TRACK = SECTOR = 0
5674 021100 012737 010000 001432    MOV          #FMT16,RMOFO ;16 BIT FORMAT
5675 021106 012737 177376 001402    MOV          #<^C<2+256.>+1>,RMWCO ;2 + 256 WORDS
5676 021114 012737 103564 001404    MOV          #RUFONE,RMBAO ;DATA BUFFER ADDRESS
5677 021122 012737 000062 001400    MOV          #WH,RMCS10 ;WRITE HEADER AND DATA
5678 021130 012737 001406 001174    MOV          #RMDAO,$TMP0 ;USE SECTOR FOR DATA PATTERN
5679 021136 012737 000001 001176    MOV          #1,$TMP1
5680 021144 004737 036620          JSR          PC,GENBUF ;GO GENERATE DATA BUFFER
5681 021150          20$:
5682
5683 ;PREPARE DEVICE FOR DATA TRANSFER
5684 021150 004737 034000          JSR          PC,TSTPRP ;PREPARE DEVICE FOR TEST
5685 021154 154130          .WORD          154130 ;TASK DESCRIPTOR
5686 021156 000404          BR          30$      ;GO TO 30$ IF NO ERROR
5687 021160 000240          NOP          ;RETURN HERE IF ERROR
5688 021162 104000          ERROR        ;ERROR # DEFINED BY TSTPRP SUBROUTINE
5689 021164 000137 021562    JMP          190$      ;GO TO 190$ IF ERROR WAS FOUND
5690 021170          30$:
5691
```

```

5692
5693 021170 012737 000063 001400 ;SETUP AND EXECUTE WRITE HEADER AND DATA COMMAND
5694 021176 012702 001535          MOV      #WH!GO,RMCS10      ;WRITE HEADER AND DATA
5695 021202 112722 000006          MOV      #PUTINX,R2        ;WRITE REGISTER INDEX TABLE
5696 021206 112722 000034          MOV      #RMDA,(R2)+
5697 021212 112722 000032          MOV      #RMDC,(R2)+
5698 021216 112722 000002          MOV      #RMOF,(R2)+
5699 021222 112722 000004          MOV      #RMMC,(R2)+
5700 021226 112722 000000          MOV      #RMDA,(R2)+
5701 021232 112722 000200          MOV      #RMCST,(R2)+
5702 021236 004737 037766          MOV      #200,(R2)+
5703 021242 000404                JSR      PC,PUT              ;GO WRITE REGISTERS VIA PUT SUB
5704 021244 000240                BR       80$                ;GO TO 80$ IF NO ERROR
5705 021246 104000                NOP                      ;RETURN HERE IF ERROR
5706 021250 000137 021562          ERROR    ;ERROR DEFINED BY PUT SUB
5707 021254                JMP      190$                ;GO TO 190$ IF ERROR WAS FOUND
5708
5709
5710 021254 004737 037432          ;SETUP INPUT REGISTER BUFFER FOR READING STATUS
5711                JSR      PC,GETSTS
5712
5713 021260 004737 040326          ;WAIT FOR WRITE COMMAND TO COMPLETE AND READ STATUS
5714 021264 004737 037516          JSR      PC,TIMOUT          ;WAIT FOR COMMAND TO COMPLETE
5715 021270 000404                JSR      PC,GET              ;GO READ REGISTERS VIA GET SUB
5716 021272 000240                BR       90$                ;GO TO 90$ IF NO ERROR
5717 021274 104000                NOP                      ;RETURN HERE IF ERROR
5718 021276 000137 021562          ERROR    ;ERROR DEFINED BY GET SUB
5719 021302                JMP      190$                ;GO TO 190$ IF ERROR WAS FOUND
5720
5721
5722 021302 004737 040512          ;VERIFY RESULTS OF WRITE COMMAND
5723 021306 000405                JSR      PC,PRIERR          ;GO CHECK FOR PRIMARY ERRORS
5724 021310 000240                BR       100$               ;GO TO 100$ IF NO ERROR
5725 021312 104000                NOP                      ;RETURN HERE IF ERROR
5726 021314 004736                ERROR    ;ERROR # DEFINED BY PRIERR SUBROUTINE
5727 021316 000137 021562          JSR      PC,@(SP)+          ;GO BACK FOR MORE ERROR CHECKS
5728 021322                JMP      190$                ;GO TO 190$ IF ERROR WAS FOUND
5729 021322 004737 053016          100$:
5730 021326 000405                JSR      PC,DASTS          ;GO VERIFY RESULTS OF DATA TRANSFER
5731 021330 000240                BR       110$               ;GO TO 110$ IF NO ERROR
5732 021332 104000                NOP                      ;RETURN HERE IF ERROR
5733 021334 004736                ERROR    ;ERROR # DEFINED BY DASTS SUBROUTINE
5734 021336 000137 021562          JSR      PC,@(SP)+          ;GO BACK FOR MORE ERROR CHECKS
5735 021342                JMP      190$                ;GO TO 190$ IF ERROR WAS FOUND
5736 021342 004737 041344          110$:
5737 021346 000405                JSR      PC,SECERR          ;GO CHECK FOR SECONDARY ERRORS
5738 021350 000240                BR       120$               ;GO TO 120$ IF NO ERROR
5739 021352 104000                NOP                      ;RETURN HERE IF ERROR
5740 021354 004736                ERROR    ;ERROR # DEFINED BY SECERR SUBROUTINE
5741 021356 000137 021562          JSR      PC,@(SP)+          ;GO BACK FOR MORE ERROR CHECKS
5742 021362                JMP      190$                ;GO TO 190$ IF ERROR WAS FOUND
5743
5744
5745
5746 021362 012737 000073 001400          ;READ HEADER AND DATA FOR SECTOR JUST WRITTEN
5747 021370 012737 104570 001404          MOV      #RH!GO,RMCS10      ;READ HEADER & DATA COMMAND
                                         MOV      #BUFTWO,RMBA0      ;CHANGE BUS ADDRESS

```



```
5748 021376 004737 037766      JSR    PC,PUT      ;GO WRITE REGISTERS VIA PUT SUB
5749 021402 000404              BR     130$      ;GO TO 130$ IF NO ERROR
5750 021404 000240              NOP                ;RETURN HERE IF ERROR
5751 021406 104000              ERROR             ;ERROR DEFINED BY PUT SUB
5752 021410 000137 021562      JMP     190$      ;GO TO 190$ IF ERROR WAS FOUND
5753 021414
5754
5755      130$:
;WAIT FOR PEAD TO COMPLETE AND GET STATUS
5756 021414 004737 040326      JSR    PC,TIMOUT    ;WAIT FOR READ TO COMPLETE
5757 021420 004737 037516      JSR    PC,GET      ;GO READ REGISTERS VIA GET SUB
5758 021424 000404              BR     140$      ;GO TO 140$ IF NO ERROR
5759 021426 000240              NOP                ;RETURN HERE IF ERROR
5760 021430 104000              ERROR             ;ERROR DEFINED BY GET SUB
5761 021432 000137 021562      JMP     190$      ;GO TO 190$ IF ERROR WAS FOUND
5762 021436
5763
5764      140$:
;VERIFY THE RESULTS OF READ OPERATION
5765 021436 004737 040512      JSR    PC,PRIERR    ;GO CHECK FOR PRIMARY ERRORS
5766 021442 000405              BR     150$      ;GO TO 150$ IF NO ERROR
5767 021444 000240              NOP                ;RETURN HERE IF ERROR
5768 021446 104000              ERROR             ;ERROR # DEFINED BY PRIERR SUBROUTINE
5769 021450 004737 021562      JSR    PC,@(SP)+    ;GO BACK FOR MORE ERROR CHECKS
5770 021452 000137 021562      JMP     190$      ;GO TO 190$ IF ERROR WAS FOUND
5771 021456
5772 021456 004737 053016      JSR    PC,DTASTS    ;GO VERIFY RESULTS OF DATA TRANSFER
5773 021462 000405              BR     160$      ;GO TO 160$ IF NO ERROR
5774 021464 000240              NOP                ;RETURN HERE IF ERROR
5775 021466 104000              ERROR             ;ERROR # DEFINED BY DTASTS SUBROUTINE
5776 021470 004736 021562      JSR    PC,@(SP)+    ;GO BACK FOR MORE ERROR CHECKS
5777 021472 000137 021562      JMP     190$      ;GO TO 190$ IF ERROR WAS FOUND
5778 021476
5779 021476 004737 041344      JSR    PC,SECERR    ;GO CHECK FOR SECONDARY ERRORS
5780 021502 000405              BR     170$      ;GO TO 170$ IF NO ERROR
5781 021504 000240              NOP                ;RETURN HERE IF ERROR
5782 021506 104000              ERROR             ;ERROR # DEFINED BY SECERR SUBROUTINE
5783 021510 004736 021562      JSR    PC,@(SP)+    ;GO BACK FOR MORE ERROR CHECKS
5784 021512 000137 021562      JMP     190$      ;GO TO 190$ IF ERROR WAS FOUND
5785 021516
5786
5787      170$:
;VERIFY DATA
5788 021516 004737 037064      JSR    PC,CMPBUF    ;GO COMPARE WRITE, READ DATA BUFFERS
5789 021522 103564              .WORD    BUFONE    ;STARTING ADDRESS OF WRITE BUFFER
5790 021524 104570              .WORD    BUFTWO    ;STARTING ADDRESS OF READ BUFFER
5791 021526 000404              BR     180$      ;GO TO 180$ IF NO ERROR
5792 021530 000240              NOP                ;RETURN HERE IF ERROR
5793 021532 104000              ERROR             ;ERROR # DEFINED BY CMPBUF SUBROUTINE
5794 021534 000137 021562      JMP     190$      ;GO TO 190$ IF ERROR WAS FOUND
5795 021540
5796
5797      180$:
;INCREMENT ADDRESS AND FORMAT NEXT SECTOR
5798 021540 062737 000001 001406  ADD     #1,RMDAO    ;ADVANCE SECTOR COUNT
5799 021546 122737 000037 001406  CMPB    #31.,RMDAO    ;DONE ALL SECTORS??
5800 021554 103402              BLO     190$      ;YES!!
5801 021556 000137 021100      JMP     15$        ;GO DO NEXT SECTOR
5802 021562
5803      190$:
```

```
5804  
5805  
5806  
5807 021562  
5808 021562 000004  
5809 021564 000240  
5810 021566 012706 001100  
5811 021572 013700 001276  
5812 021576 013701 001450  
5813 021602 012737 000021 0J 226  
5814 021610  
5815  
5816  
5817 021610 012737 000000 001434  
5818 021616 012737 000000 001406  
5819 021624 012737 010000 001432  
5820 021632 012737 177376 001402  
5821 021640 012737 103564 001404  
5822 021646 012737 000062 001400  
5823 021654 012737 001406 001174  
5824 021662 012737 000001 001176  
5825 021670 004737 036620  
5826 021674  
5827  
5828  
5829 021674 004737 034000  
5830 021700 154130  
5831 021702 000404  
5832 021704 000240  
5833 021706 104000  
5834 021710 000137 022306  
5835 021714  
5836  
5837  
5838 021714 012737 000063 001400  
5839 021722 012702 001535  
5840 021726 112722 000006  
5841 021732 112722 000034  
5842 021736 112722 000032  
5843 021742 112722 000002  
5844 021746 112722 000004  
5845 021752 112722 000000  
5846 021756 112722 000200  
5847 021762 004737 037766  
5848 021766 000404  
5849 021770 000240  
5850 021772 104000  
5851 021774 000137 022306  
5852 022000  
5853  
5854  
5855 022000 004737 037432  
5856  
5857  
5858 022004 004737 040326  
5859 022010 004737 037516
```

```
*****  
*TEST 21          FORMAT EACH TRACK ADDRESS  
*****  
TST21:  
      SCOPE          ;SCOPE CALL  
      NOP            ;START OF TEST  
      MOV     #STACK,SP ;INITIALIZE STACK POINTER  
      MOV     $BASE,R0  ;R0=UNIBUS ADDRESS  
      MOV     TSTQUE,R1 ;(R1) = DEVICE BEING TESTED  
      MOV     #21,$TESTN ;SET TEST NUMBER IN APT MAIL BOX  
10$:  
      ;SETUP PARAMETERS FOR GENERATING DATA BUFFER  
      MOV     #0,RMDCO ;CYLINDER = 0  
      MOV     #0,RMDAO ;TRACK = SECTOR = 0  
15$:  MOV     #FMT16,RMOFO ;16 BIT FORMAT  
      MOV     #<^C<2+256.>+1>,RMWCO ;2 + 256 WORDS  
      MOV     #BUF,%E,RMBAO ;DATA BUFFER ADDRESS  
      MOV     #WH,RMCS10 ;WRITE HEADER AND DATA  
      MOV     #RMDAO,$TMP0 ;USE TRACK FOR DATA PATTERN  
      MOV     #1,$TMP1  
      JSR     PC,GENBU ;GO GENERATE DATA BUFFER  
20$:  
      ;PREPARE DEVICE FOR DATA TRANSFER  
      JSR     PC,TSTPRP ;PREPARE DEVICE FOR TEST  
      .WORD   154130 ;TASK DESCRIPTOR  
      BR      30$      ;GO TO 30$ IF NO ERROR  
      NOP     ;RETURN HERE IF ERROR  
      ERROR   ;ERROR # DEFINED BY TSTPRP SUBROUTINE  
      JMP     190$     ;GO TO 190$ IF ERROR WAS FOUND  
30$:  
      ;SETUP AND EXECUTE WRITE HEADER AND DATA COMMAND  
      MOV     #WH!GO,RMCS10 ;WRITE HEADER AND DATA  
      MOV     #PUTINX,R2 ;WRITE REGISTER INDEX TABLE  
      MOVB    #RMDA,(R2)+  
      MOVB    #RMDC,(R2)+  
      MOVB    #RMOF,(R2)+  
      MOVB    #RMWC,(R2)+  
      MOVB    #RMBA,(R2)+  
      MOVB    #RMCS1,(R2)+  
      MOVB    #200,(R2)+  
      JSR     PC,PUT ;GO WRITE REGISTERS VIA PUT SUB  
      BR      80$ ;GO TO 80$ IF NO ERROR  
      NOP     ;RETURN HERE IF ERROR  
      ERROR   ;ERROR DEFINED BY PUT SUB  
      JMP     190$ ;GO TO 190$ IF ERROR WAS FOUND  
80$:  
      ;SETUP INPUT REGISTER BUFFER FOR READING STATUS  
      JSR     PC,GETSTS  
      ;WAIT FOR WRITE COMMAND TO COMPLETE AND READ STATUS  
      JSR     PC,TIMOUT ;WAIT FOR COMMAND TO COMPLETE  
      JSR     PC,GET ;GO READ REGISTERS VIA GET SUB
```



```
5860 022014 000404 BR 90$ ;GO TO 90$ IF NO ERROR
5861 022016 000240 NOP ;RETURN HERE IF ERROR
5862 022020 104000 ERROR ;ERROR DEFINED BY GET SUB
5863 022022 000137 022306 JMP 190$ ;GO TO 190$ IF ERROR WAS FOUND
5864 022026 90$:
5865
5866 ;VERIFY RESULTS OF WRITE COMMAND
5867 022026 004737 040512 JSR PC,PRIERR ;GO CHECK FOR PRIMARY ERRORS
5868 022032 000405 BR 100$ ;GO TO 100$ IF NO ERROR
5869 022034 000240 NOP ;RETURN HERE IF ERROR
5870 022036 104000 ERROR ;ERROR # DEFINED BY PRIERR SUBROUTINE
5871 022040 004736 JSR PC,@(SP)+ ;GO BACK FOR MORE ERROR CHECKS
5872 022042 000137 022306 JMP 190$ ;GO TO 190$ IF ERROR WAS FOUND
5873 022046 100$:
5874 022046 004737 053016 JSR PC,DTASTS ;GO VERIFY RESULTS OF DATA TRANSFER
5875 022052 000405 BR 110$ ;GO TO 110$ IF NO ERROR
5876 022054 000240 NOP ;RETURN HERE IF ERROR
5877 022056 104000 ERROR ;ERROR # DEFINED BY DTASTS SUBROUTINE
5878 022060 004736 JSR PC,@(SP)+ ;GO BACK FOR MORE ERROR CHECKS
5879 022062 000137 022306 JMP 190$ ;GO TO 190$ IF ERROR WAS FOUND
5880 022066 110$:
5881 022066 004737 041344 JSR PC,SECERR ;GO CHECK FOR SECONDARY ERRORS
5882 022072 000405 BR 120$ ;GO TO 120$ IF NO ERROR
5883 022074 000240 NOP ;RETURN HERE IF ERROR
5884 022076 104000 ERROR ;ERROR # DEFINED BY SECERR SUBROUTINE
5885 022100 004736 JSR PC,@(SP)+ ;GO BACK FOR MORE ERROR CHECKS
5886 022102 000137 022306 JMP 190$ ;GO TO 190$ IF ERROR WAS FOUND
5887 022106 120$:
5888
5889
5890 ;READ HEADER AND DATA FOR SECTOR JUST WRITTEN
5891 022106 012737 000073 001400 MOV #RH!GO,RMCS10 ;READ HEADER & DATA COMMAND
5892 022114 012737 104570 001404 MOV #BUFTWO,RMBAO ;CHANGE BUS ADDRESS
5893 022122 004737 037766 JSR PC,PUT ;GO WRITE REGISTERS VIA PUT SUB
5894 022126 000404 BR 130$ ;GO TO 130$ IF NO ERROR
5895 022130 000240 NOP ;RETURN HERE IF ERROR
5896 022132 104000 ERROR ;ERROR DEFINED BY PUT SUB
5897 022134 000137 022306 JMP 190$ ;GO TO 190$ IF ERROR WAS FOUND
5898 022140 130$:
5899
5900 ;WAIT FOR READ TO COMPLETE AND GET STATUS
5901 022140 004737 040326 JSR PC,TIMOUT ;WAIT FOR READ TO COMPLETE
5902 022144 004737 037516 JSR PC,GET ;GO READ REGISTERS VIA GET SUB
5903 022150 000404 BR 140$ ;GO TO 140$ IF NO ERROR
5904 022152 000240 NOP ;RETURN HERE IF ERROR
5905 022154 104000 ERROR ;ERROR DEFINED BY GET SUB
5906 022156 000137 022306 JMP 190$ ;GO TO 190$ IF ERROR WAS FOUND
5907 022162 140$:
5908
5909 ;VERIFY THE RESULTS OF READ OPERATION
5910 022162 004737 040512 JSR PC,PRIERR ;GO CHECK FOR PRIMARY ERRORS
5911 022166 000405 BR 150$ ;GO TO 150$ IF NO ERROR
5912 022170 000240 NOP ;RETURN HERE IF ERROR
5913 022172 104000 ERROR ;ERROR # DEFINED BY PRIERR SUBROUTINE
5914 022174 004736 JSR PC,@(SP)+ ;GO BACK FOR MORE ERROR CHECKS
5915 022176 000137 022306 JMP 190$ ;GO TO 190$ IF ERROR WAS FOUND
```

```
5916 022202 150$: JSR PC,DTASTS ;GO VERIFY RESULTS OF DATA TRANSFER
5917 022202 004737 053016 BR 160$ ;GO TO 160$ IF NO ERROR
5918 022206 000405 NOP ;RETURN HERE IF ERROR
5919 022210 000240 ERROR ;ERROR # DEFINED BY DTASTS SUBROUTINE
5920 022212 104000 JSR PC,@(SP)+ ;GO BACK FOR MORE ERROR CHECKS
5921 022214 004736 JMP 190$ ;GO TO 190$ IF ERROR WAS FOUND
5922 022216 000137 022306 160$: JSR PC,SECERR ;GO CHECK FOR SECONDARY ERRORS
5923 022222 004737 041344 BR 170$ ;GO TO 170$ IF NO ERROR
5924 022222 000405 NOP ;RETURN HERE IF ERROR
5925 022226 000240 ERROR ;ERROR # DEFINED BY SECERR SUBROUTINE
5926 022230 104000 JSR PC,@(SP)+ ;GO BACK FOR MORE ERROR CHECKS
5927 022232 004736 JMP 190$ ;GO TO 190$ IF ERROR WAS FOUND
5928 022234 000137 022306 170$: ;VERIFY DATA
5929 022236 000137 022306 JSR PC,CMPBUF ;GO COMPARE WRITE, READ DATA BUFFERS
5930 022242 004737 037064 .WORD BUFO1E ;STARTING ADDRESS OF WRITE BUFFER
5931 022242 103564 .WORD BUFTWO ;STARTING ADDRESS OF READ BUFFER
5932 022246 104570 BR 180$ ;GO TO 180$ IF NO ERROR
5933 022250 000404 NOP ;RETURN HERE IF ERROR
5934 022252 000240 ERROR ;ERROR # DEFINED BY CMPBUF SUBROUTINE
5935 022254 000240 JMP 190$ ;GO TO 190$ IF ERROR WAS FOUND
5936 022256 104000 180$: ;INCREMENT ADDRESS AND FORMAT NEXT TRACK
5937 022256 104000 ADD #400,RMDAO ;ADVANCE TRACK COUNT
5938 022260 000137 022306 CMP #2000,RMDAO ;DONE ALL TRACKS??
5939 022264 062737 000400 001406 BLO 190$ ;YES!!
5940 022264 022737 002000 001406 JMP 15$ ;GO DO NEXT SECTOR
5941 022302 000137 021624 190$:
5942 022306 5943 022264 062737 000400 001406
5943 022272 022737 002000 001406
5944 022300 103402
5945 022302 000137 021624
5946 022306
5947 022306
5948
5949
5950 ;*****
5951 ;*TEST 22 FORMAT PRIME CYLINDERS
5952 ;*****
5953 TST22:
5954 022306 000004 SCOPE ;SCOPE CALL
5955 022310 000240 NOP ;START OF TEST
5956 022312 012706 001100 MOV #STACK,SP ;INITIALIZE STACK POINTER
5957 022316 013700 001276 MOV $BASE,R0 ;R0=UNIBUS ADDRESS
5958 022322 013701 001450 MOV TSTQUE,R1 ;(R1) = DEVICE BEING TESTED
5959 022326 012737 000022 001226 MOV #22,$TESTN ;:SET TEST NUMBER IN APT MAIL BOX
5960 022334 10$:
5961 ;SETUP PARAMETERS FOR GENERATING DATA BUFFER
5962 022334 012737 000001 001434 MOV #1,RMDCO ;CYLINDER = 0
5963 022342 012737 000000 001406 MOV #0,RMDAO ;TRACK = SECTOR = 0
5964 022350 012737 010000 001432 15$: MOV #FMT16,RMOFO ;16 BIT FORMAT
5965 022356 012737 177376 001402 MOV #<^C<2+256.>+1>,RMCWO ;2 + 256 WORDS
5966 022364 012737 103564 001404 MOV #BUFO1E,RMBAO ;DATA BUFFER ADDRESS
5967 022372 012737 000062 001400 MOV #WH,RMCS10 ;WRITE HEADER AND DATA
5968 022400 012737 001434 001174 MOV #RMDCO,$TMP0 ;USE CYLINDER FOR DATA PATTERN
5969 022406 012737 000001 001176 MOV #1,$TMP1
5970 022414 004737 036620 JSR PC,GENBUF ;GO GENERATE DATA BUFFER
5971 022420 20$:
```

```
5972
5973
5974 022420 004737 034000      ;PREPARE DEVICE FOR DATA TRANSFER
5975 022424 154130              JSR    PC,TSTPRP      ;PREPARE DEVICE FOR TEST
5976 022426 000404              .WORD 154130      ;TASK DESCRIPTOR
5977 022430 000240              BR     30$          ;GO TO 30$ IF NO ERROR
5978 022432 104000              NOP                    ;RETURN HERE IF ERROR
5979 022434 000137 023030      ERROR          ;ERROR # DEFINED BY TSTPRP SUBROUTINE
5980 022440              JMP     190$          ;GO TO 190$ IF ERROR WAS FOUND
5981
5982
5983 022440 012737 000063 001400 ;SETUP AND EXECUTE WRITE HEADER AND DATA COMMAND
5984 022446 012702 001535      MOV     #WH!GO,RMCS10      ;WRITE HEADER AND DATA
5985 022452 112722 000006      MOV     #PUTINX,R2          ;WRITE REGISTER INDEX TABLE
5986 022456 112722 000034      MOVB    #RMDA,(R2)+
5987 022462 112722 000032      MOVB    #RMDC,(R2)+
5988 022466 112722 000002      MOVB    #RMOF,(R2)+
5989 022472 112722 000004      MOVB    #RMWC,(R2)+
5990 022476 112722 000000      MOVB    #RMBA,(R2)+
5991 022502 112722 00020C      MOVB    #RMCS1,(R2)+
5992 022506 004737 037766      MOVB    #200,(R2)+
5993 022512 000404              JSR     PC,PUT          ;GO WRITE REGISTERS VIA PUT SUB
5994 022514 000240              BR     80$          ;GO TO 80$ IF NO ERROR
5995 022516 104000              NOP                    ;RETURN HERE IF ERROR
5996 022520 000137 023030      ERROR          ;ERROR DEFINED BY PUT SUB
5997 022524              JMP     190$          ;GO TO 190$ IF ERROR WAS FOUND
5998
5999
6000 022524 004737 03743C      ;SETUP INPUT REGISTER BUFFER FOR READING STATUS
6001              JSR     PC,GETSTS
6002
6003 022530 004737 040326      ;WAIT FOR WRITE COMMAND TO COMPLETE AND READ STATUS
6004 022534 004737 037516      JSR     PC,TIMOUT      ;WAIT FOR COMMAND TO COMPLETE
6005 022540 000404              JSR     PC,GET          ;GO READ REGISTERS VIA GET SUB
6006 022542 000240              BR     90$          ;GO TO 90$ IF NO ERROR
6007 022544 104000              NOP                    ;RETURN HERE IF ERROR
6008 022546 000137 023030      ERROR          ;ERROR DEFINED BY GET SUB
6009 022552              JMP     190$          ;GO TO 190$ IF ERROR WAS FOUND
6010
6011
6012 022552 004737 040512      ;VERIFY RESULTS OF WRITE COMMAND
6013 022556 000405              JSR     PC,PRIERR      ;GO CHECK FOR PRIMARY ERRORS
6014 022560 000240              BR     100$         ;GO TO 100$ IF NO ERROR
6015 022562 104000              NOP                    ;RETURN HERE IF ERROR
6016 022564 004736              ERROR          ;ERROR # DEFINED BY PRIERR SUBROUTINE
6017 022566 000137 023030      JSR     PC,@(SP)+      ;GO BACK FOR MORE ERROR CHECKS
6018 022572              JMP     190$          ;GO TO 190$ IF ERROR WAS FOUND
6019 022572 004737 053016      100$:      JSR     PC,DASTS      ;GO VERIFY RESULTS OF DATA TRANSFER
6020 022576 000405              BR     110$         ;GO TO 110$ IF NO ERROR
6021 022600 000240              NOP                    ;RETURN HERE IF ERROR
6022 022602 104000              ERROR          ;ERROR # DEFINED BY DASTS SUBROUTINE
6023 022604 004736              JSR     PC,@(SP)+      ;GO BACK FOR MORE ERROR CHECKS
6024 022606 000137 023030      JMP     190$          ;GO TO 190$ IF ERROR WAS FOUND
6025 022612
6026 022612 004737 041344      110$:      JSR     PC,SECERR      ;GO CHECK FOR SECONDARY ERRORS
6027 022616 000405              BR     120$         ;GO TO 120$ IF NO ERROR
```

```
6028 022620 000240      NOP      ;RETURN HERE IF ERROR
6029 022622 104000      ERROR     ;ERROR # DEFINED BY SECERR SUBROUTINE
6030 022624 004736      JSR      PC,@(SP)+ ;GO BACK FOR MORE ERROR CHECKS
6031 022626 000137 023030 JMP      190$      ;GO TO 190$ IF ERROR WAS FOUND
6032 022632      120$:
6033
6034
6035      ;READ HEADER AND DATA FOR SECTOR JUST WRITTEN
6036 022632 012737 000073 0C1400 MOV      #RH!GO,RMCS10 ;READ HEADER & DATA COMMAND
6037 022640 012737 104570 001404 MOV      #BUFTWO,RMBA0 ;CHANGE BUS ADDRESS
6038 022646 004737 037766      JSR      PC,PUT      ;GO WRITE REGISTERS VIA PUT SUB
6039 022652 000404      BR      130$      ;GO TO 130$ IF NO ERROR
6040 022654 000240      NOP      ;RETURN HERE IF ERROR
6041 022656 104000      ERROR     ;ERROR DEFINED BY PUT SUB
6042 022660 000137 023030 JMP      190$      ;GO TO 190$ IF ERROR WAS FOUND
6043 022664      130$:
6044
6045      ;WAIT FOR READ TO COMPLETE AND GET STATUS
6046 022664 004737 040326      JSR      PC,TIMOUT ;WAIT FOR READ TO COMPLETE
6047 022670 004737 037516      JSR      PC,GET      ;GO READ REGISTERS VIA GET SUB
6048 022674 000404      BR      140$      ;GO TO 140$ IF NO ERROR
6049 022676 000240      NOP      ;RETURN HERE IF ERROR
6050 022700 104000      ERROR     ;ERROR DEFINED BY GET SUB
6051 022702 000137 023030 JMP      190$      ;GO TO 190$ IF ERROR WAS FOUND
6052 022706      140$:
6053
6054      ;VERIFY THE RESULTS OF READ OPERATION
6055 022706 004737 040512      JSR      PC,PRIERR ;GO CHECK FOR PRIMARY ERRORS
6056 022712 000405      BR      150$      ;GO TO 150$ IF NO ERROR
6057 022714 000240      NOP      ;RETURN HERE IF ERROR
6058 022716 104000      ERROR     ;ERROR # DEFINED BY PRIERR SUBROUTINE
6059 022720 004736      JSR      PC,@(SP)+ ;GO BACK FOR MORE ERROR CHECKS
6060 022722 000137 023030 JMP      190$      ;GO TO 190$ IF ERROR WAS FOUND
6061 022726      150$:
6062 022726 004737 053016      JSR      PC,DASTS ;GO VERIFY RESULTS OF DATA TRANSFER
6063 022732 000405      BR      160$      ;GO TO 160$ IF NO ERROR
6064 022734 000240      NOP      ;RETURN HERE IF ERROR
6065 022736 104000      ERROR     ;ERROR # DEFINED BY DASTS SUBROUTINE
6066 022740 004736      JSR      PC,@(SP)+ ;GO BACK FOR MORE ERROR CHECKS
6067 022742 000137 023030 JMP      190$      ;GO TO 190$ IF ERROR WAS FOUND
6068 022746      160$:
6069 022746 004737 041344      JSR      PC,SECERR ;GO CHECK FOR SECONDARY ERRORS
6070 022752 000405      BR      170$      ;GO TO 170$ IF NO ERROR
6071 022754 000240      NOP      ;RETURN HERE IF ERROR
6072 022756 104000      ERROR     ;ERROR # DEFINED BY SECERR SUBROUTINE
6073 022760 004736      JSR      PC,@(SP)+ ;GO BACK FOR MORE ERROR CHECKS
6074 022762 000137 023030 JMP      190$      ;GO TO 190$ IF ERROR WAS FOUND
6075 022766      170$:
6076
6077      ;VERIFY DATA
6078 022766 004737 037064      JSR      PC,CMPBUF ;GO COMPARE WRITE, READ DATA BUFFERS
6079 022772 103564      .WORD    BUFOE ;STARTING ADDRESS OF WRITE BUFFER
6080 022774 104570      .WORD    BUFTWO ;STARTING ADDRESS OF READ BUFFER
6081 022776 000404      BR      180$      ;GO TO 180$ IF NO ERROR
6082 023000 000240      NOP      ;RETURN HERE IF ERROR
6083 023002 104000      ERROR     ;ERROR # DEFINED BY CMPBUF SUBROUTINE
```

```

6084 023004 000137 023030          JMP      190$          ;GO TO 190$ IF ERROR WAS FOUND
6085 023010
6086
6087          ;INCREMENT ADDRESS AND FORMAT NEXT PRIME CYLINDER
6088 023010 006337 001434          ASL      RMDCO          ;ADVANCE CYLINDER COUNT
6089 023014 022737 001466 001434  CMP      #822.,RMDCO      ;DONE ALL CYLINDERS??
6090 023022 103402          BLO      190$          ;YES!!
6091 023024 000137 022350          JMP      15$          ;GO DO NEXT CYLINDER
6092 023030
6093
6094          ;*****
6095          ;*TEST 23          FORMAT LAST SECTOR
6096          ;*****
6097 023030  TST23:
6098 023030 000004          SCOPE          ;SCOPE CALL
6099 023032 000240          NOP          ;START OF TEST
6100 023034 012706 001100          MOV      #STACK,SP      ;INITIALIZE STACK POINTER
6101 023040 013700 001276          MOV      $BASE,R0      ;R0=UNIBUS ADDRESS
6102 023044 013701 001450          MOV      TSTQUE,R1      ;(R1) = DEVICE BEING TESTED
6103 023050 012737 000023 001226  MOV      #23,$TESTN      ;;SET TEST NUMBER IN APT MAIL BOX
6104 023056
6105
6106          ;PREPARE DEVICE FOR DATA TRANSFER
6107 023056 004737 034000          JSR      PC,TSTPRP      ;PREPARE DEVICE FOR TEST
6108 023062 154130          .WORD      154130 ;TASK DESCRIPTOR
6109 023064 000404          BR        30$          ;GO TO 30$ IF NO ERROR
6110 023066 000240          NOP          ;RETURN HERE IF ERROR
6111 023070 104000          ERROR      ;ERROR # DEFINED BY TSTPRP SUBROUTINE
6112 023072 000137 023326          JMP      190$          ;GO TO 190$ IF ERROR WAS FOUND
6113 023076
6114
6115          ;SETUP PARAMETERS FOR READING LAST SECTOR
6116 023076 012737 001466 001434  MOV      #822.,RMDCO      ;LAST CYLINDER
6117 023104 012737 002037 001406  MOV      #2037,RMDAO      ;TRACK = 4 SECTOR = 31.
6118 023112 012737 010000 001432  MOV      #FMT16,RMOFO      ;16 BIT FORMAT
6119 023120 012737 177376 001402  MOV      #<^C<2+256.>+1>,RMLCLO ;2 + 256 WORDS
6120 023126 012737 104570 001404  MOV      #BUFTWO,RMBAO      ;DATA BUFFER ADDRESS
6121 023134 012737 000073 001400  MOV      #RH!GO,RMCS10      ;WRITE HEADER AND DATA
6122
6123 023142 012702 001535          MOV      #PUTINX,R2      ;WRITE REGISTER INDEX TABLE
6124 023146 112722 000006          MOVB     #RMDA,(R2)+
6125 023152 112722 000034          MOVB     #RMDC,(R2)+
6126 023156 112722 000032          MOVB     #RMOF,(R2)+
6127 023162 112722 000004          MOVB     #RMBA,(R2)+
6128 023166 112722 000002          MOVB     #RMWC,(R2)+
6129 023172 112722 000000          MOVB     #RMCS1,(R2)+
6130 023176 112722 000200          MOVB     #200,(R2)+
6131
6132
6133 023202          120$:
6134
6135          ;READ HEADER AND DATA OF LAST SECTOR
6136 023202 004737 037766          JSR      PC,PUT      ;GO WRITE REGISTERS VIA PUT SUB
6137 023206 000404          BR        130$      ;GO TO 130$ IF NO ERROR
6138 023210 000240          NOP          ;RETURN HERE IF ERROR
6139 023212 104000          ERROR      ;ERROR DEFINED BY PUT SUB

```

```

6140 023214 000137 023326      JMP      190$      ;GO TO 190$ IF ERROR WAS FOUND
6141 023220
6142
6143      ;SETUP INPUT REGISTER BUFFER FOR READING STATUS
6144 023220 004737 037432      JSR      PC,GETSTS
6145      ;WAIT FOR READ TO COMPLETE AND GET STATUS
6146 023224 004737 040326      JSR      PC,TIMOUT      ;WAIT FOR READ TO COMPLETE
6147 023230 004737 037516      JSR      PC,GET      ;GO READ REGISTERS VIA GET SUB
6148 023234 000404      BR      140$      ;GO TO 140$ IF NO ERROR
6149 023236 000240      NOP      ;RETURN HERE IF ERROR
6150 023240 104000      ERROR     ;ERROR DEFINED BY GET SUB
6151 023242 000137 023326      JMP      190$      ;GO TO 190$ IF ERROR WAS FOUND
6152 023246
6153
6154      ;VERIFY THE RESULTS OF READ OPERATION
6155 023246 004737 040512      JSR      PC,PRIERR      ;GO CHECK FOR PRIMARY ERRORS
6156 023252 000405      BR      150$      ;GO TO 150$ IF NO ERROR
6157 023254 000240      NOP      ;RETURN HERE IF ERROR
6158 023256 104000      ERROR     ;ERROR # DEFINED BY PRIERR SUBROUTINE
6159 023260 004736      JSR      PC,@(SP)+      ;GO BACK FOR MORE ERROR CHECKS
6160 023262 000137 023326      JMP      190$      ;GO TO 190$ IF ERROR WAS FOUND
6161 023266
6162 023266 004737 053016      JSR      PC,DTASTS      ;GO VERIFY RESULTS OF DATA TRANSFER
6163 023272 000405      BR      160$      ;GO TO 160$ IF NO ERROR
6164 023274 000240      NOP      ;RETURN HERE IF ERROR
6165 023276 104000      ERROR     ;ERROR # DEFINED BY DTASTS SUBROUTINE
6166 023300 004736      JSR      PC,@(SP)+      ;GO BACK FOR MORE ERROR CHECKS
6167 023302 000137 023326      JMP      190$      ;GO TO 190$ IF ERROR WAS FOUND
6168 023306
6169 023306 004737 041344      JSR      PC,SECERR      ;GO CHECK FOR SECONDARY ERRORS
6170 023312 000405      BR      170$      ;GO TO 170$ IF NO ERROR
6171 023314 000240      NOP      ;RETURN HERE IF ERROR
6172 023316 104000      ERROR     ;ERROR # DEFINED BY SECERR SUBROUTINE
6173 023320 004736      JSR      PC,@(SP)+      ;GO BACK FOR MORE ERROR CHECKS
6174 023322 000137 023326      JMP      190$      ;GO TO 190$ IF ERROR WAS FOUND
6175 023326
6176
6177 023326
6178
6179
6180      ;*****
6181      ;*TEST 24      FORMAT W/ AOE ERROR
6182      ;*****
6182 023326
6183 023326 000004      TST24:      SCOPE      ;SCOPE CALL
6184 023330 000240      NOP      ;START OF TEST
6185 023332 012706 001100      MOV      #STACK,SP      ;INITIALIZE STACK POINTER
6186 023336 013700 001276      MOV      $BASE,R0      ;R0=UNIBUS ADDRESS
6187 023342 013701 001450      MOV      TSTQUE,R1      ;(R1) = DEVICE BEING TESTED
6188 023346 012737 000024 001226      MOV      #24,$TSTN      ;SET TEST NUMBER IN APT MAIL BOX
6189
6190      ;PREPARE DEVICE FOR DATA TRANSFER
6191 023354 004737 034000      JSR      PC,TSTPRP      ;PREPARE DEVICE FOR TEST
6192 023360 154130      .WORD      154130      ;TASK DESCRIPTOR
6193 023362 000404      BR      30$      ;GO TO 30$ IF NO ERROR
6194 023364 000240      NOP      ;RETURN HERE IF ERROR
6195 023366 104000      ERROR     ;ERROR # DEFINED BY TSTPRP SUBROUTINE
```



```
6196 023370 000137 023624          JMP      190$          ;GO TO 190$ IF ERROR WAS FOUND
6197 023374
6198
6199          ;SETUP PARAMETERS FOR READING 2 SECTORS STARTING WITH LAST SECTOR
6200 023374 012737 001466 001434      MOV      #822,RMDCO          ;START AT LAST CYLINDER
6201 023402 012737 002037 001406      MOV      #2037,RMDAO        ;TRACK = 4 SECTOR = 31.
6202 023410 012737 010000 001432      MOV      #FMT16,RMOFO        ;16 BIT FORMAT
6203 023416 012737 176774 001402      MOV      #<^C<<2+256.>*2>+1>,RMWCO      ;FORMAT 2 SECTORS
6204 023424 012737 104570 001404      MOV      #BUFTWO,RMBAO        ;DATA BUFFER ADDRESS
6205 023432 012737 000073 001400      MOV      #RH!GO,RMCS10      ;WRITE HEADER AND DATA
6206 023440 012702 001535              MOV      #PUTINX,R2          ;WRITE REGISTER INDEX TABLE
6207 023444 112722 000006              MOVB     #RMDA,(R2)+
6208 023450 112722 000034              MOVB     #RMDC,(R2)+
6209 023454 112722 000032              MOVB     #RMOF,(R2)+
6210 023460 112722 000002              MOVB     #RMWC,(R2)+
6211 023464 112722 000004              MOVB     #RMBA,(R2)+
6212 023470 112722 000000              MOVB     #RMCS1,(R2)+
6213 023474 112722 000200              MOVB     #200,(R2)+
6214 023500
6215
6216 023500
6217 023500 004737 037766              JSR      PC,PUT          ;GO WRITE REGISTERS VIA PUT SUB
6218 023504 000404                      BR       130$          ;GO TO 130$ IF NO ERROR
6219 023506 000240                      NOP                      ;RETURN HERE IF ERROR
6220 023510 104000                      ERROR          ;ERROR DEFINED BY PUT SUB
6221 023512 000137 023624              JMP      190$          ;GO TO 190$ IF ERROR WAS FOUND
6222 023516
6223
6224          ;SETUP INPUT REGISTER BUFFER FOR READING STATUS
6225 023516 004737 037432              JSR      PC,GETSTS
6226
6227          ;WAIT FOR READ TO COMPLETE AND GET STATUS
6228 023522 004737 040326              JSR      PC,TIMOUT        ;WAIT FOR READ TO COMPLETE
6229 023526 004737 037516              JSR      PC,GET          ;GO READ REGISTERS VIA GET SUB
6230 023532 000404                      BR       140$          ;GO TO 140$ IF NO ERROR
6231 023534 000240                      NOP                      ;RETURN HERE IF ERROR
6232 023536 104000                      ERROR          ;ERROR DEFINED BY GET SUB
6233 023540 000137 023624              JMP      190$          ;GO TO 190$ IF ERROR WAS FOUND
6234 023544
6235
6236          ;VERIFY THE RESULTS OF READ OPERATION
6237 023544 004737 040512              JSR      PC,PRIERR        ;GO CHECK FOR PRIMARY ERRORS
6238 023550 000405                      BR       150$          ;GO TO 150$ IF NO ERROR
6239 023552 000240                      NOP                      ;RETURN HERE IF ERROR
6240 023554 104000                      ERROR          ;ERROR # DEFINED BY PRIERR SUBROUTINE
6241 023556 004736                      JSR      PC,@(SP)+      ;GO BACK FOR MORE ERROR CHECKS
6242 023560 000137 023624              JMP      190$          ;GO TO 190$ IF ERROR WAS FOUND
6243 023564
6244 023564 004737 053016              JSR      PC,DASTS        ;GO VERIFY RESULTS OF DATA TRANSFER
6245 023570 000405                      BR       160$          ;GO TO 160$ IF NO ERROR
6246 023572 000240                      NOP                      ;RETURN HERE IF ERROR
6247 023574 104000                      ERROR          ;ERROR # DEFINED BY DASTS SUBROUTINE
6248 023576 004736                      JSR      PC,@(SP)+      ;GO BACK FOR MORE ERROR CHECKS
6249 023600 000137 023624              JMP      190$          ;GO TO 190$ IF ERROR WAS FOUND
6250 023604
6251 023604 004737 041344              JSR      PC,SECERR        ;GO CHECK FOR SECONDARY ERRORS
```

```
6252 023610 000405 BR 170$ ;GO TO 170$ IF NO ERROR
6253 023612 000240 NOP ;RETURN HERE IF ERROR
6254 023614 104000 ERROR ;ERROR # DEFINED BY SECERR SUBROUTINE
6255 023616 004736 JSR PC,2(SP)+ ;GO BACK FOR MORE ERROR CHECKS
6256 023620 000137 023624 JMP 190$ ;GO TO 190$ IF ERROR WAS FOUND
6257 023624 170$:
6258
6259 023624 190$:
6260
6261 ;*****
6262 ;*TEST 25 FORMAT INVALID SECTOR ADDRESS
6263 ;*****
6264 023624 TST25:
6265 023624 000004 SCOPE ;SCOPE CALL
6266 023626 000240 NOP ;START OF TEST
6267 023630 012706 001100 MOV #STACK,SP ;INITIALIZE STACK POINTER
6268 023634 013700 001276 MOV $BASE,R0 ;R0=UNIBUS ADDRESS
6269 023640 013701 001450 MOV TSTQUE,R1 ;(R1) = DEVICE BEING TESTED
6270 023644 012737 000025 001226 MOV #25,$TESTN ;SET TEST NUMBER IN APT MAIL BOX
6271 023652 10$:
6272
6273 ;SETUP PARAMETERS FOR GENERATING DATA BUFFER
6274 023652 012737 000000 001434 MOV #0,RMDCO ;CYLINDER = 0
6275 023660 012737 000036 001406 MOV #30.,RMDAO ;TRACK = 0, SECTOR = 30
6276 023666 012737 000000 001432 15$: MOV #0,RMOFO ;18 BIT FORMAT
6277 023674 012737 177376 001402 MOV #<^C<2+256.>+1>,RMWCO ;2 + 256 WORDS
6278 023702 012737 103564 001404 MOV #BUFONE,RMBAD ;DATA BUFFER ADDRESS
6279 023710 012737 000062 001400 MOV #WH,RMCS10 ;WRITE HEADER AND DATA
6280 023716 012737 001406 001174 MOV #RMDAO,$TMPO ;USE SECTOR FOR DATA PATTERN
6281 023724 012737 000001 001176 MOV #1,$TMP1
6282 023732 004737 036620 JSR PC,GENBUF ;GO GENERATE DATA BUFFER
6283 023736 20$:
6284
6285 ;PREPARE DEVICE FOR DATA TRANSFER
6286 023736 004737 034000 JSR PC,TSTPRP ;PREPARE DEVICE FOR TEST
6287 023742 154130 .WORD 154130 ;TASK DESCRIPTOR
6288 023744 000404 BR 30$ ;GO TO 30$ IF NO ERROR
6289 023746 000240 NOP ;RETURN HERE IF ERROR
6290 023750 104000 ERROR ;ERROR # DEFINED BY TSTPRP SUBROUTINE
6291 023752 000137 024352 JMP 190$ ;GO TO 190$ IF ERROR WAS FOUND
6292 023756 30$:
6293
6294 ;SETUP AND EXECUTE WRITE HEADER AND DATA COMMAND
6295 023756 012737 000063 001400 MOV #WH!GO,RMCS10 ;WRITE HEADER AND DATA
6296 023764 012702 001535 MOV #PUTINX,R2 ;WRITE REGISTER INDEX TABLE
6297 023770 112722 000006 MOVB #RMDA,(R2)+
6298 023774 112722 000034 MOVB #RMDC,(R2)+
6299 024000 112722 000032 MOVB #RMOF,(R2)+
6300 024004 112722 000002 MOVB #RMWC,(R2)+
6301 024010 112722 000004 MOVB #RMBA,(R2)+
6302 024014 112722 000000 MOVB #RMCS1,(R2)+
6303 024020 112722 000200 MOVB #200,(R2)+
6304 024024 004737 037766 JSR PC,PUT ;GO WRITE REGISTERS VIA PUT SUB
6305 024030 000404 BR 80$ ;GO TO 80$ IF NO ERROR
6306 024032 000240 NOP ;RETURN HERE IF ERROR
6307 024034 104000 ERROR ;ERROR DEFINED BY PUT SUB
```



```
6308 024036 000137 024352      JMP      190$      ;GO TO 190$ IF ERROR WAS FOUND
6309 024042      80$:
6310
6311      ;SETUP INPUT REGISTER BUFFER FOR READING STATUS
6312 024042 004737 037432      JSR      PC,GETSTS
6313
6314      ;WAIT FOR WRITE COMMAND TO COMPLETE AND READ STATUS
6315 024046 004737 040326      JSR      PC,TIMOUT      ;WAIT FOR COMMAND TO COMPLETE
6316 024052 004737 037516      JSR      PC,GET      ;GO READ REGISTERS VIA GET SUB
6317 024056 000404      BR      90$      ;GO TO 90$ IF NO ERROR
6318 024060 000240      NOP
6319 024062 104000      ERROR      ;RETURN HERE IF ERROR
6320 024064 000137 024352      JMP      190$      ;GO TO 190$ IF ERROR WAS FOUND
6321 024070      90$:
6322
6323      ;VERIFY RESULTS OF WRITE COMMAND
6324 024070 004737 040512      JSR      PC,PRIERR      ;GO CHECK FOR PRIMARY ERRORS
6325 024074 000405      BR      100$      ;GO TO 100$ IF NO ERROR
6326 024076 000240      NOP
6327 024100 104000      ERROR      ;RETURN HERE IF ERROR
6328 024102 004736      JSR      PC,@(SP)+      ;ERROR # DEFINED BY PRIERR SUBROUTINE
6329 024104 000137 024352      JMP      190$      ;GO BACK FOR MORE ERROR CHECKS
6330 024110      100$:
6331 024110 004737 053016      JSR      PC,DTASTS      ;GO VERIFY RESULTS OF DATA TRANSFER
6332 024114 000405      BR      110$      ;GO TO 110$ IF NO ERROR
6333 024116 000240      NOP
6334 024120 104000      ERROR      ;RETURN HERE IF ERROR
6335 024122 004736      JSR      PC,@(SP)+      ;ERROR # DEFINED BY DTASTS SUBROUTINE
6336 024124 000137 024352      JMP      190$      ;GO BACK FOR MORE ERROR CHECKS
6337 024130      110$:
6338 024130 004737 041344      JSR      PC,SECERR      ;GO CHECK FOR SECONDARY ERRORS
6339 024134 000405      BR      120$      ;GO TO 120$ IF NO ERROR
6340 024136 000240      NOP
6341 024140 104000      ERROR      ;RETURN HERE IF ERROR
6342 024142 004736      JSR      PC,@(SP)+      ;ERROR # DEFINED BY SECERR SUBROUTINE
6343 024144 000137 024352      JMP      190$      ;GO BACK FOR MORE ERROR CHECKS
6344 024150      120$:
6345
6346      ;CLEAR "IAE" ERROR AND PREPARE DEVICE
6347 024150 004737 034000      JSR      PC,TSTPRP      ;PREPARE DEVICE FOR TEST
6348 024154 154130      .WORD      154130      ;TASK DESCRIPTOR
6349 024156 000404      BR      125$      ;GO TO 125$ IF NO ERROR
6350 024160 000240      NOP
6351 024162 104000      ERROR      ;RETURN HERE IF ERROR
6352 024164 000137 024352      JMP      190$      ;ERROR # DEFINED BY TSTPRP SUBROUTINE
6353 024170      125$:
6354
6355      ;READ HEADER AND DATA FOR SECTOR JUST WRITTEN
6356 024170 012737 000073 001400      MOV      #RH!GO,RMC$IO      ;READ HEADER & DATA COMMAND
6357 024176 012737 104570 001404      MOV      #BUFTWO,RMBAO      ;CHANGE BUS ADDRESS
6358 024204 004737 037766      JSR      PC,PUT      ;GO WRITE REGISTERS VIA PUT SUB
6359 024210 000404      BR      130$      ;GO TO 130$ IF NO ERROR
6360 024212 000240      NOP
6361 024214 104000      ERROR      ;RETURN HERE IF ERROR
6362 024216 000137 024352      JMP      190$      ;ERROR DEFINED BY PUT SUB
6363 024222      130$:

```

```
6364
6365 ;SETUP INPUT REGISTER BUFFER FOR READING STATUS
6366 024222 004737 037432 JSR PC,GETSTS
6367
6368 ;WAIT FOR READ TO COMPLETE AND GET STATUS
6369 024226 004737 040326 JSR PC,TIMOUT ;WAIT FOR READ TO COMPLETE
6370 024232 004737 037516 JSR PC,GET ;GO READ REGISTERS VIA GET SUB
6371 024236 000404 BR 140$ ;GO TO 140$ IF NO ERROR
6372 024240 000240 NOP ;RETURN HERE IF ERROR
6373 024242 104000 ERROR ;ERROR DEFINED BY GET SUB
6374 024244 000137 024352 JMP 190$ ;GO TO 190$ IF ERROR WAS FOUND
6375 024250 140$:
6376
6377 ;VERIFY THE RESULTS OF READ OPERATION
6378 024250 004737 040512 JSR PC,PRIERR ;GO CHECK FOR PRIMARY ERRORS
6379 024254 000405 BR 150$ ;GO TO 150$ IF NO ERROR
6380 024256 000240 NOP ;RETURN HERE IF ERROR
6381 024260 104000 ERROR ;ERROR # DEFINED BY PRIERR SUBROUTINE
6382 024262 004736 JSR PC,@(SP)+ ;GO BACK FOR MORE ERROR CHECKS
6383 024264 000137 024352 JMP 190$ ;GO TO 190$ IF ERROR WAS FOUND
6384 024270 150$:
6385 024270 004737 053016 JSR PC,DTASTS ;GO VERIFY RESULTS OF DATA TRANSFER
6386 024274 000405 BR 160$ ;GO TO 160$ IF NO ERROR
6387 024276 000240 NOP ;RETURN HERE IF ERROR
6388 024300 104000 ERROR ;ERROR # DEFINED BY DTASTS SUBROUTINE
6389 024302 004736 JSR PC,@(SP)+ ;GO BACK FOR MORE ERROR CHECKS
6390 024304 000137 024352 JMP 190$ ;GO TO 190$ IF ERROR WAS FOUND
6391 024310 160$:
6392 024310 004737 041344 JSR PC,SECERR ;GO CHECK FOR SECONDARY ERRORS
6393 024314 000405 BR 170$ ;GO TO 170$ IF NO ERROR
6394 024316 000240 NOP ;RETURN HERE IF ERROR
6395 024320 104000 ERROR ;ERROR # DEFINED BY SECERR SUBROUTINE
6396 024322 004736 JSR PC,@(SP)+ ;GO BACK FOR MORE ERROR CHECKS
6397 024324 000137 024352 JMP 190$ ;GO TO 190$ IF ERROR WAS FOUND
6398 024330 170$
6399 024330 180$:
6400
6401 ;INCREMENT ADDRESS AND FORMAT NEXT SECTOR
6402 024330 062737 000001 001406 ADD #1,RMDAO ;ADVANCE SECTOR COUNT
6403 024336 022737 000037 001406 CMP #31,RMDAO ;DONE ALL SECTORS??
6404 024344 103402 BLO 190$ ;YES!!
6405 024346 000137 023666 JMP 15$ ;GO DO NEXT SECTOR
6406 024352 190$:
6407
6408 ;*****
6409 ;*TEST 26 FORMAT INVALID TRACK ADDRESS
6410 ;*****
6411 TST26:
6412 024352 000004 SCOPE ;SCOPE CALL
6413 024354 000240 NOP ;START OF TEST
6414 024356 012706 001100 MOV #STACK,SP ;INITIALIZE STACK POINTER
6415 024362 013700 001276 MOV $BASE,R0 ;R0=UNIBUS ADDRESS
6416 024366 013701 001450 MOV TSTQUE,R1 ;(R1) = DEVICE BEING TESTED
6417 024372 012737 000026 001226 MOV #26,$TESTN ;;SET TEST NUMBER IN APT MAIL BOX
6418 024400 10$:
6419
```

```

6420 ;SETUP PARAMETERS FOR GENERATING DATA BUFFER
6421 024400 012737 000000 001434 MOV #0,RMDCO ;CYLINDER = 0
6422 024406 012737 002400 001406 MOV #2400,RMDAO ;TRACK = 5,SECTOR 0
6423 024414 012737 010000 001432 15%: MOV #FMT16,RMOFO ;16 BIT FORMAT
6424 024422 012737 177376 001402 MOV #<^C<2+256.>+1>,RMWCO ;2 + 256 WORDS
6425 024430 012737 103564 001404 MOV #BUFONE,RMBAO ;DATA BUFFER ADDRESS
6426 024436 012737 000062 001400 MOV #WH,RMCS10 ;WRITE HEADER AND DATA
6427 024444 012737 001406 001174 MOV #RMDAO,STMP0 ;USE SECTOR FOR DATA PATTERN
6428 024452 012737 000001 001176 MOV #1,STMP1
6429 024460 004737 036620 JSR PC,GENBUF ;GO GENERATE DATA BUFFER
6430 024464 20%:
6431
6432 ;PREPARE DEVICE FOR DATA TRANSFER
6433 024464 004737 034000 JSR PC,ISTPRP ;PREPARE DEVICE FOR TEST
6434 024470 154130 .WORD 154130 ;TASK DESCRIPTOR
6435 024472 000404 BR 30% ;GO TO 30% IF NO ERROR
6436 024474 000240 NOP ;RETURN HERE IF ERROR
6437 024476 104000 ERROR ;ERROR # DEFINED BY ISTPRP SUBROUTINE
6438 024500 000137 025100 JMP 190% ;GO TO 190% IF ERROR WAS FOUND
6439 024504 30%:
6440
6441 ;SETUP AND EXECUTE WRITE HEADER AND DATA COMMAND
6442 024504 012737 000063 001400 MOV #WH!GO,RMCS10 ;WRITE HEADER AND DATA
6443 024512 012702 001535 MOV #PUTINX,R2 ;WRITE REGISTER INDEX TABLE
6444 024516 112722 000006 MOV #RMDA,(R2)+
6445 024522 112722 000034 MOV #RMDC,(R2)+
6446 024526 112722 000032 MOV #RMOF,(R2)+
6447 024532 112722 000002 MOV #RMWC,(R2)+
6448 024536 112722 000004 MOV #RMBA,(R2)+
6449 024542 112722 000000 MOV #RMCS1,(R2)+
6450 024546 112722 000200 MOV #200,(R2)+
6451 024552 004737 037766 JSR PC,PUT ;GO WRITE REGISTERS VIA PUT SUB
6452 024556 000404 BR 80% ;GO TO 80% IF NO ERROR
6453 024560 000240 NOP ;RETURN HERE IF ERROR
6454 024562 104000 ERROR ;ERROR DEFINED BY PUT SUB
6455 024564 000137 025100 JMP 190% ;GO TO 190% IF ERROR WAS FOUND
6456 024570 80%:
6457
6458 ;SETUP INPUT REGISTER BUFFER FOR READING STATUS
6459 024570 004737 037432 JSR PC,GETSTS
6460
6461 ;WAIT FOR WRITE COMMAND TO COMPLETE AND READ STATUS
6462 024574 004737 040326 JSR PC,TIMOUT ;WAIT FOR COMMAND TO COMPLETE
6463 024600 004737 037516 JSR PC,GET ;GO READ REGISTERS VIA GET SUB
6464 024604 000404 BR 90% ;GO TO 90% IF NO ERROR
6465 024606 000240 NOP ;RETURN HERE IF ERROR
6466 024610 104000 ERROR ;ERROR DEFINED BY GET SUB
6467 024612 000137 025100 JMP 190% ;GO TO 190% IF ERROR WAS FOUND
6468 024616 90%:
6469
6470 ;VERIFY RESULTS OF WRITE COMMAND
6471 024616 004737 040512 JSR PC,PRIERR ;GO CHECK FOR PRIMARY ERRORS
6472 024622 000405 BR 100% ;GO TO 100% IF NO ERROR
6473 024624 000240 NOP ;RETURN HERE IF ERROR
6474 024626 104000 ERROR ;ERROR # DEFINED BY PRIERR SUBROUTINE
6475 024630 004736 JSR PC,@(SP)+ ;GO BACK FOR MORE ERROR CHECKS

```

```

6476 024632 000137 025100      JMP      190$      ;GO TO 190$ IF ERROR WAS FOUND
6477 024636      100$:      JSR      PC,DTASTS      ;GO VERIFY RESULTS OF DATA TRANSFER
6478 024636 004737 053016      BR      110$      ;GO TO 110$ IF NO ERROR
6479 024642 000405      NOP      ;RETURN HERE IF ERROR
6480 024644 000240      ERROR    ;ERROR # DEFINED BY DTASTS SUBROUTINE
6481 024646 104000      JSR      PC,@(SP)+      ;GO BACK FOR MORE ERROR CHECKS
6482 024650 004736      JMP      190$      ;GO TO 190$ IF ERROR WAS FOUND
6483 024652 000137 025100      110$:      JSR      PC,SECERR      ;GO CHECK FOR SECONDARY ERRORS
6484 024656      BR      120$      ;GO TO 120$ IF NO ERROR
6485 024656 004737 041344      NOP      ;RETURN HERE IF ERROR
6486 024662 000405      ERROR    ;ERROR # DEFINED BY SECERR SUBROUTINE
6487 024664 000240      JSR      PC,@(SP)+      ;GO BACK FOR MORE ERROR CHECKS
6488 024666 104000      JMP      190$      ;GO TO 190$ IF ERROR WAS FOUND
6489 024670 004736      120$:      JSR      PC,TSTPRP      ;PREPARE DEVICE FOR TEST
6490 024672 000137 025100      .WORD    154130 ;TASK DESCRIPTOR
6491 024676      BR      125$      ;GO TO 125$ IF NO ERROR
6492      NOP      ;RETURN HERE IF ERROR
6493      ERROR    ;ERROR # DEFINED BY TSTPRP SUBROUTINE
6494 024676 004737 034000      JMP      190$      ;GO TO 190$ IF ERROR WAS FOUND
6495 024702 154130      125$:      ;CLEAR "IAE" ERROR AND PREPARE DEVICE
6496 024704 000404      ;READ HEADER AND DATA FOR SECTOR JUST WRITTEN
6497 024706 000240      MOV      #RH!GO,RMC$10      ;READ HEADER & DATA COMMAND
6498 024710 104000      MOV      #BUFTWO,RMBAO      ;CHANGE BUS ADDRESS
6499 024712 000137 025100      JSR      PC,PUT      ;GO WRITE REGISTERS VIA PUT SUB
6500 024716      BR      130$      ;GO TO 130$ IF NO ERROR
6501      NOP      ;RETURN HERE IF ERROR
6502      ERROR    ;ERROR DEFINED BY PUT SUB
6503 024716 012737 000073 001400      JMP      190$      ;GO TO 190$ IF ERROR WAS FOUND
6504 024724 012737 104570 001404      130$:      ;SETUP INPUT REGISTER BUFFER FOR READING STATUS
6505 024732 004737 037766      JSR      PC,GETSTS
6506 024736 000404      ;WAIT FOR READ TO COMPLETE AND GET STATUS
6507 024740 000240      JSR      PC,TIMOUT      ;WAIT FOR READ TO COMPLETE
6508 024742 104000      JSR      PC,GET      ;GO READ REGISTERS VIA GET SUB
6509 024744 000137 025100      BR      140$      ;GO TO 140$ IF NO ERROR
6510 024750      NOP      ;RETURN HERE IF ERROR
6511      ERROR    ;ERROR DEFINED BY GET SUB
6512      JMP      190$      ;GO TO 190$ IF ERROR WAS FOUND
6513 024750 004737 037432      140$:      ;VERIFY THE RESULTS OF READ OPERATION
6514      JSR      PC,PRIERR      ;GO CHECK FOR PRIMARY ERRORS
6515      BR      150$      ;GO TO 150$ IF NO ERROR
6516 024754 004737 040326      NOP      ;RETURN HERE IF ERROR
6517 024760 004737 037516      ERROR    ;ERROR # DEFINED BY PRIERR SUBROUTINE
6518 024764 000404      JSR      PC,@(SP)+      ;GO BACK FOR MORE ERROR CHECKS
6519 024766 000240      JMP      190$      ;GO TO 190$ IF ERROR WAS FOUND
6520 024770 104000      150$:      ;GO CHECK FOR PRIMARY ERRORS
6521 024772 000137 025100      BR      150$      ;GO TO 150$ IF NO ERROR
6522 024776      NOP      ;RETURN HERE IF ERROR
6523      ERROR    ;ERROR # DEFINED BY PRIERR SUBROUTINE
6524      JSR      PC,@(SP)+      ;GO BACK FOR MORE ERROR CHECKS
6525 024776 004737 040512      JMP      190$      ;GO TO 190$ IF ERROR WAS FOUND
6526 025002 000405      150$:      ;GO CHECK FOR PRIMARY ERRORS
6527 025004 000240      BR      150$      ;GO TO 150$ IF NO ERROR
6528 025006 104000      NOP      ;RETURN HERE IF ERROR
6529 025010 004736      ERROR    ;ERROR # DEFINED BY PRIERR SUBROUTINE
6530 025012 000137 025100      JSR      PC,@(SP)+      ;GO BACK FOR MORE ERROR CHECKS
6531 025016      JMP      190$      ;GO TO 190$ IF ERROR WAS FOUND

```

```
6532 025016 004737 053016      JSR    PC,DTASTS      ;GO VERIFY RESULTS OF DATA TRANSFER
6533 025022 000405              BR      160$          ;GO TO 160$ IF NO ERROR
6534 025024 000240              NOP                    ;RETURN HERE IF ERROR
6535 025026 104000              ERROR                 ;ERROR # DEFINED BY DTASTS SUBROUTINE
6536 025030 004736              JSR    PC,@(SP)+      ;GO BACK FOR MORE ERROR CHECKS
6537 025032 000137 025100      JMP      190$          ;GO TO 190$ IF ERROR WAS FOUND
6538 025036                      160$:
6539 025036 004737 041344      JSR    PC,SECERR      ;GO CHECK FOR SECONDARY ERRORS
6540 025042 000405              BR      170$          ;GO TO 170$ IF NO ERROR
6541 025044 000240              NOP                    ;RETURN HERE IF ERROR
6542 025046 104000              ERROR                 ;ERROR # DEFINED BY SECERR SUBROUTINE
6543 025050 004736              JSR    PC,@(SP)+      ;GO BACK FOR MORE ERROR CHECKS
6544 025052 000137 025100      JMP      190$          ;GO TO 190$ IF ERROR WAS FOUND
6545 025056                      170$:
6546 025056                      180$:
6547
6548                      ;INCREMENT ADDRESS AND FORMAT NEXT TRACK
6549 025056 062737 000400 001406  ADD     #400,RMDAO      ;ADVANCE TRACK COUNT
6550 025064 022737 003400 001406  CMP     #3400,RMDAO     ;DONE ALL TRACKS??
6551 025072 103402              BLO     190$          ;YES!!
6552 025074 000137 024414      JMP      15$           ;GO DO NEXT TRACK
6553 025100                      190$:
6554
6555                      ;*****
6556                      ;*TEST 27      FORMAT INVALID CYLINDER ADDRESS
6557                      ;*****
6558 025100      TST27:
6559 025100 000004              SCOPE                    ;SCOPE CALL
6560 025102 000240              NOP                    ;START OF TEST
6561 025104 012706 001100      MOV     #STACK,SP        ;INITIALIZE STACK POINTER
6562 025110 013700 001276      MOV     $BASE,R0         ;R0=UNIBUS ADDRESS
6563 025114 013701 001450      MOV     TSTQUE,R1        ;(R1) = DEVICE BEING TESTED
6564 025120 012737 000027 001226  MOV     #27,$TESTN    ;SET TEST NUMBER IN APT MAIL BOX
6565 025126                      10$:
6566
6567                      ;SETUP PARAMETERS FOR GENERATING DATA BUFFER
6568 025126 012737 001467 001434  MOV     #823.,RMDCO      ;START AT LAST CYLINDER + 1
6569 025134 012737 000000 001406  MOV     #0,RMDAO        ;TRACK = SECTOR = 0
6570 025142 012737 010000 001432  15$: MOV     #FMT16,RMOFO      ;16 BIT FORMAT
6571 025150 012737 177376 001402  MOV     #<^C<2+256.>+1>,RMWCO ;2 + 256 WORDS
6572 025156 012737 103564 001404  MOV     #BUFONE,RMBAO     ;DATA BUFFER ADDRESS
6573 025164 012737 000062 001400  MOV     #WH,RMCS10      ;WRITE HEADER AND DATA
6574 025172 012737 001434 001174  MOV     #RMDCO,$TMP0     ;USE CYLINDER FOR DATA PATTERN
6575 025200 012737 000001 001176  MOV     #1,$TMP1
6576 025206 004737 036620      JSR      PC,GENBUF        ;GO GENERATE DATA BUFFER
6577 025212                      20$:
6578
6579                      ;PREPARE DEVICE FOR DATA TRANSFER
6580 025212 004737 034000      JSR      PC,TSTPRP      ;PREPARE DEVICE FOR TEST
6581 025216 154130              .WORD    154130      ;TASK DESCRIPTOR
6582 025220 000404              BR      30$           ;GO TO 30$ IF NO ERROR
6583 025222 000240              NOP                    ;RETURN HERE IF ERROR
6584 025224 104000              ERROR                 ;ERROR # DEFINED BY TSTPRP SUBROUTINE
6585 025226 000137 025626      JMP      190$          ;GO TO 190$ IF ERROR WAS FOUND
6586 025232                      30$:
6587
```

```
6588 ;SETUP AND EXECUTE WRITE HEADER AND DATA COMMAND
6589 025232 012737 000063 001400 MOV #WH!GO,RMCS10 ;WRITE HEADER AND DATA
6590 025240 012702 001535 MOV #PUTINX,R2 ;WRITE REGISTER INDEX TABLE
6591 025244 112722 000006 MOV #RMDA,(R2)+
6592 025250 112722 000034 MOV #RMDC,(R2)+
6593 025254 112722 000032 MOV #RMOF,(R2)+
6594 025260 112722 000002 MOV #RMWC,(R2)+
6595 025264 112722 000004 MOV #RMBA,(R2)+
6596 025270 112722 000000 MOV #RMCS1,(R2)+
6597 025274 112722 000200 MOV #200,(R2)+
6598 025300 004737 037766 JSR PC,PUT ;GO WRITE REGISTERS VIA PUT SUB
6599 025304 000404 BR 80$ ;GO TO 80$ IF NO ERROR
6600 025306 000240 NOP ;RETURN HERE IF ERROR
6601 025310 104000 ERROR ;ERROR DEFINED BY PUT SUB
6602 025312 000137 025626 JMP 190$ ;GO TO 190$ IF ERROR WAS FOUND
6603 025316
6604 80$:
6605 ;SETUP INPUT REGISTER BUFFER FOR READING STATUS
6606 025316 004737 037432 JSR PC,GETSTS
6607
6608 ;WAIT FOR WRITE COMMAND TO COMPLETE AND READ STATUS
6609 025322 004737 040326 JSR PC,TIMOUT ;WAIT FOR COMMAND TO COMPLETE
6610 025326 004737 037516 JSR PC,GET ;GO READ REGISTERS VIA GET SUB
6611 025332 000404 BR 90$ ;GO TO 90$ IF NO ERROR
6612 025334 000240 NOP ;RETURN HERE IF ERROR
6613 025336 104000 ERROR ;ERROR DEFINED BY GET SUB
6614 025340 000137 025626 JMP 190$ ;GO TO 190$ IF ERROR WAS FOUND
6615 025344
6616 90$:
6617 ;VERIFY RESULTS OF WRITE COMMAND
6618 025344 004737 040512 JSR PC,PRIERR ;GO CHECK FOR PRIMARY ERRORS
6619 025350 000405 BR 100$ ;GO TO 100$ IF NO ERROR
6620 025352 000240 NOP ;RETURN HERE IF ERROR
6621 025354 104000 ERROR ;ERROR # DEFINED BY PRIERR SUBROUTINE
6622 025356 004736 JSR PC,@(SP)+ ;GO BACK FOR MORE ERROR CHECKS
6623 025360 000137 025626 JMP 190$ ;GO TO 190$ IF ERROR WAS FOUND
6624 025364
6625 025364 004737 053016 JSR PC,DASTS ;GO VERIFY RESULTS OF DATA TRANSFER
6626 025370 000405 BR 110$ ;GO TO 110$ IF NO ERROR
6627 025372 000240 NOP ;RETURN HERE IF ERROR
6628 025374 104000 ERROR ;ERROR # DEFINED BY DASTS SUBROUTINE
6629 025376 004736 JSR PC,@(SP)+ ;GO BACK FOR MORE ERROR CHECKS
6630 025400 000137 025626 JMP 190$ ;GO TO 190$ IF ERROR WAS FOUND
6631 025404
6632 025404 004737 041344 JSR PC,SECERR ;GO CHECK FOR SECONDARY ERRORS
6633 025410 000405 BR 120$ ;GO TO 120$ IF NO ERROR
6634 025412 000240 NOP ;RETURN HERE IF ERROR
6635 025414 104000 ERROR ;ERROR # DEFINED BY SECERR SUBROUTINE
6636 025416 004736 JSR PC,@(SP)+ ;GO BACK FOR MORE ERROR CHECKS
6637 025420 000137 025626 JMP 190$ ;GO TO 190$ IF ERROR WAS FOUND
6638 025424
6639 120$:
6640 ;CLEAR "IAE" ERROR AND PREPARE DEVICE
6641 025424 004737 034000 JSR PC,TSTPRP ;PREPARE DEVICE FOR TEST
6642 025430 154130 .WORD 154130 ;TASK DESCRIPTOR
6643 025432 000404 BR 125$ ;GO TO 125$ IF NO ERROR
```



```
6644 025434 000240      NOP      ;RETURN HERE IF ERROR
6645 025436 104000      ERROR     ;ERROR # DEFINED BY TSTPRP SUBROUTINE
6646 025440 000137 025626 125$: JMP 190$ ;GO TO 190$ IF ERROR WAS FOUND
6647 025444
6648
6649 ;READ HEADER AND DATA FOR SECTOR JUST WRITTEN
6650 025444 012737 000073 001400 MOV #RH!GO,RMCS10 ;READ HEADER & DATA COMMAND
6651 025452 012737 104570 001404 MOV #BUFTWO,RMBAO ;CHANGE BUS ADDRESS
6652 025460 004737 037766 JSR PC,PUT ;GO WRITE REGISTERS VIA PUT SUB
6653 025464 000404 BR 130$ ;GO TO 130$ IF NO ERROR
6654 025466 000240 NOP ;RETURN HERE IF ERROR
6655 025470 104000 ERROR ;ERROR DEFINED BY PUT SUB
6656 025472 000137 025626 JMP 190$ ;GO TO 190$ IF ERROR WAS FOUND
6657 025476 130$:
6658
6659 ;SETUP INPUT REGISTER BUFFER FOR READING STATUS
6660 025476 004737 037432 JSR PC,GETSTS
6661
6662 ;WAIT FOR READ TO COMPLETE AND GET STATUS
6663 025502 004737 040326 JSR PC,TIMOUT ;WAIT FOR READ TO COMPLETE
6664 025506 004737 037516 JSR PC,GET ;GO READ REGISTERS VIA GET SUB
6665 025512 000404 BR 140$ ;GO TO 140$ IF NO ERROR
6666 025514 000240 NOP ;RETURN HERE IF ERROR
6667 025516 104000 ERROR ;ERROR DEFINED BY GET SUB
6668 025520 000137 025626 JMP 190$ ;GO TO 190$ IF ERROR WAS FOUND
6669 025524 140$:
6670
6671 ;VERIFY THE RESULTS OF READ OPERATION
6672 025524 004737 040512 JSR PC,PRIERR ;GO CHECK FOR PRIMARY ERRORS
6673 025530 000405 BR 150$ ;GO TO 150$ IF NO ERROR
6674 025532 000240 NOP ;RETURN HERE IF ERROR
6675 025534 104000 ERROR ;ERROR # DEFINED BY PRIERR SUBROUTINE
6676 025536 004736 JSR PC,@(SP)+ ;GO BACK FOR MORE ERROR CHECKS
6677 025540 000137 025626 JMP 190$ ;GO TO 190$ IF ERROR WAS FOUND
6678 025544 150$:
6679 025544 004737 053016 JSR PC,DASTS ;GO VERIFY RESULTS OF DATA TRANSFER
6680 025550 000405 BR 160$ ;GO TO 160$ IF NO ERROR
6681 025552 000240 NOP ;RETURN HERE IF ERROR
6682 025554 104000 ERROR ;ERROR # DEFINED BY DASTS SUBROUTINE
6683 025556 004736 JSR PC,@(SP)+ ;GO BACK FOR MORE ERROR CHECKS
6684 025560 000137 025626 JMP 190$ ;GO TO 190$ IF ERROR WAS FOUND
6685 025564 160$:
6686 025564 004737 041344 JSR PC,SECERR ;GO CHECK FOR SECONDARY ERRORS
6687 025570 000405 BR 170$ ;GO TO 170$ IF NO ERROR
6688 025572 000240 NOP ;RETURN HERE IF ERROR
6689 025574 104000 ERROR ;ERROR # DEFINED BY SECERR SUBROUTINE
6690 025576 004736 JSR PC,@(SP)+ ;GO BACK FOR MORE ERROR CHECKS
6691 025600 000137 025626 JMP 190$ ;GO TO 190$ IF ERROR WAS FOUND
6692 025604 170$:
6693
6694 ;INCREMENT ADDRESS AND FORMAT NEXT CYLINDER
6695 025604 062737 000001 001434 ADD #1,RMDCO ;ADVANCE CYLINDER COUNT
6696 025612 022737 071777 001434 CMP #1777,RMDCO ;DONE ALL CYLINDERS??
6697 025620 103402 BLO 190$ ;YES!!
6698 025622 000137 025142 JMP 15$ ;GO DO NEXT SECTOR
6699 025626 190$:
```

```

6700
6701
6702
6703
6704 025626
6705 025626 000004
6706 025630 000240
6707 025632 012706 001100
6708 025636 013700 001276
6709 025642 013701 001450
6710 025646 012737 000030 001226
6711 025654
6712
6713
6714 025654 012737 000000 001434
6715 025662 012737 000000 001406
6716 025670 012737 010000 001432
6717 025676 012737 177376 001402
6718 025704 012737 103564 001404
6719 025712 012737 000063 001400
6720 025720 012737 001406 001174
6721 025726 012737 000001 001176
6722 025734 004737 036620
6723 025740
6724
6725
6726 025740 004737 034000
6727 025744 154130
6728 025746 000404
6729 025750 000240
6730 025752 104000
6731 025754 000137 026520
6732 025760
6733
6734
6735 025760 012737 000015 001400
6736 025766 012702 001535
6737 025772 112722 000006
6738 025776 112722 000034
6739 026002 112722 000032
6740 026006 112722 000000
6741 026012 112712 000200
6742 026016 004737 037766
6743 026022 000404
6744 026024 000240
6745 026026 104000
6746 026030 000137 026520
6747 026034
6748
6749
6750 026034 012737 000063 001400
6751 026042 012702 001535
6752 026046 112722 000002
6753 026052 112722 000004
6754 026056 112722 000000
6755 026062 112722 000200

```

```

*****
;TEST 30      FORMAT AT OFFSET
*****
TST30:
      SCOPE                      ;SCOPE CALL
      NOP                      ;START OF TEST
      MOV      #STACK,SP       ;INITIALIZE STACK POINTER
      MOV      $BASE,R0        ;R0=UNIBUS ADDRESS
      MOV      TSTQUE,R1       ;(R1) = DEVICE BEING TESTED
      MOV      #30,$TESTN      ;;SET TEST NUMBER IN APT MAIL BOX
10$:
;SETUP PARAMETERS FOR GENERATING DATA BUFFER
      MOV      #0,RMDCO        ;CYLINDER = 0
      MOV      #0,RMDAO        ;TRACK = SECTOR = 0
      MOV      #FMT16,RMOFO    ;16 BIT FORMAT
      MOV      #<^C<2+256.>+1>,RMWCO ;2 + 256 WOP'S
      MOV      #BUFONE,RMBAO   ;DATA BUFFER ADDRESS
      MOV      #WH!GO,RMCS10   ;WRITE HEADER AND DATA
      MOV      #RMDAO,$TMP0    ;USE SECTOR FOR DATA PATTERN
      MOV      #1,$TMP1
15$:   JSR      PC,GENBUF       ;GO GENERATE DATA BUFFER
20$:
;PREPARE DEVICE FOR DATA TRANSFER
      JSR      PC,TSTPRP       ;PREPARE DEVICE FOR TEST
      .WORD    154130          ;TASK DESCRIPTOR
      .R       30$            ;GO TO 30$ IF NO ERROR
      .R       190$           ;RETURN HERE IF ERROR
      .R       190$           ;ERROR # DEFINED BY TSTPRP SUBROUTINE
      .R       190$           ;GO TO 190$ IF ERROR WAS FOUND
30$:
;OFFSET DEVICE FOR WRITE
      MOV      #OFFSET!GO,RMCS10 ;CHANGE TO OFFSET COMMAND
      MOV      #PUTINX,R2        ;WRITE PUT INDEX TABLE
      MOVB     #RMDA,(R2)+
      MOVB     #RMDC,(R2)+
      MOVB     #RMOF,(R2)+
      MOVB     #RMCS1,(R2)+
      MOVB     #200,(R2)        ;TERMINATE TABLE
      JSR      PC,PUT           ;GO WRITE REGISTERS VIA PUT SUB
      BR       35$             ;GO TO 35$ IF NO ERROR
      NOP                      ;RETURN HERE IF ERROR
      ERROR    190$            ;ERROR DEFINED BY PUT SUB
      JMP      190$            ;GO TO 190$ IF ERROR WAS FOUND
35$:
;SETUP AND EXECUTE WRITE HEADER AND DATA COMMAND AT OFFSET
      MOV      #WH!GO,RMCS10   ;WRITE HEADER AND DATA COMMAND
      MOV      #PUTINX,R2      ;WRITE REGISTER INDEX TABLE
      MOVB     #RMWC,(R2)+
      MOVB     #RMBA,(R2)+
      MOVB     #RMCS1,(R2)+
      MOVB     #200,(R2)+

```


6756	026066	004737	037766	JSR	PC,PUT	;GO WRITE REGISTERS VIA PUT SUB
6757	026072	000404		BR	80\$	;GO TO 80\$ IF NO ERROR
6758	026074	000240		NOP		;RETURN HERE IF ERROR
6759	026076	104000		ERROR		;ERROR DEFINED BY PUT SUB
6760	026100	000137	026520	JMP	190\$	;GO TO 190\$ IF ERROR WAS FOUND
6761	026104					
6762						
6763						
6764	026104	004737	037432	JSR	PC,GETSTS	;SETUP INPUT REGISTER BUFFER FOR READING STATUS
6765						
6766						
6767	026110	004737	040326	JSR	PC,TIMOUT	;WAIT FOR COMMAND TO COMPLETE
6768	026114	004737	037516	JSR	PC,GET	;GO READ REGISTERS VIA GET SUB
6769	026120	000404		BR	90\$	;GO TO 90\$ IF NO ERROR
6770	026122	000240		NOP		;RETURN HERE IF ERROR
6771	026124	104000		ERROR		;ERROR DEFINED BY GET SUB
6772	026126	000137	026520	JMP	190\$	;GO TO 190\$ IF ERROR WAS FOUND
6773	026132					
6774						
6775						
6776	026132	004737	040512	JSR	PC,PRIERR	;GO CHECK FOR PRIMARY ERRORS
6777	026136	000405		BR	100\$	;GO TO 100\$ IF NO ERROR
6778	026140	000240		NOP		;RETURN HERE IF ERROR
6779	026142	104000		ERROR		;ERROR # DEFINED BY PRIERR SUBROUTINE
6780	026144	004736		JSR	PC,@(SP)+	;GO BACK FOR MORE ERROR CHECKS
6781	026146	000137	026520	JMP	190\$	;GO TO 190\$ IF ERROR WAS FOUND
6782	026152					
6783	026152	004737	053016	JSR	PC,DTASTS	;GO VERIFY RESULTS OF DATA TRANSFER
6784	026156	000405		BR	110\$	;GO TO 110\$ IF NO ERROR
6785	026160	000240		NOP		;RETURN HERE IF ERROR
6786	026162	104000		ERROR		;ERROR # DEFINED BY DTASTS SUBROUTINE
6787	026164	004736		JSR	PC,@(SP)+	;GO BACK FOR MORE ERROR CHECKS
6788	026166	000137	026520	JMP	190\$	;GO TO 190\$ IF ERROR WAS FOUND
6789	026172					
6790	026172	004737	041344	JSR	PC,SECERR	;GO CHECK FOR SECONDARY ERRORS
6791	026176	000405		BR	120\$	;GO TO 120\$ IF NO ERROR
6792	026200	000240		NOP		;RETURN HERE IF ERROR
6793	026202	104000		ERROR		;ERROR # DEFINED BY SECERR SUBROUTINE
6794	026204	004736		JSR	PC,@(SP)+	;GO BACK FOR MORE ERROR CHECKS
6795	026206	000137	026520	JMP	190\$	;GO TO 190\$ IF ERROR WAS FOUND
6796	026212					
6797						
6798	026212	012737	000015	MOV	#OFFSET!GO,RMCS10	;CHANGE TO OFFSET COMMAND
6799	026220	012702	001535	MOV	#PUTINX,R2	;WRITE PUT INDEX TABLE
6800	026224	112722	000006	MOVB	#RMDA,(R2)+	
6801	026230	112722	000034	MOVB	#RMDC,(R2)+	
6802	026234	112722	000032	MOVB	#RMOF,(R2)+	
6803	026240	112722	000000	MOVB	#RMCS1,(R2)+	
6804	026244	112722	000200	MOVB	#200,(R2)+	
6805	026250	004737	037766	JSR	PC,PUT	;GO WRITE REGISTERS VIA PUT SUB
6806	026254	000404		BR	125\$	;GO TO 125\$ IF NO ERROR
6807	026256	000240		NOP		;RETURN HERE IF ERROR
6808	026260	104000		ERROR		;ERROR DEFINED BY PUT SUB
6809	026262	000137	026520	JMP	190\$	;GO TO 190\$ IF ERROR WAS FOUND
6810	026266					
6811						

125\$:

001400

```
6812
6813
6814 026266 012737 000073 001400 ;READ HEADER AND DATA AT OFFSET
6815 026274 012737 104570 001404 MOV #RH!GO,RMCS10 ;READ HEADER & DATA COMMAND
6816 026302 012702 001535 MOV #BUFTWO,RMBA0 ;CHANGE BUS ADDRESS
6817 026306 112722 000002 MOV #PUTINX,R2 ;WRITE PUT INDEX TABLE
6818 026312 112722 000004 MOVB #RMWC,(R2)+
6819 026316 112722 000000 MOVB #RMBA,(R2)+
6820 026322 112722 000200 MOVB #RMCS1,(R2)+
6821 026326 004737 037766 JSR PC,PUT ;GO WRITE REGISTERS VIA PUT SUB
6822 026332 000404 BR 130$ ;GO TO 130$ IF NO ERROR
6823 026334 000240 NOP ;RETURN HERE IF ERROR
6824 026336 104000 ERROR ;ERROR DEFINED BY PUT SUB
6825 026340 000137 026520 JMP 190$ ;GO TO 190$ IF ERROR WAS FOUND
6826 026344
6827
6828 ;WAIT FOR READ TO COMPLETE AND GET STATUS
6829 026344 004737 040326 JSR PC,TIMOUT ;WAIT FOR READ TO COMPLETE
6830 026350 004737 037516 JSR PC,GET ;GO READ REGISTERS VIA GET SUB
6831 026354 000404 BR 140$ ;GO TO 140$ IF NO ERROR
6832 026356 000240 NOP ;RETURN HERE IF ERROR
6833 026360 104000 ERROR ;ERROR DEFINED BY GET SUB
6834 026362 000137 026520 JMP 190$ ;GO TO 190$ IF ERROR WAS FOUND
6835 026366
6836
6837 ;VERIFY THE RESULTS OF READ OPERATION
6838 026366 004737 040512 JSR PC,PRIERR ;GO CHECK FOR PRIMARY ERRORS
6839 026372 000405 BR 150$ ;GO TO 150$ IF NO ERROR
6840 026374 000240 NOP ;RETURN HERE IF ERROR
6841 026376 104000 ERROR ;ERROR # DEFINED BY PRIERR SUBROUTINE
6842 026400 004736 JSR PC,@(SP)+ ;GO BACK FOR MORE ERROR CHECKS
6843 026402 000137 026520 JMP 190$ ;GO TO 190$ IF ERROR WAS FOUND
6844 026406
6845 026406 004737 053016 JSR PC,DASTS ;GO VERIFY RESULTS OF DATA TRANSFER
6846 026412 000405 BR 160$ ;GO TO 160$ IF NO ERROR
6847 026414 000240 NOP ;RETURN HERE IF ERROR
6848 026416 104000 ERROR ;ERROR # DEFINED BY DASTS SUBROUTINE
6849 026420 004736 JSR PC,@(SP)+ ;GO BACK FOR MORE ERROR CHECKS
6850 026422 000137 026520 JMP 190$ ;GO TO 190$ IF ERROR WAS FOUND
6851 026426
6852 026426 004737 041344 JSR PC,SECERR ;GO CHECK FOR SECONDARY ERRORS
6853 026432 000405 BR 170$ ;GO TO 170$ IF NO ERROR
6854 026434 000240 NOP ;RETURN HERE IF ERROR
6855 026436 104000 ERROR ;ERROR # DEFINED BY SECERR SUBROUTINE
6856 026440 004736 JSR PC,@(SP)+ ;GO BACK FOR MORE ERROR CHECKS
6857 026442 000137 026520 JMP 190$ ;GO TO 190$ IF ERROR WAS FOUND
6858 026446
6859
6860 ;VERIFY DATA
6861 026446 004737 037064 JSR PC,CMPBUF ;GO COMPARE WRITE, READ DATA BUFFERS
6862 026452 103564 .WORD BUFONE ;STARTING ADDRESS OF WRITE BUFFER
6863 026454 104570 .WORD BUFTWO ;STARTING ADDRESS OF READ BUFFER
6864 026456 000404 BR 180$ ;GO TO 180$ IF NO ERROR
6865 026460 000240 NOP ;RETURN HERE IF ERROR
6866 026462 104000 ERROR ;ERROR # DEFINED BY CMPBUF SUBROUTINE
6867 026464 000137 026520 JMP 190$ ;GO TO 190$ IF ERROR WAS FOUND
```

```

6868 026470
6869 026470 032737 000200 001432
6870 026476 001010
6871 026500 052737 000200 001432
6872 026506 012737 103564 001404
6873 026514 000137 025740
6874 026520
6875
6876
6877
6878
6879 026520
6880 026520 000004
6881 026522 000240
6882 026524 012706 001100
6883 026530 013700 001276
6884 026534 013701 001450
6885 026540 012737 000031 001226
6886 026546
6887
6888
6889 026546 012737 000000 001434
6890 026554 012737 000000 001406
6891 026562 012737 010000 001432
6892 026570 012737 177376 001402
6893 026576 012737 103564 001404
6894 026604 012737 000062 001400
6895 026612 012737 001406 001174
6896 026620 012737 000001 001176
6897 026626 004737 036620
6898 026632
6899
6900
6901 026632 004737 034000
6902 026636 154130
6903 026640 000404
6904 026642 000240
6905 026644 104000
6906 026646 000137 027326
6907 026652
6908
6909
6910 026652 012737 000001 001424
6911 026660 112737 000024 001535
6912 026666 112737 000200 001536
6913 026674 004737 037766
6914 026700 000404
6915 026702 000240
6916 026704 104000
6917 026706 000137 027326
6918 026712
6919
6920
6921 026712 012737 000063 001400
6922 026720 012737 000000 001424
6923 026726 012702 001535

180$:
    BIT    #OFD,RMOFO      ;DONE BOTH OFFSETS??
    BNE    190$            ;YES!!
    BIS    #OFD,RMOFO      ;SET FORWARD OFFSET
    MOV    #BUFONE,RMBAO    ;CHANGE DATA BUFFER
    JMP    20$

190$:
    ;*****
    ;*TEST 31          IVC FORMAT TEST
    ;*****
    TST31:
        SCOPE                ;SCOPE CALL
        NOP                  ;START OF TEST
        MOV    #STACK,SP      ;INITIALIZE STACK POINTER
        MOV    $BASE,R0       ;R0=UNIBUS ADDRESS
        MOV    TSTQUE,R1      ;(R1) = DEVICE BEING TESTED
        MOV    #31,$TESTN     ;;SET TEST NUMBER IN APT MAIL BOX

10$:
    ;SETUP PARAMETERS FOR GENERATING DATA BUFFER
    MOV    #0,RMDCO           ;CYLINDER = 0
    MOV    #0,RMDAO           ;TRACK = SECTOR = 0
    MOV    #FMT16,RMOFO       ;16 BIT FORMAT
    MOV    #<^C<2+256.>+1>,RMWCO ;2 + 256 WORDS
    MOV    #BUFONE,RMBAO      ;DATA BUFFER ADDRESS
    MOV    #WH,RMCS10         ;WRITE HEADER AND DATA
    MOV    #RMDAO,$TMP0       ;USE SECTOR FOR DATA PATTERN
    MOV    #1,$TMP1
15$:    JSR    PC,GENBUF       ;GO GENERATE DATA BUFFER
20$:

;PREPARE DEVICE FOR DATA TRANSFER
    JSR    PC,TSTPRP          ;PREPARE DEVICE FOR TEST
    .WORD  154130             ;TASK DESCRIPTOR
    BR     30$                ;GO TO 30$ IF NO ERROR
    NOP                                ;RETURN HERE IF ERROR
    ERROR  #DEFINED BY TSTPRP SUBROUTINE
    JMP    190$               ;GO TO 190$ IF ERROR WAS FOUND

30$:

;RESET VOLUME VALID BY SETTING AND RESETTNG DIAGNOSTIC MODE
    MOV    #DMD,RMMR10        ;SET DIAGNOSTIC MODE
    MOV    #RMMR1,PUTINX      ;WRITE REGISTER INDEX TABLE
    MOV    #200,PUTINX+1
    JSR    PC,PUT              ;GO WRITE REGISTERS VIA PUT SUB
    BR     35$                ;GO TO 35$ IF NO ERROR
    NOP                                ;RETURN HERE IF ERROR
    ERROR  #DEFINED BY PUT SUB
    JMP    190$               ;GO TO 190$ IF ERROR WAS FOUND

35$:

;SETUP AND EXECUTE WRITE HEADER AND DATA COMMAND
    MOV    #WH!GO,RMCS10      ;WRITE HEADER AND DATA
    MOV    #0,RMMR10          ;RESET DIAGNOSTIC MODE
    MOV    #PUTINX,R2         ;WRITE REGISTER INDEX TABLE
  
```

6924	026732	112722	000024		MOVB	#RMR1,(R2)+	
6925	026736	112722	000006		MOVB	#RMDA,(R2)+	
6926	026742	112722	000034		MOVB	#RMDC,(R2)+	
6927	026746	112722	000032		MOVB	#RMOF,(R2)+	
6928	026752	112722	000002		MOVB	#RMWC,(R2)+	
6929	026756	112722	000004		MOVB	#RMDA,(R2)+	
6930	026762	112722	000000		MOVB	#RMCS1,(R2)+	
6931	026766	112722	000200		MOVB	#200,(R2)+	
6932	026772	004737	037766		JSR	PC,PUT	;GO WRITE REGISTERS VIA PUT SUB
6933	026776	000404			BR	80\$	;GO TO 80\$ IF NO ERROR
6934	027000	000240			NOP		;RETURN HERE IF ERROR
6935	027002	104000			ERROR		;ERROR DEFINED BY PUT SUB
6936	027004	000137	027326		JMP	190\$	;GO TO 190\$ IF ERROR WAS FOUND
6937	027010						
6938							
6939							
6940	027010	004737	037432		JSR	PC,GETSTS	;SETUP INPUT REGISTER BUFFER FOR READING STATUS
6941							
6942							
6943	027014	004737	040326		JSR	PC,TIMOUT	;WAIT FOR COMMAND TO COMPLETE
6944	027020	004737	037516		JSR	PC,GET	;GO READ REGISTERS VIA GET SUB
6945	027024	000404			BR	90\$	;GO TO 90\$ IF NO ERROR
6946	027026	000240			NOP		;RETURN HERE IF ERROR
6947	027030	104000			ERROR		;ERROR DEFINED BY GET SUB
6948	027032	000137	027326		JMP	190\$	;GO TO 190\$ IF ERROR WAS FOUND
6949	027036						
6950							
6951							
6952	027036	004737	040512		JSR	PC,PRIERR	;GO CHECK FOR PRIMARY ERRORS
6953	027042	000405			BR	100\$	;GO TO 100\$ IF NO ERROR
6954	027044	000240			NOP		;RETURN HERE IF ERROR
6955	027046	104000			ERROR		;ERROR # DEFINED BY PRIERR SUBROUTINE
6956	027050	004736			JSR	PC,@(SP)+	;GO BACK FOR MORE ERROR CHECKS
6957	027052	000137	027326		JMP	190\$	;GO TO 190\$ IF ERROR WAS FOUND
6958	027056						
6959	027056	032737	010000	001372	BIT	#IVC,RMER21	;IS IVC STATUS SET??
6960	027064	001012			BNE	110\$	;YES!!
6961	027066	013737	001372	001142	MOV	RMER21,\$BDDAT	;RECEIVED STATUS FOR TYPEOUT
6962	027074	013737	001372	001140	MOV	RMER21,\$GDDAT	;EXPECTED STATUS
6963	027102	052737	010000	001140	BIS	#IVC,\$GDDAT	
6964	027110	104342			ERROR	342	;IVC NOT SET DURING FORMAT
6965	027112						
6966	027112	004737	041344		JSR	PC,SECERR	;GO CHECK FOR SECONDARY ERRORS
6967	027116	000405			BR	120\$	;GO TO 120\$ IF NO ERROR
6968	027120	000240			NOP		;RETURN HERE IF ERROR
6969	027122	104000			ERROR		;ERROR # DEFINED BY SECERR SUBROUTINE
6970	027124	004736			JSR	PC,@(SP)+	;GO BACK FOR MORE ERROR CHECKS
6971	027126	000137	027326		JMP	190\$	;GO TO 190\$ IF ERROR WAS FOUND
6972	027132						
6973							
6974							
6975	027132	004737	034000		JSR	PC,TSTPRP	;PREPARE DEVICE FOR TEST
6976	027136	040100			.WORD	040100	;TASK DESCRIPTOR
6977	027140	000404			BR	125\$	;GO TO 125\$ IF NO ERROR
6978	027142	000240			NOP		;RETURN HERE IF ERROR
6979	027144	104000			ERROR		;ERROR # DEFINED BY TSTPRP SUBROUTINE

```
6980 027146 000137 J27326      JMP      190$      ;GO TO 190$ IF ERROR WAS FOUND
6981 027152      125$:
6982
6983      ;READ HEADER AND DATA FOR SECTOR JUST WRITTEN
6984 027152 012737 000073 001400      MOV      #RH!GO,RMCS10      ;READ HEADER & DATA COMMAND
6985 027160 012737 104570 001404      MOV      #BUFTWO,RMBAO      ;CHANGE BUS ADDRESS
6986 027166 004737 037766      JSR      PC,PUT      ;GO WRITE REGISTERS VIA PUT SUB
6987 027172 000404      BR      130$      ;GO TO 130$ IF NO ERROR
6988 027174 000240      NOP      ;RETURN HERE IF ERROR
6989 027176 104000      ERROR      ;ERROR DEFINED BY PUT SUB
6990 027200 000137 027326      JMP      190$      ;GO TO 190$ IF ERROR WAS FOUND
6991 027204      130$:
6992
6993      ;SETUP INPUT REGISTER BUFFER FOR READING STATUS
6994 027204 004737 037432      JSR      PC,GETSTS
6995
6996      ;WAIT FOR READ TO COMPLETE AND GET STATUS
6997 027210 004737 040326      JSR      PC,TIMOUT      ;WAIT FOR READ TO COMPLETE
6998 027214 004737 037516      JSR      PC,GET      ;GO READ REGISTERS VIA GET SUB
6999 027220 000404      BR      140$      ;GO TO 140$ IF NO ERROR
7000 027222 000240      NOP      ;RETURN HERE IF ERROR
7001 027224 104000      ERROR      ;ERROR DEFINED BY GET SUB
7002 027226 000137 027326      JMP      190$      ;GO TO 190$ IF ERROR WAS FOUND
7003 027232      140$:
7004
7005      ;VERIFY THE RESULTS OF READ OPERATION
7006 027232 004737 040512      JSR      PC,PRIERR      ;GO CHECK FOR PRIMARY ERRORS
7007 027236 000405      BR      150$      ;GO TO 150$ IF NO ERROR
7008 027240 000240      NOP      ;RETURN HERE IF ERROR
7009 027242 104000      ERROR      ;ERROR # DEFINED BY PRIERR SUBROUTINE
7010 027244 004736      JSR      PC,@(SP)+      ;GO BACK FOR MORE ERROR CHECKS
7011 027246 000137 027326      JMP      190$      ;GO TO 190$ IF ERROR WAS FOUND
7012 027252      150$:
7013 027252 032737 010000 001372      BIT      #IVC,RMER21      ;IS IVC STATUS SET??
7014 027260 001012      BNE      160$      ;YES!!
7015 027262 013737 001372 001142      MOV      RMER21,$BDDAT      ;RECEIVED STATUS FOR TIMEOUT
7016 027270 013737 001372 001140      MOV      RMER21,$GDDAT      ;EXPECTED STATUS
7017 027276 052737 010000 001140      BIS      #IVC,$GDDAT
7018 027304 104342      ERROR      342      ;IVC NOT SET DURING FORMAT
7019 027306      160$:
7020 027306 004737 041344      JSR      PC,SECERR      ;GO CHECK FOR SECONDARY ERRORS
7021 027312 000405      BR      170$      ;GO TO 170$ IF NO ERROR
7022 027314 000240      NOP      ;RETURN HERE IF ERROR
7023 027316 104000      ERROR      ;ERROR # DEFINED BY SECERR SUBROUTINE
7024 027320 004736      JSR      PC,@(SP)+      ;GO BACK FOR MORE ERROR CHECKS
7025 027322 000137 027326      JMP      190$      ;GO TO 190$ IF ERROR WAS FOUND
7026 027326      170$:
7027 027326      190$:
7028
7029      ;*****
7030      ;*TEST 32      FORMAT ERROR TEST - 18
7031      ;*****
7032      TST32:
7033 027326 000004      SCOPE      ;SCOPE CALL
7034 027330 000240      NOP      ;START OF TEST
7035 027332 012706 001100      MOV      #STACK,SP      ;INITIALIZE STACK POINTER
```

7036 027336 013700 001276 MOV \$BASE,R0 ;RO=UNIBUS ADDRESS
7037 027342 013701 001450 MOV TSTQUE,R1 ;(R1) = DEVICE BEING TESTED
7038 027346 012737 000032 001226 MOV #32,\$TESTN ;;SET TEST NUMBER IN APT MAIL BOX
7039 027354 10\$:
7040
7041 ;SETUP PARAMETERS FOR GENERATING DATA BUFFER
7042 027354 012737 000000 001434 MOV #0,RMDCO ;CYLINDER = 0
7043 027362 012737 000000 001406 MOV #0,RMDAO ;TRACK = SECTOR = 0
7044 027370 012737 000000 001432 MOV #0,RMOFO ;18 BIT FORMAT
7045 027376 012737 177376 001402 MOV #<^C<2+256.>+1>,RMWCO ;2 + 256 WORDS
7046 027404 012737 103564 001404 MOV #BUFONE,RMBAO ;DATA BUFFER ADDRESS
7047 027412 012737 00C062 0C1400 MOV #WH,RMCS10 ;WRITE HEADER AND DATA
7048 027420 012737 065104 001174 MOV #ZEROS,\$TMP0 ;USE ALL ZEROS DATA PATTERN
7049 027426 012737 000001 001176 MOV #1,\$TMP1
7050 027434 004737 036620 JSR PC,GENBUF ;GO GENERATE DATA BUFFER
7051 027440 20\$:
7052
7053 ;PREPARE DEVICE FOR DATA TRANSFER
7054 027440 004737 034000 JSR PC,TSTPRP ;PREPARE DEVICE FOR TEST
7055 027444 154130 .WORD 154130 ;TASK DESCRIPTOR
7056 027446 000404 BR 30\$;GO TO 30\$ IF NO ERROR
7057 027450 000240 NOP ;RETURN HERE IF ERROR
7058 027452 104000 ERROR ;ERROR # DEFINED BY TSTPRP SUBROUTINE
7059 027454 000137 030050 JMP 180\$;GO TO 180\$ IF ERROR WAS FOUND
7060 027460 30\$:
7061
7062 ;SETUP AND EXECUTE WRITE HEADER AND DATA COMMAND
7063 027460 012737 000063 001400 MOV #WH!GO,RMCS10 ;WRITE HEADER AND DATA
7064 027466 012702 001535 MOV #PUTINX,R2 ;WRITE REGISTER INDEX TABLE
7065 027472 112722 000006 MOVB #RMDA,(R2)+
7066 027476 112722 000034 MOVB #RMDC,(R2)+
7067 027502 112722 000032 MOVB #RMOF,(R2)+
7068 027506 112722 000002 MOVB #RMWC,(R2)+
7069 027512 112722 000004 MOVB #RMBA,(R2)+
7070 027516 112722 000000 MOVB #RMCS1,(R2)+
7071 027522 112722 000200 MOVB #200,(R2)+
7072 027526 004737 037766 JSR PC,PUT ;GO WRITE REGISTERS VIA PUT SUB
7073 027532 000404 BR 80\$;GO TO 80\$ IF NO ERROR
7074 027534 000240 NOP ;RETURN HERE IF ERROR
7075 027536 104000 ERROR ;ERROR DEFINED BY PUT SUB
7076 027540 000137 030050 JMP 180\$;GO TO 180\$ IF ERROR WAS FOUND
7077 027544 80\$:
7078
7079 ;SETUP INPUT REGISTER BUFFER FOR READING STATUS
7080 027544 004737 037432 JSR PC,GETSTS
7081
7082 ;WAIT FOR WRITE COMMAND TO COMPLETE AND READ STATUS
7083 027550 004737 040326 JSR PC,TIMOUT ;WAIT FOR COMMAND TO COMPLETE
7084 027554 004737 037516 JSR PC,GET ;GO READ REGISTERS VIA GET SUB
7085 027560 000404 BR 90\$;GO TO 90\$ IF NO ERROR
7086 027562 000240 NOP ;RETURN HERE IF ERROR
7087 027564 104000 ERROR ;ERROR DEFINED BY GET SUB
7088 027566 000137 030050 JMP 180\$;GO TO 180\$ IF ERROR WAS FOUND
7089 027572 90\$:
7090
7091 ;VERIFY RESULTS OF WRITE COMMAND


```

7092 027572 004737 040512      JSR    PC,PRIERR      ;GO CHECK FOR PRIMARY ERRORS
7093 027576 000405              BR     100$           ;GO TO 100$ IF NO ERROR
7094 027600 000240              NOP                    ;RETURN HERE IF ERROR
7095 027602 104000              ERROR                  ;ERROR # DEFINED BY PRIERR SUBROUTINE
7096 027604 004736              JSR    PC,@(SP)+        ;GO BACK FOR MORE ERROR CHECKS
7097 027606 000137 030050      JMP     180$           ;GO TO 180$ IF ERROR WAS FOUND
7098 027612
7099 027612 004737 053016      100$: JSR    PC,DTASTS      ;GO VERIFY RESULTS OF DATA TRANSFER
7100 027616 000405              BR     110$           ;GO TO 110$ IF NO ERROR
7101 027620 000240              NOP                    ;RETURN HERE IF ERROR
7102 027622 104000              ERROR                  ;ERROR # DEFINED BY DTASTS SUBROUTINE
7103 027624 004736              JSR    PC,@(SP)+        ;GO BACK FOR MORE ERROR CHECKS
7104 027626 000137 030050      JMP     180$           ;GO TO 180$ IF ERROR WAS FOUND
7105 027632
7106 027632 004737 041344      110$: JSR    PC,SECERR      ;GO CHECK FOR SECONDARY ERRORS
7107 027636 000405              BR     120$           ;GO TO 120$ IF NO ERROR
7108 027640 000240              NOP                    ;RETURN HERE IF ERROR
7109 027642 104000              ERROR                  ;ERROR # DEFINED BY SECERR SUBROUTINE
7110 027644 004736              JSR    PC,@(SP)+        ;GO BACK FOR MORE ERROR CHECKS
7111 027646 000137 030050      JMP     180$           ;GO TO 180$ IF ERROR WAS FOUND
7112 027652
7113
7114
7115
7116 027652 012737 010000 001432 ;READ HEADER AND DATA FOR SECTOR JUST WRITTEN AT 16 BIT FORMAT
7117 027660 012737 000073 001400 MOV     #FMT16,RMOFO      ;CHANGE TO 16 BIT FORMAT
7118 027666 012737 104570 001404 MOV     #RH!GO,RMCS10     ;READ HEADER & DATA COMMAND
7119 027674 004737 037766      MOV     #BUFTWO,RMBAO      ;CHANGE BUS ADDRESS
7120 027700 000404              JSR    PC,PUT          ;GO WRITE REGISTERS VIA PUT SUB
7121 027702 000240              BR     130$           ;GO TO 130$ IF NO ERROR
7122 027704 104000              NOP                    ;RETURN HERE IF ERROR
7123 027706 000137 030050      ERROR                  ;ERROR DEFINED BY PUT SUB
7124 027712              JMP     180$           ;GO TO 180$ IF ERROR WAS FOUND
7125
7126
7127 027712 004737 040326      130$: ;WAIT FOR READ TO COMPLETE AND GET STATUS
7128 027716 004737 037516      JSR    PC,TIMOUT      ;WAIT FOR READ TO COMPLETE
7129 027722 000404              JSR    PC,GET          ;GO READ REGISTERS VIA GET SUB
7130 027724 000240              BR     140$           ;GO TO 140$ IF NO ERROR
7131 027726 104000              NOP                    ;RETURN HERE IF ERROR
7132 027730 000137 030050      ERROR                  ;ERROR DEFINED BY GET SUB
7133 027734              JMP     180$           ;GO TO 180$ IF ERROR WAS FOUND
7134
7135
7136 027734 004737 040512      140$: ;VERIFY THE RESULTS OF READ OPERATION
7137 027740 000405              JSR    PC,PRIERR      ;GO CHECK FOR PRIMARY ERRORS
7138 027742 000240              BR     150$           ;GO TO 150$ IF NO ERROR
7139 027744 104000              NOP                    ;RETURN HERE IF ERROR
7140 027746 004736              ERROR                  ;ERROR # DEFINED BY PRIERR SUBROUTINE
7141 027750 000137 030050      JSR    PC,@(SP)+        ;GO BACK FOR MORE ERROR CHECKS
7142 027754              JMP     180$           ;GO TO 180$ IF ERROR WAS FOUND
7143
7144
7145 027754 032737 000020 001344 ;VERIFY THAT FORMAT ERROR IS SET
7146 027762 001022              BIT     #FER,RMER11      ;IS FORMAT ERROR SET??
7147 027764 004737 053016      BNE     160$           ;YES!!
                                JSR    PC,DTASTS      ;GO VERIFY RESULTS OF DATA TRANSFER
```

```

7148 027770 000405      BR      155$      ;GO TO 155$ IF NO ERROR
7149 027772 000240      NOP      ;RETURN HERE IF ERROR
7150 027774 104000      ERROR     ;ERROR # DEFINED BY DIASTS SUBROUTINE
7151 027776 004736      JSR      PC,@(SP)+ ;GO BACK FOR MORE ERROR CHECKS
7152 030000 000137 030050 JMP      180$      ;GO TO 180$ IF ERROR WAS FOUND
7153 030004 013737 001344 001142 155$: MOV      RMER11,$BDDAT ;BAD DATA FOR TYPEOUT
7154 030012 013737 001344 001140 MOV      RMER11,$GDDAT ;EXPECTED DATA
7155 030020 052737 000020 001140 BIS      #FER,$GDDAT
7156 030026 104343      ERROR     343      ;FORMAT ERROR NOT SET
7157 030030      160$:
7158 030030 004737 041344 JSR      PC,SECERR ;GO CHECK FOR SEC NDARY ERRORS
7159 030034 000405      BR      170$      ;GO TO 170$ IF NO ERROR
7160 030036 000240      NOP      ;RETURN HERE IF ERROR
7161 030040 104000      ERROR     ;ERROR # DEFINED BY SECERR SUBROUTINE
7162 030042 004736      JSR      PC,@(SP)+ ;GO BACK FOR MORE ERROR CHECKS
7163 030044 000137 030050 JMP      180$      ;GO TO 180$ IF ERROR WAS FOUND
7164 030050      170$:
7165 030050      180$:
7166
7167
7168 ;*****
7169 ;TEST 33      FORMAT ERROR TEST - 16
7170 ;*****
7170 030050      TST33:
7171 030050 000004      SCOPE     ;SCOPE CALL
7172 030052 000240      NOP      ;START OF TEST
7173 030054 012706 001100 MOV      #STACK,SP ;INITIALIZE STACK POINTER
7174 030060 013700 001276 MOV      $BASE,R0 ;R0=UNIBUS ADDRESS
7175 030064 013701 001450 MOV      TSTQUE,R1 ;(R1) = DEVICE BEING TESTED
7176 030070 012737 000033 001226 MOV      #33,$TESTN ;SET TEST NUMBER IN APT MAIL BOX
7177 030076      10$:
7178
7179 ;SETUP PARAMETERS FOR GENERATING DATA BUFFER
7180 030076 012737 000000 001434 MOV      #0,RMDCO ;CYLINDER = 0
7181 030104 012737 000000 001406 MOV      #0,RMDAO ;TRACK = SECTOR = 0
7182 030112 012737 010000 001432 MOV      #FMT16,RMOFO ;16 BIT FORMAT
7183 030120 012737 177376 001402 MOV      #<^C<2+256.>+1>,RMWCO ;2 + 256 WORDS
7184 030126 012737 103564 001404 MOV      #BUFONE,RMBAO ;DATA BUFFER ADDRESS
7185 030134 012737 000062 001400 MOV      #WH,RMCS10 ;WRITE HEADER AND DATA
7186 030142 012737 065104 001174 MOV      #ZEROS,$TMPO ;USE ALL ZEROS DATA PATTERN
7187 030150 012737 000001 001176 MOV      #1,$TMP1
7188 030156 004737 036620 JSR      PC,GENBUF ;GO GENERATE DATA BUFFER
7189 030162      20$:
7190
7191 ;PREPARE DEVICE FOR DATA TRANSFER
7192 030162 004737 034000 JSR      PC,TSTPRP ;PREPARE DEVICE FOR TEST
7193 030166 154130 .WORD 154130 ;TASK DESCRIPTOR
7194 030170 000404      BR      30$      ;GO TO 30$ IF NO ERROR
7195 030172 000240      NOP      ;RETURN HERE IF ERROR
7196 030174 104000      ERROR     ;ERROR # DEFINED BY TSTPRP SUBROUTINE
7197 030176 000137 030572 JMP      180$      ;GO TO 180$ IF ERROR WAS FOUND
7198 030202      30$:
7199
7200 ;SETUP AND EXECUTE WRITE HEADER AND DATA COMMAND
7201 030202 012737 000063 001400 MOV      #WH!GO,RMCS10 ;WRITE HEADER AND DATA
7202 030210 012702 001535 MOV      #PUTINX,R2 ;WRITE REGISTER INDEX TABLE
7203 030214 112722 000006 MOVB     #RMDA,(R2)+

```



```

7204 030220 112722 000034      MOVB    #RMDC,(R2)+
7205 030224 112722 000032      MOVB    #RMOF,(R2)+
7206 030230 112722 000002      MOVB    #RMWC,(R2)+
7207 030234 112722 000004      MOVB    #RMB A,(R2)+
7208 030240 112722 000000      MOVB    #RMCS1,(R2)+
7209 030244 112722 000200      MOVB    #200,(R2)+
7210 030250 004737 037766      JSR     PC,PUT          ;GO WRITE REGISTERS VIA PUT SUB
7211 030254 000404              BR      80$          ;GO TO 80$ IF NO ERROR
7212 030256 000240              NOP                    ;RETURN HERE IF ERROR
7213 030260 104000              ERROR                   ;ERROR DEFINED BY PUT SUB
7214 030262 000137 030572      JMP     180$         ;GO TO 180$ IF ERROR WAS FOUND
7215 030266
7216
7217      ;SETUP INPUT REGISTER BUFFER FOR READING STATUS
7218 030266 004737 037432      JSR     PC,GETSTS
7219
7220      ;WAIT FOR WRITE COMMAND TO COMPLETE AND READ STATUS
7221 030272 004737 040326      JSR     PC,TIMOUT        ;WAIT FOR COMMAND TO COMPLETE
7222 030276 004737 037516      JSR     PC,GET          ;GO READ REGISTERS VIA GET SUB
7223 030302 000404              BR      90$          ;GO TO 90$ IF NO ERROR
7224 030304 000240              NOP                    ;RETURN HERE IF ERROR
7225 030306 104000              ERROR                   ;ERROR DEFINED BY GET SUB
7226 030310 000137 030572      JMP     180$         ;GO TO 180$ IF ERROR WAS FOUND
7227 030314
7228
7229      ;VERIFY RESULTS OF WRITE COMMAND
7230 030314 004737 040512      JSR     PC,PRIERR        ;GO CHECK FOR PRIMARY ERRORS
7231 030320 000405              BR      100$         ;GO TO 100$ IF NO ERROR
7232 030322 000240              NOP                    ;RETURN HERE IF ERROR
7233 030324 104000              ERROR                   ;ERROR # DEFINED BY PRIERR SUBROUTINE
7234 030326 004736              JSR     PC,@(SP)+        ;GO BACK FOR MORE ERROR CHECKS
7235 030330 000137 030572      JMP     180$         ;GO TO 180$ IF ERROR WAS FOUND
7236 030334
7237 030334 004737 053016      JSR     PC,DASTS          ;GO VERIFY RESULTS OF DATA TRANSFER
7238 030340 000405              BR      110$         ;GO TO 110$ IF NO ERROR
7239 030342 000240              NOP                    ;RETURN HERE IF ERROR
7240 030344 104000              ERROR                   ;ERROR # DEFINED BY DASTS SUBROUTINE
7241 030346 004736              JSR     PC,@(SP)+        ;GO BACK FOR MORE ERROR CHECKS
7242 030350 000137 030572      JMP     180$         ;GO TO 180$ IF ERROR WAS FOUND
7243 030354
7244 030354 004737 041344      JSR     PC,SECERR        ;GO CHECK FOR SECONDARY ERRORS
7245 030360 000405              BR      120$         ;GO TO 120$ IF NO ERROR
7246 030362 000240              NOP                    ;RETURN HERE IF ERROR
7247 030364 104000              ERROR                   ;ERROR # DEFINED BY SECERR SUBROUTINE
7248 030366 004736              JSR     PC,@(SP)+        ;GO BACK FOR MORE ERROR CHECKS
7249 030370 000137 030572      JMP     180$         ;GO TO 180$ IF ERROR WAS FOUND
7250 030374
7251
7252
7253      ;READ HEADER AND DATA FOR SECTOR JUST WRITTEN AT 18 BIT FORMAT
7254 030374 012737 000000 001432  MOV     #0,RMOFO          ;SET FOR 18 BIT FORMAT
7255 030402 012737 000073 001400  MOV     #RH!GO,RMCS10       ;READ HEADER & DATA COMMAND
7256 030410 012737 104570 001404  MOV     #BUFTWO,RMBA0       ;CHANGE BUS ADDRESS
7257 030416 004737 037766      JSR     PC,PUT          ;GO WRITE REGISTERS VIA PUT SUB
7258 030422 000404              BR      130$         ;GO TO 130$ IF NO ERROR
7259 030424 000240              NOP                    ;RETURN HERE IF ERROR

```

```
7260 030426 104000          ERROR          ;ERROR DEFINED BY PLT SUB
7261 030430 000137 030572    JMP          180$    ;GO TO 180$ IF ERROR WAS FOUND
7262 030434
7263
7264          ;WAIT FOR READ TO COMPLETE AND GET STATUS
7265 030434 004737 040326    JSR          PC,TIMOUT      ;WAIT FOR READ TO COMPLETE
7266 030440 004737 037516    JSR          PC,GET        ;GO READ REGISTERS VIA GET SUB
7267 030444 000404          BR          140$    ;GO TO 140$ IF NO ERROR
7268 030446 000240          NOP          ;RETURN HERE IF ERROR
7269 030450 104000          ERROR        ;ERROR DEFINED BY GET SUB
7270 030452 000137 030572    JMP          180$    ;GO TO 180$ IF ERROR WAS FOUND
7271 030456
7272
7273          ;VERIFY THE RESULTS OF READ OPERATION
7274 030456 004737 040512    JSR          PC,PRIERR      ;GO CHECK FOR PRIMARY ERRORS
7275 030462 000405          BR          150$    ;GO TO 150$ IF NO ERROR
7276 030464 000240          NOP          ;RETURN HERE IF ERROR
7277 030466 104000          ERROR        ;ERROR # DEFINED BY PRIERR SUBROUTINE
7278 030470 004736          JSR          PC,@(SP)+      ;GO BACK FOR MORE ERROR CHECKS
7279 030472 000137 030572    JMP          180$    ;GO TO 180$ IF ERROR WAS FOUND
7280 030476
7281
7282          ;VERIFY THAT FORMAT ERROR IS SET
7283 030476 032737 000020 001344 BIT          #FER,RMER11      ;IS FORMAT ERROR SET??
7284 030504 001022          BNE          160$    ;YES!!
7285 030506 004737 053016    JSR          PC,DASTS      ;GO VERIFY RESULTS OF DATA TRANSFER
7286 030512 000405          BR          155$    ;GO TO 155$ IF NO ERROR
7287 030514 000240          NOP          ;RETURN HERE IF ERROR
7288 030516 104000          ERROR        ;ERROR # DEFINED BY DASTS SUBROUTINE
7289 030520 004736          JSR          PC,@(SP)+      ;GO BACK FOR MORE ERROR CHECKS
7290 030522 000137 030572    JMP          180$    ;GO TO 180$ IF ERROR WAS FOUND
7291 030526 013737 001344 001142 155$: MOV          RMER11,$BDDAT      ;RECEIVED STATUS FOR TIMEOUT
7292 030534 013737 001344 001140    MOV          RMER11,$GDDAT      ;EXPECTED STATUS
7293 030542 052737 000020 001140    BIS          #FER,$GDDAT
7294 030550 104343          ERROR        343      ;FORMAT ERROR NOT SET
7295 030552
7296 030552 004737 041344    JSR          PC,SECERR      ;GO CHECK FOR SECONDARY ERRORS
7297 030556 000405          BR          170$    ;GO TO 170$ IF NO ERROR
7298 030560 000240          NOP          ;RETURN HERE IF ERROR
7299 030562 104000          ERROR        ;ERROR # DEFINED BY SECERR SUBROUTINE
7300 030564 004736          JSR          PC,@(SP)+      ;GO BACK FOR MORE ERROR CHECKS
7301 030566 000137 030572    JMP          180$    ;GO TO 180$ IF ERROR WAS FOUND
7302 030572
7303 030572
7304
7305
7306          ;*****
7307          ;*TEST 34      FORMAT HCE, FIRST HEADER WORD
7308          ;*****
7308 030572          TST34:
7309 030572 000004          SCOPE          ;SCOPE CALL
7310 030574 000240          NOP          ;START OF TEST
7311 030576 012706 001100    MOV          #STACK,SP      ;INITIALIZE STACK POINTER
7312 030602 013700 001276    MOV          $BASE,R0      ;R0=UNIBUS ADDRESS
7313 030606 013701 001450    MOV          TSTQUE,R1      ;(R1) = DEVICE BEING TESTED
7314 030612 012737 000034 001226    MOV          #34,$TESTN      ;SET TEST NUMBER IN APT MAIL BOX
7315 030620 012737 000001 031576    MOV          #1,190$      ;INIT BIT POSITION
```

```

7316 030626
7317
7318 ;SETUP PARAMETERS FOR GENERATING DATA BUFFER
7319 030626 012737 000000 001434 MOV #0,RMDCO ;CYLINDER = 0
7320 030634 012737 000000 001406 MOV #0,RMDAO ;TRACK = SECTOR = 0
7321 030642 012737 010000 001432 MOV #FMT16,RMFO ;16 BIT FORMAT
7322 030650 012737 177376 001402 MOV #<^C<2+256.>+1>,RMWCO ;2 + 256 WORDS
7323 030656 012737 103564 001404 MOV #BUFONE,RMBAO ;DATA BUFFER ADDRESS
7324 030664 012737 000062 001400 MOV #WH,RMCS10 ;WRITE HEADER AND DATA
7325 030672 012737 065104 001174 MOV #ZEROS,$TMP0 ;USE ALL ZEROS DATA PATTERN
7326 030700 012737 000001 001176 MOV #1,$TMP1
7327 030706 004737 036620 JSR PC,GENBUF ;GO GENERATE DATA BUFFER
7328 030712
7329
7330 ;PREPARE DEVICE FOR DATA TRANSFER
7331 030712 004737 034000 JSR PC,TSTPRP ;PREPARE DEVICE FOR TEST
7332 030716 154130 .WORD 154130 ;TASK DESCRIPTOR
7333 030720 000404 BR 30$ ;GO TO 30$ IF NO ERROR
7334 030722 000240 NOP ;RETURN HERE IF ERROR
7335 030724 104000 ERROR ;ERROR # DEFINED BY TSTPRP SUBROUTINE
7336 030726 000137 031750 JMP 240$ ;GO TO 240$ IF ERROR WAS FOUND
7337 030732
7338
7339 ;COMPLEMENT DATA BIT IN FIRST HEADER WORD
7340 030732 033737 031576 103564 BIT 190$,BUFONE ;IS BIT IN HEADER ON??
7341 030740 001404 BEQ 31$ ;NO!!
7342 030742 043737 031576 103564 BIC 190$,BUFONE ;RESET BIT IN HEADER
7343 030750 000403 BR 32$
7344 030752 053737 031576 103564 31$: BIS 190$,BUFONE ;SET BIT IN HEADER
7345
7346 030760
7347
7348 ;SETUP AND EXECUTE WRITE HEADER AND DATA COMMAND
7349 030760 012737 000063 001400 MOV #WH!GO,RMCS10 ;WRITE HEADER AND DATA
7350 030766 012702 001535 MOV #PUTINX,R2 ;WRITE REGISTER INDEX TABLE
7351 030772 112722 000006 MOV #RMDA,(R2)+
7352 030776 112722 000034 MOV #RMDC,(R2)+
7353 031002 112722 000032 MOV #RMOF,(R2)+
7354 031006 112722 000002 MOV #RMWC,(R2)+
7355 031012 112722 000004 MOV #RMBA,(R2)+
7356 031016 112722 000000 MOV #RMCS1,(R2)+
7357 031022 112722 000200 MOV #200,(R2)+
7358 031026 004737 037766 JSR PC,PUT ;GO WRITE REGISTERS VIA PUT SUB
7359 031032 000404 BR 80$ ;GO TO 80$ IF NO ERROR
7360 031034 000240 NOP ;RETURN HERE IF ERROR
7361 031036 104000 ERROR ;ERROR DEFINED BY PUT SUB
7362 031040 000137 031574 JMP 180$ ;GO TO 180$ IF ERROR WAS FOUND
7363 031044
7364
7365 ;SETUP INPUT REGISTER BUFFER FOR READING STATUS
7366 031044 004737 037432 JSR PC,GETSTS
7367
7368 ;WAIT FOR WRITE COMMAND TO COMPLETE AND READ STATUS
7369 031050 004737 040326 JSR PC,TIMOUT ;WAIT FOR COMMAND TO COMPLETE
7370 031054 004737 037516 JSR PC,GET ;GO READ REGISTERS VIA GET SUB
7371 031060 000404 BR 90$ ;GO TO 90$ IF NO ERROR

```

```
7372 031062 000240      NOP      ;RETURN HERE IF ERROR
7373 031064 104000      ERROR     ;ERROR DEFINED BY GET SUB
7374 031066 000137 031574 90$:    JMP      180$    ;GO TO 180$ IF ERROR WAS FOUND
7375 031072
7376
7377      ;VERIFY RESULTS OF WRITE COMMAND
7378 031072 004737 040512      JSR      PC,PRIERR    ;GO CHECK FOR PRIMARY ERRORS
7379 031076 000405          BR      100$    ;GO TO 100$ IF NO ERROR
7380 031100 000240      NOP      ;RETURN HERE IF ERROR
7381 031102 104000      ERROR     ;ERROR # DEFINED BY PRIERR SUBROUTINE
7382 031104 004736      JSR      PC,@(SP)+  ;GO BACK FOR MORE ERROR CHECKS
7383 031106 000137 031574      JMP      180$    ;GO TO 180$ IF ERROR WAS FOUND
7384 031112
7385 031112 004737 053016      JSR      PC,DTASTS    ;GO VERIFY RESULTS OF DATA TRANSFER
7386 031116 000405          BR      110$    ;GO TO 110$ IF NO ERROR
7387 031120 000240      NOP      ;RETURN HERE IF ERROR
7388 031122 104000      ERROR     ;ERROR # DEFINED BY DTASTS SUBROUTINE
7389 031124 004736      JSR      PC,@(SP)+  ;GO BACK FOR MORE ERROR CHECKS
7390 031126 000137 031574      JMP      180$    ;GO TO 180$ IF ERROR WAS FOUND
7391 031132
7392 031132 004737 041344      JSR      PC,SECERR    ;GO CHECK FOR SECONDARY ERRORS
7393 031136 000405          BR      120$    ;GO TO 120$ IF NO ERROR
7394 031140 000240      NOP      ;RETURN HERE IF ERROR
7395 031142 104000      ERROR     ;ERROR # DEFINED BY SECERR SUBROUTINE
7396 031144 004736      JSR      PC,@(SP)+  ;GO BACK FOR MORE ERROR CHECKS
7397 031146 000137 031574      JMP      180$    ;GO TO 180$ IF ERROR WAS FOUND
7398 031152
7399
7400
7401      ;READ HEADER AND DATA FOR SECTOR JUST WRITTEN
7402 031152 012737 000073 001400  MOV      #RH!GO,RMC$10    ;READ HEADER & DATA COMMAND
7403 031160 012737 104570 001404  MOV      #BUFTWO,RMBA0    ;CHANGE BUS ADDRESS
7404 031166 004737 037766          JSR      PC,PUT      ;GO WRITE REGISTERS VIA PUT SUB
7405 031172 000404          BR      130$    ;GO TO 130$ IF NO ERROR
7406 031174 000240      NOP      ;RETURN HERE IF ERROR
7407 031176 104000      ERROR     ;ERROR DEFINED BY PUT SUB
7408 031200 000137 031574      JMP      180$    ;GO TO 180$ IF ERROR WAS FOUND
7409 031204
7410
7411      ;WAIT FOR READ TO COMPLETE AND GET STATUS
7412 031204 004737 040326      JSR      PC,TIMOUT    ;WAIT FOR READ TO COMPLETE
7413 031210 004737 037516      JSR      PC,GET      ;GO READ REGISTERS VIA GET SUB
7414 031214 000404          BR      140$    ;GO TO 140$ IF NO ERROR
7415 031216 000240      NOP      ;RETURN HERE IF ERROR
7416 031220 104000      ERROR     ;ERROR DEFINED BY GET SUB
7417 031222 000137 031574      JMP      180$    ;GO TO 180$ IF ERROR WAS FOUND
7418 031226
7419
7420      ;VERIFY THE RESULTS OF READ OPERATION
7421 031226 004737 040512      JSR      PC,PRIERR    ;GO CHECK FOR PRIMARY ERRORS
7422 031232 000405          BR      150$    ;GO TO 150$ IF NO ERROR
7423 031234 000240      NOP      ;RETURN HERE IF ERROR
7424 031236 104000      ERROR     ;ERROR # DEFINED BY PRIERR SUBROUTINE
7425 031240 004736      JSR      PC,@(SP)+  ;GO BACK FOR MORE ERROR CHECKS
7426 031242 000137 031574      JMP      180$    ;GO TO 180$ IF ERROR WAS FOUND
7427 031246
150$:
```

```

7428 031246 032737 140000 031576      BIT      #MSE!USE,190$      ;IS THIS BSE ??
7429 031254 001033      BNE      152$      ;YES !!
7430 031256 032737 010000 031576      BIT      #FMT16,190$      ;IS THIS FER ??
7431 031264 001466      BEQ      155$      ;NO !!
7432
7433
7434 031266 032737 000020 001344      ;VERIFY THAT FER IS SET
7435 031274 001122      BIT      #FER,RMER11      ;IS FER SET ??
7436 031276 004737 053016      BNE      160$      ;YES !!
7437 031302 000405      JSR      PC,DTASTS      ;GO VERIFY RESULTS OF DATA TRANSFER
7438 031304 000240      BR      151$      ;GO TO 151$ IF NO ERROR
7439 031306 104000      NOP      ;RETURN HERE IF ERROR
7440 031310 004736      ERROR    ;ERROR # DEFINED BY DTASTS SUBROUTINE
7441 031312 000137 031574      JSR      PC,@(SP)+      ;GO BACK FOR MORE ERROR CHECKS
7442 031316 013737 001344 001142 151$: MOV      RMER11,$BDDAT      ;GO TO 180$ IF ERROR WAS FOUND
7443 031324 013737 001344 001140      MOV      RMER11,$GDDAT      ;RECEIVED STATUS
7444 031332 052737 000020 001140      BIS      #FER,$GDDAT      ;EXPECTED STATUS
7445 031340 104343      ERROR    343      ;FORMAT ERROR NOT SET
7446 031342 000514      BR      180$
7447 031344
7448
7449 031344 032737 100000 001372      ;VERIFY THAT BAD SECTOR ERROR IS SET
7450 031352 001073      BIT      #BSE,RMER21      ;IS BSE SET ??
7451 031354 004737 053016      BNE      160$      ;YES !!
7452 031360 000405      JSR      PC,DTASTS      ;GO VERIFY RESULTS OF DATA TRANSFER
7453 031362 000240      BR      153$      ;GO TO 153$ IF NO ERROR
7454 031364 104000      NOP      ;RETURN HERE IF ERROR
7455 031366 004736      ERROR    ;ERROR # DEFINED BY DTASTS SUBROUTINE
7456 031370 000137 031574      JSR      PC,@(SP)+      ;GO BACK FOR MORE ERROR CHECKS
7457 031374      JMP      180$      ;GO TO 180$ IF ERROR WAS FOUND
7458 031374 013737 001372 001142 153$: MOV      RMER21,$BDDAT      ;RECEIVED STATUS
7459 031402 013737 001372 001140      MOV      RMER21,$GDDAT      ;EXPECTED STATUS
7460 031410 052737 100000 001140      BIS      #BSE,$GDDAT
7461 031416 013737 103564 001174      MOV      BUFONE,$TMP0      ;WRITTEN HEADER
7462 031424 013737 104570 001176      MOV      BUFTWO,$TMP1      ;READ HEADER WORD
7463 031432 013737 031576 001200      MOV      190$,$TMP2      ;FAILING BIT POSITION
7464      ; ERROR    345      ;FAILED TO DETECT BSE
7465 031440 000455      BR      180$      ;SKIP REST OF TEST
7466 031442
7467
7468
7469 031442 032737 000200 001344      ;VERIFY THAT HEADER COMPARE ERROR IS SET
7470 031450 001034      BIT      #HCE,RMER11      ;IS 'HCE' SET??
7471 031452 004737 053016      BNE      160$      ;YES!!
7472 031456 000405      JSR      PC,DTASTS      ;GO VERIFY RESULTS OF DATA TRANSFER
7473 031460 000240      BR      156$      ;GO TO 156$ IF NO ERROR
7474 031462 104000      NOP      ;RETURN HERE IF ERROR
7475 031464 004736      ERROR    ;ERROR # DEFINED BY DTASTS SUBROUTINE
7476 031466 000137 031574      JSR      PC,@(SP)+      ;GO BACK FOR MORE ERROR CHECKS
7477 031472 013737 001344 001142 156$: MOV      RMER11,$BDDAT      ;GO TO 180$ IF ERROR WAS FOUND
7478 031500 013737 001344 001140      MOV      RMER11,$GDDAT      ;RECEIVED STATUS FOR TYPEOUT
7479 031506 052737 000200 001140      BIS      #HCE,$GDDAT      ;EXPECTED STATUS
7480 031514 013737 103564 001174      MOV      BUFONE,$TMP0      ;WRITTEN HEADER
7481 031522 013737 104570 001176      MOV      BUFTWO,$TMP1      ;READ HEADER WORD
7482 031530 013737 031576 001200      MOV      190$,$TMP2      ;FAILING BIT POSITION
7483 031536 104344      ERROR    344      ;FORMAT ERROR NOT SET
  
```

```
7484 031540 000415 BR 180$
7485
7486 031542 160$:
7487
7488 ;CHECK FOR OTHER ERRORS
7489 031542 004737 041344 JSR PC,SECERR ;GO CHECK FOR SECONDARY ERRORS
7490 031546 000405 BR 165$ ;GO TO 165$ IF NO ERROR
7491 031550 000240 NOP ;RETURN HERE IF ERROR
7492 031552 104000 ERROR ;ERROR # DEFINED BY SECERR SUBROUTINE
7493 031554 004736 JSR PC,2(SP)+ ;GO BACK FOR MORE ERROR CHECKS
7494 031556 000137 031574 JMP 180$ ;GO TO 180$ IF ERROR WAS FOUND
7495 031562 165$:
7496
7497
7498
7499 ;ADVANCE THE BIT POSITION AND FORMAT AGAIN IF NOT DONE
7500 031562 006337 031576 ASL 190$ ;SHIFT TO NEXT BIT POSITION
7501 031566 001404 BEQ 200$ ;EXIT IF DONE
7502 031570 000137 030626 JMP 10$ ;GO DO NEXT SECTOR
7503 031574 180$:
7504 031574 000465 BR 240$ ;JUMP OVER STORAGE
7505 031576 190$:
7506 031576 000000 .WORD ;STORAGE FOR BIT POSITION
7507 031600 200$:
7508 ; MOV #0,RMDCO ;REFORMAT THE SECTOR IN 16 BIT MODE
7509 ; MOV #0,RMDAO ;
7510 031600 012737 010000 001432 MOV #FMT16,RMOFO ; 16 BIT MODE
7511 031606 012737 177776 001402 MOV #-2,RMWCO ;ONLY TWO HEADER WORDS
7512 031614 012737 103564 001404 MOV #BUFONE,RMBAO ;SELECT THE BUFFER
7513 031622 012737 000062 001400 MOV #WH,RMCS10 ;WRITE HEAD AND DATA COMMAND
7514 031630 004737 036620 JSR PC,GENBUF ;GENERATE THE BUFFER PATTERN
7515
7516 031634 004737 034000 JSR PC,TSTPRP ;PREPARE DEVICE FOR TEST
7517 031640 154130 .WORD 154130 ;TASK DESCRIPTOR
7518 031642 000404 BR 210$ ;GO TO 210$ IF NO ERROR
7519 031644 000240 NOP ;RETURN HERE IF ERROR
7520 031646 104000 ERROR ;ERROR # DEFINED BY TSTPRP SUBROUTINE
7521 031650 000137 031654 JMP 210$ ;GO TO 210$ IF ERROR WAS FOUND
7522 031654 012737 000063 001400 210$: MOV #WH!GO,RMCS10 ;SET THE GO BIT
7523 031662 012702 001535 MOV #PUTINX,R2 ;PUT THE REGISTER ADDRESS INTO TABLE
7524 031666 112722 000006 MOVB #RMDA,(R2)+
7525 031672 112722 000034 MOVB #RMDC,(R2)+
7526 031676 112722 000032 MOVB #RMOF,(R2)+
7527 031702 112722 000002 MOVB #RMWC,(R2)+
7528 031706 112722 000004 MOVB #RMBA,(R2)+
7529 031712 112722 000000 MOVB #RMCS1,(R2)+
7530 031716 112722 000200 MOVB #200,(R2)+ ;TERMINATOR
7531 031722 004737 037766 JSR PC,PUT ;GO WRITE REGISTERS VIA PUT SUB
7532 031726 000404 BR 220$ ;GO TO 220$ IF NO ERROR
7533 031730 000240 NOP ;RETURN HERE IF ERROR
7534 031732 104000 ERROR ;ERROR DEFINED BY PUT SUB
7535 031734 000137 031750 JMP 240$ ;GO TO 240$ IF ERROR WAS FOUND
7536 031740 000240 220$: NOP
7537 031742 004737 040326 JSR PC,TIMOUT ;WAIT UNTIL IT FINISH
7538 031746 000240 NOP
7539 031750 240$:
```



```
7540
7541
7542
7543
7544 031750
7545 031750 000004
7546 031752 000240
7547 031754 012706 001100
7548 031760 013700 001276
7549 031764 013701 001450
7550 031770 012737 000035 001226
7551 031776 012737 000001 032560
7552 032004
7553
7554
7555 032004 012737 000000 001434
7556 032012 012737 000000 001406
7557 032020 012737 010000 001432
7558 032026 012737 177376 001402
7559 032034 012737 103564 001404
7560 032042 012737 000062 001400
7561 032050 012737 065104 001174
7562 032056 012737 000001 001176
7563 032064 004737 036620
7564 032070
7565
7566
7567 032070 004737 034000
7568 032074 154130
7569 032076 000404
7570 032100 000240
7571 032102 104000
7572 032104 000137 032732
7573 032110
7574
7575
7576 032110 033737 032560 103566
7577 032116 001404
7578 032120 043737 032560 103566
7579 032126 000403
7580 032130 053737 032560 103566
7581
7582 032136
7583
7584
7585 032136 012737 000063 001400
7586 032144 012702 001535
7587 032150 112722 000006
7588 032154 112722 000034
7589 032160 112722 000032
7590 032164 112722 000002
7591 032170 112722 000004
7592 032174 112722 000000
7593 032200 112722 000200
7594 032204 004737 037766
7595 032210 000404

*****
*TEST 35          FORMAT HCE, SECOND HEADER WORD
*****
TST35:
      SCOPE          ;SCOPE CALL
      NOP            ;START OF TEST
      MOV     #STACK,SP  ;INITIALIZE STACK POINTER
      MOV     $BASE,R0   ;R0=UNIBUS ADDRESS
      MOV     TSTQUE,R1  ;(R1) = DEVICE BEING TESTED
      MOV     #35,$TESTN ;SET TEST NUMBER IN APT MAIL BOX
      MOV     #1,190$    ;INIT BIT POSITION

10$:
;SETUP PARAMETERS FOR GENERATING DATA BUFFER
      MOV     #0,RMDCO   ;CYLINDER = 0
      MOV     #0,RMDAO   ;TRACK = SECTOR = 0
      MOV     #FMT16,RMOFO ;16 BIT FORMAT
      MOV     #<^C<2+256.>+1>,RMWCO ;2 + 256 WORDS
      MOV     #BUFONE,RMBAO ;DATA BUFFER ADDRESS
      MOV     #WH,RMC$10 ;WRITE HEADER AND DATA
      MOV     #ZEROS,$TMP0 ;USE ALL ZEROS DATA PATTERN
      MOV     #1,$TMP1
      JSR     PC,GENBUF   ;GO GENERATE DATA BUFFER

20$:
;PREPARE DEVICE FOR DATA TRANSFER
      JSR     PC,TSTPRP   ;PREPARE DEVICE FOR TEST
      .WORD   154130 ;TASK DESCRIPTOR
      BR      30$         ;GO TO 30$ IF NO ERROR
      NOP                    ;RETURN HERE IF ERROR
      ERROR   #DEFINED BY TSTPRP SUBROUTINE
      JMP     240$        ;GO TO 240$ IF ERROR WAS FOUND

30$:
;COMPLEMENT DATA BIT IN SECOND HEADER WORD
      BIT     190$,BUFONE+2 ;IS BIT IN HEADER ON??
      BEQ     31$          ;NO!!
      BIC     190$,BUFONE+2 ;RESET BIT IN HEADER
      BR      32$
31$:  BIS     190$,BUFONE+2 ;SET BIT IN HEADER

32$:
;SETUP AND EXECUTE WRITE HEADER AND DATA COMMAND
      MOV     #WH!GO,RMC$10 ;WRITE HEADER AND DATA
      MOV     #PUTINX,R2    ;WRITE REGISTER INDEX TABLE
      MOVB    #RMDA,(R2)+
      MOVB    #RMDC,(R2)+
      MOVB    #RMOF,(R2)+
      MOVB    #RMWC,(R2)+
      MOVB    #RMBA,(R2)+
      MOVB    #RMC$1,(R2)+
      MOVB    #200,(R2)+
      JSR     PC,PUT        ;GO WRITE REGISTERS VIA PUT SUB
      BR      80$          ;GO TO 80$ IF NO ERROR
```

```
7596 032212 000240      NOP      ;RETURN HERE IF ERROR
7597 032214 104000      ERROR     ;ERROR DEFINED BY PUT SUB
7598 032216 000137 032556      JMP      180$ ;GO TO 180$ IF ERROR WAS FOUND
7599 032222      80$:
7600
7601      ;SETUP INPUT REGISTER BUFFER FOR READING STATUS
7602 032222 004737 037432      JSR      PC,GETSTS
7603
7604      ;WAIT FOR WRITE COMMAND TO COMPLETE AND READ STATUS
7605 032226 004737 040326      JSR      PC,TIMOUT ;WAIT FOR COMMAND TO COMPLETE
7606 032232 004737 037516      JSR      PC,GET ;GO READ REGISTERS VIA GET SUB
7607 032236 000404      BR      90$ ;GO TO 90$ IF NO ERROR
7608 032240 000240      NOP      ;RETURN HERE IF ERROR
7609 032242 104000      ERROR     ;ERROR DEFINED BY GET SUB
7610 032244 000137 032556      JMP      180$ ;GO TO 180$ IF ERROR WAS FOUND
7611 032250      90$:
7612
7613      ;VERIFY RESULTS OF WRITE COMMAND
7614 032250 004737 040512      JSR      PC,PRIERR ;GO CHECK FOR PRIMARY ERRORS
7615 032254 000405      BR      100$ ;GO TO 100$ IF NO ERROR
7616 032256 000240      NOP      ;RETURN HERE IF ERROR
7617 032260 104000      ERROR     ;ERROR # DEFINED BY PRIERR SUBROUTINE
7618 032262 004736      JSR      PC,@(SP)+ ;GO BACK FOR MORE ERROR CHECKS
7619 032264 000137 032556      JMP      180$ ;GO TO 180$ IF ERROR WAS FOUND
7620 032270      100$:
7621 032270 004737 053016      JSR      PC,DTASTS ;GO VERIFY RESULTS OF DATA TRANSFER
7622 032274 000405      BR      110$ ;GO TO 110$ IF NO ERROR
7623 032276 000240      NOP      ;RETURN HERE IF ERROR
7624 032300 104000      ERROP     ;ERROR # DEFINED BY DTASTS SUBROUTINE
7625 032302 004736      JSR      PC,@(SP)+ ;GO BACK FOR MORE ERROR CHECKS
7626 032304 000137 032556      JMP      180$ ;GO TO 180$ IF ERROR WAS FOUND
7627 032310      110$:
7628 032310 004737 041344      JSR      PC,SECERR ;GO CHECK FOR SECONDARY ERRORS
7629 032314 000405      BR      120$ ;GO TO 120$ IF NO ERROR
7630 032316 000240      NOP      ;RETURN HERE IF ERROR
7631 032320 104000      ERROR     ;ERROR # DEFINED BY SECERR SUBROUTINE
7632 032322 004736      JSR      PC,@(SP)+ ;GO BACK FOR MORE ERROR CHECKS
7633 032324 000137 032556      JMP      180$ ;GO TO 180$ IF ERROR WAS FOUND
7634 032330      120$:
7635
7636      ;READ HEADER AND DATA FOR SECTOR JUST WRITTEN
7637
7638 032330 012737 000073 001400      MOV      #RH!GO,RMC$10 ;READ HEADER & DATA COMMAND
7639 032336 012737 104570 001404      MOV      #BUFTWO,RMB$0 ;CHANGE BUS ADDRESS
7640 032344 004737 037766      JSR      PC,PUT ;GO WRITE REGISTERS VIA PUT SUB
7641 032350 000404      BR      130$ ;GO TO 130$ IF NO ERROR
7642 032352 000240      NOP      ;RETURN HERE IF ERROR
7643 032354 104000      ERROR     ;ERROR DEFINED BY PUT SUB
7644 032356 000137 032556      JMP      180$ ;GO TO 180$ IF ERROR WAS FOUND
7645 032362      130$:
7646
7647      ;WAIT FOR READ TO COMPLETE AND GET STATUS
7648 032362 004737 040326      JSR      PC,TIMOUT ;WAIT FOR READ TO COMPLETE
7649 032366 004737 037516      JSR      PC,GET ;GO READ REGISTERS VIA GET SUB
7650 032372 000404      BR      140$ ;GO TO 140$ IF NO ERROR
7651 032374 000240      NOP      ;RETURN HERE IF ERROR
```



```
7652 032376 104000          ERROR          ;ERROR DEFINED BY GET SUB
7653 032400 000137 032556    JMP          180$      ;GO TO 180$ IF ERROR WAS FOUND
7654 032404          140$:
7655
7656          ;VERIFY THE RESULTS OF READ OPERATION
7657 032404 004737 040512    JSR          PC,PRIERR      ;GO CHECK FOR PRIMARY ERRORS
7658 032410 000405          BR          150$          ;GO TO 150$ IF NO ERROR
7659 032412 000240          NOP          ;RETURN HERE IF ERROR
7660 032414 104000          ERROR        ;ERROR # DEFINED BY PRIERR SUBROUTINE
7661 032416 004736          JSR          PC,@(SP)+      ;GO BACK FOR MORE ERROR CHECKS
7662 032420 000137 032556    JMP          180$          ;GO TO 180$ IF ERROR WAS FOUND
7663 032424          150$:
7664
7665          ;VERIFY THAT HEADER COMPARE ERROR IS SET
7666 032424 032737 000200 001344    BIT          #HCE,RMER11      ;IS 'HCE' SET??
7667 032432 001034          BNE          160$          ;YES!!
7668 032434 004737 053016    JSR          PC,DTASTS      ;GO VERIFY RESULTS OF DATA TRANSFER
7669 032440 000405          BR          155$          ;GO TO 155$ IF NO ERROR
7670 032442 000240          NOP          ;RETURN HERE IF ERROR
7671 032444 104000          ERROR        ;ERROR # DEFINED BY DTASTS SUBROUTINE
7672 032446 004736          JSR          PC,@(SP)+      ;GO BACK FOR MORE ERROR CHECKS
7673 032450 000137 032556    JMP          180$          ;GO TO 180$ IF ERROR WAS FOUND
7674 032454 013737 001344 001142    155$: MOV          RMER11,$BDDAT      ;RECEIVED STATUS FOR TYPEOUT
7675 032462 013737 001344 001140    MOV          RMER11,$GDDAT      ;EXPECTED STATUS
7676 032470 052737 000200 001140    BIS          #HCE,$GDDAT
7677 032476 013737 103566 001174    MOV          BUFOFF+2,$TMP0      ;WRITTEN HEADER
7678 032504 013737 104572 001176    MOV          BUFTWO+2,$TMP1      ;READ HEADER WORD
7679 032512 013737 032560 001200    MOV          190$,$TMP2      ;FAILING BIT POSITION
7680 032520 104344          ERROR        344          ;FORMAT ERROR NOT SET
7681 032522 000415          BR          180$
7682
7683 032524          160$:
7684
7685          ;CHECK FOR OTHER ERRORS
7686 032524 004737 041344    JSR          PC,SECERR      ;GO CHECK FOR SECONDARY ERRORS
7687 032530 000405          BR          165$          ;GO TO 165$ IF NO ERROR
7688 032532 000240          NOP          ;RETURN HERE IF ERROR
7689 032534 104000          ERROR        ;ERROR # DEFINED BY SECERR SUBROUTINE
7690 032536 004736          JSR          PC,@(SP)+      ;GO BACK FOR MORE ERROR CHECKS
7691 032540 000137 032556    JMP          180$          ;GO TO 180$ IF ERROR WAS FOUND
7692 032544          165$:
7693
7694          ;ADVANCE THE BIT POSITION AND FORMAT NEXT SECTOR IF NOT DONE
7695
7696 032544 006337 032560    ASL          190$          ;SHIFT TO NEXT BIT POSITION
7697 032550 001404          BEQ          200$          ;EXIT IF DONE
7698 032552 000137 032004    JMP          10$          ;GO DO NEXT SECTOR
7699 032556          180$:
7700 032556 000465          BR          240$          ;JUMP OVER STORAGE
7701 032560          190$:
7702 032560 000000          .WORD          ;STORAGE FOR BIT POSITION
7703 032562          200$:
7704          ;
7705          ;
7706 032562 012737 010000 001432    MOV          #0,RMDCO      ;REFORMAT THE SECTOR IN 16 BIT MODE
7707 032570 012737 177776 001402    MOV          #0,RMDAO      ;SECTOR 0, TRACK 0, CYL 0
7708          MOV          #FMT16,RMOFO      ;16 BIT MODE
7709          MOV          #-2,RMWCO      ;2 HEADER WORDS ONLY
```

CZRMDCO RM03/2 FCTNL TST 2
CZRMDC.P11 12-DEC-78 08:24

MACY11 30A(1052) 04-JAN-79 11:23 PAGE 153
T35 FORMAT MCE, SECOND HEADER WORD

K 12

SEQ 0153

```
7708 032576 012737 103564 001404      MOV      #BUFONE,RMBA0      ;BUFFER ADDRESS
7709 032604 012737 000062 001400      MOV      #WH,RMCS10      ;WRITE HEAD AND DATA COMMAND
7710 032612 004737 036620              JSR      PC,GENBUF      ;SET UP THE BUFFER
7711 032616 004737 034000              JSR      PC,TSTPRP      ;PREPARE DEVICE FOR TEST
7712 032622 154130              .WORD    154130 ;TASK DESCRIPTOR
7713 032624 000404              BR        210$      ;GO TO 210$ IF NO ERROR
7714 032626 000240              NOP                      ;RETURN HERE IF ERROR
7715 032630 104000              ERROR      ;ERROR # DEFINED BY TSTPRP SUBROUTINE
7716 032632 000137 032636              JMP      210$      ;GO TO 210$ IF ERROR WAS FOUND
7717 032636 012737 000063 001400 210$: MOV      #WH!GO,RMCS10      ;SET GO BIT
7718 032644 012702 001535              MOV      #PUTINX,R2      ;TABLE ADDRESS
7719 032650 112722 000006              MOVB     #RMDA,(R2)+
7720 032654 112722 000034              MOVB     #RMDC,(R2)+
7721 032660 112722 000032              MOVB     #RMOF,(R2)+
7722 032664 112722 000004              MOVB     #RMBA,(R2)+
7723 032670 112722 000002              MOVB     #RMWC,(R2)+
7724 032674 112722 000000              MOVB     #RMCS1,(R2)+
7725 032700 112722 000200              MOVB     #200,(R2)+      ;TERMINATOR
7726 032704 004737 037766              JSR      PC,PUT      ;GO WRITE REGISTERS VIA PUT SUB
7727 032710 000404              BR        220$      ;GO TO 220$ IF NO ERROR
7728 032712 000240              NOP                      ;RETURN HERE IF ERROR
7729 032714 104000              ERROR      ;ERROR DEFINED BY PUT SUB
7730 032716 000137 032732              JMP      240$      ;GO TO 240$ IF ERROR WAS FOUND
7731 032722 000240              220$: NOP
7732 032724 004737 040326              JSR      PC,TIMOUT      ;WAIT FOR TIME OUT
7733 032730 000240              NOP
7734 032732              240$:
7735
7736              ;PUT NEWTEST HERE
```

```
7737 032732          $EOSP:
7738 032732 000240      NOP
7739 032734 013700 001450  MOV    TSTQUE,RO
7740 032740 062700 000002  ADD    #2,RO
7741 032744 010037 001450  MOV    RO,TSTQUE
7742 032750 005710      TST    (RO)
7743 032752 001402      BEQ    1$
7744 032754 000137 007124  JMP    READY
7745 032760 012737 001452 001450 1$:  MOV    #TSTQUE+2,TSTQUE
7746          .SBTTL  END OF PASS ROUTINE
7747
7748          ;*****
7749          ;*INCREMENT THE PASS NUMBER ($PASS)
7750          ;*TYPE 'END PASS #XXXXX TOTAL NUMBER OF ERRORS SINCE LAST REPORT YYYYYY'
7751          ;*WHERE XXXXX AND YYYYY ARE DECIMAL NUMBERS
7752          ;*IF THERES A MONITOR GO TO IT
7753          ;*IF THERE ISN'T JUMP TO SHUT
7754
7755 032766          $EOP:
7756 032766 000240      NOP
7757 032770 005037 001116  CLR    $TSTNM          ;;ZERO THE TEST NUMBER
7758 032774 005037 001206  CLR    $TIMES          ;;ZERO THE NUMBER OF ITERATIONS
7759 033000 005237 001230  INC    $PASS          ;;INCREMENT THE PASS NUMBER
7760 033004 042737 100000 001230  BIC    #100000,$PASS      ;;DON'T ALLOW A NEG. NUMBER
7761 033012 005327      DEC    (PC)+          ;;LOOP?
7762 033014 000001      $EOPCT: .WORD 1
7763 033016 003063      BGT    $DOAGN          ;;YES
7764 033020 012737      MOV    (PC)+,@(PC)+      ;;RESTORE COUNTER
7765 033022 000001      $ENDCT: .WORD 1
7766 033024 033014      $EOPCT
7767 033026 104401 033034  TYPE    ,65$          ;;TYPE ASCII STRING
7768 033032 000407      BR      64$          ;;GET OVER THE ASCII
7769          ;;65$: .ASCIIZ <12><15>/END PASS #/
7770          64$:
7771 033052 013746 001230  MOV    $PASS,-(SP)      ;;SAVE $PASS FOR TYPEOUT
7772          ;;TYPE PASS NUMBER
7773 033056 104405      TYPDS          ;;GO TYPE--DECIMAL ASCII WITH SIGN
7774 033060 104401 033066  TYPE    ,67$          ;;TYPE ASCII STRING
7775 033064 000421      BR      66$          ;;GET OVER THE ASCII
7776          ;;67$: .ASCIIZ / TOTAL ERRORS SINCE LAST REPORT /
7777          66$:
7778 033130          MOV    $ERTTL,-(SP)          ;;SAVE $ERTTL FOR TYPEOUT
7779          ;;TOTAL NUMBER OF ERRORS
7780 033134 104405      TYPDS          ;;GO TYPE--DECIMAL ASCII WITH SIGN
7781 033136 104401 001217  TYPE    ,$CRLF        ;;TYPE CARRIAGE RETURN, LINE FEED
7782 033142 005037 001126  CLR    $ERTTL          ;;CLEAR ERROR TOTAL
7783 033146 013700 000042  $GET42: MOV    @#42,RO      ;;GET MONITOR ADDRESS
7784 033152 001405      BEQ    $DOAGN          ;;BRANCH IF NO MONITOR
7785 033154 000005      RESET          ;;CLEAR THE WORLD
7786 033156 004710      $ENDAD: JSR    PC,(RO)        ;;GO TO MONITOR
7787 033160 000240      NOP          ;;SAVE ROOM
7788 033162 000240      NOP          ;;FOR
7789 033164 000240      NOP          ;;ACT11
7790          $DOAGN:
7791 033166 000137      JMP    @(PC)+          ;;RETURN
7792 033170 057372      $RTNAD: .WORD  SHUT
```

CZRMDCO RM03/2 FCTNL TST 2
CZRMDC.P11 12-DEC-78 08:24

MACY11 30A(1052) 04-JAN-79 11:23 PAGE 155
END OF PASS ROUTINE

M 12

SEQ 0155

7793 033172 377 377 000 \$ENULL: .BYTE -1,-1,0 ;:NULL CHARACTER STRING
7794 033176 .EVEN

```

7795 .SBTTL SUBROUTINES
7796
7797 ;*****
7798 .SBTTL ERROR TYPEOUT ROUTINE
7799
7800 ;*THE ERROR TYPEOUT ROUTINE ASSEMBLES AND PRINTS INFORMATION
7801 ;*REGARDING THE DETECTION OF AN ERROR AS FOLLOWS:
7802 ;*
7803 ;* .UNIT NUMBER, TEST NUMBER, ERROR NUMBER AND PROGRAM COUNTER ARE
7804 ;*PRINTED ON THE FIRST LINE;
7805 ;* .ERROR MESSAGE IS ASSEMBLED, FORMATTED AND PRINTED ON
7806 ;*ONE OR MORE SUCCEEDING LINES;
7807 ;* .PAIRED LINES OF ERROR HEADERS AND ERROR DATA
7808 ;*ARE PRINTED AFTER THE ERROR MESSAGE.
7809
7810 ERRTP:
7811 033176 SAVREG
7812 033176 104414 BIT #SW13,SWR ;INHIBIT TYPEOUTS??
7813 033200 032777 020000 145746 BEQ 1$ ;NO!!
7814 033210 000137 033726 JMP 21$ ;YES!!
7815 ;TYPE UNIT NUMBER, TEST NUMBER, ERROR NUMBER, AND PROGRAM COUNTER
7816 033214 104401 001217 1$: TYPE ,CRLF
7817 033220 104401 033742 TYPE ,ERTY00 ;TYPE 'UNIT#'
7818 033224 013746 001234 MOV $UNIT,-(SP) ;SAVE $UNIT FOR TYPEOUT
7819 ;TYPE UNIT NUMBER
7820 033230 104403 TYPOS ;GO TYPE--OCTAL ASCII
7821 033232 003 .BYTE 3 ;TYPE 3 DIGIT(S)
7822 033233 000 .BYTE 0 ;SUPPRESS LEADING ZEROS
7823 033234 005037 033732 CLR TSTNMB ;LOAD TEST NUMBER FOR
7824 033240 013737 001226 033732 MOV $TESTN,TSTNMB
7825 033246 104401 033750 TYPE ,ERTY01 ;TYPE 'TST#'
7826 033252 013746 033732 MOV TSTNMB,-(SP) ;SAVE TSTNMB FOR TYPEOUT
7827 ;TYPE TEST NUMBER
7828 033256 104403 TYPOS ;GO TYPE--OCTAL ASCII
7829 033260 003 .BYTE 3 ;TYPE 3 DIGIT(S)
7830 033261 000 .BYTE 0 ;SUPPRESS LEADING ZEROS
7831 033262 005037 033734 CLR ERRNMB ;LOAD ERROR NUMBER FOR
7832 033266 113737 001130 033734 MOVB $ITEMB,ERRNMB ;TYPEOUT
7833 033274 001406 BEQ 2$ ;SKIP IF NO ERROR CALLED
7834 033276 104401 033760 TYPE ,ERTY02 ;TYPE 'ERR#'
7835 033302 013746 033734 MOV ERRNMB,-(SP) ;SAVE ERRNMB FOR TYPEOUT
7836 ;TYPE ERROR NUMBER
7837 033306 104403 TYPOS ;GO TYPE--OCTAL ASCII
7838 033310 003 .BYTE 3 ;TYPE 3 DIGIT(S)
7839 033311 000 .BYTE 0 ;SUPPRESS LEADING ZEROS
7840 033312 104401 033767 2$: TYPE ,ERTY03 ;TYPE 'PC='
7841 033316 013746 001132 MOV $ERRPC,-(SP) ;SAVE $ERRPC FOR TYPEOUT
7842 ;TYPE PROGRAM COUNTER
7843 033322 104403 TYPOS ;GO TYPE--OCTAL ASCII
7844 033324 006 .BYTE 6 ;TYPE 6 DIGIT(S)
7845 033325 001 .BYTE 1 ;TYPE LEADING ZEROS
7846 ;GENERATE POINTER TO ERROR TABLE UNLESS ERROR NUMBER IS 0
7847 033326 005737 033734 3$: TST ERRNMB ;WAS AN ERROR CALLED?
7848 033332 001575 BEQ 21$ ;NO!!
7849 033334 104401 001217 TYPE ,CRLF ;YES-TYPE CRLF
7850 033340 105037 033740 CLRB BOTFLG ;CLEAR BOT FLAG

```

```
7851 033344 105037 033741 CLR B CHRCNT ;CLEAR CHARACTER COUNTER
7852 033350 013700 033734 MOV ERRMB,R0 ;R0 POINTS TO FIRST OF
7853 033354 006300 ASL R0 ;FOUR ENTRIES IN ERROR
7854 033356 006300 ASL R0 ;TABLE
7855 033360 006300 ASL R0
7856 033362 062700 001554 ADD #ERRTB-8.,R0
7857 033366 011001 MOV (R0),R1 ;R1 POINTS TO ERROR MESSAGE
7858 ;TABLE
7859 033370 001507 BEQ 13$ ;BRANCH IF NO ERROR MESSAGE
7860 ;TYPE THE ERROR MESSAGE
7861 033372 012102 4$: MOV (R1)+,R2 ;R2=ADDRESS OF MESSAGE STRING
7862 033374 001505 BEQ 12$ ;BRANCH IF END OF MESSAGE
7863 033376 010237 033544 MOV R2,11$ ;LOAD ADDRESS OF STRING
7864 033402 005037 033736 CLR BOTADR ;CLEAR BOT ADDRESS
7865 033406 112203 5$: MOVB (R2)+,R3 ;END OF STRING??
7866 033410 001454 BEQ 10$ ;YES!!
7867 033412 122703 000015 CMPB #CR,R3 ;CARRIAGE RETURN??
7868 033416 001003 BNE 6$ ;NO!!
7869 033420 105037 033741 CLR B CHRCNT ;YES-CLEAR CHAR COUNT
7870 033424 000770 BR 5$ ;GET NEXT CHARACTER
7871 033426 122703 000012 6$: CMPB #LF,R3 ;LINE FEED??
7872 033432 001765 BEQ 5$ ;YES-GET NEXT CHARACTER
7873 033434 122703 000011 CMPB #HT,R3 ;HORIZONTAL TAB??
7874 033440 001007 BNE 8$ ;NO!!
7875 033442 105237 033741 7$: INCB CHRCNT ;ADJUST CHARACTER COUNT
7876 033446 132737 000007 033741 BITB #7,CHRCNT
7877 033454 001372 BNE 7$
7878 033456 000407 BR 9$
7879 033460 105237 033741 8$: INCB CHRCNT ;INCREMENT CHARACTER COUNT
7880 033464 122703 000040 CMPB #' ,R3 ;SPACE??
7881 033470 001002 BNE 9$ ;NO!!
7882 033472 010237 033736 MOV R2,BOTADR ;SAVE ADDRESS OF SPACE
7883 033476 122737 000100 033741 9$: CMPB #64.,CHRCNT ;END OF LINE??
7884 033504 103340 BHIS 5$ ;NO!!
7885 033506 013704 033736 MOV BOTADR,R4 ;GET ADDRESS OF LAST SPACE
7886 033512 001007 BNE 90$ ;BRANCH IF SPACE DETECTED
7887 033514 104401 001217 TYPE ,$CRLF ;TYPE CRLF
7888 033520 105037 033741 CLR B CHRCNT ;CLEAR CHARACTER COUNT
7889 033524 013702 033544 MOV 11$,R2 ;SET UP R2 FOR TESTING
7890 033530 000726 BR 5$
7891 033532 105044 90$: CLR B -(R4) ;REPLACE SPACE
7892 033534 112737 177777 033740 MOVB #-1,BOTFLG ;SET BOT FLAG
7893 033542 104401 10$: TYPE ;TYPE ERROR MESSAGE STRING
7894 033544 000000 11$: .WORD ;STRING ADDRESS GOES HERE
7895 033546 105737 033740 TSTB BOTFLG ;WAS STRING TRUNCATED??
7896 033552 001707 BEQ 4$ ;NO!!
7897 033554 104401 001217 TYPE ,$CRLF ;YES-TYPE CRLF
7898 033560 105037 033740 CLR B BOTFLG ;CLEAR BOT FLAG
7899 033564 105037 033741 CLR B CHRCNT ;CLEAR CHARACTER COUNT
7900 033570 013702 033736 MOV BOTADR,R2 ;SETUP R2 FOR TESTING
7901 033574 010237 033544 MOV R2,11$ ;SETUP 11$ FOR TYPING
7902 033600 112742 000040 MOVB #' ,-(R2) ;RESTORE SPACE
7903 033604 105722 TSTB (R2)+ ;RESTORE R2
7904 033606 000677 BR 5$ ;TYPE REST OF STRING
7905 12$:
7906 ;TYPE ERROR HEADER AND ERROR DATA
```



```

7907 033610
7908 033610 016001 000002
7909 033614 001444
7910 033616 104401 001217
7911 033622 016002 000004
7912 033626 016003 000006
7913 033632 012137 033642
7914 033636 001433
7915
7916 033640 104401
7917 033642 000000
7918 033644 104401 001217
7919 033650 005702
7920 033652 001767
7921 033654 012204
7922 033656 012305
7923 033660 105725
7924 033662 100407
7925 033664 001403
7926 033666 013446
7927 033670 104405
7928 033672 000405
7929 033674 013446
7930 033676 104402
7931 033700 000402
7932 033702 013446
7933 033704 104406
7934 033706 005714
7935 033710 001403
7936 033712 104401 033775
7937 033716 000760
7938 033720 104401 001217
7939 033724 000742
7940 033726 104415
7941 033730 000207
7942
7943 033732 000000
7944 033734 000000
7945 033736 000000
7946 033740 000
7947 033741 000
7948
7949 033742 047125 052111 000043
7950 033750 020054 042524 052123
7951 033756 000043
7952 033760 020054 051105 021522
7953 033766 000
7954 033767 054 050040 036503
7955 033774 000
7956 033775 040 000040
7957
7958

13$: MOV 2(R0),R1 ;R1 POINTS TO ERROR HEADER TABLE
      BEQ 21$ ;BRANCH IF NO HEADER
      TYPE ,%CRLF ;(ASSUME NO DATA)
      MOV 4(R0),R2 ;R2 POINTS TO DATA ADDRESS TABLE
      MOV 6(R0),R3 ;R3 POINTS TO FORMAT TABLE
14$: MOV (R1)+,15$ ;PUT HEADER ADDRESS FOR TYPE
      BEQ 21$ ;BRANCH IF END OF HEADERS
      ;(ASSUME END OF DATA)
      TYPE
15$: .WORD 0 ;HEADER ADDRESS GOES HERE
      TYPE ,%CRLF
      TST R2 ;DATA WITH HEADER??
      BEQ 14$ ;NO!!
      MOV (R2)+,R4 ;R4 POINTS TO DATA ADDRESS
      MOV (R3)+,R5 ;R5 POINTS TO FORMAT
16$: TSTB (R5)+ ;WHAT KIND OF DATA??
      BMI 18$ ;BINARY
      BEQ 17$ ;OCTAL
      MOV @ (R4)+,-(SP) ;DECIMAL
      TYPDS
      BR 19$
17$: MOV @ (R4)+,-(SP)
      TYPDC
      BR 19$
18$: MOV @ (R5)+,-(SP)
      TYPBN
19$: TST (R4) ;MORE DATA??
      BEQ 20$ ;NO!!
      TYPE ,ERTY04 ;YES-TYPE 2 SPACES
      BR 16$ ;AND CONTINUE
20$: TYPE ,%CRLF ;TYPE ONE BLANK LINE
      BR 14$ ;BEFORE NEXT HEADER
21$: RESREG
      RTS PC

TSTNMB: .WORD 0 ;TEST NUMBER
ERRNMB: .WORD 0 ;ERROR NUMBER
BOTADR: .WORD 0 ;BEGINNING OF TEXT ADDRESS
BOTFLG: .BYTE 0 ;BOT FLAG
CHRCNT: .BYTE 0 ;CHARACTER COUNT

ERTY00: .ASCIZ @UNIT#@
ERTY01: .ASCIZ @, TEST#@
ERTY02: .ASCIZ @, ERR#@
ERTY03: .ASCIZ @, PC=@
ERTY04: .ASCIZ @ @
.EVEN
```

```
7959 .SBTTL TEST PREPARATION MODULE
7960
7961 ; THIS MODULE PREPARES THE RM03 SUBSYSTEM FOR THE EXECUTION OF A TEST,
7962 ; REPORTING AN ERROR TO THE USER IF AN ERROR IS DETECTED. THE USER
7963 ; SPECIFIES TASKS TO BE PERFORMED, WHICH THE MODULE EXECUTES
7964 ; USING SUBROUTINES.
7965
7966 ;CALL:
7967 JSR PC,TSTPRP
7968 .WORD TASK/VERIFY DESCRIPTOR
7969 BR ?? RETURN HERE IF NO ERROR
7970 NOP RETURN HERE IF ERROR
7971 ERROR ERROR DEFINED BY MODULE
7972
7973 ;TASK/VERIFY DESCRIPTOR
7974 BIT 15 = 1 SELECT DEVICE AND VERIFY DEVICE IS AVAILABLE
7975 BIT 14 = 1 CLEAR CONTROLLER AND SELECT DEVICE
7976 BIT 13 (RESERVED FOR DRIVE CLEAR)
7977 BIT 12 = 1 PACK ACKNOWLEDGE IF VOLUME NOT VALID
7978 BIT 11 = 1 RECALIBRATE IF POSITIONING IN PROGRESS
7979 BIT 10
7980 BIT 9
7981 BIT 8
7982 BIT 7
7983 BIT 6 = 1 VERIFY CONTROLLER CLEAR OPERATION
7984 BIT 5 (RESERVED FOR DRIVE CLEAR)
7985 BIT 4 = 1 VERIFY PACK ACKNOWLEDGE
7986 BIT 3 = 1 VERIFY RECALIBRATION
7987 BIT 2
7988 BIT 1
7989 BIT 0
7990
7991 034000 TSTPRP:
7992
7993 ;STORE TASK DESCRIPTOR AND CLEAR USER'S ERROR CALL
7994 034000 017637 000000 034712 MOV @ (SP),500$ ;STORE DESCRIPTOR
7995 034006 062716 000006 ADD #6,(SP) ;MOVE SP TO USERS ERROR CALL
7996 034012 105076 000000 CLRB @ (SP) ;CLEAR ERROR CALL
7997 034016 162716 000004 SUB #4,(SP) ;MOVE SP TO NO ERROR RETURN
7998
7999 ;*****
8000 034022 032737 100000 034712 ;SELECT DEVICE AND VERIFY DEVICE AVAILABLE IF BIT 15 SET IN TASK
8001 034030 001414 BIT #BIT15,500$ ;SELECT DEVICE??
8002 034032 004737 045206 BEQ 30$ ;NO!!
8003 034036 000411 JSR PC,DEVSEL ;GO SELECT DEVICE
8004 034040 000401 BR 30$ ;NO ERROR - CONTINUE
8005 034042 000000 BR 20$
8006 034044 062716 000004 10$: .WORD ;ERROR NUMBER FROM DEVSEL
8007 034050 113776 034042 000000 20$: ADD #4,(SP) ;TRANSFER ERROR TO USER
8008 034056 000137 034700 MOVB 10$,@ (SP)
8009 034062 JMP 400$
8010
8011 ;*****
8012 ;CLEAR CONTROLLER IF BIT 14 IS SET IN TASK
8013 034062 032737 040000 034712 BIT #BIT14,500$ ;CLEAR CONTROLLER??
8014 034070 001453 BEQ 120$ ;NO!!
```



```
8015 034072 004737 046660      JSR    PC,CNTCLR      ;GO CLEAR CONTROLLER
8016 034076 000411              BR     60$             ;CONTINUE - NO ERROR
8017 034100 000401              BR     50$
8018 034102 000000      40$:   .WORD              ;ERROR NUMBER FROM CNTCLR
8019 034104 062716 000004      50$:   ADD     #4,(SP)      ;TRANSFER ERROR TO USER
8020 034110 113776 034102 000000      MOVB    40$,a(SP)
8021 034116 000137 034700      JMP     400$
8022 034122              60$:
8023                          ;*****
8024                          ;VERIFY CONTROLLER CLEAR IF BIT6 SET IN TASK
8025 034122 032737 000100 034712      BIT     #BIT6,500$      ;VERIFY??
8026 034130 001433              BEQ     120$              ;NO!!
8027 034132 004737 037432      JSR     PC,GETSTS      ;SETUP INDEX TABLE
8028 034136 004737 037516      JSR     PC,GET          ;GO GET STATUS
8029 034142 000411              BR     90$             ;NO ERROR GETTING STATUS
8030 034144 000401              BR     80$
8031 034146 000000      70$:   .WORD              ;ERROR FROM GETTING STATUS
8032 034150 062716 000004      80$:   ADD     #4,(SP)      ;TRANSFER ERROR TO USER
8033 034154 113776 034146 000000      MOVB    70$,a(SP)
8034 034162 000137 034700      JMP     400$
8035 034166 004737 046776      90$:   JSR     PC,CLRSTS      ;GO VERIFY STATUS CLEAR
8036 034172 000412              BR     120$            ;NO ERROR IN CLEAR
8037 034174 000401              BR     110$
8038 034176 000000      100$:  .WORD              ;ERROR IN STATUS CLEAR
8039 034200 005726      110$:  TST     (SP)+          ;STRIP RETURN ADDRESS TO
8040 034202 062716 000004      ADD     #4,(SP)          ;SUBROUTINE AND TRANSFER
8041 034206 113776 034176 000000      MOVB    100$,a(SP)      ;ERROR TO USER
8042 034214 000137 034700      JMP     400$
8043 034220              120$:
8044
8045                          ;*****
8046                          ;EXECUTE PACK ACKNOWLEDGE IF BIT12 SET IN TASK AND VOLUME IS
8047                          ;NOT VALID
8048 034220 032737 010000 034712      BIT     #BIT12,500$      ;PACK ACKNOWLEDGE??
8049 034226 001511              BEQ     240$              ;NO!!
8050 034230 112737 000012 001506      MOVB    #RMDS,GETINX      ;GET RMDS
8051 034236 112737 000200 001507      MOVB    #200,GETINX+1
8052 034244 004737 037516      JSR     PC,GET          ;
8053 034250 000411              BR     150$            ;NO ERROR GETTING RMDS
8054 034252 000401              BR     140$
8055 034254 000000      130$:  .WORD              ;
8056 034256 062716 000004      140$:  ADD     #4,(SP)      ;TRANSFER ERROR TO USER
8057 034262 113776 034254 000000      MOVB    130$,a(SP)
8058 034270 000137 034700      JMP     400$
8059 034274 032737 000100 001342      150$:  BIT     #VV,RMDS1      ;IS VOLUME VALID??
8060 034302 001063              BNE     240$              ;YES!!
8061 034304 005037 001474      CLR     MEDENB          ;CLEAR MEDIA ENABLE
8062 034310 012737 000023 001400      MOV     #PAKACK!GO,RMCS10      ;LOAD PACK ACK COMMAND
8063 034316 112737 000000 001535      MOVB    #RMCS1,PUTINX      ;SETUP REGISTER INDEX TABLE
8064 034324 112737 000200 001536      MOVB    #200,PUTINX+1
8065 034332 004737 037766      JSR     PC,PUT          ;GO WRITE COMMAND
8066 034336 000410              BR     180$            ;NO ERROR LOADING REGISTER
8067 034340 000401              BR     170$
8068 034342 000000      160$:  .WORD              ;ERROR FROM PUT SUB
8069 034344 062716 000004      170$:  ADD     #4,(SP)      ;TRANSFER ERROR TO USER
8070 034350 113776 034342 000000      MOVB    160$,a(SP)
```

8071	034356	000550			BR	400\$	
8072	034360				180\$:		
8073							
8074							
8075					;*****		
8076	034360	032737	000020	034712	;VERIFY PACK ACKNOWLEDGE IF #BIT4 SET IN TASK		
8077	034366	001431			BIT	#BIT4,500\$	;VERIFY PACK ACKNOWLEDGE??
8078	034370	004737	037432		BEQ	240\$	;NO!!
8079	034374	004737	037516		JSR	PC,GETSTS	;SETUP FOR STATUS
8080	034400	000410			JSR	PC,GET	;GO GET STATUS
8081	034402	000401			BR	210\$	;NO ERROR GETTING STATUS
8082	034404	000000			BR	200\$	
8083	034406	062716	000004		190\$:	.WORD	;ERROR FROM GET SUB
8084	034412	113776	034404	000000	200\$:	ADD	#4,(SP)
8085	034420	000527				MOV	190\$,a(SP)
8086	034422	004737	047656			BR	400\$
8087	034426	000411			210\$:	JSR	PC,ACKSTS
8088	034430	000401				BR	240\$
8089	034432	000000				BR	230\$
8090	034434	005726			220\$:	.WORD	;PACK ACKNOWLEDGE ERROR
8091	034436	062716	000004		230\$:	TST	(SP)+
8092	034442	113776	034432	000000		ADD	#4,(SP)
8093	034450	000513				MOV	220\$,a(SP)
8094	034452					BR	400\$
8095					240\$:		
8096							
8097					;*****		
8098	034452	032737	004000	034712	;RECALIBRATE DRIVE IF BIT 11 SET IN TASK AND PIP IS ACTIVE		
8099	034460	001513			BIT	#BIT11,500\$	;RECALIBRATE??
8100	034462	112737	000012	001506	BEQ	410\$	;NO!!
8101	034470	112737	000200	001507	MOV	#RMD5,GETINX	;LOAD REGISTER INDEX TABLE
8102	034476	004737	037516		MOV	#200,GETINX+1	
8103	034502	000410			JSR	PC,GET	;GO GET RMD5
8104	034504	000401			BR	270\$	;NO ERROR GETTING RMD5
8105	034506	000000			BR	260\$	
8106	034510	062716	000004		250\$:	.WORD	;ERROR FROM GET SUB
8107	034514	113776	034506	000000	260\$:	ADD	#4,(SP)
8108	034522	000466				MOV	250\$,a(SP)
8109	034524	032737	020000	001342	270\$:	BR	400\$
8110	034532	001466				BIT	#PIP,RMD5I
8111	034534	012737	000007	001400		BEQ	410\$
8112	034542	112737	000000	001535		MOV	#RECAL!GO,RMCS10
8113	034550	112737	000200	001536		MOV	#RMCS1,PUTINX
8114	034556	004737	037766			MOV	#200,PUTINX+1
8115	034562	000410			JSR	PC,PUT	;GO ISSUE RECALIBRATE
8116	034564	000401			BR	300\$	;NO ERROR
8117	034566	000000			BR	290\$	
8118	034570	062716	000004		280\$:	.WORD	;ERROR IN REGISTER TRANSFER
8119	034574	113776	034566	000000	290\$:	ADD	#4,(SP)
8120	034602	000436				MOV	280\$,a(SP)
8121	034604	004737	037432			BR	400\$
8122	034610	004737	040326		300\$:	JSR	PC,GETSTS
8123						JSR	PC,TIMOUT
8124							;WAIT FOR COMPLETION
8125					;*****		
8126	034614	032737	000010	034712	;VERIFY RECALIBRATE IF BIT 3 SET IN TASK		
					BIT	#BIT3,500\$	;VERIFY RECALIBRATE??

8127	034622	001432			BEQ	410\$		:NO:!
8128	034624	004737	037516		JSR	PC,GET		:GO GET STATUS
8129	034630	000410			BR	330\$		:NO ERROR GETTING STATUS
8130	034632	000401			BR	320\$		
8131	034634	000000			310\$:	.WORD		:ERROR FROM GET
8132	034636	062716	000004		320\$:	ADD #4,(SP)		:TRANSFER ERROR TO USER
8133	034642	113776	034634	000000	MOVB	310\$,2(SP)		
8134	034650	000413			BR	400\$		
8135	034652	004737	050452		330\$:	JSR PC,RCLSTS		:GO CHECK RECALIBRATE
8136	034656	000414			BR	410\$		:NO ERROR DURING RECALIBRATE
8137	034660	000401			BR	350\$		
8138	034662	000000			340\$:	.WORD		:ERROR DURING RECALIBRATE
8139	034664	005726			350\$:	TST (SP)+		:STRIP RETURN TO SUB AND
8140	034666	062716	000004		ADD	#4,(SP)		:TRANSFER ERROR TO USER
8141	034672	113776	034662	000000	MOVB	340\$,2(SP)		
8142	034700	162716	000002		400\$:	SUB #2,(SP)		:MOVE SP BACK BEFORE ERROR
8143	034704	000240			NOP			
8144	034706	000240			NOP			
8145	034710	000207			410\$:	RTS PC		:RETURN TO USER
8146								
8147	034712	000000			500\$:	.WORD		:TASK/VERIFY DESCRIPTOR

```
8148 .SBTTL BAD SECTOR MODULE
8149
8150 ;THE BAD SECTOR MODULE PERFORMS TWO MAJOR FUNCTIONS, I.E.,
8151 ;RECOVER THE BAD SECTOR FILE FROM THE LAST TRACK, AND,
8152 ;APPROVE THE USAGE OF A SECTOR BASED ON INFORMATION IN
8153 ;THE BAD SECTOR FILE OR ASSIGN A NEW SECTOR IF THE ONE ELECTED IS
8154 ;NOT AVAILABLE FOR USE.
8155
8156 ;INFORMATION REQUIRED BY THE MODULE INCLUDES
8157 ;.RMDCO, THE DESIRED CYLINDER,
8158 ;.RMDAO, THE TRACK AND SECTOR ADDRESS,
8159 ;.RMWCO, THE WORD COUNT,
8160 ;.RMCS10, THE COMMAND.
8161
8162 ;MODULE CALL IS AS FOLLOWS,
8163
8164 JSR PC,BADSCT
8165 BR ??? ;RETURN HERE IF NO ERROR
8166 TYPE ,MESSAGE ;RETURN HERE IF THE BAD SECTOR FILE
8167 ;CANNOT BE RECOVERED
8168 ERROR THE MODULE DEFINES THE ERROR NUMBER
8169
8170 ;THE MODULE IS INTENDED TO BE CALLED PRIOR TO CALLING THE BUFFER
8171 ;GENERATOR SUBROUTINE, AND PRESERVES THE 'PUT BUFFER' SO THAT THE
8172 ;BUFFER NEED ONLY BE FILLED ONCE FOR THE EXECUTION OF A FORMAT
8173 ;OPERATION.
8174
8175 ;THE MODULE RETURNS TO THE CALLING TEST WITH THE APPROVED OR ASSIGNED
8176 ;SECTOR IN THE PUT BUFFER AND ALSO IN LOCATIONS 'ASNDA' AND 'ASNDC'
8177 ;SO THAT A REFERENCE IS AVAILABLE TO THE TEST OUTSIDE OF THE PUT BUFFER.
8178
8179
8180 034714 BADSCT:
8181
8182 ;TEST 'MEDIA ENABLE' TO DETERMINE WHETHER OR NOT THE BAD SECTOR FILES
8183 ;HAVE BEEN RECOVERED.
8184 034714 005737 001474 TST MEDENB
8185 034720 001402 BEQ 10$
8186 034722 000137 036140 JMP 300$ ;BAD SECTOR FILE IS AVAILABLE
8187
8188 ;*****
8189 ;RECOVER THE BAD SECTOR FILE FROM THE LAST TRACK
8190 034726 10$:
8191
8192 ;SAVE THE USER'S PUT BUFFER
8193 034726 010046 MOV R0,-(SP) ;;PUSH R0 ON STACK
8194 034730 005000 CLR R0
8195 034732 016060 001400 103564 20$: MOV PUTBUF(R0),BUFFER(R0)
8196 034740 062700 000002 ADD #2,R0 ;ADVANCE TO NEXT BUFFER POSITION
8197 034744 022700 000046 CMP #46,R0 ;END OF BUFFER
8198 034750 103370 BHIS 20$ ;NO !!
8199
8200 ;SET RETRY COUNT AND LOAD PUT BUFFER AND REGISTER INDEX TABLE
8201 034752 012737 000003 036606 MOV #3,500$ ;RETRY COUNT
8202 034760 012737 002000 001406 MOV #002000,RMDAO ;STARTING SECTOR ADDRESS
8203 034766 012737 001466 001434 MOV #822.,RMDCO ;DESIRED CYLINDER
```

```

8204 034774 012737 177376 001402      MOV    #<^C258.+1>,RMWCO      ;WORD COUNT
8205 035002 012737 010000 001432      MOV    #FMT16,RMOFO      ;16 BIT FORMAT
8206 035010 012737 101544 001404      MOV    #MFGFIL,RMBAO     ;BUFFER ADDRESS
8207
8208 035016 012700 001535      MOV    #PUTINX,RO        ;RO POINTS TO REGISTER INDEX TABLE
8209 035022 112720 000006      MOVB   #RMDA,(RO)+
8210 035026 112720 000034      MOVB   #RMDC,(RO)+
8211 035032 112720 000002      MOVB   #RMWC,(RO)+
8212 035036 112720 000032      MOVB   #RMOF,(RO)+
8213 035042 112720 000004      MOVB   #RMBA,(RO)+
8214 035046 112720 000000      MOVB   #RMCS1,(RO)+
8215 035052 112720 000200      MOVB   #200,(RO)+
8216 035056 012600      MOV    (SP)+,RO          ;;POP STACK INTO RO
8217
8218      ;SET GET INDEX TABLE FOR READING STATUS
8219 035060 004737 037432      JSR     PC,GETSTS        ;SETUP GET INDEX REGISTER FOR STATUS
8220 035064      30$:
8221
8222      ;CLEAR THE DEVICE USING DRIVE CLEAR COMMAND
8223 035064 012737 000011 001400      MOV    #DRVCLR!GO,RMCS10    ;LOAD COMMAND IN PUT BUFFER
8224 035072 004737 037766      JSR     PC,PUT           ;OUTPUT COMMAND
8225 035076 000411      BR      45$            ;RETURN HERE IF NO ERROR
8226 035100 000401      BR      40$            ;GET AROUND ERROR #
8227 035102 000000      35$: .WORD            ;ERROR # GOES HERE
8228
8229 035104 062716 000006      40$: ADD    #6,(SP)        ;MOVE SP TO USERS ERROR CALL
8230 035110 113776 035102 000000      MOVB   35$,a(SP)        ;MOVE ERROR NUMBER TO USER
8231 035116 000137 035616      JMP     215$
8232 035122 004737 037516      45$: JSR     PC,GET           ;GO GET STATUS
8233 035126 000411      BR      60$            ;RETURN HERE IF NO ERROR
8234 035130 000401      BR      55$            ;GET AROUND ERROR #
8235 035132 000000      50$: .WORD            ;ERROR # GOES HERE
8236
8237 035134 062716 000006      55$: ADD    #6,(SP)        ;MOVE SP TO USERS ERROR CALL
8238 035140 113776 035132 000000      MOVB   50$,a(SP)        ;MOVE ERROR # TO USERS ERROR CALL
8239 035146 000137 035616      JMP     215$
8240
8241 035152 004737 052214      60$: JSR     PC,DRVSTS        ;GO VERIFY DRIVE CLEAR COMMAND
8242 035156 000412      BR      75$            ;RETURN HERE IF NO ERROR
8243 035160 000401      BR      70$            ;GET AROUND ERROR
8244 035162 000000      65$: .WORD            ;ERROR # GOES HERE
8245
8246 035164 005726      70$: TST     (SP)+          ;STRIP RETURN TO SUBROUTINE
8247 035166 062716 000006      ADD    #6,(SP)        ;MOVE SP TO USERS ERROR CALL
8248 035172 113776 035162 000000      MOVB   65$,a(SP)        ;MOVE ERROR # TO USER CALL
8249 035200 000137 035616      JMP     215$
8250
8251 035204      75$:
8252
8253      ;ISSUE A PACK ACKNOWLEDGE IF VOLUME VALID IS RESET
8254 035204 032737 000100 001342      BIT     #VV,RMDS1        ;IS VV RESET ??
8255 035212 001050      BNE     120$            ;NO !!
8256 035214 012737 000023 001400      MOV    #PACACK!GO,RMCS10    ;LOAD COMMAND
8257 035222 004737 037766      JSR     PC,PUT           ;GO PUT COMMAND TO DRIVE
8258 035226 000411      BR      90$            ;RETURN HERE IF NO OUTPUT ERROR
8259 035230 000401      BR      85$            ;GET AROUND ERROR #

```

```
8260 035232 000000      80$: .WORD          ;ERROR # GOES HERE
8261
8262 035234 062716 000006      85$: ADD #6,(SP)      ;MOVE SP TO USERS ERROR CALL
8263 035240 113776 035232 000000      MOVB 80%,2(SP)    ;MOVE ERROR # TO ERROR CALL
8264 035246 000137 035616      JMP 215$
8265 035252 004737 037516      90$: JSR PC,GET      ;GO GET STATUS FOR PACK ACK
8266 035256 000411      BR 105$      ;RETURN HERE IF NO ERROR
8267 035260 000401      BR 100$      ;GET AROUND ERROR #
8268 035262 000000      95$: .WORD          ;ERROR # GOES HERE
8269
8270 035264 062716 000006      100$: ADD #6,(SP)     ;MOVE SP TO USERS ERROR CALL
8271 035270 113776 035262 000000      MOVB 95%,2(SP)    ;MOVE ERROR # TO CALL
8272 035276 000137 035616      JMP 215$
8273
8274 035302 004737 047656      105$: JSR PC,ACKSTS    ;GO VERIFY ACKNOWLEDGE STATUS
8275 035306 000412      BR 120$      ;RETURN HERE IF NO ERROR
8276 035310 000401      BR 115$      ;GET AROUND ERROR #
8277 035312 000000      110$: .WORD          ;ERROR # GOES HERE
8278
8279 035314 005726      115$: TST (SP)+      ;STRIP RETURN TO SUBROUTINE
8280 035316 062716 000006      ADD #6,(SP)     ;MOVE SP TO USERS ERROR CALL
8281 035322 113776 035312 000000      MOVB 110%,2(SP)    ;MOVE ERROR # TO USERS ERROR CALL
8282 035330 000137 035616      JMP 215$
8283
8284 035334      120$:
8285
8286      ;RECALIBRATE THE DRIVE IF PIP IS SET
8287 035334 032737 020000 001342      BIT #PIP,RMDS1    ;IS PIP SET ??
8288 035342 001452      BEQ 165$      ;NO !!
8289
8290 035344 012737 000007 001400      MOV #RECAL!GO,RMCS10    ;LOAD RECALIBRATE COMMAND
8291 035352 004737 037766      JSR PC,PUT      ;PUT THE RECAL COMMAND
8292 035356 000411      BR 135$      ;RETURN HERE IF NO ERROR
8293 035360 000401      BR 130$      ;GET AROUND ERROR #
8294 035362 000000      125$: .WORD          ;ERROR # GOES HERE
8295
8296 035364 062716 000006      130$: ADD #6,(SP)     ;MOVE SP TO USERS ERROR CALL
8297 035370 113776 035362 000000      MOVB 125%,2(SP)    ;MOVE ERROR # TO USERS CALL
8298 035376 000137 035616      JMP 215$
8299 035402
8300 035402 004737 040326      135$: JSR PC,TIMOUT    ;WAIT FOR RECALIBRATE TO COMPLETE
8301 035406 004737 037516      JSR PC,GET      ;GO GET RECAL STATUS
8302 035412 000411      BR 150$      ;RETURN HERE IF NO ERROR
8303 035414 000401      BR 145$      ;GET AROUND ERROR #
8304 035416 000000      140$: .WORD          ;ERROR # GOES HERE
8305
8306 035420 062716 000006      145$: ADD #6,(SP)     ;MOVE SP TO USERS ERROR CALL
8307 035424 113776 035416 000000      MOVB 140%,2(SP)    ;MOVE ERROR TO USERS CALL
8308 035432 000137 035616      JMP 215$
8309
8310 035436 004737 050452      150$: JSR PC,RCLSTS    ;GO VERIFY RECALIBRATE STATUS
8311 035442 000412      BR 165$      ;RETURN HERE IF NO ERROR
8312 035444 000401      BR 160$      ;GET AROUND ERROR #
8313 035446 000000      155$: .WORD          ;ERROR # GOES HERE
8314
8315 035450 005726      160$: TST (SP)+      ;STRIP RETURN TO SUBROUTINE
```



```
8316 035452 062716 000006          ADD    #6,(SP)          ;MOVE SP TO USERS ERROR CALL
8317 035456 113776 035446 000000    MOV    155$,2(SP)        ;MOVE ERROR # TO USERS CALL
8318 035464 000137 035616          JMP    215$
8319
8320 035470          165$:
8321
8322          ;READ THE SECTOR IDENTIFIED BY RMDAO, INCLUDING HEADER AND DATA
8323
8324 035470 012737 000073 001400    MOV    #RH!GO,RMCS10    ;LOAD READ HEADER AND DATA COMMAND
8325 035476 004737 037766          JSR    PC,PUT          ;PUT COMMAND
8326 035502 000411          BR      180$          ;RETURN HERE IF NO ERROR
8327 035504 000401          BR      175$          ;GET AROUND ERROR #
8328 035506 000000          170$: .WORD          ;ERROR # GOES HERE
8329
8330 035510 062716 000006          175$: ADD    #6,(SP)          ;MOVE SP TO USERS ERROR CALL
8331 035514 113776 035506 000000    MOV    170$,2(SP)        ;MOVE ERROR # TO USERS ERROR CALL
8332 035522 000137 035616          JMP    215$
8333
8334 035526 004737 040326          180$: JSR    PC,TIMOUT        ;WAIT FOR READ OPERATION TO COMPLETE
8335 035532 004737 037516          JSR    PC,GET          ;GO GET STATUS FOR READ OPERATION
8336 035536 000411          BR      195$          ;RETURN HERE IF NO ERROR
8337 035540 000401          BR      190$          ;GET AROUND ERROR #
8338 035542 000000          185$: .WORD          ;ERROR # GOES HERE
8339
8340 035544 062716 000006          190$: ADD    #6,(SP)          ;MOVE SP TO USERS ERROR CALL
8341 035550 113776 035542 000000    MOV    185$,2(SP)        ;MOVE ERROR # TO CALL
8342 035556 000137 035616          JMP    215$
8343
8344 035562 004737 053016          195$: JSR    PC,DASTS        ;GO VERIFY RESULTS OF READ OPERATION
8345 035566 000412          BR      210$          ;RETURN HERE IF NO ERROR
8346 035570 000401          BR      205$          ;GET AROUND ERROR #
8347 035572 000000          200$: .WORD          ;ERROR # GOES HERE
8348
8349 035574 005726          205$: TST    (SP)+          ;STRIP RETURN ADDRESS TO SUBROUTINE
8350 035576 062716 000006          ADD    #6,(SP)          ;MOVE SP TO USERS ERROR CALL
8351 035602 113776 035572 000000    MOV    200$,2(SP)        ;MOVE ERROR # TO USERS CALL
8352 035610 000137 035616          JMP    215$
8353
8354 035614 000456          210$: BR      240$
8355
8356 035616          215$:
8357
8358          ;AN ERROR HAS BEEN DETECTED IN TRYING TO READ THE BAD SECTOR FILE.
8359          ;THE SECTOR WILL BE RETRIED IF POSSIBLE.
8360
8361 035616 032737 010000 001342          BIT    #MOL,RMDS1        ;IS MEDIUM ON LINE ??
8362 035624 001446          BEQ    230$          ;YES !!
8363
8364 035626 005337 036606          DEC    500$          ;DECREMENT RETRY COUNT
8365 035632 100037          RPL    225$          ;RETRY IF COUNT NOT NEG
8366
8367          ;THE RETRY COUNT HAS EXPIRED - SEE IF THE ERROR IS MEDIA RELATED
8368 035634 013746 001344          MOV    RMER11,-(SP)        ;GET ER1
8369 035640 042716 100720          BIC    #DCK!HCRC!HCE!FER!ECH,(SP)
8370 035644 032737 000010 001372          BIT    #DPE,RMER21        ;WAS THER A DATA PARITY ERROR ??
8371 035652 001402          BEQ    220$          ;NO !!
```

```

8372 035654 042716 000010
8373 035660 005726
8374 035662 001027
8375 035664 013746 001372
8376 035670 042726 100010
8377 035674 001022
8378
8379
8380
8381
8382
8383 035676 062737 000002 001406
8384 035704 122737 000012 001406
8385 035712 001413
8386 035714 122737 000040 001406
8387 035722 001407
8388 035724 012737 000003 036606
8389 035732 162716 000006
8390 035736 000137 035064
8391
8392 035742
8393
8394
8395 035742 162716 000004
8396 035746 000137 036602
8397
8398 035752
8399
8400
8401
8402
8403
8404 035752 122737 000011 001406
8405 035760 103451
8406
8407
8408
8409 035762 032737 140000 101544
8410 035770 001410
8411
8412 035772 012737 002012 001406
8413 036000 012737 000003 036606
8414 036006 000137 035064
8415 036012
8416
8417
8418 036012 010046
8419 036014 010146
8420 036016 012701 000374
8421 036022 012700 000014
8422 036026 012760 177777 101544
8423 036034 012760 177777 102554
8424 036042 062700 000002
8425 036046 005301
8426 036050 001366
8427 036052 012701 000006

      BIC      #PAR,(SP)      ;YES - CLEAR PAR
220$:  TST      (SP)+         ;ARE THERE ANY ERRORS NOT DUE TO MEDIA ?
      BNE      230$          ;YES !!
      MOV      RMER21,-(SP)    ;GET ER2
      BIC      #BSE!DPE,(SP)+ ;CLEAR MEDIA ERRORS
      BNE      230$          ;BRANCH IF NONMEDIA ERRORS DETECTED

;THE ERRORS DETECTED WHILE TRYING TO RECOVER THE BAD SECTOR FILE ARE
;DUE TO THE MEDIA. SEE IF THE BAD SECTOR FILE CAN BE RECOVERED FROM
;ANOTHER AREA ON THE LAST TRACK

      ADD      #2,RMDAO        ;ADVANCE SECTOR ADDRESS
      CMPB     #10.,RMDAO      ;QUIT IF ALL MFG SECTORS HAVE BEEN
      BEQ      230$          ;TRIED
      CMPB     #32.,RMDAO      ;QUIT IF ALL USER SECTORS HAVE
      BEQ      230$          ;BEEN TRIED
      MOV      #3,500$        ;REINSTATE RETRY COUNT FOR THIS SECTOR
225$:  SUB      #6,(SP)        ;MOVE SP BACK TO NO ERROR
      JMP      30$           ;RETRY THE READ OPERATION

230$:

;THE BAD SECTOR FILE CANNOT BE READ
      SUB      #4,(SP)        ;MOVE SP TO ERROR RETURN
      JMP      410$          ;GO TO MODULE EXIT

240$:

;THE SECTOR WAS RECOVERED WITHOUT ERROR -
; READ THE USER FILE IF THIS IS THE MFG FILE
; OR ELSE DONE

      CMPB     #9.,RMDAO      ;WAS THE USER FILE READ ??
      BLO      260$          ;YES - READ IS COMPLETE

;IF 144 IS IMPLEMENTED THEN READ THE USER FILE -
; ELSE DUMMY THE BAD SECTOR FILE
      BIT      #MSE!USE,MFGFIL ;ARE THE BAD SECTOR FLAGS OFF ??
      BEQ      250$          ;YES - 144 IS DISABLED

      MOV      #002012,RMDAO   ;READ THE USER FILE
      MOV      #3,500$        ;RELOAD THE RETRY COUNT FOR THIS SECTOR
      JMP      30$           ;GO READ THE USER FILE

250$:

;DUMMY THE BAD SECTOR FILES
      MOV      R0,-(SP)        ;;PUSH R0 ON STACK
      MOV      R1,-(SP)        ;;PUSH R1 ON STACK
      MOV      #252.,R1        ;R1 = NUMBER OF ENTRIES IN FILES
      MOV      #14,R0          ;R0 = ADDRESS INDEX TO FILE STORAGE
255$:  MOV      #-1,MFGFIL(R0) ;ENTER ALL ONES IN MFG FILE
      MOV      #-1,USRFIL(R0) ;ENTER ALL ONES IN USER FILE
      ADD      #2,R0          ;ADVANCE ADDRESS
      DEC      R1             ;DECREMENT COUNT
      BNE      255$          ;CONTINUE IF NOT DONE
      MOV      #6.,R1        ;CLEAR ID, SERIAL NUMBER ETC

```


8428	036056	005000				CLR	R0	
8429	036060	005060	101544		256\$:	CLR	MFGFIL(R0)	
8430	036064	005060	102554			CLR	USRFIL(R0)	
8431	036070	062700	000002			ADD	#2,R0	
8432	036074	005301				DEC	R1	
8433	036076	001370				BNE	256\$	
8434								
8435	036100	012601				MOV	(SP)+,R1	::POP STACK INTO R1
8436	036102	012600				MOV	(SP)+,R0	::POP STACK INTO R0
8437	036104				260\$:			
8438								
8439								;SET MEDIA ENABLE AND RESTORE THE USERS PUT BUFFER
8440	036104	012737	177777	001474		MOV	#-1,MEDENB	
8441								
8442	036112	010046				MOV	R0,-(SP)	::PUSH R0 ON STACK
8443	036114	005000				CLR	R0	::R0 IS REGISTER INDEX
8444	036116	016060	103564	001400	265\$:	MOV	BUFFER(R0),PUTBUF(R0)	
8445	036124	062700	100100			ADD	#2,R0	::ADVANCE R0
8446	036130	022700	100100			CMP	#46,R0	::DONE ??
8447	036134	103300				BHIS	265\$	
8448								
8449	036136	012600				MOV	(SP)+,R0	::POP STACK INTO R0
8450	036140				270\$:			
8451								
8452	036140				300\$:			
8453								
8454								::*****
8455								;VERIFY THAT THE DESIRED SECTOR IS NOT IN THE MFG BAD SECTOR FILE
8456								;AND NOT IN THE USERS BAD SECTOR FILE. ASSIGN A NEW SECTOR IF THE
8457								;SECTOR IS IN EITHER FILE.
8458								
8459								;LOAD INITIAL VARIABLES AND COMPUTE THE NUMBER OF SECTORS
8460	036140	010046				MOV	R0,-(SP)	::PUSH R0 ON STACK
8461	036142	010146				MOV	R1,-(SP)	::PUSH R1 ON STACK
8462	036144	010246				MOV	R2,-(SP)	::PUSH R2 ON STACK
8463	036146	013737	001434	001476		MOV	RMDCO,ASNDC	::LOAD REQUESTED CYLINDER, TRACK,
8464	036154	013737	001406	001500		MOV	RMDAO,ASNDA	::AND SECTOR ADDRESS IN ASSIGNED STORAGE
8465	036162	005002				CLR	R2	::R2 = NUMBER OF SECTORS
8466	036164	013700	001402			MOV	RMWCO,R0	::R0 = WORD COUNT
8467	036170	005300				DEC	R0	::CONVERT FROM 2'S COMPLEMENT
8468	036172	005100				COM	R0	
8469	036174	012701	000400			MOV	#256,R1	::R1 = NUMBER OF WORDS PER SECTOR
8470	036200	032737	000002	001400		BIT	#BIT1,RMCS10	::IS THIS A HEADER AND DATA COMMAND ??
8471	036206	001402				BEQ	305\$	::NO !!
8472	036210	012701	000402			MOV	#258,R1	::CHANGE WORDS PER SECTOR
8473	036214	020100			305\$:	CMP	R1,R0	::IS THERE A FULL SECTOR ??
8474	036216	101404				BLOS	310\$	::YES !!
8475	036220	005700				TST	R0	::IS R0 ZERO ??
8476	036222	001405				BEQ	315\$	::YES !!
8477	036224	005202				INC	R2	::INCREMENT FOR PARTIAL SECTOR
8478	036226	000403				BR	315\$	
8479	036230	160100			310\$:	SUB	R1,R0	::SUBTRACT ONE SECTOR FROM WORD COUNT
8480	036232	005202				INC	R2	::INCREMENT SECTOR COUNT
8481	036234	000767				BR	305\$	
8482	036236	010237	036606		315\$:	MOV	R2,500\$	::SAVE SECTOR COUNT
8483								

```

8484 036242 316$:
8485
8486 ;LOAD PARAMETERS AND SEARCH THE MFG AND USER BAD SECTOR FILES FOR
8487 ;THE ASSIGNED SECTOR AND ADJACENT SECTORS IF THE SECTOR COUNT IS
8488 ;MORE THAN ONE.
8489
8490 036242 012737 101560 036616 MOV #MFGFIL+14,540$ ;MOVE THE STARTING ADDRESS OF MFG
8491 ;FILE TO BASE ADDRESS STORAGE
8492 036250 013737 001476 036612 320$: MOV ASNDC,520$ ;LOAD COMPARING CYLINDER ADDRESS
8493 036256 013737 001500 036614 MOV ASNDA,530$ ;LOAD COMPARING TRACK, SECTOR ADDRESS
8494 036264 013737 036606 036610 MOV 500$,510$ ;LOAD NUMBER OF SECTORS TO CONFIRM
8495
8496 ;SETUP FOR A BINARY SEARCH OF THE CURRENT FILE FOR THE COMPARING
8497 ;CYLINDER, TRACK AND SECTOR ADDRESS
8498 036272 013700 036616 325$: MOV 540$,R0 ;LOAD THE BASE ADDRESS IN R0
8499 036276 012701 000376 MOV #<<127.*4>/2>,R1 ;R1 = LENGTH OF FILE
8500 036302 060100 ADD R1,R0 ;START BINARY DIVIDE AT CENTER
8501 036304 021037 036612 330$: CMP (R0),520$ ;DOES TABLE ENTRY = COMPARING CYLINDER ?
8502 036310 001405 BEQ 345$ ;YES !!
8503 036312 101002 BHI 340$ ;BRANCH IF ENTRY > COMPARING CYLINDER
8504 036314 335$:
8505
8506 ;FILE ENTRY IS LESS THAN COMPARING CYLINDER (OR TRACK AND SECTOR),
8507 ;SO ADD DISPLACEMENT TO CURRENT POSITION
8508 036314 060100 ADD R1,R0
8509 036316 000410 BR 350$
8510 036320 340$:
8511
8512 ;FILE ENTRY IS GREATER THAN COMPARING CYLINDER SO SUBTRACT DISPLACEMENT
8513 ;FROM CURRENT POSITION
8514 036320 160100 SUB R1,R0
8515 036322 000406 BR 350$
8516 036324 345$:
8517
8518 ;FILE ENTRY EQUALS COMPARING CYLINDER. SEE IF THE NEXT ENTRY EQUALS
8519 ;THE COMPARING TRACK, AND SECTOR.
8520 036324 026037 000002 036614 CMP 2(R0),530$ ;ARE THEY EQUAL ??
8521 036332 001413 BEQ 360$ ;YES !!
8522 036334 101371 BHI 340$ ;BRANCH IF HIGHER
8523 036336 000766 BR 335$ ;BRANCH IF LOWER
8524 036340 350$:
8525
8526 ;THE POINTER (R0) HAS BEEN ADJUSTED. HALVE THE DISPLACEMENT AND
8527 ;CONTINUE THE SEARCH IF DISPLACEMENT NOT ZERO
8528 036340 005701 TST R1 ;IS DISPLACEMENT ZERO ??
8529 036342 001440 BEQ 370$ ;YES !!
8530 036344 006201 ASR R1 ;HALVE THE DISPLACEMENT
8531 036346 042701 000003 BIC #3,R1
8532 036352 020037 036616 CMP R0,540$ ;IS THE NEW POINTER WITHIN BOUNDS ??
8533 036356 103432 BLO 370$ ;NO !!
8534 036360 000751 BR 330$ ;CONTINUE SEARCH
8535 036362 360$:
8536
8537 ;THE COMPARING CYLINDER, TRACK AND SECTOR IS IN THE BAD SECTOR FILE.
8538 ;ADVANCE THE ASSIGNED SECTOR AND START THE SEARCH ALL OVER.
8539 036362 105237 001500 INCB ASNDA ;INCREMENT SECTOR

```

```
8540 036366 122737 000037 001500      CMPB    #31.,ASNDA      ;SECTOR OK ??
8541 036374 103022                BHIS    365$           ;YES !!
8542 036376 105037 001500      CLRB    ASNDA           ;CLEAR SECTOR AND ADVANCE TRACK
8543 036402 105237 001501      INCB    AS'DA+1
8544 036406 122737 000004 001501      CMPB    #4.,ASNDA+1      ;TRACK OK ??
8545 036414 103012                BHIS    365$           ;YES !!
8546 036416 005037 001500      CLR     ASNDA           ;CLEAR TRACK AND SECTOR
8547 036422 005237 001476      INC     ASNDC          ;INCREMENT CYLINDER
8548 036426 022737 001466 001476      CMP     #822.,ASNDC      ;CYLINDER OK ??
8549 036434 103002                BHIS    365$           ;YES !!
8550 036436 005037 001476      CLR     ASNDC
8551 036442 000677                365$: BR      316$      ;REPEAT SEARCH
8552
8553 036444                370$:
8554
8555      ;THE COMPARING SECTOR IS NOT IN THE BAD SECTOR FILES. DECREMENT THE
8556      ;NUMBER OF SECTORS TO COMPARE AND SEARCH THE NEXT SECTOR IF THE NUMBER
8557      ;IS NOT ZERO.
8558
8559 036444 005337 036610      DEC     510$           ;DECREMENT NUMBER OF SECTORS TO COMPARE
8560 036450 001432                BEQ     380$           ;DONE IF ZERO
8561 036452 105237 036614      INCB    530$           ;INCREMENT THE COMPARING SECTOR
8562 036456 122737 000037 036614      CMPB    #31.,530$      ;SECTOR OK ??
8563 036464 103022                BHIS    375$           ;YES !!
8564 036466 105037 036614      CLRB    530$           ;CLEAR SECTOR
8565 036472 105237 036615      INCB    530$+1          ;INCREMENT TRACK
8566 036476 122737 000004 036615      CMPB    #4,530$+1      ;TRACK OK ??
8567 036504 103012                BHIS    375$           ;YES !!
8568 036506 005037 036614      CLR     530$           ;CLEAR SECTOR TRACK
8569 036512 005237 036612      INC     520$           ;INCREMENT CYLINDER
8570 036516 022737 001466 036612      CMP     #822.,520$      ;CYLINDER OK ??
8571 036524 103002                BHIS    375$           ;YES !!
8572 036526 005037 036612      CLR     520$           ;CLEAR CYLINDER
8573 036532 000137 036272      375$: JMP     325$      ;SEARCH NEXT SECTOR
8574
8575 036536                380$:
8576
8577      ;THE ASSIGNED SECTOR (AND REQUIRED ADJACENT SECTORS) ARE NOT IN
8578      ;THE BAD SECTOR FILE JUST SEARCHED. SEARCH THE USER FILE IF IT
8579      ;HAS NOT YET BEEN SEARCHED, ELSE ASSIGN THE SECTOR AND RETURN TO USER.
8580
8581 036536 022737 102570 036616      CMP     #USRFIL+14,540$ ;TEST BASE ADDRESS
8582 036544 001405                BEQ     400$           ;DONE IF BASE = USER
8583 036546 012737 102570 036616      MOV     #USRFIL+14,540$ ;LOAD BASE ADDRESS
8584 036554 000137 036250      390$: JMP     320$      ;SEARCH USER FILE
8585
8586
8587 036560                400$:
8588
8589      ;ASSIGN THE SECTOR AND RETURN TO USER
8590 036560 013737 001476 001434      MOV     ASNDC,RMDCO      ;LOAD CYLINDER
8591 036566 013737 001500 001406      MOV     ASNDA,RMDAO      ;LOAD TRACK AND SECTOR
8592 036574 012602                MOV     (SP)+,R2      ;;POP STACK INTO R2
8593 036576 012601                MOV     (SP)+,R1      ;;POP STACK INTO R1
8594 036600 012600                MOV     (SP)+,R0      ;;POP STACK INTO R0
8595 036602 000240      410$: NOP
```

CZRMDCO RM03/2 FCTNL TST 2
CZRMDC.P11 12-DEC-78 08:24

MACY11 30A(1052) 04-JAN-79 11:23 PAGE 171
BAD SECTOR MODULE

C 14

SEQ 0171

8596 036604 000207

RTS PC

8597

8598

8599

,THE FOLLOWING ARE STORAGE LOCATIONS FOR THE MODULE

8600 036606 000000

500\$: .WORD ;RETRY COUNT/ NUMBER OF SECTORS REQUIRED

8601 036610 000000

510\$: .WORD ;NUMBER OF SECTORS TO COMPARE

8602 036612 000000

520\$: .WORD ;COMPARING CYLINDER

8603 036614 000000

530\$: .WORD ;COMPARING TRACK AND SECTOR

8604 036616 000000

540\$: .WORD ;BASE ADDRESS OF BAD SECTOR FILE BEING SEARCHED

```
8605 .SBTTL BUFFER GENERATOR SUBROUTINE
8606
8607 ; THIS SUBROUTINE GENERATES A DATA BUFFER FOR WRITE COMMANDS. THE
8608 ; BUFFER STARTS AT RMBA AND IS RMWC WORDS LONG. THE BUFFER
8609 ; CONTAINS A REPETITIVE DATA PATTERN CONSISTING OF $TMP1 WORDS
8610 ; FROM THE DATA PATTERN TABLE, BEGINNING AT ADDRESS $TMP0.
8611 ; HEADER INFORMATION FOR THE BUFFER IS EXTRACTED FROM RMDC,
8612 ; RMDA AND RMOF.
8613
8614 ;CALL:
8615 ;(1) JSR PC,GENBUF
8616 ;(2) ?? RETURN HERE
8617
8618 GENBUF:
8619 036620 010046 MOV R0,-(SP) ;;PUSH R0 ON STACK
8620 036622 010146 MOV R1,-(SP) ;;PUSH R1 ON STACK
8621 036624 010246 MOV R2,-(SP) ;;PUSH R2 ON STACK
8622 036626 010346 MOV R3,-(SP) ;;PUSH R3 ON STACK
8623 036630 010446 MOV R4,-(SP) ;;PUSH R4 ON STACK
8624 036632 013700 001404 MOV RMBAO,R0 ;LOAD DATA BUFFER ADDRESS
8625 036636 013701 001402 MOV RMWCO,R1 ;LOAD WORD COUNT
8626 036642 013737 001434 037060 MOV RMDCO,60$ ;LOAD STARTING CYLINDER ADDRESS
8627 036650 013737 001406 037062 MOV RMDAO,65$ ;LOAD STARTING TRACK,SECTOR ADDRESS
8628 036656 032737 000002 001400 10$: BIT #BIT1,RMCS10 ;WRITE HEADER & DATA??
8629 036664 001450 BEQ 25$ ;NO!!
8630 036666 013710 037060 MOV 60$,(R0) ;WRITE HEADER WORD #1
8631 036672 042710 176000 BIC #^CCYLMSK,(R0)
8632 036676 052710 140000 BIS #MSE!USE,(R0) ;SET (DISABLE) BAD SECTOR FLAGS
8633 036702 012702 000035 MOV #29,,R2 ;R2 = MAXIMUM SECTOR ADDRESS
8634 036706 032737 010000 001432 BIT #FMT16,RMOFO ;16 BIT FORMAT??
8635 036714 001404 BEQ 15$ ;NO!!
8636 036716 052710 010000 BIS #FMT16,(R0) ;SET FORMAT BIT IN HEADER
8637 036722 012702 000037 MOV #31,,R2 ;CHANGE MAXIMUM SECTOR ADDRESS
8638 036726 005201 15$: INC R1 ;INCREMENT WORD COUNT
8639 036730 001444 BEQ 50$ ;EXIT IF DONE
8640 036732 062700 000002 ADD #2,R0 ;MOVE R0 TO HEADER WORD #2
8641 036736 013720 037062 MOV 65$,(R0)+ ;WRITE HEADER WORD #2
8642 036742 005201 INC R1 ;INCREMENT WORD COUNT AND
8643 036744 001436 BEQ 50$ ;EXIT IF DONE
8644 036746 012703 037062 MOV #65$,R3 ;ADVANCE SECTOR ADDRESS
8645 036752 105213 INCB (R3)
8646 036754 120213 CMPB R2,(R3) ;SECTOR OVERFLOW ??
8647 036756 103013 BHIS 25$ ;NO !!
8648 036760 105013 CLRB (R3) ;YES - CLEAR SECTOR ADDRESS
8649 036762 105263 000001 INCB 1(R3) ;ADVANCE TRACK ADDRESS
8650 036766 122763 000004 000001 CMPB #4,1(R3) ;TRACK OVERFLOW ??
8651 036774 103004 BHIS 25$ ;NO !!
8652 036776 105063 000001 CLRB 1(R3) ;YES - CLEAR TRACK ADDRESS
8653 037002 105237 037060 INCB 60$ ;ADVANCE CYLINDER ADDRESS
8654 037006 012704 000400 25$: MOV #256,,R4 ;LOAD SECTOR DATA COUNT
8655 037012 013702 001174 30$: MOV $TMP0,R2 ;LOAD PATTERN ADDRESS
8656 037016 013703 001176 MOV $TMP1,R3 ;LOAD PATTERN COUNT
8657 037022 012220 40$: MOV (R2)+,(R0)+ ;WRITE DATA PATTERN
8658 037024 005201 INC R1 ;INCREMENT WORD COUNT AND
8659 037026 001405 BEQ 50$ ;EXIT IF DONE
8660 037030 005304 DEC R4 ;DECREMENT SECTOR COUNT
```

MACY11 30A(1052) 04-JAN-79 11:23 E 14
BUFFER GENERATOR SUBROUTINE PAGE 173

E 14
PAGE 173

Address	Op-Code	Op-Code Hex	Op-Code Dec	Op-Code Name	Comments
8661	037032	001711	BEQ	10\$	; START NEXT SECTOR IF 0
8662	037034	005303	DEC	R3	; DECREMENT PATTERN COUNT
8663	037036	001765	BEQ	30\$	; RESTART PATTERN IF 0
8664	037040	000770	BR	40\$	; CONTINUE DATA PATTERN
8665					
8666	037042			50\$:	
8667	037042	012604	MOV	(SP)+,R4	; POP STACK INTO R4
8668	037044	012603	MOV	(SP)+,R3	; POP STACK INTO R3
8669	037046	012602	MOV	(SP)+,R2	; POP STACK INTO R2
8670	037050	012601	MOV	(SP)+,R1	; POP STACK INTO R1
8671	037052	012600	MOV	(SP)+,R0	; POP STACK INTO R0
8672	037054	000240	NOP		
8673	037056	000207	RTS	PC	
8674					
8675	037060	000000		60\$:	.WORD ; CYLINDER ADDRESS STORAGE
8676	037062	000000		65\$:	.WORD ; TRACK, SECTOR ADDRESS STORAGE


```
8677 .SBTTL COMPARE BUFFER SUBROUTINE
8678
8679 ;THIS SUBROUTINE COMPARES THE CONTENTS OF BUFONE AND BUFTWO,
8680 ;ASSUMING THAT BUFONE IS THE BUFFER FROM WHICH DATA WAS WRITTEN
8681 ;AND BUFTWO IS THE BUFFER TO WHICH DATA WAS READ. ERRORS IN BUFFER
8682 ;COMPARISON ARE REPORTED TO THE USER VIA THE USER'S ERROR CALL.
8683
8684 ;CALL:
8685 ;(1) JSR PC,CMPBUF
8686 ;(2) .WORD WRITE BUFFER ADDRESS
8687 ; .WORD READ BUFFER ADDRESS
8688 ;(3) BR ?? RETURN HERE IF NO ERROR
8689 ;(4) NOP RETURN HERE IF ERROR
8690 ;(5) ERROR ERROR DEFINED BY SUBROUTINE
8691 ;(6) ???
8692
8693 CMPBUF:
8694 037064 010046 MOV R0,-(SP) ;;PUSH R0 ON STACK
8695 037066 010146 MOV R1,-(SP) ;;PUSH R1 ON STACK
8696 037070 010246 MOV R2,-(SP) ;;PUSH R2 ON STACK
8697 037072 010346 MOV R3,-(SP) ;;PUSH R3 ON STACK
8698
8699 037074 005037 037430 CLR 150$ ;CLEAR CORRECTION FLAG
8700 ;DETERMINE IF DATA SHOULD BE CORRECTED
8701 037100 032737 100000 001344 BIT #DCK,RMER11 ;WAS THERE A DATA CHECK ??
8702 037106 001465 BEQ 80$ ;NO !!
8703 037110 032737 000100 001344 BIT #ECH,RMER11 ;IS IT A HARD ERROR ??
8704 037116 001061 BNE 80$ ;YES !!
8705 037120 033737 004000 001362 BIT ECI,RMOF1 ;WAS ECC CORRECTION ALLOWED ??
8706 037126 001055 BNE 80$ ;NO !!
8707 037130 032737 010000 001362 BIT #FMT16,RMOF1 ;IS THIS 16 BIT FORMAT ??
8708 037136 001451 BEQ 80$ ;NO !!
8709
8710 ;CORRECT DATA USING ECC INFORMATION
8711 037140 013700 001404 MOV RMBAO,R0 ;R0 = STARTING BUFFER ADDRESS
8712 037144 013701 001374 MOV RMEC11,R1 ;R1 = ECC POSITION
8713 037150 052737 100000 037430 BIS #BIT15,150$ ;SET CORRECTION FLAG
8714 ;MOVE R0 TO WORD BOUNDARY OF ERROR BURST
8715
8716 037156 022701 000020 10$: CMP #16.,R1 ;IS BIT POSITION > 1 WORD
8717 037162 103005 BHIS 20$ ;NO !!
8718 037164 162701 000020 SUB #16.,R1 ;SUBTRACT 1 WORDS WORTH
8719 037170 062700 000002 ADD #2,R0 ;ADVANCE BUFFER ADDRESS 1 WORD
8720 037174 000770 BR 10$
8721 037176 012702 000001 - 20$: MOV #1,R2 ;R2 = BIT POINTER
8722 037202 010203 MOV R2,R3 ;R3 = BIT NUMBER
8723 ;MOVE R2 TO STARTING BIT OF ERROR BURST
8724
8725 037204 020301 30$: CMP R3,R1 ;IS R3 SAME AS R1 ??
8726 037206 001403 BEQ 35$ ;YES !!
8727 037210 006302 ASL R2 ;SHIFT BIT POINTER
8728 037212 005203 INC R3 ;INCREMENT BIT NUMBER
8729 037214 000773 BR 30$
8730 037216 012703 000013 35$: MOV #11.,R3 ;R3 = LENGTH OF ERROR BURST
8731
8732 ;CORRECT THE ERROR BURST
```

```
8733 037222 030237 001376      40$: BIT R2,RMEC21      ;IS THIS BIT SET IN ECC PATTERN ??
8734 037226 001405              BEQ 60$              ;NO - DO NOT CORRECT THIS BIT
8735 037230 030210              BIT R2,(R0)           ;IS THE BIT PRESENTLY SET ??
8736 037232 001402              BEQ 50$              ;NO
8737 037234 040210              BIC R2,(R0)           ;RESET THE BIT
8738 037236 000401              BR 60$
8739 037240 050210      50$: BIS R2,(R0)              ;SET THE BIT
8740 037242 006302      60$: ASL R2                  ;SHIFT TO NEXT BIT
8741 037244 001004              BNE 70$
8742 037246 012702 000001      MOV #1,R2              ;CONTINUE WITH FIRST BIT OF NEXT WORD
8743 037252 062700 000002      ADD #2,R0
8744 037256 005303      70$: DEC R3                  ;END OF BURST ??
8745 037260 001360              BNE 40$              ;NO !!
8746 037262 017600 000010      80$: MOV @10(SP),R0      ;R0 = WRITE BUFFER
8747 037266 062766 000002 090010      ADD #2,10(SP)    ;MOVE SP TO READ ADDRESS
8748 037274 017601 000010      MOV @10(SP),R1          ;R1 = READ BUFFER
8749 037300 062766 000002 0CJ010      ADD #2,10(SP)    ;MOVE SP TO RETURN ADDRESS
8750 037306 013702 001332      MOV RMWC1,R2           ;R2 = NUMBER OF WORDS TRANSFER
8751 037312 163702 001402      SUB RMWC0,R2
8752 037316 022021      90$: CMP (R0)+,(R1)+          ;COMPARE DATA WORDS
8753 037320 001003              BNE 100$              ;EXIT IF NOT EQUAL
8754 037322 005302              DEC R2                ;DECREMENT WORD COUNT
8755 037324 001374              BNE 90$               ;CONTINUE IF NOT DONE
8756 037326 000433              BR 110$               ;DONE COMPARE - NO ERROR
8757 037330      100$:
8758 037330 014037 001140      MOV -(R0),SGDDAT        ;STORE GOOD DATA FOR TYPEOUT
8759 037334 014137 001142      MOV -(R1),SBDDAT        ;STORE BAD DATA FOR TYPEOUT
8760 037340 010037 001134      MOV R0,SGDADR          ;STORE ADDRESS OF GOOD DATA
8761 037344 010137 001136      MOV R1,SBDADR          ;STORE ADDRESS OF BAD DATA
8762 037350 010237 001174      MOV R2,$TMP0           ;STORE WORD COUNT OF ERROR
8763 037354 062766 000004 000010      ADD #4,10(SP)    ;MOVE SP TO USER'S ERROR CALL
8764 037362 112776 000336 000010      MOVB #336,@10(SP) ;WRITE ERROR NUMBER IN CALL
8765
8766 ;CHANGE ERROR NUMBER IF ECC CORRECTION FAILED
8767 037370 032737 100000 037430      BIT #BIT15,150$   ;WAS ECC CORRECTION USED ??
8768 037376 001403              BEQ 105$              ;NO !!
8769 037400 112776 000163 000010      MOVB #163,@10(SP) ;ECC CORRECTION FAILED
8770 037406 162766 000002 000010      105$: SUB #2,10(SP) ;MOVE SP TO RETURN IF ERROR
8771 037414 000240              NOP
8772      110$:
8773 037416 012603              MOV (SP)+,R3           ;;POP STACK INTO R3
8774 037420 012602              MOV (SP)+,R2           ;;POP STACK INTO R2
8775 037422 012601              MOV (SP)+,R1           ;;POP STACK INTO R1
8776 037424 012600              MOV (SP)+,R0           ;;POP STACK INTO R0
8777 037426 000207              RTS PC                  ;RETURN TO USER
8778
8779 037430 000000      150$: .WORD                      ;ECC CORRECTION FLAG
```



```

8780      .SBTTL  GET STATUS SUBROUTINE
8781      :
8782      :THIS SUBROUTINE SETS UP THE "GET INDEX TABLE" AND THE "GET
8783      :BUFFER" FOR READING ALL SUBSYSTEM REGISTERS VIA THE GET SUBROUTINE
8784      :AND THEN RETURNS TO THE USER.
8785      :
8786      :CALL:  JSR      PC,GETSTS
8787      :      ???
8788      :
8789      GETSTS:
8790      MOV      R0,-(SP)      ;:PUSH R0 ON STACK
8791      MOV      R1,-(SP)      ;:PUSH R1 ON STACK
8792      MOV      R2,-(SP)      ;:PUSH R2 ON STACK
8793      MOV      #GETINX,R0    ;:R0= ADDRESS OF INDEX TABLE
8794      MOV      #RMEC21+2,R1  ;:R1 = ADDRESS OF GET BUFFER
8795      MOV      #RMEC2,R2     ;:R2 = REGISTER INDE
8796      2$:      MOVB      R2,(R0)+ ;:WRITE REGISTER INDEX IN TABLE
8797      CLR      -(R1)         ;:CLEAR CORRESPONDING LOCATION
8798      3$:      SUB      #2,R2   ;:DECREMENT TO NEXT INDEX
8799      BMI      4$           ;:BRANCH OUT IF DONE
8800      CMP      #RMDB,R2      ;:DONT WRITE RMDB INDEX
8801      BNE      2$
8802      CLR      -(R1)
8803      BR       3$
8804      4$:      MOVB      #200,(R0)+ ;:WRITE TERMINATOR
8805      MOV      (SP)+,R2      ;:POP STACK INTO R2
8806      MOV      (SP)+,R1      ;:POP STACK INTO R1
8807      MOV      (SP)+,R0      ;:POP STACK INTO R0
8808      NOP
8809      RTS      PC
8810

```

```
8811 .SBTTL GET SUBROUTINE
8812
8813 ;THIS SUBROUTINE READS THE REGISTERS WHICH ARE LISTED IN THE
8814 ;"GET INDEX TABLE" AND STORES THEIR VALUES IN THE CORRESPONDING
8815 ;LOCATION IN THE "GET REGISTER BUFFER". FOR EXAMPLE, AN
8816 ;ENTRY OF 04 IN THE TABLE WILL CAUSE THE SUBROUTINE TO
8817 ;READ "RMB4" AND STORE ITS CONTENTS AT THE LOCATION IN
8818 ;THE BUFFER ASSIGNED TO THAT REGISTER. THE NUMBER OF
8819 ;REGISTERS TO BE READ IS VARIABLE FROM 1 TO 22; THE INDEX
8820 ;TABLE MUST BE TERMINATED WITH A CONTROL BYTE (200)
8821 ;WHICH SHOULD FOLLOW THE LAST ENTRY.
8822
8823 ;SUBROUTINE CALL:
8824 ;(1) "GET INDEX TABLE" HAS BEEN LOADED WITH REGISTER INDEX
8825 ;VALUES AND TERMINATED WITH A CONTROL BYTE
8826 ;(2) "GET INPUT BUFFER" IS AVAILABLE FOR USE. (NOTE THAT
8827 ;UNUSED LOCATIONS, I.E., ENTRIES IN BUFFER CORRESPONDING
8828 ;TO REGISTERS NOT READ, ARE NOT CHANGED.)
8829 ;(3) JSR PC,GET
8830 ;BR ??? RETURN HERE IF NO ERROR FOUND
8831 ;NOP RETURN HERE IF ANY ERROR FOUND
8832 ;ERROR SUB DEFINES ERROR NUMBER
8833 ;???
8834
8835 GET: NOP
8836 ADD #4,(SP) ;CLEAR ERROR NUMBER IN USER'S
8837 CLRB @ (SP) ;ERROR CALL
8838 SUB #4,(SP)
8839 MOV R0,-(SP) ;;PUSH R0 ON STACK
8840 MOV R1,-(SP) ;;PUSH R1 ON STACK
8841 MOV R2,-(SP) ;;PUSH R2 ON STACK
8842 MOV R3,-(SP) ;;PUSH R3 ON STACK
8843 MOV R4,-(SP) ;;PUSH R4 ON STACK
8844 MOV ERRVEC,-(SP) ;;PUSH ERRVEC ON STACK
8845 MOV ERRVEC+2,-(SP) ;;PUSH ERRVEC+2 ON STACK
8846 MOV $BASE,R0
8847 MOV #GETBUF,R2
8848 MOV #GETINX,R4
8849 MOV #5$,ERRVEC ;SETUP FOR TIMEOUT
8850 MOV #PR6,ERRVEC+2
8851 1$: MOV RMCS2(R0),STMP0 ;GET "NED" STATUS
8852 MOV RMCS1(R0),STMP1 ;GET "DVA" STATUS
8853 BIT #DVA,STMP1 ;DEVICE AVAILABLE??
8854 BNE 3$ ;YES!!
8855 ADD #4,16(SP) ;WRITE ERROR NUMBER IN USER'S
8856 MOVB #112,@16(SP) ;ERROR CALL
8857 BR 7$
8858 3$: TSTB (R4) ;DONE??
8859 BMI 9$ ;YES!!
8860 MOVB (R4),R1 ;R1 = REGISTER ADDRESS
8861 BIC #^C1DXMSK,R1 ;CLEAR ANY SIGN EXTENSION
8862 ADD R0,R1
8863 MOVB (R4)+,R3 ;R3 = STORAGE ADDRESS FOR REGISTER
8864 BIC #^C1DXMSK,R3 ;CLEAR ANY SIGN EXTENSION
8865 ADD R2,R3
8866 MOV (R1),(R3) ;READ REGISTER
```

```

8867 037676 000764          BR      3$
8868
8869 037700 022626          5$:    CMP      (SP)+,(SP)+      ;RESTORE STACK
8870 037702 062766 000004 000016  ADD      #4,16(SP)      ;WRITE ERROR NUMBER IN
8871 037710 112776 000007 000016  MCVB     #7,216(SP)      ;USER'S ERROR CALL
8872 037716 162766 000002 000016  7$:    SUB      #2,16(SP)
8873 037724 105714          8$:    TSTB     (R4)              ;DONE CLEARING??
8874 037726 100405          BMI      9$              ;YES!!
8875 037730 005003          CLR      R3              ;CLEAR REMAINING STORAGE
8876 037732 112403          MOVB     (R4)+,R3          ;LOCATIONS
8877 037734 060203          ADD      R2,R3
8878 037736 005013          CLR      (R3)
8879 037740 000771          BR      8$
8880 037742
8881 037742 012637 000006          9$:    MOV      (SP)+,ERRVEC+2      ;;POP STACK INTO ERRVEC+2
8882 037746 012637 000004          MOV      (SP)+,ERRVEC      ;;POP STACK INTO ERRVEC
8883 037752 012604          MOV      (SP)+,R4          ;;POP STACK INTO R4
8884 037754 012603          MOV      (SP)+,R3          ;;POP STAC ' INTO R3
8885 037756 012602          MOV      (SP)+,R2          ;;POP STACK INTO R2
8886 037760 012601          MOV      (SP)+,R1          ;;POP STACK INTO R1
8887 037762 012600          MOV      (SP)+,R0          ;;POP STACK INTO R0
8888 037764 000207          RTS      PC              ;RETURN
8889

```

```

8890      .SBTTL PUT SUBROUTINE
8891
8892      ;THIS SUBROUTINE WRITES THE REGISTERS WHICH ARE LISTED IN THE
8893      ;'PUT INDEX TABLE' WITH THE CONTENTS OF THE CORRESPONDING
8894      ;LOCATION IN THE 'PUT REGISTER BUFFER'. THE NUMBER OF
8895      ;REGISTERS WRITTEN IS VARIABLE; THE INDEX TABLE MUST
8896      ;BE TERMINATED WITH A CONTROL BYTE (200) WHICH SHOULD
8897      ;FOLLOW THE LAST ENTRY.
8898
8899      ;SUBROUTINE CALL:
8900
8901      ;(1) 'PUT INDEX TABLE' HAS BEEN LOADED WITH INDEX VALUES
8902      ;      OF REGISTERS TO BE WRITTEN.
8903      ;(2) 'PUT REGISTER BUFFER' CONTAINS CONTENTS OF EACH
8904      ;      REGISTER TO BE WRITTEN.
8905      ;(3) JSR      PC,PUT
8906      ;      BR      ??? RETURN HERE IF NO ERROR FOUND
8907      ;      NOP      RETURN HERE IF ANY ERROR FOUND
8908      ;      ERROR    SUB DEFINES ERROR NUMBER
8909      ;      ???
8910
8911      PUT:  NOP
8912      MOV   R0,-(SP)      ;;PUSH R0 ON STACK
8913      MOV   R1,-(SP)      ;;PUSH R1 ON STACK
8914      MOV   R2,-(SP)      ;;PUSH R2 ON STACK
8915      MOV   R3,-(SP)      ;;PUSH R3 ON STACK
8916      MOV   R4,-(SP)      ;;PUSH R4 ON STACK
8917      MOV   ERRVEC,-(SP)  ;;PUSH ERRVEC ON STACK
8918      MOV   ERRVEC+2,-(SP) ;;PUSH ERRVEC+2 ON STACK
8919      MOV   $BASE,R0
8920      MOV   #PUTBUF,R2
8921      MOV   #PUTINX,R4
8922      MOV   #5$,ERRVEC    ;SETUP FOR TIMEOUT
8923      MOV   #PR6,ERRVEC+2
8924      1$:  MOV   RMCS2(R0),$TMP0 ;GET 'MED' STATUS
8925      MOV   RMCS1(R0),$TMP1 ;GET 'DVA' STATUS
8926      BIT   #DVA,$TMP1      ;DEVICE AVAILABLE??
8927      BNE   3$             ;YES!!
8928      ADD   #4,16(SP)       ;WRITE ERROR NUMBER IN
8929      MOVB  #112,216(SP)    ;USER'S ERROR CALL
8930      BR    7$
8931      3$:  TSTB  (R4)        ;DONE??
8932      BMI   9$             ;YES!!
8933      MOVB  (R4),R1         ;R1 = REGISTER ADDRESS
8934      BIC   #^CIDXMSK,R1    ;CLEAR ANY SIGN EXTENSION
8935      ADD   R0,R1
8936      MOVB  (R4)+,R3        ;R3 = STORAGE ADDRESS
8937      BIC   #^CIDXMSK,R3    ;CLEAR ANY SIGN EXTENSION
8938      ADD   R2,R3
8939      MOV   (R3),(R1)       ;WRITE REGISTER
8940      BR    3$
8941
8942      5$:  CMP   (SP)+,(SP)+  ;ADJUST STACK
8943      ADD   #4,16(SP)       ;WRITE ERROR NUMBER IN
8944      MOVB  #7,216(SP)      ;USER'S ERROR CALL
8945      7$:  SUB   #2,16(SP)

```

L 14

PAGE 180

8946						
8947	040160			98:		
8948	040160	012637	000006	MOV	(SP)+,ERRVEC+2	::POP STACK INTO ERRVEC+2
8949	040164	012637	000004	MOV	(SP)+,ERRVEC	::POP STACK INTO ERRVEC
8950	040170	012604		MOV	(SP)+,R4	::POP STACK INTO R4
8951	040172	012603		MOV	(SP)+,R3	::POP STACK INTO R3
8952	040174	012602		MOV	(SP)+,R2	::POP STACK INTO R2
8953	040176	012601		MOV	(SP)+,R1	::POP STACK INTO R1
8954	040200	012600		MOV	(SP)+,R0	::POP STACK INTO R0
8955	040202	000207		RTS	PC	::RETURN
8956						

```

8957      .SBTTL  SIZE CLOCK SUBROUTINE
8958
8959      040204      SIZCLK:
8960      040204      013746      000004      MOV      ERRVEC,-(SP)      ;;PUSH ERRVEC ON STACK
8961      040210      013746      000006      MOV      ERRVEC+2,-(SP)      ;;PUSH ERRVEC+2 ON STACK
8962      040214      012737      040252      000004      MOV      #1$,ERRVEC      ;;SET UP FOR BUS TIMEOUT
8963      040222      012737      000300      000006      MOV      #PR6,ERRVEC+2
8964      040230      012737      177546      001502      MOV      #177546,CLKADR      ;;LOAD ADDRESSES FOR KW11-L
8965      040236      012737      000100      001504      MOV      #100,CLKVCT
8966      040244      005777      141232      TST      @CLKADR      ;;TEST FOR KW11-L PRESENT
8967      040250      000421      BR      3$      ;;YES - KW11-L IS PRESENT
8968      040252      022626      1$:      CMP      (SP)+,(SP)+      ;;RESTORE SP
8969      040254      012737      040304      000004      MOV      #2$,ERRVEC      ;;SET UP FOR BUS TIMEOUT
8970      040262      012737      172540      001502      MOV      #172540,CLKADR      ;;LOAD ADDRESSES FOR KW11-P CLOCK
8971      040270      012737      000104      001504      MOV      #104,CLKVCT
8972      040276      005777      141200      TST      @CLKADR      ;;TEST FOR KW11-P PRESENT
8973      040282      000404      BR      3$      ;;YES - KW11-P IS PRESENT
8974      040304      022626      2$:      CMP      (SP)+,(SP)+      ;;RESTORE SP
8975      040306      062766      000002      000004      ADD      #2,4(SP)      ;;MOVE RETURN TO ERROR
8976      040314      3$:
8977      040314      012637      000006      MOV      (SP)+,ERRVEC+2      ;;POP STACK INTO ERRVEC+2
8978      040320      012637      000004      MOV      (SP)+,ERRVEC      ;;POP STACK INTO ERRVEC
8979      040324      000207      RTS      PC      ;;RETURN TO USER
  
```



```
8980      .SBTTL  TIMEOUT SUBROUTINE
8981      :
8982      :THIS SUBROUTINE WAITS FOR GO TO RESET OR FOR A TIMEOUT GREATER THAN
8983      :500 MS, WHICH EVER OCCURS FIRST, AND THEN RETURNS.
8984      :
8985      :CALL:  JSR      PC, TIMEOUT
8986      :              ???
8987      :              RETURN HERE
8988      TIMEOUT:
8989      040326 010046      MOV      R0, -(SP)      ;; PUSH RC ON STACK
8990      040330 010146      MOV      R1, -(SP)      ;; PUSH R1 ON STACK
8991      040332 010246      MOV      R2, -(SP)      ;; PUSH R2 ON STACK
8992      040334 013746 000004      MOV      ERRVEC, -(SP)      ;; PUSH ERRVEC ON STACK
8993      040340 013746 000006      MOV      ERRVEC+2, -(SP)      ;; PUSH ERRVEC+2 ON STACK
8994      040344 012737 040446 000004      MOV      #4$, ERRVEC      ;; SETUP FOR BUS TIMEOUT - 04 TRAP
8995      040352 012737 000300 000006      MOV      #PR6, ERRVEC+2
8996      040360 013700      MOV      $BASE, R0      ; R0=RM03 ADDRESS
8997      040364 013701      MOV      CLKADR, R1      ; R1=CLOCK ADDRESS
8998      040370 012702 000037      MOV      #31, R2      ; R2=NUMBER OF CLOCK CYCLES
8999      040374 020127 172540      1$:  CMP      R1, #172540      ; KW11-P CLOCK??
9000      040400 001003      BNE      2$      ; NO!!
9001      040402 012761 000001 000002      MOV      #1, 2(R1)      ; SET COUNTER
9002      040410 012711 000005      2$:  MOV      #BIT2:BIT0, (R1) ; START COUNTER
9003
9004      040414 016046 000000      3$:  MOV      RMCS1(R0), -(SP) ; GET STATUS
9005      040420 042716 177576      BIC      #^C<RDY!GO>, (SP)
9006      040424 022726 000200      CMP      #RDY, (SP)+      ; RDY=1, GO=0??
9007      040430 001420      BEQ      5$      ; YES!!
9008      040432 032711 000200      BIT      #BIT7, (R1)      ; TIMER DONE??
9009      040436 001766      BEQ      3$      ; NO!!
9010      040440 005302      DEC      R2      ; DEC NUMBER OF CYCLES
9011      040442 001354      BNE      1$      ; CONTINUE IF NOT DONE
9012      040444 000412      BR       5$
9013      040446 022626      4$:  CMP      (SP)+, (SP)+      ; ADJUST STACK
9014      040450 062766 000004 000012      ADD      #4, 12(SP)      ; MOVE SP TO USER'S CALL
9015      040456 112776 000007 000012      MOVB     #7, 212(SP)      ; WRITE ERROR NUMBER
9016      040464 162766 000002 000012      SUB      #2, 12(SP)
9017
9018      040472      5$:  MOV      (SP)+, ERRVEC+2      ;; POP STACK INTO ERRVEC+2
9019      040472 012637 000006      MOV      (SP)+, ERRVEC      ;; POP STACK INTO ERRVEC
9020      040476 012637 000004      MOV      (SP)+, R2      ;; POP STACK INTO R2
9021      040502 012602      MOV      (SP)+, R1      ;; POP STACK INTO R1
9022      040504 012601      MOV      (SP)+, R0      ;; POP STACK INTO R0
9023      040506 012600      MOV      (SP)+, R0
9024      040510 000207      RTS      PC      ; RETURN TO USER
9025
```

9026
9027
9028
9029
9030
9031
9032
9033
9034
9035
9036
9037
9038
9039
9040
9041
9042
9043
9044
9045
9046
9047
9048
9049
9050
9051
9052
9053
9054
9055
9056
9057
9058
9059
9060
9061
9062
9063
9064 040512
9065
9066
9067 040512 062716 000004
9068 040516 105076 000000
9069 040522 162716 000004
9070
9071
9072
9073 040526 013737 001340 001142
9074 040534 042737 177770 001142
9075 040542 013737 001234 001140
9076 040550 042737 177770 001140
9077 040556 123737 001140 001142
9078
9079 040564 001415
9080 040566 062716 000004
9081 040572 112776 000001 000000

.SBTTL PRIMARY ERROR CHECK SUBROUTINE

:THE PURPOSE OF THIS SUBROUTINE IS TO VERIFY THAT STAUTS IS VALID AND
:THAT FURTHER ERROR AND STATUS CHECKING SHOULD BE PERFORMED. THE
:FOLLOWING CHECKS ARE MADE::CURRENT UNIT IS SELECTED, I.E., THE UNIT SELECT BITS OF RMCS2
:(BITS 0-2) EQUAL THE UNIT BEING TESTED;:SELECTED UNIT IS AVAILABLE, I.E., DVA (BIT 11 OF RMCS1) IS SET
:AND NED (BIT 12 OF RMCS2) IS RESET;:LAST COMMAND WAS COMPLETED, I.E., THE MASSBUS CONTROLLER IS
:READY (BIT 7 OF RMCS1) AND THE GO BIT IS RESET (BIT 0 OF RMCS1) OR THE
:DRIVE READY BIT (BIT 7 OF RMDS) IS SET.

:NO PARITY ERROR OCCURRED WHEN READING REMOTE REGISTERS.

:I.E., MCPE = 0

:NO PARITY ERROR OCCURRED WHEN WRITING REMOTE REGISTERS.

:I.E., PAR = 0, OR, PAR = DPE = 1

:THE SUBROUTINE ASSUMES THAT:

:STATUS HAS BEEN STORED IN THE REGISTER INPUT BUFFER,
:IN PARTICULAR, RMCS1, RMCS2 AND RMDS HAVE BEEN STORED IN THEIR
:CORRESPONDING LOCATIONS OF THE "GET" BUFFER.

:(\$UNIT) CONTAINS THE DRIVE NUMBER

:THE SUBROUTINE IS CALLED AS FOLLOWS:

(1) JSR PC,PRIERR
BR ??? RETURN HERE IF NO ERROR
NOP RETURN HERE TO REPORT AN ERROR
ERROR ERROR NUMBER DEFINED BY SUB
JSR PC,@(SP)+ GO BACK TO SUB FOR MORE ERROR CHECKS
??? RETURN HERE IF NO MORE ERRORS

PRIERR:

:CLEAR USER'S ERROR CALL

ADD #4,(SP) :MOVE (SP) TO ERROR CALL
CLRB @ (SP) :CLEAR ERROR NUMBER
SUB #4,(SP) :MOVE (SP) TO NO ERROR RETURN

:REPORT AN ERROR IF THE WRONG UNIT IS SELECTED

MOV RMCS2I,\$BDDAT :CORRECT UNIT SELECTED??
BIC #^CUNTMSK,\$BDDAT
MOV \$UNIT,\$GDDAT :GOOD DATA FOR TYPEOUT
BIC #^CUNTMSK,\$GDDAT
CMPB \$GDDAT,\$BDDAT :COMPARE EXPECTED AND RECEIVED
:DRIVE NUMBERS
BEQ 1\$:YES!!
ADD #4,(SP)
MOVB #1,@(SP) :ERROR 1

9082	040600	162716	000002		SUB	#2,(SP)	:MOVE SP TO RETURN FOR ERROR
9083	040604	004736			JSR	PC,@(SP)+	:REPORT WRONG UNIT SELECTED
9084	040606	162716	000010		SUB	#10,(SP)	:RESTORE (SP)
9085	040612	000240			NOP		
9086	040614	000137	041334		JMP	10\$	:SKIP OTHER CHECKS
9087	040620			1\$:			
9088							
9089							:REPORT AN ERROR IF THE DEVICE IS NOT AVAILABLE OR IF
9090							:THE DEVICE IS NONEXISTANT
9091	040620	032737	004000	001330	BIT	#DVA,RMCS11	:DEVICE AVAILABLE??
9092	040626	001045			BNE	5\$	:YES!!
9093	040630	013737	001330	001140	MOV	RMCS11,\$GDDAT	:EXPECTED STATUS
9094	040636	052737	004000	001140	BIS	#DVA,\$GDDAT	
9095	040644	013737	001330	001142	MOV	RMCS11,\$BDDAT	:RECEIVED STATUS
9096	040652	062716	000004		ADD	#4,(SP)	
9097	040656	112776	000002	000000	MOVB	#2,@(SP)	:ERROR #2
9098	040664	032737	010000	001340	BIT	#NED,RMCS21	:WAS NED SET??
9099	040672	001414			BEQ	2\$	:NO!!
9100	040674	013737	001340	001140	MOV	RMCS21,\$GDDAT	:EXPECTED STATUS
9101	040702	013737	001340	001142	MOV	RMCS21,\$BDDAT	:RECEIVED STATUS
9102	040710	042737	010000	001140	BIC	#NED,\$GDDAT	
9103	040716	112776	000003	000000	MOVB	#3,@(SP)	:YES - CHANGE ERROR NUMBER
9104	040724	162716	000002		SUB	#2,(SP)	:MOVE SP TO RETURN FOR ERROR
9105	040730	004736			JSR	PC,@(SP)+	:REPORT DEVICE NOT AVAILABLE
9106	040732	162716	000010		SUB	#10,(SP)	:RESTORE (SP)
9107	040736	000240			NOP		
9108	040740	000575			BR	10\$	:SKIP OTHER CHECKS
9109	040742			5\$:			
9110							
9111							:REPORT AN ERROR IF MASSBUS CONTROLLER IS NOT READY
9112	040742	032737	000200	001330	BIT	#RDY,RMCS11	:CONTROLLER READY??
9113	040750	001030			BNE	7\$	:YES!!
9114	040752	013737	001330	001140	MOV	RMCS11,\$GDDAT	:EXPECTED STATUS
9115	040760	052737	000200	001140	BIS	#RDY,\$GDDAT	
9116	040766	042737	160001	001140	BIC	#SC!TRE!MCPE!GO,\$GDDAT	
9117	040774	013737	001330	001142	MOV	RMCS11,\$BDDAT	:RECEIVED STATUS
9118	041002	062716	000004		ADD	#4,(SP)	
9119	041006	112776	000004	000000	MOVB	#4,@(SP)	:ERROR #4
9120	041014	162716	000002		SUB	#2,(SP)	:MOVE SP TO RETURN FOR ERROR
9121	041020	004736			JSR	PC,@(SP)+	:REPORT CONTROLLER NOT READY
9122	041022	162716	000010		SUB	#10,(SP)	:RESTORE (SP)
9123	041026	000240			NOP		
9124	041030	000541			BR	10\$	:SKIP OTHER CHECKS
9125	041032			7\$:			
9126							
9127							:REPORT AN ERROR IF GO IS NOT ZERO AND DRY IS NOT ONE
9128	041032	032737	000001	001330	BIT	#GO,RMCS11	:GO RESET??
9129	041040	001431			BEQ	8\$	:YES!!
9130	041042	032737	000200	001342	BIT	#DRY,RMDS1	:DRIVE READY??
9131	041050	001025			BNE	8\$	:YES!!
9132	041052	013737	001330	001140	MOV	RMCS11,\$GDDAT	:EXPECTED STATUS
9133	041060	042737	160001	001140	BIC	#SC!TRE!MCPE!GO,\$GDDAT	
9134	041066	013737	001330	001142	MOV	RMCS11,\$BDDAT	:RECEIVED STATUS
9135	041074	062716	000004		ADD	#4,(SP)	
9136	041100	112776	000005	000000	MOVB	#5,@(SP)	:ERROR #5
9137	041106	162716	000002		SUB	#2,(SP)	:MOVE SP TO RETURN FOR ERROR

```
9138 041112 004736      JSR    PC,@(SP)+      ;REPORT DRIVE NOT READY
9139 041114 162716 000010 SUB    #10,(SP)      ;RESTORE (SP)
9140 041120 000240      NOP
9141 041122 000504      BR      10$
9142 041124      8$:
9143
9144      ;REPORT AN ERROR IF THE RM CONTROLLER DETECTED BAD
9145      ;PARITY ON THE MASSBUS CONTROL BUS
9146 041124 072737 020000 001330 BIT    #MCPE,RMC$11    ;PARITY ERROR ??
9147 041132 001425      BEQ      9$      ;NO!!
9148 041134 013737 001330 001140 MOV    RMC$11,$GDDAT    ;EXPECTED STATUS
9149 041142 042737 160001 001140 BIC    #SC!TRE!MCPE!GO,$GDDAT
9150 041150 013737 001330 001142 MOV    RMC$11,$BDDAT    ;RECEIVED STATUS
9151 041156 062716 000004      ADD    #4,(SP)      ;MOVE STACK TO USER'S ERROR
9152 041162 112776 000013 000000 MOVB   #13,@(SP)      ;ERROR #47
9153 041170 162716 000002      SUB    #2,(SP)      ;MOVE SP TO RETURN FOR ERROR
9154 041174 004736      JSR    PC,@(SP)+      ;REPORT ERROR VIA USER
9155 041176 162716 000010 SUB    #10,(SP)      ;RESTORE STACK
9156 041202 000240      NOP
9157 041204 000453      BR      10$
9158 041206      9$:
9159
9160      ;REPORT AN ERROR IF THE RMO3 DETECTED A CONTROL BUS PARITY ERROR
9161 041206 032737 000010 001344 BIT    #PAR,RMER11    ;WAS THERE A PARITY ERROR??
9162 041214 001451      BEQ      11$      ;NO!!
9163 041216 032737 000010 001372 BIT    #DPE,RMER21    ;WAS IT THE CONTROL BUS??
9164 041224 001045      BNE      11$      ;NOT SURE!!
9165 041226 032737 000010 001414 BIT    #PAR,RMER10    ;DID TEST SET PAR ??
9166 041234 001413      BEQ      93$      ;NO!!
9167 041236 010046      MOV    R0,-(SP)      ;;PUSH R0 ON STACK
9168 041240 012700 001535      MOV    #PUTINX,R0      ;R0 POINTS TO INDEX TABLE
9169 041244 122710 000014      91$: CMPB   #RMER1,(R0)    ;SEARCH TABLE FOR RMER1
9170 041250 001002      BNE      92$
9171 041252 012600      MOV    (SP)+,R0      ;;POP STACK INTO R0
9172 041254 000431      BR      11$      ;PAR WAS SET BY TEST
9173 041256 105720      92$: TSTB   (R0)+      ;END OF TABLE??
9174 041260 100371      BPL      91$      ;NO!!
9175 041262 012600      MOV    (SP)+,R0      ;;POP STACK INTO R0
9176 041264 013737 001344 001140 93$: MOV    RMER11,$GDDAT    ;EXPECTED STATUS
9177 041272 042737 000010 001140 BIC    #PAR,$GDDAT
9178 041300 013737 001344 001142 MOV    RMER11,$BDDAT    ;RECEIVED STATUS
9179 041306 062716 000004      ADD    #4,(SP) ;MOVE SP TO USER'S ERROR CALL
9180 041312 112776 000050 000000 MOVB   #50,@(SP)      ;WRITE THE ERROR NUMBER
9181 041320 162716 000002      SUB    #2,(SP)      ;MOVE SP TO RETURN FOR ERROR
9182 041324 004736      JSR    PC,@(SP)+      ;REPORT THE ERROR
9183 041326 162716 000010      SUB    #10,(SP)      ;MOVE SP TO NO ERROR RETURN
9184 041332 000240      NOP
9185 041334 062716 000010      10$: ADD    #10,(SP)      ;RETURN TO ERROR
9186 041340 000240      11$: NOP      ;RETURN TO NO ERROR
9187 041342 000207      RTS    PC
9188
```

```
9189 .SBTTL SECONDARY ERROR CHECK SUBROUTINE
9190
9191 ;THE ERROR CHECK SUBROUTINE PROVIDES DETECTION OF SECONDARY ERRORS
9192 ;SUCH AS UNEXPECTED ERRORS AND UNEXPECTED REGISTER
9193 ;CONTENTS. THESE ERRORS ARE DEEMED
9194 ;SECONDARY IN THAT THEY ARE NOT NECESSARILY ASSOCIATED WITH THE OPERATION
9195 ;BEING PERFORMED. WHEN THE SUBROUTINE IDENTIFIES SUCH AN ERROR, IT MOVES
9196 ;THE ERROR NUMBER TO THE ERROR CALL IN THE TEST ROUTINE AND THEN RETURNS
9197 ;TO THE TEST ROUTINE WHICH MAKES THE ERROR CALL. AFTER THE TEST ROUTINE
9198 ;MAKES THE ERROR CALL, IT RETURNS TO THE SUBROUTINE WHICH THEN LOOKS FOR
9199 ;OTHER ERRORS. WHEN ALL ERRORS HAVE BEEN REPORTED, THE SUBROUTINE
9200 ;RETURNS TO THE ADDRESS FOLLOWING THE SUBROUTINE CALL.
9201
9202 ;CALL: JSR PC,SECERR
9203 ;      BR ??? RETURN HERE IF NO ERROR
9204 ;      NOP RETURN HERE TO REPORT AN ERROR
9205 ;      ERROR ERROR NUMBER DEFINED BY SUB
9206 ;      JSR PC,@(SP)+ GO BACK TO SUB FOR MORE ERROR CHECKS
9207 ;      ??? RETURN HERE IF NO MORE ERRORS
9208
9209 ;NOTE: THE SUBROUTINE ASSUMES THAT REGISTERS HAVE BEEN STORED AT THE
9210 ;INPUT REGISTER BUFFER.
9211
9212 041344 SECERR:
9213
9214 ;*****
9215 ;STORE FUNCTION CODE AND CLEAR USER'S ERROR NUMBER
9216 041344 013737 001400 045204 MOV RMCS10,515$ ;STORE FUNCTION CODE
9217 041352 042737 177701 045204 BIC #^C<:0!F1!F2!F3!F4>,515$
9218 041360 062716 000004 ADD #4,(SP) ;MOVE (SP) TO ERROR CALL
9219 041364 105076 000000 CLRB @(SP) ;CLEAR ERROR NUMBER
9220 041370 162716 000004 SUB #4,(SP) ;MOVE (SP) TO NO ERROR RETURN
9221
9222 ;*****
9223 ;CHECK SECONDARY ERRORS COMMON TO ALL COMMANDS
9224
9225 ;REPORT ERROR IF DRIVE IS NOT READY, I.E., IF DRY = 0
9226 041374 032737 000200 001342 BIT #DRY,RMDS1 ;DRIVE READY??
9227 041402 001024 BNE 5$ ;YES!!
9228 041404 013737 001342 001142 MOV RMDS1,$BDDAT ;BAD DATA FOR TYPEOUT
9229 041412 042737 177577 001142 BIC #^CDRY,$BDDAT
9230 041420 012737 000200 001140 MOV #DRY,$GDDAT ;GOOD DATA FOR TYPEOUT
9231 041426 062716 000004 ADD #4,(SP)
9232 041432 112776 000010 000000 MOVB #10,@(SP) ;ERROR NUMBER
9233 041440 162716 000002 SUB #2,(SP) ;MOVE SP TO RETURN FOR ERROR
9234 041444 004736 JSR PC,@(SP)+ ;REPORT NOT READY
9235 041446 162716 000010 SUB #10,(SP) ;RESTORE (SP) TO ERROR N
9236 041452 000240 NOP
9237
9238 ;REPORT ERROR IF GO BIT IS NOT RESET
9239 041454 032737 000001 001330 5$: BIT #GO,RMCS11 ;GO BIT RESET??
9240 041462 001423 BEQ 10$ ;YES!!
9241 041464 013737 001330 001142 MOV RMCS11,$BDDAT ;BAD DATA FOR TYPEOUT
9242 041472 042737 177776 001142 BIC #^CGO,$BDDAT
9243 041500 005037 001140 CLR $GDDAT ;GOOD DATA FOR TYPEOUT
9244 041504 062716 000004 ADD #4,(SP)
```

```
9245 041510 112776 000011 000000      MOVB    #1, @ (SP)      ;ERROR NUMBER
9246 041516 162716 000002              SUB     # (SP)        ;MOVE SP TO RETURN FOR ERROR
9247 041522 004736              JSR     PC, @ (SP)+    ;REPORT DEVICE NOT AVAILABLE
9248 041524 162716 000010              SUB     #10, (SP)      ;RESTORE (SP)
9249 041530 000240              NOP
9250
9251                                ;REPORT ERROR IF FUNCTION CODE READ FROM DEVICE IS NOT CORRECT
9252 041532 013737 001330 001142 10$: MOV     RMCS11, $BDDAT    ;IS FUNCTION CODE CORRECT??
9253 041540 042737 177701 001142      BIC     #^C76, $BDDAT
9254 041546 013737 045204 001140      MOV     515$, $GDDAT    ;EXPECTED FUNCTION CODE
9255 041554 023737 001142 001140      CMP     $BDDAT, $GDDAT
9256 041562 001413              BEQ     15$              ;YES!!
9257 041564 062716 000004              ADD     #4, (SP)
9258 041570 112776 000012 000000      MOVB    #12, @ (SP)    ;ERROR NUMBER
9259 041576 162716 000002              SUB     #2, (SP)        ;MOVE SP TO RETURN FOR ERROR
9260 041602 004736              JSR     PC, @ (SP)+    ;REPORT WRONG FUNCTION CODE
9261 041604 162716 000010              SUB     #10, (SP)      ;RESTORE (SP)
9262 041610 000240              NOP
9263 041612
9264                                15$:
9265                                ;REPORT AN ERROR IF COMPOSITE ERROR IS SET AND NO OTHER
9266                                ;ERRORS ARE SET, OR IF COMPOSITE ERROR IS NOT SET AND
9267                                ;OTHER ERRORS ARE SET
9268 041616 005037 001140              CLR     $GDDAT        ;EXPECT 'ERR'=0
9269 041622 001003 001344              TST     RMER11         ;IS RMER1 =0??
9270 041624 005737 001372              BNE     20$              ;NO!!
9271 041630 001403              TST     RMER21         ;IS RMER2=0??
9272 041632 052737 040000 001140      BEQ     25$              ;YES!!
9273 041640 013737 001342 001142 20$: BIS     #ERR, $GDDAT    ;'ERR' SHOULD BE SET
9274 041646 042737 137777 001142 25$: MOV     RMDS1, $BDDAT
9275 041654 023737 001140 001142      BIC     #^CERR, $BDDAT
9276 041662 001412              CMP     $GDDAT, $BDDAT    ;IS 'ERR' OK??
9277 041664 062716 000004              BEQ     30$              ;YES!!
9278 041670 112776 000047 000000      ADD     #4, (SP)        ;MOVE SP TO USER'S ERROR
9279 041676 162716 000002              MOVB    #47, @ (SP)    ;WRITE ERROR NUMBER
9280 041702 004736              SUB     #2, (SP)        ;MOVE SP TO ERROR RETURN
9281 041704 162716 000010              JSR     PC, @ (SP)+    ;REPORT INVALID COMP ERROR
9282                                SUB     #10, (SP)
9283                                ;REPORT AN ERROR IF 'TRE' IS SET AND NONE OF THE BITS WHICH SET
9284                                ;TRE IS SET, OR IF TRE IS NOT SET AND ONE OR MORE BITS WHICH
9285                                ;SET TRE IS SET
9286 041710 005037 001140 30$: CLR     $GDDAT        ;EXPECT 'TRE' =0
9287 041714 013746 001340              MOV     RMCS21, -(SP)    ;WAS DLT, WCE, UPE, NED, NEM
9288 041720 042726 000377              BIC     #377, (SP)+    ;PGE, MXF OR MDPE SET
9289 041724 001010              BNE     35$              ;YES!!
9290 041726 032737 040000 001342      BIT     #ERR, RMDS1    ;WAS EXCEPTION RECEIVED??
9291 041734 001407              BEQ     40$              ;NO!!
9292 041736 022737 000030 045204      CMP     #SEARCH, 515$    ;WAS DATA TRANSFERRED??
9293 041744 103003              BHIS    40$              ;NO!!
9294 041746 052737 040000 001140 35$: BIS     #TRE, $GDDAT    ;'TRE' SHOULD BE SET
9295 041754 013737 001330 001142 40$: MOV     RMCS11, $BDDAT    ;BAD DATA FOR TYPEOUT
9296 041762 042737 137777 001142      BIC     #^CTRE, $BDDAT
9297 041770 023737 001140 001142      CMP     $GDDAT, $BDDAT    ;IS 'TRE' OK??
9298 041776 001413              BEQ     45$              ;YES!!
9299 042000 062716 000004              ADD     #4, (SP)        ;MOVE SP TO USER'S ERROR CALL
9300 042004 112776 000014 000000      MOVB    #14, @ (SP)    ;WRITE ERROR NUMBER
```

```
9301 042012 162716 000002          SUB    #2,(SP)          ;MOVE SP TO RETURN FOR ERROR
9302 042016 004736                JSR    PC,@(SP)+        ;REPORT TRE ERROR
9303 042020 162716 000010          SUB    #10,(SP)         ;RESTORE (SP)
9304 042024 000240                NOP
9305 042026                45$:
9306
9307                ;*****
9308                ;USING THE FUNCTION CODE TABLE, CHECK FOR THE FOLLOWING ERRORS:
9309                ;.STATUS BITS NOT SET THAT SHOULD BE SET, E.G., ATA AND ILF
9310                ;.STATUS BITS SET THAT SHOULD NOT BE SET, E.G., WCE AND ECH
9311                ;NOTE THAT SOME ERROR BITS ARE CONDITIONAL ON THE COMMAND AND OTHER
9312                ;STATUS CONDITIONS, E.G., WRITE LOCK ERROR SHOULD ONLY BE SET IF
9313                ;WRITE LOCK IS ON AND THE COMMAND IS A WRITE.
9314
9315                ;GET AND STORE THE ENTRY FROM THE FUNCTION CODE TABLE
9316 042026 010046                MOV    R0,-(SP)            ;;PUSH R0 ON STACK
9317 042030 013700 045204        MOV    515$,R0            ;;R0 = FUNCTION CODE
9318 042034 016037 064672 045176  MOV    FNCDTB(R0),500$      ;STORE ENTRY
9319 042042 012600                MOV    (SP)+,R0            ;;POP STACK INTO R0
9320
9321                ;REPORT AN ERROR IF AN UNEXPECTED ATTENTION OCCURRED OR IF
9322                ;ATA IS NOT SET AND SHOULD BE SET.
9323 042044 013737 045176 001140    MOV    500$,$GDDAT        ;GET EXPECTED ATA STATUS
9324 042052 032737 040000 001342    BIT    #ERR,RMDSI        ;IS COMPOSITE ERROR SET ??
9325 042060 001403                BEQ    50$                ;NO !!
9326 042062 052737 100000 001140    BIS    #ATA,$GDDAT        ;EXPECT AN ATTENTION
9327 042070 042737 077777 001140 50$: BIC    #^CATA,$GDDAT    ;STRIP DONT CARES
9328 042076 013737 001342 001142    MOV    RMDSI,$BDDAT      ;GET RECEIVED ATA
9329 042104 042737 077777 001142    BIC    #^CATA,$BDDAT    ;STRIP DONT CARES
9330 042112 023737 001140 001142    CMP    $GDDAT,$BDDAT    ;IS ATA OK ??
9331 042120 001413                BEQ    55$                ;YES !!
9332 042122 062716 000004                ADD    #4,(SP)        ;MOVE SP TO USERS ERROR CALL
9333 042126 112776 000006 000000    MOVB   #6,@(SP)        ;LOAD ERROR # IN CALL
9334 042134 162716 000002                SUB    #2,(SP)        ;MOVE SP TO ERROR RETURN
9335 042140 004736                JSR    PC,@(SP)+        ;REPORT ERROR
9336 042142 162716 000010                SUB    #10,(SP)       ;RESTORE SP
9337 042146 000240                NOP
9338 042150                55$:
9339
9340                ;REPORT ERROR IF ILF IS INCORRECT, I.E., IF ILF DOES NOT COMPARE
9341                ;WITH FUNCTION CODE TABLE
9342 042150 013737 045176 001140    MOV    500$,$GDDAT        ;GET EXPECTED !LF
9343 042156 042737 177776 001140    BIC    #^CILF,$GDDAT    ;CLEAR ALL OTHER BITS
9344 042164 013737 001344 001142    MOV    RMERRI,$BDDAT    ;GET RECEIVED !LF
9345 042172 042737 177776 001142    BIC    #^CILF,$BDDAT    ;CLEAR ALL OTHER BITS
9346 042200 023737 001140 001142    CMP    $GDDAT,$BDDAT    ;IS ILF OK ??
9347 042206 001412                BEQ    60$                ;YES !!
9348 042210 062716 000004                ADD    #4,(SP)        ;MOVE SP TO USERS ERROR CALL
9349 042214 112776 000254 000000    MOVB   #254,@(SP)       ;WRITE ERROR NUMBER IN CALL
9350 042222 162716 000002                SUB    #2,(SP)        ;MOVE SP TO ERROR RETURN
9351 042226 004736                JSR    PC,@(SP)+        ;REPORT ERROR AND RETURN
9352 042230 162716 000010                SUB    #10,(SP)       ;MOVE SP TO NO ERROR
9353 042234 005037 001140 60$:    CLR     $GDDAT            ;CLEAR EXPECTED STATUS
9354
9355                ;REPORT AN ERROR IF WCE IS SET AND SHOULD NOT BE SET
9356 042240 013746 045176        MOV    500$,-(SP)          ;GET WCE STATUS ENABLE
```

9357 042244 052716 137777
9358 042250 013737 001340 001142
9359 042256 042637 001142
9360 042262 001412
9361 042264 062716 000004
9362 042270 112776 000026 000000
9363 042276 162716 000002
9364 042302 004736
9365 042304 162716 000010
9366 042310
9367
9368
9369 042310 013746 045176
9370 042314 052716 157777
9371 042320 013737 001344 001142
9372 042326 042637 001142
9373 042332 001412
9374 042334 062716 000004
9375 042340 112776 000164 000000
9376 042346 162716 000002
9377 042352 004736
9378 042354 162716 000010
9379 042360
9380
9381
9382
9383 042360 013746 045176
9384 042364 032737 000100 001342
9385 042372 001402
9386 042374 042716 010000
9387 042400 052716 167777
9388 042404 013737 001372 001142
9389 042412 042637 001142
9390 042416 001412
9391 042420 062716 000004
9392 042424 112776 000165 000000
9393 042432 162716 000002
9394 042436 004736
9395 042440 162716 000010
9396 042444
9397
9398
9399
9400
9401
9402
9403
9404
9405
9406
9407
9408 042444 012746 177777
9409 042450 032737 004000 045176
9410 042456 001404
9411 042460 032737 004000 001342
9412 042466 001002

BIS #^CWCE,(SP) ;SET ALL OTHER BITS
MOV RMCS21,\$BDDAT ;RECEIVED STATUS
BIC (SP)+,\$BDDAT ;CLEAR WCE IF ENABLED
BEQ 90\$;BRANCH IF WCE OK
ADD #4,(SP) ;MOVE SP TO USER'S ERROR CALL
MOVB #26,@(SP) ;WRITE ERROR NUMBER
SUB #2,(SP) ;MOVE SP TO ERROR RETURN
JSR PC,@(SP)+ ;REPORT ERROR
SUB #10,(SP) ;RESTORE ERROR

90\$:
;REPORT ERROR IF OF. STATUS IS SET AND SHOULD NOT BE SET
MOV 500\$,-(SP) ;GET OPI STATUS ENABLE
BIS #^COP1,(SP) ;SET ALL OTHER BITS
MOV RMER11,\$BDDAT ;GET RECEIVED STATUS
BIC (SP)+,\$BDDAT ;CLEAR OPI IF ENABLED
BEQ 100\$;BRANCH IF OPI OK
ADD #4,(SP) ;MOVE SP TO USER'S ERROR CALL
MOVB #164,@(SP) ;WRITE ERROR NUMBER IN CALL
SUB #2,(SP) ;MOVE SP TO ERROR RETURN
JSR PC,@(SP)+ ;REPORT ERROR
SUB #10,(SP) ;RESTORE SP

100\$:
;REPORT ERROR IF IVC IS SET AND IS NOT ENABLED OR IF IVC IS
;SET AND VV IS NOT RESET
MOV 500\$,-(SP) ;GET IVC STATUS ENABLE
BIT #1V,RMDS1 ;IS VV SET
BEQ 105\$;NO !!
BIC #IVC,(SP) ;YES - IVC SHOULD BE 0
BIS #^CIVC,(SP) ;SET ALL OTHER BITS
MOV RMER21,\$BDDAT ;GET RECEIVED STATUS
BIC (SP)+,\$BDDAT ;CLEAR IVC IF ENABLED
BEQ 110\$;BRANCH IF IVC OK
ADD #4,(SP) ;MOVE SP TO USER'S ERROR CALL
MOVB #165,@(SP) ;WRITE ERROR NUMBER IN CALL
SUB #2,(SP) ;MOVE SP TO ERROR RETURN
JSR PC,@(SP)+ ;REPORT ERROR
SUB #10,(SP) ;RESTORE SP TO NO ERROR

105\$:
110\$:
;BIT 11 (WLE) OF THE FUNCTION CODE TABLE IS THE ENABLING BIT FOR
; ALL WRITE ERRORS, I.E.,
; RMER1 - WLE, WCF
; RMER2 - DPE
; RMCS2 - UPE.
;EACH OF THESE ERRORS IS CHECKED TO SEE IF AN ERROR IS SET WHEN THE
;WRITE ERROR ENABLE BIT IS RESET.
;REPORT AN ERROR IF WLE IS SET AND WRITE ERRORS ARE NOT ENABLED, OR IF
;THE DRIVE IS NOT WRITE PROTECTED
MOV #-1,-(SP) ;ASSUME WRITE ERRORS ENABLED
BIT #WLE,500\$;ARE WRITE ERRORS ENABLED ??
BEQ 115\$;NO !!
BIT #WRL,RMDS1 ;IS THE DRIVE WRITE PROTECTED ??
BNE 120\$;YES ..

Address	Hex	Op	Op2	Op3	Op4	Op5	Op6	Op7	Op8	Op9	Op10	Op11	Op12	Op13	Op14	Op15	Op16	Op17	Op18	Op19	Op20	Op21	Op22	Op23	Op24	Op25	Op26	Op27	Op28	Op29	Op30	Op31	Op32	Op33	Op34	Op35	Op36	Op37	Op38	Op39	Op40	Op41	Op42	Op43	Op44	Op45	Op46	Op47	Op48	Op49	Op50	Op51	Op52	Op53	Op54	Op55	Op56	Op57	Op58	Op59	Op60	Op61	Op62	Op63	Op64	Op65	Op66	Op67	Op68	Op69	Op70	Op71	Op72	Op73	Op74	Op75	Op76	Op77	Op78	Op79	Op80	Op81	Op82	Op83	Op84	Op85	Op86	Op87	Op88	Op89	Op90	Op91	Op92	Op93	Op94	Op95	Op96	Op97	Op98	Op99	Op100	Op101	Op102	Op103	Op104	Op105	Op106	Op107	Op108	Op109	Op110	Op111	Op112	Op113	Op114	Op115	Op116	Op117	Op118	Op119	Op120	Op121	Op122	Op123	Op124	Op125	Op126	Op127	Op128	Op129	Op130	Op131	Op132	Op133	Op134	Op135	Op136	Op137	Op138	Op139	Op140	Op141	Op142	Op143	Op144	Op145	Op146	Op147	Op148	Op149	Op150	Op151	Op152	Op153	Op154	Op155	Op156	Op157	Op158	Op159	Op160	Op161	Op162	Op163	Op164	Op165	Op166	Op167	Op168	Op169	Op170	Op171	Op172	Op173	Op174	Op175	Op176	Op177	Op178	Op179	Op180	Op181	Op182	Op183	Op184	Op185	Op186	Op187	Op188	Op189	Op190	Op191	Op192	Op193	Op194	Op195	Op196	Op197	Op198	Op199	Op200	Op201	Op202	Op203	Op204	Op205	Op206	Op207	Op208	Op209	Op210	Op211	Op212	Op213	Op214	Op215	Op216	Op217	Op218	Op219	Op220	Op221	Op222	Op223	Op224	Op225	Op226	Op227	Op228	Op229	Op230	Op231	Op232	Op233	Op234	Op235	Op236	Op237	Op238	Op239	Op240	Op241	Op242	Op243	Op244	Op245	Op246	Op247	Op248	Op249	Op250	Op251	Op252	Op253	Op254	Op255	Op256	Op257	Op258	Op259	Op260	Op261	Op262	Op263	Op264	Op265	Op266	Op267	Op268	Op269	Op270	Op271	Op272	Op273	Op274	Op275	Op276	Op277	Op278	Op279	Op280	Op281	Op282	Op283	Op284	Op285	Op286	Op287	Op288	Op289	Op290	Op291	Op292	Op293	Op294	Op295	Op296	Op297	Op298	Op299	Op300	Op301	Op302	Op303	Op304	Op305	Op306	Op307	Op308	Op309	Op310	Op311	Op312	Op313	Op314	Op315	Op316	Op317	Op318	Op319	Op320	Op321	Op322	Op323	Op324	Op325	Op326	Op327	Op328	Op329	Op330	Op331	Op332	Op333	Op334	Op335	Op336	Op337	Op338	Op339	Op340	Op341	Op342	Op343	Op344	Op345	Op346	Op347	Op348	Op349	Op350	Op351	Op352	Op353	Op354	Op355	Op356	Op357	Op358	Op359	Op360	Op361	Op362	Op363	Op364	Op365	Op366	Op367	Op368	Op369	Op370	Op371	Op372	Op373	Op374	Op375	Op376	Op377	Op378	Op379	Op380	Op381	Op382	Op383	Op384	Op385	Op386	Op387	Op388	Op389	Op390	Op391	Op392	Op393	Op394	Op395	Op396	Op397	Op398	Op399	Op400	Op401	Op402	Op403	Op404	Op405	Op406	Op407	Op408	Op409	Op410	Op411	Op412	Op413	Op414	Op415	Op416	Op417	Op418

9469 ;REPORT AN ERROR IF IAE IS SET AND IS NOT ENABLED
9470 042754 013746 045176 MOV 500\$,-(SP) ;GET IAE ENABLE
9471 042760 052716 175777 BIS #ACIAE,(SP) ;SET ALL OTHER BITS
9472 042764 013737 001344 001142 MOV RMER11,\$BDDAT ;GET RECEIVED STATUS
9473 042772 042637 001142 BIC (SP)+,\$BDDAT ;CLEAR IAE IF ENABLED
9474 042776 001412 BEQ 160\$;BRANCH IF IAE IS OK
9475 043000 062716 000004 ADD #4,(SP) ;MOVE SP TO USERS ERROR CALL
9476 043004 112776 000166 000000 MOVB #166,@(SP) ;WRITE ERROR NUMBER
9477 043012 162716 000002 SUB #2,(SP) ;MOVE SP TO ERROR RETURN
9478 043016 004736 JSR PC,@(SP)+ ;REPORT ERROR AND RETURN
9479 043020 162716 000010 SUB #10,(SP) ;MOVE SP TO NO ERROR
9480 043024 160\$:
9481
9482 ;BIT 09 (AOE) OF THE FUNCTION CODE TABLE IS THE ENABLING BIT FOR
9483 ; ALL READ/WRITE ERRORS, I.E.,
9484 ; RMCS1 - TRE
9485 ; RMCS2 - DLT,NEM,MXF
9486 ; RMD5 - LBT
9487 ; RMER1 - AOE
9488 ;NOTE:
9489 ; LBT IS NOT CHECKED BECAUSE IT ONLY RESETS WHEN THE DESIRED
9490 ;CYLINDER REGISTER IS WRITTEN
9491 ;NOTE:
9492 ; AOE CANNOT BE SET IF LBT IS NOT ALSO SET
9493 ;NOTE:
9494 ; TRE IS CHECKED AS A FUNCTION OF OTHER ERROR CONDITONS ABOVE
9495
9496
9497 ;REPORT AN EPROR IF DLT IS SET AND READ/WRITE ERRORS ARE NOT ENABLED
9498 043024 012746 177777 MOV #-1,-(SP) ;ASSUME ERRORS ARE ENABLED
9499 043030 032737 001000 045176 BIT #AOE,500\$;ARE ERRORS ENABLED ??
9500 043036 001002 BNE 165\$;YES !!
9501 043040 042716 100000 BIC #DLT,(SP) ;RESET DLT ENABLE
9502 043044 013737 001340 001142 165\$: MOV RMCS21,\$BDDAT ;GET RECEIVED STATUS
9503 043052 042637 001142 BIC (SP)+,\$BDDAT ;CLEAR DLT IF ENABLED
9504 043056 001412 BEQ 170\$;BRANCH IF DLT IS OK
9505 043060 062716 000004 ADD #4,(SP) ;MOVE SP TO USERS ERROR CALL
9506 043064 112776 000032 000000 MOVB #32,@(SP) ;WRITE ERROR NUMBER IN CALL
9507 043072 162716 000002 SUB #2,(SP) ;MOVE SP TO ERROR RETURN
9508 043076 004736 JSR PC,@(SP)+ ;REPORT ERROR AND RETURN
9509 043100 162716 000010 SUB #10,(SP) ;MOVE SP TO NO ERROR
9510 043104 170\$:
9511
9512 ;REPORT ERROR IF NEM IS SET AND READ/WRITE ERRORS ARE NOT ENABLED
9513 043104 012746 177777 MOV #-1,-(SP) ;ASSUME ERRORS ARE ENABLED
9514 043110 032737 001000 045176 BIT #AOE,500\$;ARE ERRORS ENABLED ??
9515 043116 001002 BNE 175\$;YES !!
9516 043120 042716 004000 BIC #NEM,(SP) ;DISABLE NEM
9517 043124 013737 001340 001142 175\$: MOV RMCS21,\$BDDAT ;GET RECEIVED STATUS
9518 043132 042637 001142 BIC (SP)+,\$BDDAT ;CLEAR NEM IF ENABLED
9519 043136 001412 BEQ 180\$;BRANCH IF NEM IS OK
9520 043140 062716 000004 ADD #4,(SP) ;MOVE SP TO USERS ERROR CALL
9521 043144 112776 000167 000000 MOVB #167,@(SP) ;WRITE ERROR NUMBER IN CALL
9522 043152 162716 000002 SUB #2,(SP) ;MOVE SP TO ERROR RETURN
9523 043156 004736 JSR PC,@(SP)+ ;REPORT ERROR AND RETURN
9524 043160 162716 000010 SUB #10,(SP) ;MOVE SP TO NO ERROR


```
9525 043164 180$:
9526
9527 ;REPORT ERROR IF MXF IS SET AND READ/WRITE ERRORS ARE NOT ENABLED
9528 043164 012746 177777 MOV #-1,-(SP) ;ASSUME ERRORS ARE ENABLED
9529 043170 032737 001000 045176 BIT #AOE,500$ ;ARE DATA ERRORS ENABLED ??
9530 043176 001002 BNE 185$ ;YES !!
9531 043200 042716 001000 BIC #MXF,(SP) ;DISABLE MXF ERROR
9532 043204 013737 001340 001142 185$: MOV RMCS21,$BDDAT ;GET RECEIVED STATUS
9533 043212 042637 001142 BIC (SP)+,$BDDAT ;CLEAR MXF IF ENABLED
9534 043216 001412 BEQ 190$ ;BRANCH IF MXF IS OK
9535 043220 062716 000004 ADD #4,(SP) ;MOVE SP TO USERS ERROR CALL
9536 043224 112776 000033 000000 MOVB #33,@(SP) ;WRITE ERROR NUMBER IN CALL
9537 043232 162716 000002 SUB #2,(SP) ;MOVE SP TO ERROR RETURN
9538 043236 004736 JSR PC,@(SP)+ ;REPORT ERROR AND RETURN
9539 043240 162716 000010 SUB #10,(SP) ;MOVE SP TO NO ERROR
9540 043244 190$:
9541
9542 ;REPORT ERROR IF AOE IS SET AND DATA ERRORS ARE NOT ENABLED
9543 043244 012746 177777 MOV #-1,-(SP) ;ASSUME DATA ERRORS ARE ENABLED
9544 043250 032737 001000 045176 BIT #AOE,500$ ;ARE DATA ERRORS EAMBLED ??
9545 043256 001404 BEQ 191$ ;NO !!
9546 043260 032737 002000 001342 BIT #LBT,RMDS1 ;IS LBT ALSO SET ??
9547 043266 001002 BNE 195$ ;YES !!
9548 043270 042716 001000 191$: BIC #AOE,(SP) ;DISABLE AOE
9549 043274 013737 001344 001142 195$: MOV RMER11,$BDDAT ;GET RECEIVED STATUS
9550 043302 042637 001142 BIC (SP)+,$BDDAT ;CLEAR AOE IF ENABLED
9551 043306 001412 BEQ 200$ ;BRANCH IF AOE IS OK
9552 043310 062716 000004 ADD #4,(SP) ;MOVE SP TO USERS ERROR CALL
9553 043314 112776 000020 000000 MOVB #20,@(SP) ;WRITE ERROR NUMBER
9554 043322 162716 000002 SUB #2,(SP) ;MOVE SP TO ERROR RETURN
9555 043326 004736 JSR PC,@(SP)+ ;REPORT ERROR AND RETURN
9556 043330 162716 000010 SUB #10,(SP) ;MOVE SP TO NO ERROR
9557 043334 200$:
9558
9559 ;BIT 07 (HCE) OF THE FUNCTION CODE TABLE IS THE ENABLING BIT FOR
9560 ;HEADER ERRORS, I.E.,
9561 ; RMER1 - HCRC,HCE,FER
9562 ; RMER2 - BSE
9563
9564 ;RESET THE ENABLING BIT (HCE) IF HEADER COMPARE INHIBIT IS SET
9565 043334 032737 002000 001362 BIT #HCI,RMOFI ;IS HCI SET ??
9566 043342 001403 BEQ 201$ ;NO !!
9567 043344 042737 000200 045176 BIC #HCE,500$ ;YES - DISABLE ALL HEADER ERRORS
9568 043352 201$:
9569
9570 ;REPORT AN ERROR IF HCRC IS SET AND HEADER ERRORS ARE NOT ENABLED
9571 043352 012746 177777 MOV #-1,-(SP) ;ASSUME ERRORS ENABLED
9572 043356 032737 000200 045176 BIT #HCE,500$ ;ARE HEADER ERRORS ENABLED ??
9573 043364 001002 BNE 205$ ;YES !!
9574 043366 042716 000400 BIC #HCRC,(SP) ;DISABLE HCRC
9575 043372 013737 001344 001142 205$: MOV RMER11,$BDDAT ;GET RECEIVED STATUS
9576 043400 042637 001142 BIC (SP)+,$BDDAT ;RESET HCRC IF ENABLED
9577 043404 001412 BEQ 210$ ;BRANCH IF HCRC IS OK
9578 043406 062716 000004 ADD #4,(SP) ;MOVE SP TO USERS ERROR CALL
9579 043412 112776 000035 000000 MOVB #35,@(SP) ;WRITE ERROR NUMBER IN CALL
9580 043420 162716 000002 SUB #2,(SP) ;MOVE SP TO ERROR RETURN
```

```

9581 043424 004736          JSR    PC,@(SP)+      ;REPORT ERROR AND RETURN
9582 043426 162716 000010    SUB    #10,(SP)      ;MOVE SP TO NO ERROR
9583 043432          210$:
9584
9585          ;REPORT ERROR IF HCE IS SET AND HEADER ERRORS ARE NOT ENABLED
9586 043432 012746 177777    MOV    #-1,-(SP)      ;ASSUME ERRORS ENABLED
9587 043436 032737 000200 045176 BIT    #HCE,500$      ;ARE ERRORS ENABLED ??
9588 043444 001002          BNE    215$          ;YES !!
9589 043446 042716 000200    BIC    #HCE,(SP)      ;DISABLE HCE
9590 043452 013737 001344 001142 215$: MOV    RMER11,$BDDAT ;GET RECEIVED STATUS
9591 043460 042637 001142    BIC    (SP)+,$BDDAT ;CLEAR HCE IF ENABLED
9592 043464 001412          BEQ    220$          ;BRANCH IF HCE IS OK
9593 043466 062716 000004    ADD    #4,(SP)      ;MOVE SP TO USERS ERROR CALL
9594 043472 112776 000036 000000    MOVB  #36,@(SP)    ;WRITE ERROR NUMBER IN CALL
9595 043500 162716 000002    SUB    #2,(SP)      ;MOVE SP TO ERROR RETURN
9596 043504 004736          JSR    PC,@(SP)+      ;REPORT ERROR AND RETURN
9597 043506 162716 000010    SUB    #10,(SP)      ;MOVE SP TO NO ERROR
9598 043512          220$:
9599
9600          ;REPORT ERROR IF FER IS SET AND HEADER ERRORS ARE NOT ENABLED
9601 043512 012746 177777    MOV    #-1,-(SP)      ;ASSUME FER IS ENABLED
9602 043516 032737 000200 045176 BIT    #HCE,500$      ;ARE HEADER ERRORS ENABLED ??
9603 043524 001002          BNE    225$          ;YES !!
9604 043526 042716 000020    BIC    #FER,(SP)      ;DISABLE FER
9605 043532 013737 001344 001142 225$: MOV    RMER11,$BDDAT ;GET RECEIVED STATUS
9606 043540 042637 001142    BIC    (SP)+,$BDDAT ;RESET FER IF ENABLED
9607 043544 001412          BEQ    230$          ;BRANCH IF FER OK
9608 043546 062716 000004    ADD    #4,(SP)      ;MOVE SP TO USERS ERROR CALL
9609 043552 112776 000037 000000    MOVB  #37,@(SP)    ;WRITE ERROR NUMBER IN CALL
9610 043560 162716 000002    SUB    #2,(SP)      ;MOVE SP TO ERROR RETURN
9611 043564 004736          JSR    PC,@(SP)+      ;REPORT ERROR AND RETURN
9612 043566 162716 000010    SUB    #10,(SP)      ;MOVE SP TO NO ERROR
9613 043572          230$:
9614
9615          ;REPORT ERROR IF BSE IS SET AND HEADER ERRORS ARE NOT ENABLED
9616 043572 012746 177777    MOV    #-1,-(SP)      ;ASSUME ERRORS ENABLED
9617 043576 032737 000200 045176 BIT    #HCE,500$      ;ARE THEY ENABLED ??
9618 043604 001002          BNE    235$          ;YES !!
9619 043606 042716 100000    BIC    #BSE,(SP)      ;DISABLE BSE
9620 043612 013737 001372 001142 235$: MOV    RMER21,$BDDAT ;GET RECEIVED STATUS
9621 043620 042637 001142    BIC    (SP)+,$BDDAT ;CLEAR BSE IF ENABLED
9622 043624 001412          BEQ    240$          ;BRANCH IF BSE OK
9623 043626 062716 000004    ADD    #4,(SP)      ;MOVE SP TO USERS ERROR CALL
9624 043632 112776 000354 000000    MOVB  #354,@(SP)   ;WRITE ERROR NUMBER
9625 043640 162716 000002    SUB    #2,(SP)      ;MOVE SP TO ERROR RETURN
9626 043644 004736          JSR    PC,@(SP)+      ;REPORT ERROR AND RETURN
9627 043646 162716 000010    SUB    #10,(SP)      ;MOVE SP TO NO ERROR
9628 043652          240$:
9629
9630          ;BIT 06 OF THE FUNCTION CODE TABLE IS THE ENABLING BIT FOR DATA
9631          ;FIELD ERRORS, I.E.,
9632          ;   RMCS2 - MDPE
9633          ;   RMER1 - DCK,ECH
9634          ;NOTE:
9635          ;   ECH CANNOT SET UNLESS IT IS ENABLED AND ECI IS RESET AND
9636          ;   DCK IS SET.

```

```
9637
9638 ;REPORT ERROR IF MDPE IS SET AND IS NOT ENABLED
9639 043652 012746 177777 MOV #1,-(SP) ;ASSUME ENABLED
9640 043656 032737 000100 045176 BIT #ECH,500$ ;ARE DATA FIELD ERRORS ENABLED ??
9641 043664 001002 BNE 245$ ;YES !!
9642 043666 042716 000400 BIC #MDPE,(SP) ;DISABLE MDPE
9643 043672 013737 001340 001142 245$: MOV RMCS21,$BDDAT ;GET RECEIVED STATUS
9644 043700 042637 001142 BIC (SP)+,$BDDAT ;CLEAR MDPE IF ENABLED
9645 043704 001412 BEQ 250$ ;BRANCH IF MDPE OK
9646 043706 062716 000004 ADD #4,(SP) ;MOVE SP TO USERS ERROR CALL
9647 043712 112776 000027 000000 MOV #27,@(SP) ;WRITE ERROR NUMBER IN CALL
9648 043720 162716 000002 SUB #2,(SP) ;MOVE SP TO ERROR RETURN
9649 043724 004736 JSR PC,@(SP)+ ;REPORT ERROR AND RETURN
9650 043726 162716 000010 SUB #10,(SP) ;MOVE SP TO NO ERROR
9651 043732 250$:
9652
9653 ;REPORT ERROR IF DCK IS SET AND DATA FIELD ERRORS ARE NOT ENABLED
9654 043732 012746 177777 MOV #1,-(SP) ;ASSUME ENABLED
9655 043736 032737 000100 045176 BIT #ECH,500$ ;ARE THEY ENABLED ??
9656 043744 001002 BNE 255$ ;YES !!
9657 043746 042716 100000 BIC #DCK,(SP) ;DISABLE DCK
9658 043752 013737 001344 001142 255$: MOV RMER11,$BDDAT ;GET RECEIVED STATUS
9659 043760 042637 001142 BIC (SP)+,$BDDAT ;CLEAR DCK IF ENABLED
9660 043764 001412 BEQ 260$ ;BRANCH IF DCK IS OK
9661 043766 062716 000004 ADD #4,(SP) ;MOVE SP TO USERS ERROR CALL
9662 043772 112776 000030 000000 MOV #30,@(SP) ;WRITE ERROR NUMBER IN CALL
9663 044000 162716 000002 SUB #2,(SP) ;MOVE SP TO ERROR RETURN
9664 044004 004736 JSR PC,@(SP)+ ;REPORT ERROR AND RETURN
9665 044006 162716 000010 SUB #10,(SP) ;MOVE SP TO NO ERROR
9666 044012 260$:
9667
9668 ;REPORT ERROR IF ECH IS SET AND,
9669 ;DATA FIELD ERRORS ARE NOT ENABLED, OR
9670 ;ECI IS SET, OR
9671 ;DCK IS NOT SET.
9672 044012 012746 177777 MOV #1,-(SP) ;ASSUME ENABLED
9673 044016 032737 000100 045176 BIT #ECH,500$ ;ARE ERRORS ENABLED ??
9674 044024 001410 BEQ 265$ ;NO !!
9675 044026 032737 004000 001362 BIT #ECI,RMOF1 ;IS ECI SET ??
9676 044034 001004 BNE 265$ ;YES !!
9677 044036 032737 100000 001344 BIT #DCK,RMER11 ;IS DCK ALSO SET ??
9678 044044 001002 BNE 270$ ;YES !!
9679 044046 042716 000100 265$: BIC #ECH,(SP) ;DISABLE ECH
9680 044052 013737 001344 001142 270$: MOV RMER11,$BDDAT ;GET RECEIVED STATUS
9681 044060 042637 001142 BIC (SP)+,$BDDAT ;CLEAR ECH IF ENABLED
9682 044064 001412 BEQ 275$ ;BRANCH IF ECH IS OK
9683 044066 062716 000004 ADD #4,(SP) ;MOVE SP TO USERS ERROR CALL
9684 044072 112776 000031 000000 MOV #31,@(SP) ;WRITE ERROR NUMBER IN CALL
9685 044100 162716 000002 SUB #2,(SP) ;MOVE SP TO ERROR RETURN
9686 044104 004736 JSR PC,@(SP)+ ;REPORT ERROR AND RETURN
9687 044106 162716 000010 SUB #10,(SP) ;MOVE SP TO NO ERROR
9688 044112 275$:
9689
9690 ;*****
9691 ;PERFORM THE REMAINING ERROR CHECKS ONLY FOR DATA TRANSFER COMMANDS
9692
```

CZRMDCO RM03/2 FCTNL TST 2
CZRMDC.P11 12-DEC-78 08:24

MACY11 30A(1052) 04-JAN-79 11:23 PAGE 195
SECONDARY ERROR CHECK SUBROUTINE

SEQ 0195

9693	044112	022737	000030	045204	CMP	#SEARCH,515\$	:WAS DATA TRANSFERRED??
9694	044120	103402			BLO	280\$	:YES!!
9695	044122	000137	045150		JMP	355\$	
9696							

```

9697 ;THE FOLLOWING STATUS CHECKS ARE FOR DATA TRANSFER COMMANDS ONLY
9698 ;REPORT ERROR IF RMWC NOT ZERO AND TRE IS ZERO
9699 044126 013737 001332 001142 280$: MOV RMWC1,$BDDAT ;WORD COUNT ZERO??
9700 044134 001421 BEQ 285$ ;YES
9701 044136 032737 040000 001330 BIT #TRE,RMCS11 ;TRANSFER ERROR DETECTED??
9702 044144 001015 BNE 285$ ;YES!!
9703 044146 062716 000004 ADD #4,(SP)
9704 044152 112776 000015 000000 MOVB #15,@(SP) ;ERROR NUMBER
9705 044160 005037 001140 CLR $GDDAT ;GOOD DATA FOR TYPEOUT
9706 044164 162716 000002 SUB #2,(SP) ;MOVE SP TO RETURN FOR ERROR
9707 044170 004736 JSR PC,@(SP)+ ;REPORT WORD COUNT NOT ZERO
9708 044172 162716 000010 SUB #10,(SP) ;RESTORE (SP)
9709 044176 000240 NOP
9710 ;REPORT ERROR IF RMBA IS NOT CORRECT
9711 044200 013737 001332 001140 285$: MOV RMWC1,$GDDAT ;NUMBER OF WORDS TRANSFERRED
9712 044206 163737 001402 001140 SUB RMWC0,$GDDAT
9713 044214 006337 001140 ASL $GDDAT
9714 044220 063737 001140 ADD RMBA0,$GDDAT ;EXPECTED BUS ADDRESS
9715 044226 032737 001340 BIT #BA1,RMCS21 ;WAS BAI SET ??
9716 044234 001403 BEQ 290$ ;NO !!
9717 044236 013737 001404 001140 MOV RMBA0,$GDDAT ;ADDRESS SHOULD NOT HAVE CHANGED
9718 044244 023737 001140 001334 290$: CMP $GDDAT,RMBA1 ;BUS ADDRESS OK??
9719 044252 001416 BEQ 295$ ;YES!!
9720 044254 013737 001334 001142 MOV RMBA1,$BDDAT ;BAD DATA FOR TYPEOUT
9721 044262 062716 000004 ADD #4,(SP)
9722 044266 112776 000016 000000 MOVB #16,@(SP) ;ERROR NUMBER
9723 044274 162716 000002 SUB #2,(SP) ;MOVE SP TO RETURN FOR ERROR
9724 044300 004736 JSR PC,@(SP)+ ;REPORT UNEXPECTED ADDRESS
9725 044302 162716 000010 SUB #10,(SP) ;RESTORE (SP)
9726 044306 000240 NOP
9727 ;COMPUTE NUMBER OF SECTORS TRANSFERRED
9728 044310 005046 295$: CLR -(SP) ;NUMBER OF SECTORS TRANSFERRED
9729 044312 013746 001332 MOV RMWC1,-(SP) ;NUMBER OF WORDS TRANSFERRED
9730 044316 163716 001402 SUB RMWC0,(SP)
9731 044322 012746 000400 MOV #256,-(SP) ;NUMBER OF WORDS PER SECTOR
9732 044326 032737 000002 001400 BIT #BIT1,RMCS10 ;HEADER & DATA COMMAND ??
9733 044334 001402 BEQ 300$ ;NO !!
9734 044336 012716 000402 MOV #258,(SP) ;YES - CHANGE WORDS PER SECTOR
9735 044342 005266 000004 300$: INC 4(SP) ;INCREMENT SECTOR COUNT
9736 044346 161666 000002 SUB (SP),2(SP) ;SUBTRACT ONE SECTOR'S WORTH
9737 044352 003373 BGT 300$ ;CONTINUE IF NOT DONE
9738 044354 022626 CMP (SP)+,(SP)+ ;STRIP 2 FROM STACK
9739 ;COMPUTE EXPECTED SECTOR, TRACK AND CYLINDER ADDRESS FROM NUMBER OF SECTORS
9740 044356 013737 001406 045202 MOV RMDAO,510$ ;STORE ORIGINAL SECTOR
9741 044364 013737 001406 045200 MOV RMDAO,505$ ;STORE ORIGINAL TRACK
9742 044372 013737 001434 045176 MOV RMDCO,500$ ;STORE ORIGINAL CYLINDER
9743 044400 042737 177740 045202 BIC #^C37,510$
9744 044406 000337 045200 SWAB 505$
9745 044412 042737 177770 045200 BIC #^C7,505$
9746 044420 062637 045202 ADD (SP)+,510$
9747
9748 044424 023727 045202 000040 305$: CMP 510$,#32. ;SECTOR OVEFLOWED??
9749 044432 103420 BLO 315$ ;NO!!
9750 044434 023727 045202 000240 CMP 510$,#<5*32.> ;CYLINDERS WORTH??
9751 044442 103406 BLO 310$ ;NO!!
9752 044444 005237 045176 INC 500$ ;YES INCREMENT CYLINDER

```

```

9753 044450 162737 000240 045202 SUB #<5*32.>,510$ ;ADJUST SECTOR
9754 044456 000762 BR 305$ ;TRY AGAIN
9755 044460 005237 045200 310$: INC 505$ ;INCREMENT TRACK
9756 044464 162737 000040 045202 SUB #32.,510$ ;ADJUST SECTOR
9757 044472 000754 BR 305$ ;TRY AGAIN
9758
9759 044474 023727 045200 000005 315$: CMP 505$,#5 ;TRACK OVERFLOWED??
9760 044502 103406 BLO 320$ ;NO!!
9761 044504 005237 045176 INC 500$ ;INCREMENT CYLINDER
9762 044510 162737 000005 045200 SUB #5,505$ ;ADJUST TRACK
9763 044516 000766 BR 315$ ;TRY AGAIN
9764 ;REPORT ERROR IF "LBT" IS NOT CORRECT
9765 044520 005037 001140 320$: CLR $GDDAT ;SET GOOD DATA FOR LBT=0
9766 044524 022737 001467 045176 CMP #823.,500$ ;SHOULD LBT BE SET??
9767 044532 101007 BHI 325$ ;NO!!
9768 044534 032737 002000 001344 BIT #IAE,RMER1 ;WAS IAE SET ??
9769 044542 001003 BNE 325$ ;YES - LBT SHOULD NOT BE SET
9770 044544 012737 002000 001140 MOV #LBT,$GDDAT ;SET GOOD DATA FOR LBT=1
9771 044552 013737 001342 001142 325$: MOV RMDS1,$BDDAT ;BAD DATA FOR TYPEOUT
9772 044560 042737 175777 001142 BIC #^CLBT,$BDDAT
9773 044566 023737 001140 001142 CMP $GDDAT,$BDDAT ;IS LBT CORRECT??
9774 044574 001413 BEQ 330$ ;YES!!
9775 044576 062716 000004 ADD #4,(SP)
9776 044602 112776 000017 000000 MOVB #17,@(SP) ;ERROR NUMBER
9777 044610 162716 000002 SUB #2,(SP) ;MOVE SP TO RETURN FOR ERROR
9778 044614 004736 JSR PC,@(SP)+ ;REPORT LBT IS WRONG
9779 044616 162716 000010 SUB #10,(SP) ;RESTORE (SP)
9780 044622 000240 NOP
9781 ;REPORT ERROR IF "AOE" IS INCORRECT
9782 044624 005037 001140 330$: CLR $GDDAT ;SET FOR AOE=0
9783 044630 032737 002000 001344 BIT #IAE,RMER1 ;WAS "IAE" DETECTED??
9784 044636 001031 BNE 340$ ;YES-"AOE" SHOULD BE ZERO
9785 044640 022737 001467 045176 CMP #823.,500$ ;SHOULD AOE BE SET??
9786 044646 101025 BHI 340$ ;NO!!
9787 044650 005737 045200 TST 505$ ;MAYBE
9788 044654 001012 BNE 335$ ;YES
9789 044656 005737 045202 TST 510$
9790 044662 001007 BNE 335$ ;YES !!
9791 044664 032737 000010 045204 BIT #F2,515$ ;WAS THIS READ OR WRITE CHECK ??
9792 044672 001413 BEQ 340$ ;NO !!
9793 044674 005737 001332 TST RMWC1 ;WAS ALL DATA TRANSFERRED ??
9794 044700 001410 BEQ 340$ ;YES !!
9795 044702 012737 001000 001140 335$: MOV #AOE,$GDDAT ;SET FOR AOE=1
9796 044710 005037 045200 CLR 505$ ;CLEAR EXPECTED TRACK
9797 044714 012737 000001 045202 MOV #1,510$ ;EXPECT SECTOR=1
9798 044722 013737 001344 001142 340$: MOV RMER1,$BDDAT ;BAD DATA FOR TYPEOUT
9799 044730 042737 176777 001142 BIC #^CAOE,$BDDAT
9800 044736 023737 001140 001142 CMP $GDDAT,$BDDAT ;IS AOE CORRECT??
9801 044744 001413 BEQ 345$ ;YES!!
9802 044746 062716 000004 ADD #4,(SP)
9803 044752 112776 000020 000000 MOVB #20,@(SP) ;ERROR NUMBER
9804 044760 162716 000002 SUB #2,(SP) ;MOVE SP TO RETURN FOR ERROR
9805 044764 004736 JSR PC,@(SP)+ ;REPORT AOE IS WRONG
9806 044766 162716 000010 SUB #10,(SP) ;RESTORE (SP)
9807 044772 000240 NOP
9808 ;REPORT ERROR IF RMDA IS NOT CORRECT

```



```

9809 044774 032737 002000 001344 345$: BIT #IAE,RMER11 ;WAS THERE AN IAE ERROR ??
9810 045002 001062 BNE 355$ ;YES - DONT CHECK RMDA,RMDC
9811 045004 013737 045200 001140 MOV 505$,$GDDAT ;SETUP EXPECTED DISK ADDRESS
9812 045012 000337 001140 SWAB $GDDAT
9813 045016 113737 045202 001140 MOVB 510$,$GDDAT
9814 045024 013737 001336 001142 MOV RMDA1,$BDDAT ;SETUP RECEIVED DISK ADDRESS
9815 045032 023737 001140 001142 CMP $GDDAT,$BDDAT ;COMPARE EXPECTED & RECEIVED
9816 045040 001413 BEQ 350$ ;BRANCH IF EQUAL
9817 045042 062716 000004 ADD #4,(SP)
9818 045046 112776 000021 000000 MOVB #21,@(SP) ;ERROR NUMBER
9819 045054 162716 000002 SUB #2,(SP) ;MOVE SP TO RETURN FOR ERROR
9820 045060 004736 JSR PC,@(SP)+ ;REPORT BAD DISK ADDRESS
9821 045062 162716 000010 SUB #10,(SP) ;RESTORE (SP)
9822 045066 000240 NOP
9823 ;REPORT ERROR IF RMDC IS INCORRECT
9824 045070 013737 045176 001140 350$: MOV 500$,$GDDAT ;SETUP EXPECTED CYLINDER
9825 045076 042737 176000 001140 BIC #^C1777,$GDDAT
9826 045104 013737 001364 001142 MOV RMDC1,$BDDAT ;SETUP RECEIVED CYLINDER
9827 045112 023737 001140 001142 CMP $GDDAT,$BDDAT ;COMPARE CYLINDERS
9828 045120 001413 BEQ 355$ ;BRANCH IF EQUAL
9829 045122 062716 000004 ADD #4,(SP)
9830 045126 112776 000022 000000 MOVB #22,@(SP) ;ERROR NUMBER
9831 045134 162716 000002 SUB #2,(SP) ;MOVE SP TO RETURN FOR ERROR
9832 045140 004736 JSR PC,@(SP)+ ;REPORT BAD CYLINDER
9833 045142 162716 000010 SUB #10,(SP) ;RESTORE (SP)
9834 045146 000240 NOP
  
```

CZRMDCO RM03/2 FCTNL TST 2
CZRMDC.P11 12-DEC-78 08:24

E 16
MACY11 30A(1052) 04-JAN-79 11:23 PAGE 199
SECONDARY ERROR CHECK SUBROUTINE

SEQ 0199

9835	045150	062716	000004	355\$:	ADD	#4,(SP)	;MOVE (SP) TO ERROR CALL
9836	045154	105776	000000		TSTB	@(SP)	;WAS ERROR FOUND??
9837	045160	001403			BEQ	360\$	
9838	045162	062716	000004		ADD	#4,(SP)	;MOVE (SP) TO ERROR RETURN
9839	045166	000402			BR	365\$	
9840	045170	162716	000004	360\$:	SUB	#4,(SP)	;MOVE (SP) TO NO ERROR RETURN
9841	045174	000207		365\$:	RTS	PC	
9842							
9843	045176	000000		500\$:	.WORD	0	;CYLINDER
9844	045200	000000		505\$:	.WORD	0	;TRACK
9845	045202	000000		510\$:	.WORD	0	;SECTOR
9846	045204	000000		515\$:	.WORD	0	;FUNCTION CODE
9847							
9848							


```

9849      .SBTTL  DEVICE SELECT SUBROUTINE
9850
9851      ; THIS SUBROUTINE SELECTS THE DEVICE, GETTING THE DEVICE NUMBER FROM THE
9852      ; TEST QUEUE.
9853
9854      ;CALL:
9855      ;(1)   JSR      PC,DEVSEL
9856      ;(2)   BR       ??
9857      ;(3)   NOP
9858      ;(4)   ERROR
9859
9860      DEVSEL:
9861
9862      ;CLEAR USER'S ERROR CALL
9863      ADD     #4,(SP)      ;MOVE SP TO USER'S ERROR
9864      CLRB    @2(SP)      ;CLEAR LOW ORDER BYTE OF CALL
9865      SUB     #4,(SP)      ;MOVE SP BACK
9866
9867      ;SAVE USER'S INFORMATION AND SETUP REGISTERS
9868      MOV     ERRVEC,-(SP)  ;PUSH ERRVEC ON STACK
9869      MOV     ERRVEC+2,-(SP) ;PUSH ERRVEC+2 ON STACK
9870      MOV     R0,-(SP)     ;PUSH R0 ON STACK
9871      MOV     R1,-(SP)     ;PUSH R1 ON STACK
9872      MOV     #20$,ERRVEC  ;SETUP FOR BUS TIMEOUT
9873      MOV     #PR6,ERRVEC+2
9874      MOV     $BASE,R0    ;R0 = UNIBUS ADDRESS
9875      MOV     TSTQUE,R1   ;R1 POINTS TO DEVICE NUMBER
9876
9877      ;SELECT DEVICE AND VERIFY THAT DEVICE IS AVAILABLE
9878      MOVB    (R1),RMCS2(R0) ;WRITE UNIT SELECT BITS
9879      MOV     RMCS1(R0),$TMP1 ;GET 'DVA' STATUS
9880      MOV     RMCS2(R0),$TMP0 ;GET 'NED' STATUS
9881      BIT     #NED,$TMP0     ;IS DEVICE NONEXISTENT??
9882      BEQ     10$           ;NO!!
9883      ADD     #4,10(SP)      ;MOVE SP TO USERS ERROR CALL
9884      MOVB    #111,@10(SP)  ;WRITE ERROR NUMBER
9885      BR      30$
9886      BIT     #DVA,$TMP1     ;IS DEVICE AVAILABLE??
9887      BNE     35$           ;YES!!
9888      ADD     #4,10(SP)
9889      MOVB    #112,@10(SP)
9890      BR      30$
9891
9892      20$:
9893      ;HANDLE BUS TIMEOUT
9894      CMP     (SP)+,(SP)+    ;ADJUST SP
9895      ADD     #4,10(SP)
9896      MOVB    #113,@10(SP)
9897      SUB     #2,10(SP)      ;MOVE SP TO RETURN IF ERROR
9898
9899      30$:
9900
9901      ;RESTORE USERS DATA AND RETURN TO ADDRESS ON STACK
9902      MOV     (SP)+,R1      ;POP STACK INTO R1
9903      MOV     (SP)+,R0      ;POP STACK INTO R0
9904

```

CZRMDCO RM03/2 FCTNL TST 2
CZRMDC.P11 12-DEC-78 08:24

MACY11 30A(1052) 04-JAN-79 11:23 6 16
PAGE 201
DEVICE SELECT SUBROUTINE

SEQ 0201

9905 045406 012637 000006
9906 045412 012637 000004
9907 045416 000207

MOV (SP)+,ERRVEC+2 ;:POP STACK INTO ERRVEC+2
MOV (SP)+,ERRVEC ;:POP STACK INTO ERRVEC
RTS PC ;EXIT

```
9908 .SBTTL SEEK STATUS CHECK SUBROUTINE
9909 ;
9910 ;THIS SUBROUTINE VERIFIES THE RESULTS OF SEEK TESTS USING STATUS
9911 ;STORED IN THE GET BUFFER AND TEST PARAMETERS STORED IN THE PUT BUFFER.
9912 ;
9913 ;
9914 ;THE SUBROUTINE RETURNS TO THE CALLING ROUTINE IF AN ERROR IS DETECTED
9915 ;AFTER HAVING LOADED THE APPROPRIATE ERROR NUMBER IN THE 'ERROR' TRAP
9916 ;OF THE CALLING ROUTINE. SEEK STATUS IS CHECKED AS FOLLOWS:
9917 ;
9918 ;CALL:
9919 ;(1) JSR PC,SEKSTS
9920 ; BR ??? RETURN HERE IF NO ERROR
9921 ; NOP RETURN HERE TO REPORT AN ERROR
9922 ; ERROR ERROR NUMBER DEFINED BY SUB
9923 ; JSR PC,@(SP)+ GO BACK TO SUB FOR MORE ERROR CHECKS
9924 ; ??? RETURN HERE IF NO MORE ERRORS
9925 ;
9926 045420 SEKSTS:
9927 ;
9928 ;CLEAR USER'S ERROR CALL
9929 045420 000240 NOP
9930 045422 062716 000004 ADD #4,(SP) ;MOVE (SP) TO ERROR CALL
9931 045426 105076 000000 CLRB @(SP) ;CLEAR ERROR NUMBER
9932 045432 162716 000004 SUB #4,(SP) ;MOVE (SP) TO NO ERROR RETURN
9933 045436 005037 046656 CLR 300$ ;CLEAR ERROR FLAGS
9934 ;
9935 ;TEST FOR MASSBUS CONTROL BUS PARITY ERROR WHEN WRITING
9936 ;LOCAL REGISTERS, I.E., 'PAR' = 1 AND 'DPE' = 0
9937 045442 032737 000010 001344 BIT #PAR,RMER11 ;WAS PARITY ERROR DETECTED??
9938 045450 001424 BEQ 1$ ;NO!!
9939 045452 032737 000010 001372 BIT #DPE,RMER21 ;WAS IT DUE TO CONTROL BUS??
9940 045460 001020 BNE 1$ ;NOT SURE!!
9941 ;
9942 ;REPORT REGISTER PARITY ERROR VIA USER'S ERROR CALL
9943 045462 005037 001140 CLR $GDDAT ;EXPECTED STATUS
9944 045466 013737 001344 001142 MOV RMER11,$BDDAT ;RECEIVED STATUS
9945 045474 062716 000004 ADD #4,(SP) ;MOVE STACK TO USER'S ERROR
9946 045500 112776 000050 000000 MOVB #50,@(SP) ;ERROR #50
9947 045506 162716 000002 SUB #2,(SP) ;MOVE SP TO RETURN FOR ERROR
9948 045512 004736 JSR PC,@(SP)+
9949 045514 162716 000010 SUB #10,(SP) ;RESTORE STACK
9950 045520 000437 BR 3$ ;IAE SHOULD BE ZERO
9951 ;
9952 ;
9953 ;DETERMINE THE VALUE OF 'IAE' STATUS BASED ON TRACK,SECTOR AND
9954 ;CYLINDER ADDRESS USED DURING SEEK OPERATION
9955 045522 012737 002000 001140 1$: MOV #IAE,$GDDAT ;SET UP FOR IAE = 1
9956 045530 052737 040000 046656 BIS #SKI,300$ ;SET SKI ERROR FLAG
9957 045536 023727 001434 001466 CMP RMDCO,#822. ;CYLINDER > 822??
9958 045544 101025 BHI 3$ ;YES!!
9959 045546 042737 040000 046656 BIC #SKI,300$ ;CLEAR SKI ERROR FLAG
9960 045554 123727 001406 000037 CMPB RMDAO,#31. ;SECTOR > 31??
9961 045562 101016 BHI 3$ ;YES!!
9962 045564 123727 001406 000035 CMPB RMDAO,#29. ;SECTOR > 29 ??
9963 045572 101404 BLOS 2$ ;NO!!
```

```

9964 045574 032737 010000 001432      BIT      #FMT16,RMOFO      ;30 SECTOR FORMAT??
9965 045602 001406      BEQ      3$              ;YES!!
9966 045604 123727 001407 000004 2$:    CMPB     RMDAO+1,#4.      ;TRACK >4??
9967 045612 101002      BHI      3$              ;YES!!
9968 045614 005037 001140      CLR      $GDDAT      ;"IAE" SHOULD BE 0
9969
9970      ;COMPARE EXPECTED AND RECEIVED "IAE" STATUS
9971 045620 013737 001344 001142 3$:    MOV      RMER11,$BDDAT      ;IS IAE OK??
9972 045626 042737 175777 001142      BIC      #^CIAE,$BDDAT
9973 045634 023737 001140 001142      CMP      $GDDAT,$BDDAT
9974 045642 001004      BNE      35$              ;IAE IN ERROR
9975 045644 042737 040000 046656      BIC      #SKI,300$      ;CLEAR SKI FLAG
9976 045652 000413      BR       5$              ;GO CHECK NEXT ERROR
9977 045654
9978      35$:
9979      ;REPORT INCORRECT "IAE" STATUS VIA USER'S ERROR CALL
9980 045654 062716 000004      ADD      #4,(SP)
9981 045660 112776 000051 000000      MOVB     #51,@(SP)      ;ERROR 51
9982 045666 162716 000002      SUB      #2,(SP)      ;MOVE SP TO RETURN FOR ERROR
9983 045672 004736      JSR      PC,@(SP)+      ;REPORT INCORRECT IAE
9984 045700 000240      SUB      #10,(SP)      ;RESTORE (SP)
9985 045702
9986
9987      5$:
9988      ;REPORT ANY IVC ERROR AS
9989      ; IVC ERROR WITH VOLUME VALID ZERO
9990      ; ERRONEOUS IVC ERROR, VOLUME VALID IS SET
9991 045702 032737 010000 001372      BIT      #IVC,RMER21      ;IVC ERROR??
9992 045710 001427      BEQ      52$              ;NO!!
9993 045712 005037 001140      CLR      $GDDAT      ;EXPECTED STATUS
9994 045716 013737 001372 001142      MOV      RMER21,$BDDAT      ;RECEIVED STATUS
9995 045724 062716 000004      ADD      #4,(SP)      ;MOVE SP TO USER'S ERROR
9996 045730 112776 000060 000000      MOVB     #60,@(SP)      ;ERROR 60 IF VV = 0
9997 045736 032737 000100 001342      BIT      #VV,RMDSI
9998 045744 001403      BEQ      51$              ;ERROR 61 IF VV = 1
9999 045746 112776 000061 000000 51$:    MOVB     #61,@(SP)      ;MOVE SP TO RETURN FOR ERROR
10000 045754 162716 000002      SUB      #2,(SP)      ;REPORT ERROR VIA USER
10001 045760 004736      JSR      PC,@(SP)+      ;RESTORE SP
10002 045762 162716 000010      SUB      #10,(SP)
10003 045766 000240      NOP
10004
10004 045770 013737 001372 001142 52$:    MOV      RMER21,$BDDAT      ;RECEIVED STATUS
10005 045776 042737 137777 001142      BIC      #^CSKI,$BDDAT      ;CLEAR DONT CARES
10006 046004 013737 046656 001140      MOV      300$,$GDDAT      ;GET EXPECTED SKI STATUS
10007 046012 042737 137777 001140      BIC      #^CSKI,$GDDAT      ;CLEAR DONT CARES
10008 046020 001417      BEQ      53$              ;BRANCH IF 0 EXPECTED
10009
10010      ;REPORT ERROR IF SKI IS NOT SET (IAE WAS NOT DETECTED)
10011 046022 032737 040000 001142      BIT      #SKI,$BDDAT      ;WAS SKI DETECTED ??
10012 046030 001032      BNE      54$              ;YES !!
10013 046032 062716 000004      ADD      #4,(SP)      ;MOVE SP TO USERS ERROR CALL
10014 046036 112776 000267 000000      MOVB     #267,@(SP)      ;WRITE ERROR NUMBER
10015 046044 162716 000002      SUB      #2,(SP)      ;MOVE SP TO ERROR RETURN
10016 046050 004736      JSR      PC,@(SP)+      ;REPORT ERROR AND RETURN
10017 046052 162716 000010      SUB      #10,(SP)      ;MOVE SP TO NO ERROR
10018 046056 000443      BR       6$              ;GO TO NEXT ERROR CHECK
10019 046060      53$:

```

```
10020
10021 ;REPORT ERROR IF SKI IS SET
10022 046060 032737 040000 001142 BIT #SKI,$BDDAT ;IS SKI SET ??
10023 046066 001413 BEQ 54$ ;NO - SKI IS OK
10024 046070 062716 000004 ADD #4,(SP) ;MOVE (SP) TO ERROR
10025 046074 112776 000054 000000 MOVB #54,@(SP) ;LOAD ERROR NUMBER
10026 046102 162716 000002 SUB #2,(SP) ;MOVE SP TO RETURN FOR ERROR
10027 046106 004736 JSR PC,@(SP)+ ;REPORT SEEK ERROR
10028 046110 162716 000010 SUB #10,(SP) ;RESTORE (SP)
10029 046114 000240 NOP
10030
10031 ;REPORT ANY DEVICE CHECK
10032 046116 032737 000200 001372 54$: BIT #DVC,RMER21 ;WAS THERE DVC DURING SEEK??
10033 046124 001420 BEQ 6$ ;NO!!
10034 046126 005037 001140 CLR $GDDAT ;EXPECTED STATUS
10035 046132 013737 001372 001142 MOV RMER21,$BDDAT ;RECEIVED STATUS
10036 046140 062716 000004 ADD #4,(SP)
10037 046144 112776 000055 000000 MOVB #55,@(SP) ;ERROR #55
10038 046152 162716 000002 SUB #2,(SP) ;MOVE SP TO RETURN FOR ERROR
10039 046156 004736 JSR PC,@(SP)+ ;REPORT ERROR VIA USER
10040 046160 162716 000010 SUB #10,(SP) ;RESTORE SP
10041 046164 000240 NOP
10042
10043 ;REPORT ANY 'OPI' ERROR AS OPI WITH MOL =0, OR OPI
10044 ;BECAUSE ON CYLINDER LATCH DIDN'T RESET
10045 046166 032737 020000 001344 6$: BIT #OPI,RMER11 ;'OPI' ERROR??
10046 046174 001427 BEQ 8$ ;NO!!
10047 046176 005037 001140 CLR $GDDAT ;EXPECTED STATUS
10048 046202 013737 001344 001142 MOV RMER11,$BDDAT ;RECEIVED STATUS
10049 046210 062716 000004 ADD #4,(SP) ;MOVE (SP) TO ERROR
10050 046214 112776 000052 000000 MOVB #52,@(SP) ;LOAD ERROR NUMBER
10051 046222 032737 010000 001342 BIT #MOL,RMDSI ;WAS MEDIUM ON LINE??
10052 046230 001403 BEQ 7$ ;NO!!
10053 046232 112776 000053 000000 MOVB #53,@(SP) ;YES - CHANGE ERROR NUMBER
10054 046240 162716 000002 7$: SUB #2,(SP) ;MOVE SP TO RETURN FOR ERROR
10055 046244 004736 JSR PC,@(SP)+ ;REPORT 'OPI' ERROR
10056 046246 162716 000010 SUB #10,(SP) ;RESTORE (SP)
10057 046252 000240 NOP
10058
10059 ;SEE IF 'PIP' IS 0, AND 'ATA','MOL'AND'VV' =1
10060 046254 013746 001342 8$: MOV RMDSI,-(SP)
10061 046260 042716 047677 BIC #^C<ATA!PIP!MOL!VV>,(SP)
10062 046264 022726 110100 CMP #ATA!MOL!VV,(SP)+
10063 046270 001002 BNE 9$ ;ERROR IN RMDS
10064 046272 000137 046626 JMP 14$ ;RMDS IS OK
10065
10066 ;REPORT ERROR IF MOL = 0 AND OPI = 0
10067 046276 032737 010000 001342 9$: BIT #MOL,RMDSI ;IS MOL RESET??
10068 046304 001030 BNE 10$ ;NO - MOL IS SET
10069 046306 032737 020000 001344 BIT #OPI,RMER11 ;WAS OPI SET
10070 046314 001024 BNE 10$ ;YES - DONT REPORT ERROR
10071 046316 013737 001342 001140 MOV RMDSI,$GDDAT ;EXPECTED STATUS
10072 046324 052737 010000 001140 BIS #MOL,$GDDAT
10073 046332 013737 001342 001142 MOV RMDSI,$BDDAT ;RECEIVED STATUS
10074 046340 062716 000004 ADD #4,(SP)
10075 046344 112776 000062 000000 MOVB #62,@(SP)
```

10076	046352	162716	000002		SUB	#2,(SP)	;MOVE SP TO RETURN FOR ERROR
10077	046356	004736			JSR	PC,@(SP)+	;REPORT ERROR VIA USER
10078	046360	162716	000010		SUB	#10,(SP)	
10079	046364	000240			NOP		
10080							
10081					;REPORT AN ERROR IF 'PIP' IS STIL SET AND SKI NOT SET		
10082	046366	032737	020000	001342	10\$: BIT	#PIP,RMDSI	;IS 'PIP' STILL SET??
10083	046374	001430			BEQ	11\$	;NO!!
10084	046376	032737	040000	001372	BIT	#SKI,PMER2I	;WAS 'SKI' SET??
10085	046404	001024			BNE	11\$	;YES-DONT REPORT PIP
10086	046406	013737	001342	001140	MOV	RMDSI,\$GDDAT	;EXPECTED STATUS
10087	046414	042737	020000	001142	BIC	#PIP,\$BDDAT	
10088	046422	013737	001342	001142	MOV	RMDSI,\$BDDAT	;RECEIVED STATUS
10089	046430	062716	000004		ADD	#4,(SP)	;MOVE (SP) TO ERROR
10090	046434	112776	000056	000000	MOVB	#56,@(SP)	;LOAD ERROR NUMBER
10091	046442	162716	000002		SUB	#2,(SP)	;MOVE SP TO RETURN FOR ERROR
10092	046446	004736			JSR	PC,@(SP)+	;REPORT 'PIP' SET AFTER SEEK
10093	046450	162716	000010		SUB	#10,(SP)	;RESTORE (SP)
10094	046454	000240			NOP		
10095							
10096					;REPORT AN ERROR IF 'ATA' IS NOT SET		
10097	046456	032737	100000	001342	11\$: BIT	#ATA,RMDSI	;WAS 'ATA' SET ??
10098	046464	001024			BNE	13\$	;YES!!
10099	046466	013737	001342	001140	MOV	RMDSI,\$GDDAT	;EXPECTED STATUS
10100	046474	052737	110600	001140	BIS	#ATA!MOL!DPR!DRY,\$GDDAT	
10101	046502	013737	001342	001142	MOV	RMDSI,\$BDDAT	;RECEIVED STATUS
10102	046510	062716	000004		ADD	#4,(SP)	;MOVE (SP) TO ERROR
10103	046514	112776	000057	000000	MOVB	#57,@(SP)	;LOAD ERROR NUMBER
10104	046522	162716	000002		SUB	#2,(SP)	;MOVE SP TO RETURN FOR ERROR
10105	046526	004736			JSR	PC,@(SP)+	;REPORT ATTENTION NOT SET DURING
10106							;SEEK TEST
10107	046530	162716	000010		SUB	#10,(SP)	;RESTORE (SP)
10108	046534	000240			NOP		
10109							
10110					;REPORT ERROR IF VOLUME VALID IS RESET AND IVC IS ZERO		
10111	046536	032737	000100	001342	13\$: BIT	#VV,RMDSI	;IS VV = 0 ??
10112	046544	001030			BNE	14\$	;NO!!
10113	046546	032737	010000	001372	BIT	#IVC,RMER2I	;IS IVC ALSO 0 ??
10114	046554	001024			BNE	14\$	;NO - IVC IS SET
10115	046556	013737	001342	001140	MOV	RMDSI,\$GDDAT	;EXPECTED STATUS
10116	046564	052737	000100	001140	BIS	#VV,\$GDDAT	
10117	046572	013737	001342	001142	MOV	RMDSI,\$BDDAT	;RECEIVED STATUS
10118	046600	062716	000004		ADD	#4,(SP)	
10119	046604	112776	000064	000000	MOVB	#64,@(SP)	;ERROR #64
10120	046612	162716	000002		SUB	#2,(SP)	;MOVE SP TO RETURN FOR ERROR
10121	046616	004736			JSR	PC,@(SP)+	
10122	046620	162716	000010		SUB	#10,(SP)	
10123	046624	000240			NOP		
10124	046626				14\$:		
10125							
10126					;MODIFY THE RETURN ADDRESS IF AN ERROR WAS DETECTED		
10127	046626	000240			NOP		
10128	046630	062716	000004		ADD	#4,(SP)	;MOVE (SP) TO ERROR CALL
10129	046634	105776	000000		TSTB	@(SP)	;WAS ERROR CALLED??
10130	046640	001403			BEQ	15\$	;NO!!
10131	046642	062716	000004		ADD	#4,(SP)	;MOVE TO ERROR RETURN

CZRMDCO RM03/2 FCTNL TST 2
CZRMDC.P11 12-DEC-78 08:24

MACY11 30A(1052) 04-JAN-79 11:23 L 16
SEEK STATUS CHECK SUBROUTINE PAGE 206

SEQ 0206

10132	046646	000402		BR	16\$	
10133						
10134	046650	162716	000004	15\$: SUB	#4,(SP)	:MOVE (SP) TO NO ERROR RETURN
10135	046654	000207		16\$: RTS	PC	:RETURN
10136						
10137	046656	000000		300\$: .WORD	0	:ERROR FLAGS
10138						

```

10139 .SBTTL CONTROLLER CLEAR SUBROUTINE
10140
10141 ;THIS SUBROUTINE CLEARS THE MASSBUS CONTROLLER, MASSBUS ADAPTERS,
10142 ;AND DRIVES, THEN SELECTS THE DRIVE.
10143
10144 ;CALL: JSR PC,CNTCLR
10145 ;      BR ??? RETURN HERE IF NO ERROR FOUND
10146 ;      NOP RETURN HERE IF ANY ERROR FOUND
10147 ;      ERROR SUB DEFINES ERROR NUMBER
10148 ;      ???
10149
10150 CNTCLR:
10151 046660 010046 MOV RO,-(SP) ;;PUSH RO ON STACK
10152 046662 010146 MOV R1,-(SP) ;;PUSH R1 ON STACK
10153 046664 013746 000004 MOV ERRVEC,-(SP) ;;PUSH ERRVEC ON STACK
10154 046670 013746 000006 MOV ERRVEC+2,-(SP) ;;PUSH ERRVEC+2 ON STACK
10155 046674 012737 046734 000004 MOV #10$,ERRVEC ;SETUP FOR BUS TIMEOUT
10156 046702 012737 000300 000006 MOV #PR6,ERRVEC+2
10157 046710 013700 001276 MOV $BASE,RO ;RO=UNIBUS ADDRESS
10158 046714 012760 000040 000010 MOV #CLR,RMCS2(RO) ;CLEAR MASSBUS
10159 046722 013701 001450 MOV TSTQUE,R1
10160 046726 111160 000010 MOVB (R1),RMCS2(RO) ;SELECT DEVICE
10161 046732 000412 BR 20$
10162 046734 022626 10$: CMP (SP)+,(SP)+ ;ADJUST STACK
10163 046736 062766 000004 000010 ADD #4,10(SP) ;MOVE SP TO USER'S ERROR CALL
10164 046744 112776 000007 000010 MOVB #7,10(SP) ;WRITE THE ERROR NUMBER
10165 046752 162766 000002 000010 SUB #2,10(SP)
10166 046760 20$: MOV (SP)+,ERRVEC+2 ;;POP STACK INTO ERRVEC+2
10167 046760 012637 000006 MOV (SP)+,ERRVEC ;;POP STACK INTO ERRVEC
10168 046764 012637 000004 MOV (SP)+,R1 ;;POP STACK INTO R1
10169 046770 012601 MOV (SP)+,RO ;;POP STACK INTO RO
10170 046772 012600 RTS
10171 046774 000207 PC
10172

```



```
10173 .SBTTL CONTROLLER CLEAR STATUS CHECK SUBROUTINE
10174
10175 ;THIS SUBROUTINE VERIFIES THAT THE RM03 SUBSYSTEM IS INITIALIZED BASED ON
10176 ;STATUS STORED IN THE GET BUFFER. THIS SUBROUTINE SHOULD ONLY BE
10177 ;USED FOLLOWING A CONTROLLER CLEAR OPERATION, I.E., WRITING A 1 IN BIT
10178 ;5 OF RMCS2, BECAUSE THE ERROR MESSAGES ARE BASED ON THAT CONDITION.
10179
10180 ;STATUS PERTINENT TO THE DEVICE IS NOT CHECKED. IN PARTICULAR, THE
10181 ;FOLLOWING STATUS BITS ARE NOT CHECKED:
10182
10183 .ATA,ERR,PIP,MOL,WRL,LBT,PGM,VV,OM,UNS,SKI,DVC
10184
10185
10186 ;CALL:
10187 ;(1) JSR PC,CLRSTS
10188 ; BR ??? RETURN HERE IF NO ERROR
10189 ; NOP RETURN HERE TO REPORT AN ERROR
10190 ; ERROR ERROR NUMBER DEFINED BY SUB
10191 ; JSR PC,@(SP)+ GO BACK TO SUB FOR MORE ERROR CHECKS
10192 ; ??? RETURN HERE IF NO MORE ERRORS
10193
10194 CLRSTS:
10195
10196 ;CLEAR USER'S ERROR CALL
10197 046776 062716 000004 ADD #4,(SP) ;MOVE SP TO ERROR
10198 047002 105076 000000 CLRB @(SP) ;CLEAR ERROR NUMBER
10199 047006 162716 000004 SUB #4,(SP) ;MOVE SP BACK TO NO ERROR
10200
10201 ;REPORT ERROR IF RMCS1 NOT INITIALIZED
10201 047012 013737 001330 001142 4$: MOV RMCS1,$BDDAT ;VERIFY RMCS1
10202 047020 042737 100000 001142 BIC #SC,$BDDAT ;IGNORE SPECIAL CONDITION
10203 047026 012737 004200 001140 MOV #DVA!RDY,$GDDAT ;EXPECT DVA & RDY
10204 047034 023737 001140 001142 CMP $GDDAT,$BDDAT ;COMPARE EXPECTED, RECEIVED
10205 047042 001413 BEQ 5$ ;BRANCH IF EQUAL
10206 047044 062716 000004 ADD #4,(SP) ;MOVE SP TO USER'S ERROR CALL
10207 047050 112776 000126 000000 MOVB #126,@(SP) ;WRITE ERROR NUMBER IN CALL
10208 047056 162716 000002 SUB #2,(SP) ;MOVE SP TO RETURN FOR ERROR
10209 047062 004736 JSR PC,@(SP)+ ;REPORT ERROR VIA USER
10210 047064 162716 000010 SUB #10,(SP) ;MOVE SP BACK TO NO ERROR
10211 047070 000240 NOP
10212
10213 ;REPORT ERROR IF RMBA NOT RESET
10213 047072 005037 001140 5$: CLR $GDDAT ;VERIFY RMBA IS ZERO
10214 047076 013737 001334 001142 MOV RMBA1,$BDDAT
10215 047104 001413 BEQ 7$ ;BRANCH IF ZERO
10216 047106 062716 000004 ADD #4,(SP) ;MOVE SP TO USER'S ERROR CALL
10217 047112 112776 000127 000000 MOVB #127,@(SP) ;WRITE ERROR NUMBER IN CALL
10218 047120 162716 000002 SUB #2,(SP) ;MOVE SP TO RETURN FOR ERROR
10219 047124 004736 JSR PC,@(SP)+ ;REPORT ERROR VIA USER
10220 047126 162716 000010 SUB #10,(SP) ;MOVE SP BACK TO NO ERROR
10221 047132 000240 NOP
10222
10223 ;REPORT ERROR IF RMCS2 NOT INITIALIZED
10223 047134 013737 001340 001142 7$: MOV RMCS21,$BDDAT ;VERIFY RMCS2
10224 047142 010146 MOV R1,-(SP) ;PUSH R1 ON STACK
10225 047144 005046 CLR -(SP) ;EXPECT IR & UNIT NUMBER
10226 047146 013701 001450 MOV TSTQUE,R1 ;R1 = ADDRESS OF TEST QUE
10227 047152 111116 MOVB (R1),(SP)
10228 047154 052716 000100 BIS #IR,(SP)
```

```
10229 047160 012637 001140      MOV      (SP)+,$GDDAT
10230 047164 012601      MOV      (SP)+,R1      ;;POP STACK INTO R1
10231 047166 023737 001140 001142  CMP      $GDDAT,$BDDAT      ;;COMPARE EXPECTED & RECEIVED
10232 047174 001413      BEQ      9$      ;;BRANCH IF EQUAL
10233 047176 062716 000004      ADD      #4,(SP)      ;;MOVE SP TO USER'S ERROR CALL
10234 047202 112776 000130 000000  MOVB     #130,@(SP)      ;;WRITE ERROR NUMBER IN CALL
10235 047210 162716 000002      SUB      #2,(SP)      ;;MOVE SP TO RETURN FOR ERROR
10236 047214 004736      JSR      PC,@(SP)+      ;;REPORT ERROR VIA USER
10237 047216 162716 000010      SUB      #10,(SP)      ;;MOVE SP BACK TO NO ERROR
10238 047222 000240      NOP
10239      ;REPORT ERROR IF RMER1 NOT RESET-IGNORE UNS
10240 047224 005037 001140 9$:      CLR      $GDDAT      ;;VERIFY RMER1
10241 047230 013737 001344 001142  MOV      RMER1,$BDDAT
10242 047236 042737 040000 001142  BIC      #UNS,$BDDAT      ;;IGNORE UNSAFE
10243 047244 001413      BEQ      13$      ;;BRANCH IF ZERO
10244 047246 062716 000004      ADD      #4,(SP)      ;;MOVE SP TO USER'S ERROR CALL
10245 047252 112776 000131 000000  MOVB     #131,@(SP)      ;;WRITE ERROR NUMBER IN CALL
10246 047260 162716 000002      SUB      #2,(SP)      ;;MOVE SP TO RETURN FOR ERROR
10247 047264 004736      JSR      PC,@(SP)+      ;;REPORT ERROR VIA USER
10248 047266 162716 000010      SUB      #10,(SP)      ;;MOVE SP BACK TO NO ERROR
10249 047272 000240      NOP
10250      ;REPORT ERROR IF RMMR1 NOT INITIALIZED-IGNORE WC,LS,LST
10251 047274 013737 001354 001142 13$:      MOV      RMMR1,$BDDAT      ;;VERIFY RMMR
10252 047302 042737 000046 001142  BIC      #WC!LS!LST,$BDDAT      ;;IGNORE WORD CLOCK, SCT, TRK
10253 047310 012737 000010 001140  MOV      #MWD,$GDDAT      ;;EXPECT WRITE DATA BIT
10254 047316 023737 001140 001142  CMP      $GDDAT,$BDDAT      ;;COMPARE EXPECTED AND RECEIVED
10255 047324 001413      BEQ      17$      ;;BRANCH IF 0
10256 047326 062716 000004      ADD      #4,(SP)      ;;MOVE SP TO USER'S ERROR CALL
10257 047332 112776 000133 000000  MOVB     #133,@(SP)      ;;WRITE ERROR NUMBER IN CALL
10258 047340 162716 000002      SUB      #2,(SP)      ;;MOVE SP TO RETURN FOR ERROR
10259 047344 004736      JSR      PC,@(SP)+      ;;REPORT ERROR VIA USER
10260 047346 162716 000010      SUB      #10,(SP)      ;;MOVE SP BACK TO NO ERROR
10261 047352 000240      NOP
10262      ;REPORT AN ERROR IF RMEC2 IS NOT RESET
10263 047354 005037 001140 17$:      CLR      $GDDAT      ;;EXPECT ZEROS
10264 047360 013737 001376 001142  MOV      RMEC2,$BDDAT      ;;VERIFY RMEC2=0
10265 047366 001413      BEQ      19$      ;;BRANCH IF ZERO
10266 047370 062716 000004      ADD      #4,(SP)      ;;MOVE SP TO USER'S ERROR CALL
10267 047374 112776 000135 000000  MOVB     #135,@(SP)      ;;WRITE ERROR NUMBER IN CALL
10268 047402 162716 000002      SUB      #2,(SP)      ;;MOVE SP TO RETURN FOR ERROR
10269 047406 004736      JSR      PC,@(SP)+      ;;REPORT ERROR VIA USER
10270 047410 162716 000010      SUB      #10,(SP)      ;;MOVE SP BACK TO NO ERROR
10271 047414 000240      NOP
10272      ;REPORT ERROR IF RMMR2 NOT INITIALIZED-IGNORE RQA,RQB
10273 047416 013737 001370 001142 19$:      MOV      RMMR2,$BDDAT      ;;VERIFY RMMR2
10274 047424 042737 140000 001142  BIC      #RQA!RQB,$BDDAT
10275 047432 012737 011777 001140  MOV      #TST!1777,$GDDAT      ;;EXPECT TEST BIT ON
10276 047440 023737 001140 001142  CMP      $GDDAT,$BDDAT
10277 047446 001413      BEQ      21$      ;;BRANCH IF ZERO
10278 047450 062716 000004      ADD      #4,(SP)      ;;MOVE SP TO USER'S ERROR CALL
10279 047454 112776 000136 000000  MOVB     #136,@(SP)      ;;WRITE ERROR NUMBER IN CALL
10280 047462 162716 000002      SUB      #2,(SP)      ;;MOVE SP TO RETURN FOR ERROR
10281 047466 004736      JSR      PC,@(SP)+      ;;REPORT ERROR VIA USER
10282 047470 162716 000010      SUB      #10,(SP)      ;;MOVE SP BACK TO NO ERROR
10283 047474 000240      NOP
10284      ;REPORT ERROR IF RMER2 NOT RESET-IGNORE SKI,DVC
```

```

10285 047476 005037 001140      21$: CLR      $GDDAT      ;EXPECT ALL ZEROS
10286 047502 013737 001372 001142 MOV      RMER21,$BDDAT ;VERIFY RMER2
10287 047510 042737 040200 001142 BIC      #SKI!DVC,$BDDAT ;IGNORE DEVICE ERRORS
10288 047516 001413          BEQ      215$      ;BRANCH IF OTHER BITS 0
10289 047520 062716 000004          ADD      #4,(SP)      ;MOVE SP TO USER'S ERROR CALL
10290 047524 112776 000174 000000 MOVB     #174,@(SP)      ;WRITE ERROR NUMBER IN CALL
10291 047532 162716 000002          SUB      #2,(SP)      ;MOVE SP TO RETURN FOR ERROR
10292 047536 004736          JSR      PC,@(SP)+      ;REPORT ERROR VIA USER
10293 047540 162716 000010          SUB      #10,(SP)      ;MOVE SP BACK TO NO ERROR
10294 047544 000240          NOP
10295          ;REPORT ERROR IF RMD5 NOT INITIALIZED
10296 047546 013737 001342 001142 215$: MOV      RMD51,$BDDAT ;TEST DRIVE STATUS REGISTER
10297 047554 042737 177177 001142 BIC      #^C<DRY!DPR>,$BDDAT
10298 047562 012737 000600 001140 MOV      #DPR!DRY,$GDDAT ;EXPECTED DRIVE STATUS
10299 047570 023737 001140 001142 CMP      $GDDAT,$BDDAT ;COMPARE EXPECTED & RECEIVED
10300 047576 001413          BEQ      22$      ;BRANCH IF EQUAL
10301 047600 062716 000004          ADD      #4,(SP)      ;MOVE SP TO USER'S ERROR CALL
10302 047604 112776 000134 000000 MOVB     #134,@(SP)      ;WRITE ERROR NUMBER
10303 047612 162716 000002          SUB      #2,(SP)      ;MOVE SP TO RETURN FOR ERROR
10304 047616 004736          JSR      PC,@(SP)+      ;REPORT ERROR TO USER
10305 047620 162716 000010          SUB      #10,(SP)      ;MOVE SP BACK TO NO ERROR
10306 047624 000240          NOP
10307 047626 062716 000004      22$: ADD      #4,(SP)      ;MOVE SP TO ERROR CALL
10308 047632 105776 000000          TSTB     @(SP)      ;WAS AN ERROE DETECTED??
10309 047636 001403          BEQ      23$      ;NO!!
10310 047640 062716 000004          ADD      #4,(SP)      ;YES - MOVE TO ERROR RETURN
10311 047644 000402          BR       24$
10312 047646 162716 000004      23$: SUB      #4,(SP)      ;MOVE SP TO NO ERROR RETURN
10313 047652 000240      24$: NOP
10314 047654 000207          RTS      PC

```

```
10315 .SBTTL PACK ACKNOWLEDGE STATUS CHECK
10316
10317 ;THIS SUBROUTINE CHECKS THE RESULTS OF A PACK ACKNOWLEDGE
10318 ;COMMAND USING THE STATUS STORED IN THE GET BUFFER. ERRORS ARE
10319 ;REPORTED TO THE USER VIA THE USER'S ERROR CALL.
10320
10321 ;CALL:
10322 ;(1) JSR PC,ACKSTS
10323 ; BR ??? RETURN HERE IF NO ERROR
10324 ; NOP RETURN HERE TO REPORT AN ERROR
10325 ; ERROR ERROR NUMBER DEFINED BY SUB
10326 ; JSR PC,@(SP)+ GO BACK TO SUB FOR MORE ERROR CHECKS
10327 ; ??? RETURN HERE IF NO MORE ERRORS
10328
10329 047656 ACKSTS:
10330
10331 ;CLEAR USER'S ERROR CALL
10332 047656 062716 000004 ADD #4,(SP) ;MOVE SP TO ERROR CALL
10333 047662 105076 000000 CLRB @(SP) ;CLEAR LOW ORDER BYTE
10334 047666 162716 000004 SUB #4,(SP) ;MOVE SP BACK
10335
10336 ;REPORT AN ERROR IF 'VV' IS 0
10337 047672 032737 000100 001342 BIT #VV,RMDS1 ;IS VOLUME VALID SET??
10338 047700 001024 BNE 1$ ;YES!!
10339 047702 013737 001342 001140 MOV RMDS1,$GDDAT ;EXPECTED STATUS
10340 047710 052737 000100 001140 BIS #VV,$GDDAT
10341 047716 013737 001342 001142 MOV RMDS1,$BDDAT ;RECEIVED STATUS
10342 047724 062716 000004 ADD #4,(SP) ;MOVE SP TO ERROR CALL
10343 047730 112776 000155 000000 MOVB #155,@(SP) ;WRITE NUMBER IN ERROR CALL
10344 047736 162716 000002 SUB #2,(SP) ;MOVE SP TO RETURN FOR ERROR
10345 047742 004736 JSR PC,@(SP)+ ;REPORT THE ERROR
10346 047744 162716 000010 SUB #10,(SP) ;MOVE SP BACK TO BRANCH
10347 047750 000240 NOP
10348 047752 1$:
10349
10350 ;REPORT AN ERROR IF 'MOL' IS 0
10351 047752 032737 010000 001342 BIT #MOL,RMDS1 ;IS MOL SET??
10352 047760 001024 BNE 2$ ;YES!!
10353 047762 013737 001342 001140 MOV RMDS1,$GDDAT ;EXPECTED STATUS
10354 047770 052737 010000 001140 BIS #MOL,$GDDAT
10355 047776 013737 001342 001142 MOV RMDS1,$BDDAT ;RECEIVED STATUS
10356 050004 062716 000004 ADD #4,(SP) ;MOVE SP TO ERROR CALL
10357 050010 112776 000041 000000 MOVB #41,@(SP) ;WRITE NUMBER OF ERROR IN CALL
10358 050016 162716 000002 SUB #2,(SP) ;MOVE SP TO RETURN FOR ERROR
10359 050022 004736 JSR PC,@(SP)+ ;REPORT THE ERROR
10360 050024 162716 000010 SUB #10,(SP) ;MOVE SP TO BRANCH
10361 050030 000240 NOP
10362 050032 2$:
10363
10364 ;SEE IF 'UNS','OPI','RMR','ILR', OR 'ILF' IS SET
10365 050032 032737 060007 001344 BIT #UNS!OPI!RMR!ILR!ILF,RMER11
10366 050040 001570 BEQ 7$
10367
10368 ;REPORT AN ERROR IF 'UNS' IS SET
10369 050042 032737 040000 001344 BIT #UNS,RMER11 ;WAS UNS SET??
10370 050050 001424 BEQ 3$ ;NO!!
```

10371	050052	013737	001344	001142	MOV	RMR11,\$BDDAT	:RECEIVED STATUS
10372	050060	013737	001344	001140	MOV	RMR11,\$GDDAT	:EXPECTED STATUS
10373	050066	042737	040000	001140	BIC	#UNS,\$GDDAT	
10374	050074	062716	000004		ADD	#4,(SP)	:MOVE SP TO ERROR CALL
10375	050100	112776	000042	000000	MOVB	#42,@(SP)	:WRITE NUMBER OF ERROR IN CALL
10376	050106	162716	000002		SUB	#2,(SP)	:MOVE SP TO RETURN FOR ERROR
10377	050112	004736			JSR	PC,@(SP)+	:REPORT THE ERROR VIA USER
10378	050114	162716	000010		SUB	#10,(SP)	:MOVE SP TO NO ERROR RETURN
10379	050120	000240			NOP		
10380	050122						
10381							
10382							
10383	050122	032737	020000	001344	:REPORT ANY OPI ERROR		
10384	050130	001424			BIT	#OPI,RMR11	:WAS OPI SET ??
10385	050132	013737	001344	001142	BEQ	4\$	:NO!!
10386	050140	013737	001344	001140	MOV	RMR11,\$BDDAT	:RECEIVED STATUS
10387	050146	042737	020000	001140	MOV	RMR11,\$GDDAT	:EXPECTED STATUS
10388	050154	062716	000004		BIC	#OPI,\$GDDAT	
10389	050160	112776	000043	000000	ADD	#4,(SP)	:MOVE SP TO ERROR CALL
10390	050166	162716	000002		MOVB	#43,@(SP)	:WRITE NUMBER OF ERROR IN CALL
10391	050172	004736			SUB	#2,(SP)	:MOVE SP TO RETURN FOR ERROR
10392	050174	162716	000010		JSR	PC,@(SP)+	:REPORT THE ERROR VIA USER
10393	050200	000240			SUB	#10,(SP)	:MOVE SP TO NO ERROR RETURN
10394	050202				NOP		
10395							
10396							
10397	050202	032737	000004	001344	:REPORT ANY RMR ERROR		
10398	050210	001424			BIT	#RMR,RMR11	:WAS RMR SET??
10399	050212	013737	001344	001142	BEQ	5\$	:NO!!
10400	050220	013737	001344	001140	MOV	RMR11,\$BDDAT	:RECEIVED STATUS
10401	050226	042737	000004	001140	MOV	RMR11,\$GDDAT	:EXPECTED STATUS
10402	050234	062716	000004		BIC	#RMR,\$GDDAT	
10403	050240	112776	000044	000000	ADD	#4,(SP)	:MOVE SP TO ERROR CALL
10404	050246	162716	000002		MOVB	#44,@(SP)	:WRITE NUMBER OF ERROR IN CALL
10405	050252	004736			SUB	#2,(SP)	:MOVE SP TO RETURN FOR ERROR
10406	050254	162716	000010		JSR	PC,@(SP)+	:REPORT THE ERROR VIA USER
10407	050260	000240			SUB	#10,(SP)	:MOVE SP TO NO ERROR RETURN
10408	050262				NOP		
10409							
10410							
10411	050262	032737	000002	001344	:REPORT ANY ILR ERROR		
10412	050270	001424			BIT	#ILR,RMR11	:WAS ILR SET??
10413	050272	013737	001344	001142	BEQ	6\$	:NO!!
10414	050300	013737	001344	001140	MOV	RMR11,\$BDDAT	:RECEIVED STATUS
10415	050306	042737	000002	001140	MOV	RMR11,\$GDDAT	:EXPECTED STATUS
10416	050314	062716	000004		BIC	#ILR,\$GDDAT	
10417	050320	112776	000045	000000	ADD	#4,(SP)	:MOVE SP TO ERROR CALL
10418	050326	162716	000002		MOVB	#45,@(SP)	:WRITE NUMBER OF ERROR IN CALL
10419	050332	004736			SUB	#2,(SP)	:MOVE SP TO RETURN FOR ERROR
10420	050334	162716	000010		JSR	PC,@(SP)+	:REPORT THE ERROR VIA USER
10421	050340	000240			SUB	#10,(SP)	:MOVE SP TO NO ERROR RETURN
10422	050342				NOP		
10423							
10424							
10425	050342	032737	000001	001344	:REPORT ANY ILF ERROR		
10426	050350	001424			BIT	#ILF,RMR11	:WAS ILF SET??
					BEQ	7\$	:NO!!

```
10427 050352 013737 001344 001142      MOV      RMER11,$BDDAT      ;RECEIVED STATUS
10428 050360 013737 001344 001140      MOV      RMER11,$GDDAT      ;EXPECTED STATUS
10429 050366 042737 000001 001140      BIC      #1LF,$GDDAT
10430 050374 062716 000004      ADD      #4,(SP)          ;MOVE SP TO ERROR CALL
10431 050400 112776 000046 000000      MOVB     #46,@(SP)        ;WRITE NUMBER OF ERROR IN CALL
10432 050406 162716 000002      SUB      #2,(SP)          ;MOVE SP TO RETURN FOR ERROR
10433 050412 004736      JSR      PC,@(SP)+        ;REPORT THE ERROR VIA USER
10434 050414 162716 000010      SUB      #10,(SP)        ;MOVE SP TO NO ERROR RETURN
10435 050420 000240      NOP
10436 050422
10437
10438      ; AUGMENT RETURN ADDRESS IF ERROR WAS FOUND
10439 050422 062716 000004      ADD      #4,(SP)          ;MOVE SP TO ERROR CALL
10440 050426 105776 000000      TSTB     @(SP)            ;WAS ERROR FOUND??
10441 050432 001403      BEQ      8$              ;NO!!
10442 050434 062716 000004      ADD      #4,(SP)          ;YES - MOVE TO ERROR RETURN
10443 050440 000402      BR       9$
10444 050442 162716 000004      8$: SUB      #4,(SP)        ;MOVE SP TO NO ERROR RETURN
10445 050446 000240      9$: NOP
10446 050450 000207      RTS      PC
10447
```



```

10448 .SBTTL RECALIBRATE STATUS CHECK SUBROUTINE
10449
10450 ;THIS SUBROUTINE CHECKS THE RESULTS OF A RECALIBRATE OPERATION
10451 ;USING THE STATUS STORED IN THE GET BUFFER.
10452
10453 ;CALL:
10454
10455 ;(1) JSR PC,RCLSTS ;CALL SUBROUTINE
10456 ; BR ??? ;RETURN HERE IF NO ERROR
10457 ; NOP ;RETURN HERE TO REPORT AN ERROR
10458 ; ERROR ;ERROR NUMBER DEFINED BY SUB
10459 ; JSR PC,@(SP)+ ;GO BACK TO SUB FOR MORE ERROR CHECKS
10460 ; ??? ;RETURN HERE IF NO MORE ERRORS
10461
10462 050452 RCLSTS:
10463
10464 ;CLEAR USER'S ERROR NUMBER
10465 050452 062716 000004 ADD #4,(SP)
10466 050456 105076 000000 CLR @ (SP) ;CLEAR USER'S ERROR CALL
10467 050462 162716 000004 SUB #4,(SP) ;MOVE SP BACK TO BRANCH
10468
10469
10470 ;SEE IF "PAR" OR "ILF" OR "OPI" OR "IAE" IS SET
10471 050466 032737 022011 001344 BIT #OPI:PAR:ILF:IAE,RMER11
10472 050474 001553 BEQ 4$ ;NONE ARE SET - GO TO NEXT CHECK
10473
10474 ;REPORT ANY MASSBUS CONTROL BUS PARITY ERROR, I.E.,
10475 ;"PAR" = 1 AND "DPE" = 0
10476 050476 032737 000010 001344 BIT #PAR,RMER11 ;WAS "PAR" SET??
10477 050504 001430 BEQ 1$ ;NO!!
10478 050506 032737 000010 001372 BIT #DPE,RMER21 ;WAS "DPE" SET??
10479 050514 001024 BNE 1$ ;YES - NOT A REGISTER ERROR
10480 050516 013737 001344 001140 MOV RMER11,$GDDAT ;EXPECTED STATUS
10481 050524 042737 000010 001140 BIC #PAR,$GDDAT
10482 050532 013737 001344 001142 MOV RMER11,$BDDAT ;RECEIVED STATUS
10483 050540 062716 000004 ADD #4,(SP) ;MOVE SP TO USER'S ERROR CALL
10484 050544 112776 000050 000000 MOVB #50,@(SP) ;WRITE ERROR NUMBER IN CALL
10485 050552 162716 000002 SUB #2,(SP) ;MOVE SP TO RETURN FOR ERROR
10486 050556 004736 JSR PC,@(SP)+ ;GO REPORT ERROR
10487 050560 162716 000010 SUB #10,(SP) ;MOVE SP BACK TO BRANCH
10488 050564 000240 NOP
10489 050566 1$:
10490
10491 ;REPORT ANY "ILF" ERROR
10492 050566 032737 000001 001344 BIT #ILF,RMER11 ;WAS "ILF" SET??
10493 050574 001424 BEQ 2$ ;NO!!
10494 050576 013737 001344 001140 MOV RMER11,$GDDAT ;EXPECTED STATUS
10495 050604 042737 000001 001140 BIC #ILF,$GDDAT
10496 050612 013737 001344 001142 MOV RMER11,$BDDAT ;RECEIVED STATUS
10497 050620 062716 000004 ADD #4,(SP) ;MOVE SP TO USER'S ERROR CALL
10498 050624 112776 000071 000000 MOVB #71,@(SP) ;WRITE ERROR NUMBER IN CALL
10499 050632 162716 000002 SUB #2,(SP) ;MOVE SP TO RETURN FOR ERROR
10500 050636 004736 JSR PC,@(SP)+ ;REPORT ERROR VIA USER
10501 050640 162716 000010 SUB #10,(SP) ;MOVE SP BACK TO BRANCH
10502 050644 000240 NOP
10503 050646 2$:

```

```

10504
10505
10506
10507
10508 050646 032737 020000 001344
10509 050654 001433
10510 050656 013737 001344 001140
10511 050664 042737 020000 001140
10512 050672 013737 001344 001142
10513 050700 062716 000004
10514 050704 112776 000072 000000
10515 050712 032737 010000 001342
10516 050720 001403
10517 050722 112776 000073 000000
10518 050730 162716 000002
10519 050734 004736
10520 050736 162716 000010
10521 050742 000240
10522 050744
10523
10524
10525 050744 032737 002000 001344
10526 050752 001424
10527 050754 013737 001344 001140
10528 050762 042737 002000 001140
10529 050770 013737 001344 001142
10530 050776 062716 000004
10531 051002 112776 000070 000000
10532 051010 162716 000002
10533 051014 004736
10534 051016 162716 000010
10535 051022 000240
10536 051024
10537
10538
10539 051024 032737 050200 001372
10540 051032 001517
10541
10542
10543
10544
10545
10546 051034 032737 010000 001372
10547 051042 001433
10548 051044 013737 001372 001140
10549 051052 042737 010000 001140
10550 051060 013737 001372 001142
10551 051066 062716 000004
10552 051072 112776 000074 000000
10553 051100 032737 000100 001342
10554 051106 001403
10555 051110 112776 000075 000000
10556 051116 162716 000002
10557 051122 004736
10558 051124 162716 000010
10559 051130 000240

;REPORT ANY 'OPI' ERROR AS
;
; OPI DUE TO 'MOL' = 0
;
; OPI BECAUSE ON CYLINDER LATCH DIDN'T RESET
;
; WAS OPI SET??
; NO!!
; EXPECTED STATUS
;
; RECEIVED STATUS
; MOVE SP TO USER'S ERROR CALL
; WRITE ERROR NUMBER IN USER'S CALL
; WAS 'MOL' = 0??
; YES!!
; NO - CHANGE ERROR NUMBER
; MOVE SP TO RETURN FOR ERROR
; REPORT ERROR VIA USER
; MOVE SP BACK TO BRANCH

3$:
SUB #2,(SP)
JSR PC,@(SP)+
SUB #10,(SP)
NOP

31$:

;REPORT AN ERROR IF 'IAE' IS SET
;
; IS 'IAE' SET??
; NO!!
; EXPECTED STATUS
;
; RECEIVED STATUS
; MOVE SP TO ERROR CALL
; WRITE ERROR NUMBER IN USER'S CALL
; MOVE SP TO RETURN FOR ERROR
; REPORT ERROR
; MOVE SP BACK TO NO ERROR RETURN

4$:

;SEE IF 'SKI' OR 'IVC' OR 'DVC' IS SET
;
; SKI!IVC!DVC,RMER21
;
; NONE OF THE BITS ARE SET

8$:

;REPORT ANY 'IVC' ERROR AS
;
; IVC WITH VV = 0
;
; ERRONEOUS IVC ERROR
;
; WAS IVC SET??
; NO!!
; EXPECTED STATUS
;
; RECEIVED STATUS
; MOVE SP TO USER'S ERROR CALL
; WRITE ERROR NUMBER IN CALL
; WAS VV = 0??
; YES!!
; NO - CHANGE ERROR NUMBER
; MOVE SP TO RETURN FOR ERROR
; REPORT ERROR VIA USER
; MOVE SP BACK TO BRANCH

5$:
SUB #2,(SP)
JSR PC,@(SP)+
SUB #10,(SP)
NOP

```


10560 051132
10561
10562
10563 051132 032737 040000 001372
10564 051140 001424
10565 051142 013737 001372 001140
10566 051150 042737 040000 001140
10567 051156 013737 001372 001142
10568 051164 062716 000004
10569 051170 112776 000076 000000
10570 051176 162716 000002
10571 051202 004736
10572 051204 162716 000010
10573 051210 000240
10574 051212
10575
10576
10577 051212 032737 000200 001372
10578 051220 001424
10579 051222 013737 001372 001140
10580 051230 042737 000200 001140
10581 051236 013737 001372 001142
10582 051244 062716 000004
10583 051250 112776 000077 000000
10584 051256 162716 000002
10585 051262 004736
10586 051264 162716 000010
10587 051270 000240
10588 051272
10589
10590
10591 051272 013746 001342
10592 051276 042716 047676
10593 051302 022726 110100
10594 051306 001002
10595 051310 000137 051724
10596 051314
10597
10598
10599
10600 051314 032737 010000 001342
10601 051322 001030
10602 051324 032737 020000 001344
10603 051332 001024
10604 051334 013737 001342 001140
10605 051342 052737 010000 001140
10606 051350 013737 001342 001142
10607 051356 062716 000004
10608 051362 112776 000100 000000
10609 051370 162716 000002
10610 051374 004736
10611 051376 162716 000010
10612 051402 000240
10613 051404
10614
10615

6\$:
;REPORT ANY "SKI" ERROR
BIT #SKI,RMER21 ;WAS SKI SET??
BEQ 7\$;NO!!
MOV RMER21,\$GDDAT ;EXPECTED STATUS
BIC #SKI,\$GDDAT
MOV RMER21,\$BDDAT ;RECEIVED STATUS
ADD #4,(SP) ;MOVE SP TO USER'S ERROR CALL
MOVB #76,@(SP) ;WRITE ERROR NUMBER
SUB #2,(SP) ;MOVE SP TO RETURN FOR ERROR
JSR PC,@(SP)+ ;REPORT ERROR VIA USER
SUB #10,(SP) ;MOVE SP TO BRANCH
NOP

7\$:
;REPORT ANY "DVC" ERROR
BIT #DVC,RMER21 ;WAS "DVC" SET??
BEQ 8\$;NO!!
MOV RMER21,\$GDDAT ;EXPECTED STATUS
BIC #DVC,\$GDDAT
MOV RMER21,\$BDDAT ;RECEIVED STATUS
ADD #4,(SP) ;MOVE SP TO USER'S ERROR CALL
MOVB #77,@(SP) ;WRITE ERROR NUMBER
SUB #2,(SP) ;MOVE SP TO RETURN FOR ERROR
JSR PC,@(SP)+ ;REPORT ERROR VIA USER
SUB #10,(SP) ;MOVE SP TO USER'S BRANCH
NOP

8\$:
;SEE IF "PIP" AND "OM" ARE 0, AND "ATA","MOL" AND "VV" ARE 1
MOV RMDS1,-(SP) ;PUT RMDS ON STACK
BIC #^C<PIP!MOL!VV!OM!ATA>,(SP)
CMP #ATA!MOL!VV,(SP)+
BNE 85\$
JMP 13\$

85\$:
;REPORT AN ERROR IF MOL = 0 AND OPI = 0, I.E., MEDIUM WENT OFF
;LINE AFTER RECALIBRATE WAS INITIATED
BIT #MOL,RMDS1 ;DID MOL DROP??
BNE 9\$;NO!!
BIT #OPI,RMER11 ;WAS OPI ERROR REPORTED??
BNE 9\$;YES - DON'T REPORT MOL=0
MOV RMDS1,\$GDDAT ;EXPECTED STATUS
BIS #MOL,\$GDDAT
MOV RMDS1,\$BDDAT ;RECEIVED STATUS
ADD #4,(SP) ;MOVE SP TO USER'S ERROR CALL
MOVB #100,@(SP) ;WRITE ERROR NUMBER
SUB #2,(SP) ;MOVE SP TO RETURN FOR ERROR
JSR PC,@(SP)+ ;REPORT ERROR VIA USER
SUB #10,(SP) ;MOVE SP BACK TO USER'S BRANCH
NOP

9\$:
;REPORT AN ERROR IF "VV" = 0 AND "IVC" = 0

CZRMDCO RM03/2 FCTNL TST 2
CZRMDC.P11 12-DEC-78 08:24

MACY11 30A(1052) 04-JAN-79 11:23 PAGE 217
RECALIBRATE STATUS CHECK SUBROUTINE

SEQ 0217

```

10616 051404 032737 000100 001342      BIT      #VV,RMDSI      ;DID 'VV' DROP??
10617 051412 001030                BNE      10$          ;NO!!
10618 051414 032737 010000 001372      BIT      #IVC,RMER21    ;WAS THERE A IVC ERROR??
10619 051422 001024                BNF      10$          ;YES - DONT REPORT VV=0
10620 051424 013737 001342 001140      MOV      RMDSI,$GDDAT    ;EXPECTED STATUS
10621 051432 013737 001342 001142      MOV      RMDSI,$BDDAT    ;RECEIVED STATUS
10622 051440 052737 000100 001140      BIS      #VV,$GDDAT
10623 051446 062716 000004                ADD      #4,(SP)      ;MOVE SP TO USER'S ERROR CALL
10624 051452 112776 000101 000000      MOV      #101,@(SP)    ;WRITE ERROR NUMBER IN CALL
10625 051460 162716 000002                SUB      #2,(SP)      ;MOVE SP TO RETURN FOR ERROR
10626 051464 004736                JSR      PC,@(SP)+
10627 051466 162716 000010                SUB      #10,(SP)     ;MOVE SP BACK TO USER'S BRANCH
10628 051472 000240                NOP
10629 051474
10630
10631                                ;REPORT AN ERROR IF ATA IS NOT SET
10632 051474 032737 100000 001342      BIT      #ATA,RMDSI    ;WAS ATA SET DURING RECALIBRATE??
10633 051502 001024                BNE      11$          ;YES!!
10634 051504 013737 001342 001140      MOV      RMDSI,$GDDAT    ;EXPECTED STATUS
10635 051512 052737 100000 001140      BIS      #ATA,$GDDAT
10636 051520 013737 001342 001142      MOV      RMDSI,$BDDAT    ;RECEIVED STATUS
10637 051526 062716 000004                ADD      #4,(SP)      ;MOVE SP TO USER'S ERROR CALL
10638 051532 112776 000102 000000      MOV      #102,@(SP)    ;WRITE ERROR NUMBER IN CALL
10639 051540 162716 000002                SUB      #2,(SP)
10640 051544 004736                JSR      PC,@(SP)+
10641 051546 162716 000010                SUB      #10,(SP)     ;MOVE SP TO USER'S BRANCH
10642 051552 000240                NOP
10643
10644 051554
10645
10646                                ;REPORT AN ERROR IF 'OM' IS NOT ZERO BECAUSE RECALIBRATE SHOULD
10647                                ;ALWAYS CLEAR OFFSET MODE
10648 051554 032737 000001 001342      BIT      #OM,RMDSI    ;WAS 'OM' RESET??
10649 051562 001424                BEQ      12$          ;YES!!
10650 051564 013737 001342 001140      MOV      RMDSI,$GDDAT    ;EXPECTED STATUS
10651 051572 042737 000001 001140      BIC      #OM,$GDDAT
10652 051600 013737 001342 001142      MOV      RMDSI,$BDDAT    ;RECEIVED STATUS
10653 051606 062716 000004                ADD      #4,(SP)      ;MOVE SP TO USER'S ERROR CALL
10654 051612 112776 000103 000000      MOV      #103,@(SP)    ;WRITE ERROR NUMBER
10655 051620 162716 000002                SUB      #2,(SP)      ;MOVE SP TO RETURN FOR ERROR
10656 051624 004736                JSR      PC,@(SP)+
10657 051626 162716 000010                SUB      #10,(SP)     ;REPORT ERROR VIA USER
10658 051632 000240                NOP
10659 051634
10660                                ;REPORT AN ERROR IF 'PIP' IS STILL ON, I.E., DRIVE NOT ON
10661                                ;CYLINDER
10662 051634 032737 020000 001342      BIT      #PIP,RMDSI    ;IS DRIVE OFF CYLINDER??
10663 051642 001430                BEQ      13$          ;NO!!
10664 051644 032737 040000 001372      BIT      #SKI,RMER21    ;WAS 'SKI' DETECTED??
10665 051652 001024                BNE      13$          ;YES-DONT REPORT 'PIP'
10666 051654 013737 001342 001140      MOV      RMDSI,$GDDAT    ;EXPECTED STATUS
10667 051662 042737 020000 001140      BIC      #PIP,$GDDAT
10668 051670 013737 001342 001142      MOV      RMDSI,$BDDAT    ;RECEIVED STATUS
10669 051676 062716 000004                ADD      #4,(SP)      ;MOVE SP TO USER'S ERROR CALL
10670 051702 112776 000104 000000      MOV      #104,@(SP)    ;WRITE ERROR NUMBER
10671
```

```
10672 051710 162716 000002          SUB    #2,(SP)          ;MOVE SP TO RETURN FOR ERROR
10673 051714 004736                JSR    PC,@(SP)+
10674 051716 162716 000010          SUB    #10,(SP)         ;MOVE SP BACK TO USER'S BRANCH
10675 051722 000240                NOP
10676 051724                13$:
10677
10678                ;SEE IF "ILR" OR "RMR" OR "UNS" IS SET
10679 051724 032737 040006 001344    BIT    #ILR!RMR!UNS,RMER11
10680 051732 001514                BEQ    16$
10681
10682                ;REPORT AN ERROR IF "ILR" IS SET
10683 051734 032737 000002 001344    BIT    #ILR,RMER11      ;WAS ILR SET DURING RECALIBRATE??
10684 051742 001424                BEQ    14$              ;NO!!
10685 051744 013737 001344 001140    MOV    RMER11,$GDDAT    ;EXPECTED STATUS
10686 051752 042737 000002 001140    BIC    #ILR,$GDDAT
10687 051760 013737 001344 001142    MOV    RMER11,$BDDAT    ;RECEIVED STATUS
10688 051766 062716 000004          ADD    #4,(SP)         ;MOVE SP TO USER'S ERROR CALL
10689 051772 112776 000105 000000    MOV    #105,@(SP)      ;WRITE ERROR NUMBER IN CALL
10690 052000 162716 000002          SUB    #2,(SP)         ;MOVE SP TO RETURN FOR ERROR
10691 052004 004736                JSR    PC,@(SP)+
10692 052006 162716 000010          SUB    #10,(SP)         ;MOVE SP TO USER'S BRANCH
10693 052012 000240                NOP
10694 052014                14$:
10695
10696                ;REPORT AN ERROR IF "RMR" IS SET
10697 052014 032737 000004 001344    BIT    #RMR,RMER11      ;WAS RMR SET??
10698 052022 001424                BEQ    15$              ;NO!!
10699 052024 013737 001344 001140    MOV    RMER11,$GDDAT    ;EXPECTED STATUS
10700 052032 042737 000004 001140    BIC    #RMR,$GDDAT
10701 052040 013737 001344 001142    MOV    RMER11,$BDDAT    ;RECEIVED STATUS
10702 052046 062716 000004          ADD    #4,(SP)         ;MOVE SP TO USER'S ERROR CALL
10703 052052 112776 000106 000000    MOV    #106,@(SP)      ;WRITE ERROR NUMBER IN USER'S CALL
10704 052060 162716 000002          SUB    #2,(SP)         ;MOVE SP TO RETURN FOR ERROR
10705 052064 004736                JSR    PC,@(SP)+
10706 052066 162716 000010          SUB    #10,(SP)         ;MOVE SP TO USER'S BRANCH
10707 052072 000240                NOP
10708 052074                15$:
10709
10710                ;REPORT AN ERROR IF "UNS" IS SET AND "DVC" IS 0
10711 052074 032737 040000 001344    BIT    #UNS,RMER11      ;WAS UNSAFE ON??
10712 052102 001430                BEQ    16$              ;NO!!
10713 052104 032737 000200 001372    BIT    #DVC,RMER21      ;WAS THERE A DEVICE CHECK??
10714 052112 001024                BNE    16$              ;YES - DON'T REPORT UNSAFE
10715 052114 013737 001344 001140    MOV    RMER11,$GDDAT    ;EXPECTED STATUS
10716 052122 042737 040000 001140    BIC    #UNS,$GDDAT
10717 052130 013737 001344 001142    MOV    RMER11,$BDDAT    ;RECEIVED STATUS
10718 052136 062716 000004          ADD    #4,(SP)         ;MOVE SP TO USER'S ERROR CALL
10719 052142 112776 000107 000000    MOV    #107,@(SP)      ;WRITE ERROR NUMBER
10720 052150 162716 000002          SUB    #2,(SP)         ;MOVE SP TO RETURN FOR ERROR
10721 052154 004736                JSR    PC,@(SP)+
10722 052156 162716 000010          SUB    #10,(SP)         ;MOVE SP BACK TO USER'S BRANCH
10723 052162 000240                NOP
10724 052164                16$:
10725
10726                ;AUGMENT THE RETURN ADDRESS IF ANY ERROR WAS DETECTED
10727 052164 062716 000004          ADD    #4,(SP)         ;MOVE SP TO USER'S ERROR CALL
```

MACY11 30A(1052) 04-JAN-79 11:23 PAGE 219
RECALIBRATE STATUS CHECK SUBROUTINE

10728	052170	105776	000000
10729	052174	001403	
10730	052176	062716	000004
10731	052202	000402	
10732	052204	162716	000004
10733	052210	000240	
10734	052212	000207	
10735			

```

TSTB      2(SP)          ; WAS AN ERROR REPORTED??
BEQ        17$           ; NO!!
ADD        #4,(SP)        ; YES - AUGMENT SP RETURN
BR         18$
17$:      SUB        #4,(SP) ; NO ERROR - RETURN SP TO BRANCH
18$:      NOP
RTS        PC             ; STATUS CECK IS COMPLETE

```

10736					.SBTTL	DRIVE CLEAR STATUS CHECK SUBROUTINE	
10737					BR	???	RETURN HERE IF NO ERROR
10738					NOP		RETURN HERE TO REPORT AN ERROR
10739					ERROR		ERROR NUMBER DEFINED BY SUB
10740					JSR	PC,@(SP)+	GO BACK TO SUB FOR MORE ERROR CHECKS
10741					???		RETURN HERE IF NO MORE ERRORS
10742							
10743	052214				DRVSTS:		
10744							
10745					;CLEAR USER'S ERROR CALL		
10746	052214	062716	000004		ADD	#4,(SP)	;MOVE SP TO ERROR CALL
10747	052220	105076	000000		CLRB	@(SP)	;CLEAR ERROR CALL
10748	052224	162716	000004		SUB	#4,(SP)	;MOVE SP TO USER'S BRANCH
10749					;REPORT ERROR IF RMCS1 NOT INITIALIZED		
10750	052230	013737	001330	001142	4\$:	MOV	RMCS1I,\$BDDAT ;CHECK RMCS1
10751	052236	042737	173700	001142		BIC	#^C<DVA!FNCMSK>,\$BDDAT ;CLEAR DONT CARES
10752	052244	012737	004010	001140		MOV	#DVA!DRVCLR,\$GDDAT ;EXPECT DVA
10753	052252	023737	001140	001142		CMF	\$GDDAT,\$BDDAT ;COMPARE EXPECTED & RECEIVED
10754	052260	001443				BEQ	6\$;BRANCH IF EQUAL
10755	052262	062716	000004			ADD	#4,(SP) ;MOVE SP TO ERROR CALL
10756	052266	112776	000141	000000		MOVB	#141,@(SP) ;WRITE NUMBER OF ERROR IN CALL
10757	052274	162716	000002			SUB	#2,(SP) ;MOVE SP TO RETURN FOR ERROR
10758	052300	004736				JSR	PC,@(SP)+ ;REPORT THE ERROR VIA USER
10759	052302	162716	000010			SUB	#10,(SP) ;MOVE SP TO NO ERROR RETURN
10760	052306	000240				NOP	
10761					;REPORT ERROR IF RMDS NOT INITIALIZED		
10762	052310	013737	001342	001142	5\$:	MOV	RMDSI,\$BDDAT ;CHECK RMDS
10763	052316	042737	021101	001142		BIC	#PGM!OM!VV!PIP,\$BDDAT ;CLEAR DONT CARES
10764	052324	012737	010600	001140		MOV	#MOL!DPR!DRY,\$GDDAT ;EXPECT DRY & DPR
10765	052332	023737	001140	001142		CMF	\$GDDAT,\$BDDAT ;COMPARE EXPECTED & RECEIVED
10766	052340	001413				BEQ	6\$;BRANCH IF EQUAL
10767	052342	062716	000004			ADD	#4,(SP) ;MOVE SP TO ERROR CALL
10768	052346	112776	000142	000000		MOVB	#142,@(SP) ;WRITE NUMBER OF ERROR IN CALL
10769	052354	162716	000002			SUB	#2,(SP) ;MOVE SP TO RETURN FOR ERROR
10770	052360	004736				JSR	PC,@(SP)+ ;REPORT THE ERROR VIA USER
10771	052362	162716	000010			SUB	#10,(SP) ;MOVE SP TO NO ERROR RETURN
10772	052366	000240				NOP	
10773					;REPORT ERROR IF RMER1 NOT INITIALIZED		
10774	052370	005037	001140		6\$:	CLR	\$GDDAT ;EXPECT 0'S
10775	052374	013737	001344	001142		MOV	RMER1I,\$BDDAT ;CHECK RMER1
10776	052402	001413				BEQ	8\$;BRANCH IF EQUAL
10777	052404	062716	000004			ADD	#4,(SP) ;MOVE SP TO ERROR CALL
10778	052410	112776	000143	000000		MOVB	#143,@(SP) ;WRITE NUMBER OF ERROR IN CALL
10779	052416	162716	000002			SUB	#2,(SP) ;MOVE SP TO RETURN FOR ERROR
10780	052422	004736				JSR	PC,@(SP)+ ;REPORT THE ERROR VIA USER
10781	052424	162716	000010			SUB	#10,(SP) ;MOVE SP TO NO ERROR RETURN
10782	052430	000240				NOP	
10783					;REPORT ERROR IF ATA NOT INITIALIZED		
10784	052432	013737	001346	001142	8\$:	MOV	RMASI,\$BDDAT ;CHECK ATTENTION BIT
10785	052440	010146				MOV	R1,-(SP) ;;PUSH R1 ON STACK
10786	052442	010246				MOV	R2,-(SP) ;;PUSH R2 ON STACK
10787	052444	013701	001450			MOV	TSTQUE,R1
10788	052450	116102	000001			MOVB	1(R1),R2
10789	052454	042702	177400			BIC	#^CATNMSK,R2
10790	052460	005102				COM	R2
10791	052462	040237	001142			BIC	R2,\$BDDAT

```
10792 052466 012602      MOV      (SP)+,R2      ;;POP STACK INTO R2
10793 052470 012601      MOV      (SP)+,R1      ;;POP STACK INTO R1
10794 052472 005737 001142  TST      $BDDAT      ;;IS ATTENTION CLEARED??
10795 052476 001413      BEQ      9$      ;;BRANCH IF ATTENTION CLEARED
10796 052500 062716 000004  ADD      #4,(SP)      ;;MOVE SP TO ERROR CALL
10797 052504 112776 000004 000000  MOVB    #144,a(SP)      ;;WRITE NUMBER OF ERROR IN CALL
10798 052512 162716 000002      SUB      #2,(SP)      ;;MOVE SP TO RETURN FOR ERROR
10799 052516 004736      JSR      PC,a(SP)+      ;;REPORT THE ERROR VIA USER
10800 052520 162716 000010      SUB      #10,(SP)      ;;MOVE SP TO NO ERROR RETURN
10801 052524 000240      NOP
10802      ;REPORT ERROR IF RMMR1 NOT INITIALIZED
10803 052526 013737 001354 001142 9$: MOV      RMMR1,$BDDAT      ;;CHECK RMMR
10804 052534 042737 000046 001142  BIC      #WC!LS!LST,$BDDAT      ;;CLEAR DONT CARES
10805 052542 012737 000010 001140  MOV      #MWD,$GDDAT      ;;EXPECT WRITE DATA ON
10806 052550 023737 001140 001142  CMP      $GDDAT,$BDDAT      ;;COMPARE EXPECTED AND RECEIVED
10807 052556 001413      BEQ      11$      ;;BRANCH IF ZERO
10808 052560 062716 000004      ADD      #4,(SP)      ;;MOVE SP TO ERROR CALL
10809 052564 112776 000145 000000  MOVB    #145,a(SP)      ;;WRITE NUMBER OF ERROR IN CALL
10810 052572 162716 000002      SUB      #2,(SP)      ;;MOVE SP TO RETURN FOR ERROR
10811 052576 004736      JSR      PC,a(SP)+      ;;REPORT THE ERROR VIA USER
10812 052600 162716 000010      SUB      #10,(SP)      ;;MOVE SP TO NO ERROR RETURN
10813 052604 000240      NOP
10814      ;REPORT ERROR IF RMMR2 NOT INITIALIZED
10815 052606 013737 001370 001142 11$: MOV      RMMR2,$BDDAT      ;;CHECK RMMR2
10816 052614 042737 140000 001142  BIC      #RQA!RQB,$BDDAT      ;;CLEAR REQA, REQB
10817 052622 012737 011777 001140  MOV      #TST!1777,$GDDAT      ;;EXPECT TEST BIT ON
10818 052630 023737 001140 001142  CMP      $GDDAT,$BDDAT      ;;COMPARE EXPECTED & RECEIVED
10819 052636 001413      BEQ      15$      ;;BRANCH IF EQUAL
10820 052640 062716 000004      ADD      #4,(SP)      ;;MOVE SP TO ERROR CALL
10821 052644 112776 000146 000000  MOVB    #146,a(SP)      ;;WRITE NUMBER OF ERROR IN CALL
10822 052652 162716 000002      SUB      #2,(SP)      ;;MOVE SP TO RETURN FOR ERROR
10823 052656 004736      JSR      PC,a(SP)+      ;;REPORT THE ERROR VIA USER
10824 052660 162716 000010      SUB      #10,(SP)      ;;MOVE SP TO NO ERROR RETURN
10825 052664 000240      NOP
10826 052666 005037 001140 15$: CLR      $GDDAT      ;;EXPECT ZEROS
10827      ;REPORT ERROR IF RMEC2 NOT RESET
10828 052672 013737 001376 001142 17$: MOV      RMEC2,$BDDAT      ;;CHECK RMEC2
10829 052700 001413      BEQ      17$      ;;BRANCH IF 0
10830 052702 062716 000004      ADD      #4,(SP)      ;;MOVE SP TO ERROR CALL
10831 052706 112776 000150 000000  MOVB    #150,a(SP)      ;;WRITE NUMBER OF ERROR IN CALL
10832 052714 162716 000002      SUB      #2,(SP)      ;;MOVE SP TO RETURN FOR ERROR
10833 052720 004736      JSR      PC,a(SP)+      ;;REPORT THE ERROR VIA USER
10834 052722 162716 000010      SUB      #10,(SP)      ;;MOVE SP TO NO ERROR RETURN
10835 052726 000240      NOP
10836      ;REPORT ERROR IF RMER2 NOT RESET
10837 052730 013737 001372 001142 17$: MOV      RMER2,$BDDAT      ;;CHECK RMER2
10838 052736 001413      BEQ      18$      ;;BRANCH IF NO ERROR
10839 052740 062716 000004      ADD      #4,(SP)      ;;MOVE SP TO ERROR CALL
10840 052744 112776 000147 000000  MOVB    #147,a(SP)      ;;WRITE NUMBER OF ERROR IN CALL
10841 052752 162716 000002      SUB      #2,(SP)      ;;MOVE SP TO RETURN FOR ERROR
10842 052756 004736      JSR      PC,a(SP)+      ;;REPORT THE ERROR VIA USER
10843 052760 162716 000010      SUB      #10,(SP)      ;;MOVE SP TO NO ERROR RETURN
10844 052764 000240      NOP
10845 052766      18$:
10846
10847 052766      19$:
```


MACY11 30A(1052) 04-JAN-79 11:23 C 2 PAGE 222
DRIVE CLEAR STATUS CHECK SUBROUTINE

C 2

Address	Op-Code	Op-Code Hex	Op-Code Dec	Instruction	Comment
10848					
10849				: AUGMENT RETURN ADDRESS IF ANY ERROR WAS FOUND	
10850	052766	062716	000004	ADD #4, (SP)	: MOVE SP TO ERROR CALL
10851	052772	105776	000000	TSTB @ (SP)	: WAS AN ERROR DETECTED??
10852	052776	001403		BEQ 21\$	: NO!!
10853	053000	062716	000004	ADD #4, (SP)	: YES - MOVE SP TO ERROR RETURN
10854	053004	000402		BR 23\$	
10855	053006	162716	000004	21\$: SUB #4, (SP)	: MOVE SP BACK TO NO ERROR RETURN
10856	053012	000240		23\$: NOP	
10857	053014	000207		RTS PC	: RETURN TO USER

```
10858 .SBTTL DATA TRANSFER COMMAND STATUS CHECK SUBROUTINE
10859
10860 ;THIS SUBROUTINE VERIFIES THE RESULTS OF ALL DATA TRANSFER COMMANDS
10861 ;USING STATUS STORED IN THE GET BUFFER AND TEST PARAMETERS
10862 ;STORED IN THE PUT BUFFER. ERRORS ARE REPORTED BY WRITING
10863 ;THE ERROR NUMBER IN THE USERS ERROR CALL.
10864
10865 ;USER'S SUBROUTINE CALL:
10866 ;(1) JSR PC,DTASTS
10867 ;(2) BR ??
10868 ;(3) NOP
10869 ;(4) ERROR
10870 ;(5) JSR PC,@(SP)+
10871 ;(6) ??
10872
10873 DTASTS:
10874 053016
10875
10876 ;CLEAR USER'S ERROR CALL AND ERROR FLAGS
10877 053016 062716 000004 ADD #4,(SP) ;MOVE SP TO USER'S ERROR
10878 053022 105076 000000 CLR3 @(SP) ;CLEAR LOW ORDER BYTE OF TRAP
10879 053026 162716 000004 SUB #4,(SP) ;RESTORE SP TO NO ERROR
10880 053032 005037 056412 CLR 500$ ;CLEAR ERROR FLAGS
10881
10882 ;REPORT ANY CONTROL BUS PARITY ERROR WHILE READING REMOTE REGISTERS, I.E., MCPE = 1
10883 053036 032737 020000 001330 BIT #MCPE,RMCS11 ;WAS THERE A PARITY ERROR??
10884 053044 001422 BEQ 10$ ;NO!!
10885 053046 013737 001330 001140 MOV RMCS11,$GDDAT ;EXPECTED STATUS
10886 053054 042737 020000 001140 BIC #MCPE,$GDDAT
10887 053062 013737 001330 001142 MOV RMCS11,$BDDAT ;RECEIVED STATUS
10888 053070 062716 000004 ADD #4,(SP) ;MOVE SP TO USER'S ERROR CALL
10889 053074 112776 000013 000000 MOV8 #13,@(SP) ;WRITE ERROR NUMBER
10890 053102 162716 000002 SUB #2,(SP) ;MOVE SP TO RETURN IF ERROR
10891 053106 004736 JSR PC,@(SP)+ ;REPORT ERROR AND RETURN
10892 053110 000466 BR 30$
10893 053112
10894
10895 ;REPORT ANY CONTROL BUS PARITY ERROR WHILE WRING REMOTE REGISTERS, I.E.,
10896 ;PAR=1 AND DPE = 0
10897 053112 032737 000010 001344 BIT #PAR,RMER11 ;WAS THERE A PARITY ERROR??
10898 053120 001435 BEQ 20$ ;NO!!
10899 053122 032737 000010 001372 BIT #DPE,RMER21 ;WAS IT DUE TO CONTROL BUS??
10900 053130 001031 BNE 20$ ;NO!!
10901 053132 013737 001344 001140 MOV RMER11,$GDDAT ;EXPECTED STATUS
10902 053140 042737 000010 001140 BIC #PAR,$GDDAT
10903 053146 013737 001344 001142 MOV RMER11,$BDDAT ;RECEIVED STATUS
10904 053154 062716 000004 ADD #4,(SP) ;MOVE SP TO USER'S ERROR
10905 053160 112776 000050 000000 MOV8 #50,@(SP) ;WRITE ERROR NUMBER
10906 053166 032737 001000 001330 BIT #MXF,RMCS11 ;DID MXF GET SET??
10907 053174 001003 BNE 15$ ;YES!!
10908 053176 112776 000274 000000 MOV8 #274,@(SP) ;NO - CHANGE ERROR NUMBER
10909 053204 162716 000002 SUB #2,(SP) ;MOVE SP TO RETURN IF ERROR
10910 053210 004736 JSR PC,@(SP)+ ;REPORT ERROR AND RETURN
10911 053212 000425 BR 30$
10912
10913 053214 20$:
```



```
10914
10915 ;LOOK FOR ANY ERRORS WHICH MAY HAVE OCCURRED DURING COMMAND INITIATION OR
10916 ;MECHANICAL POSITIONING
10917
10918 ;FIRST TEST MXF WHICH WOULD INDICATE COMPOSITE ERROR SET WHEN FUNCTION
10919 ;CODE AND GO BIT WERE LOADED
10920 053214 032737 001000 001340 BIT #MXF,RMCS21 ;WAS 'MISSED TRANSFER' SET??
10921 053222 001425 BEQ 40$ ;NO!!
10922 053224 013737 001340 001140 MOV RMCS21,$GDDAT ;EXPECTED STATUS
10923 053232 042737 001000 001140 BIC #MXF,$GDDAT
10924 053240 013737 001340 001142 MOV RMCS21,$BDDAT ;RECEIVED STATUS
10925 053246 062716 000004 ADD #4,(SP) ;MOVE SP TO USER'S ERROR CALL
10926 053252 112776 000275 000000 MOVB #275,@(SP) ;WRITE ERROR NUMBER
10927 053260 162716 000002 SUB #2,(SP) ;MOVE SP TO RETURN IF ERROR
10928 053264 004736 JSR PC,@(SP)+ ;REPORT ERROR AND RETURN
10929 053266 30$:
10930
10931 ;RESTORE SP TO NO ERROR RETURN AND BYPASS FURTHER STATUS CHECKING
10932 053266 162716 000010 SUB #10,(SP) ;MOVE SP TO NO ERROR
10933 053272 000137 056364 JMP 380$ ;SKIP TO END OF SUB
10934
10935 053276 40$:
10936
10937 ;REPORT AN ERROR IF 'OPI' ERROR OCCURRED DUE TO 'MOL' = 0, OR IF 'OPI'
10938 ;AND 'MOL' ARE SET, BUT 'VV' IS RESET, INDICATING AN INTERMITTENT
10939 ;'MOL'
10940 053276 032737 020000 001344 BIT #OPI,RMER11 ;IS 'OPI' SET??
10941 053304 001447 BEQ 60$ ;NO!!
10942 053306 013737 001344 001140 MOV RMER11,$GDDAT ;EXPECTED STATUS
10943 053314 042737 020000 001140 BIC #OPI,$GDDAT
10944 053322 013737 001344 001142 MOV RMER11,$BDDAT ;RECEIVED STATUS
10945 053330 032737 010000 001342 BIT #MOL,RMDSI ;WAS MEDIUM OFF LINE??
10946 053336 001404 BEQ 45$ ;YES!!
10947 053340 032737 000100 001342 BIT #VV,RMDSI ;WAS 'MOL' INTERMITTENT??
10948 053346 001013 BNE 50$ ;NO!!
10949 053350 062716 000004 45$: ADD #4,(SP) ;MOVE SP TO USER'S ERROR CALL
10950 053354 112776 000276 000000 MOVB #276,@(SP) ;WRITE ERROR NUMBER IN CALL
10951 053362 162716 000002 SUB #2,(SP) ;MOVE SP TO RETURN IF ERROR
10952 053366 004736 JSR PC,@(SP)+ ;REPORT ERROR AND RETURN
10953 053370 162716 000010 SUB #10,(SP) ;RESTORE SP TO NO ERROR
10954 053374 000413 BR 60$
10955 053376 50$:
10956
10957 ;REPORT 'OPI' ERROR, WHICH IS DUE TO 'ON CYLINDER' NOT DROPPING OR
10958 ;'RUN' TIMEOUT (20 MS) OR SEARCH TIMEOUT (50 MS)
10959 053376 062716 000004 ADD #4,(SP) ;MOVE SP TO USER'S ERROR CALL
10960 053402 112776 000277 000000 MOVB #277,@(SP) ;WRITE ERROR NUMBER IN CALL
10961 053410 162716 000002 SUB #2,(SP) ;MOVE SP TO RETURN IF ERROR
10962 053414 004736 JSR PC,@(SP)+ ;REPORT ERROR AND RETURN
10963 053416 162716 000010 SUB #10,(SP) ;RESTORE SP TO NO ERROR
10964 053422 000240 NOP
10965 053424 60$:
10966
10967 ;LOOK FOR 'IVC' ERROR DURING COMMAND INITIATION
10968 053424 032737 010000 001372 BIT #IVC,RMER21 ;WAS THERE AN 'IVC' ERROR??
10969 053432 001432 BEQ 70$ ;NO!!
```

10970					:REPORT 'IVC' ERROR DUE TO 'VV' = 0, OR REPORT ERRONEOUS 'IVC' ERROR
10971	053434	013737	001372	001140	MOV RMER21,\$GDDAT ;EXPECTED STATUS
10972	053442	042737	010000	001140	BIC #IVC,\$GDDAT
10973	053450	013737	001372	001142	MOV RMER21,\$BDDAT ;RECEIVED STATUS
10974	053456	062716	000004		ADD #4,(SP) ;MOVE SP TO USER'S ERROR
10975	053462	112776	000300	000000	MOVB #300,@(SP) ;WRITE ERROR NUMBER IN CALL
10976	053470	032737	000100	001342	BIT #VV,RMDSI ;WAS VOLUME VALID??
10977	053476	001403			BEQ 65\$;NO!!
10978	053500	112776	000301	000000	MOVB #301,@(SP) ;CHANGE ERROR NUMBER
10979	053506	162716	000002		65\$: SUB #2,(SP) ;MOVE SP TO RETURN IF ERROR
10980	053512	004736			JSR PC,@(SP)+ ;REPORT 'IVC' ERROR AND RETURN
10981	053514	162716	000010		SUB #10,(SP) ;RESTORE SP TO NO ERROR
10982	053520				70\$:
10983					
10984					:SEE IF 'ILF' OR 'RMR' IS SET
10985	053520	032737	000007	001344	BIT #ILR!ILF!RMR,RMER11
10986	053526	001510			BEQ 100\$;NO ERRORS DETECTED
10987					:REPORT AN ERROR IF 'ILR' IS SET
10988	053530	032737	000002	001344	BIT #ILR,RMER11 ;WAS 'ILR' DETECTED??
10989	053536	001424			BEQ 80\$;NO!!
10990	053540	013737	001344	001140	MOV RMER11,\$GDDAT ;EXPECTED STATUS
10991	053546	042737	000002	001140	BIC #ILR,\$GDDAT
10992	053554	013737	001344	001142	MOV RMER11,\$BDDAT ;RECEIVED STATUS
10993	053562	062716	000004		ADD #4,(SP) ;MOVE SP TO USER'S ERROR CALL
10994	053566	112776	000302	000000	MOVB #302,@(SP) ;WRITE ERROR NUMBER IN CALL
10995	053574	162716	000002		SUB #2,(SP) ;MOVE SP TO RETURN IF ERROR
10996	053600	004736			JSR PC,@(SP)+ ;REPORT ERROR AND RETURN
10997	053602	162716	000010		SUB #10,(SP) ;RESTORE SP TO NO ERROR
10998	053606	000240			NOP
10999	053610				80\$:
11000					
11001					:REPORT AN ERROR IF 'ILF' IS SET
11002	053610	032737	000001	001344	BIT #ILF,RMER11 ;WAS 'ILF' DETECTED??
11003	053616	001424			BEQ 90\$;NO!!
11004	053620	013737	001344	001140	MOV RMER11,\$GDDAT ;EXPECTED STATUS
11005	053626	042737	000001	001140	BIC #ILF,\$GDDAT
11006	053634	013737	001344	001142	MOV RMER11,\$BDDAT ;RECEIVED STATUS
11007	053642	062716	000004		ADD #4,(SP) ;MOVE SP TO USER'S ERROR CALL
11008	053646	112776	000303	000000	MOVB #303,@(SP) ;WRITE ERROR NUMBER IN CALL
11009	053654	162716	000002		SUB #2,(SP) ;MOVE SP TO RETURN IF ERROR
11010	053660	004736			JSR PC,@(SP)+ ;REPORT ERROR AND RETURN
11011	053662	162716	000010		SUB #10,(SP) ;RESTORE SP TO NO ERROR
11012	053666	000240			NOP
11013	053670				90\$:
11014					
11015					:REPORT AN ERROR IF 'RMR' IS SET
11016	053670	032737	000004	001344	BIT #RMR,RMER11 ;WAS 'RMR' DETECTED??
11017	053676	001424			BEQ 100\$;NO!!
11018	053700	013737	001344	001140	MOV RMER11,\$GDDAT ;EXPECTED STATUS
11019	053706	042737	000004	001140	BIC #RMR,\$GDDAT
11020	053714	013737	001344	001142	MOV RMER11,\$BDDAT ;RECEIVED STATUS
11021	053722	062716	000004		ADD #4,(SP) ;MOVE SP TO USER'S ERROR CALL
11022	053726	112776	000304	000000	MOVB #304,@(SP) ;WRITE ERROR NUMBER IN CALL
11023	053734	162716	000002		SUB #2,(SP) ;MOVE SP TO RETURN IF ERROR
11024	053740	004736			JSR PC,@(SP)+ ;REPORT ERROR AND RETURN
11025	053742	162716	000010		SUB #10,(SP) ;RESTORE SP TO NO ERROR

```
11026 053746 000240      NOP
11027 053750      100$:
11028      ; DETERMINE WHETHER OR NOT "IAE" SHOULD BE SET AND CHECK FOR ERROR
11029 053750 012737 002000 001140      MOV      #IAE,$GDDAT      ; SETUP FOR "IAE" = 1
11030 053756 052737 040000 056412      BIS      #SKI,500$      ; SET SKI FLAG
11031 053764 022737 001466 001434      CMP      #822.,RMDCO      ; IS CYLINDER > 822??
11032 053772 103425      BLO      110$      ; YES!!
11033 053774 042737 040000 056412      BIC      #SKI,500$      ; RESET SKI FLAG
11034 054002 122737 000004 001407      CMPB     #4,RMDAO+1      ; IS TRACK > 4??
11035 054010 103416      BLO      110$      ; YES!!
11036 054012 122737 000037 001406      CMPB     #31.,RMDAO      ; IS SECTOR > 31??
11037 054020 103412      BLO      110$      ; YES!!
11038 054022 122737 000035 001406      CMPB     #29.,RMDAO      ; IS SECTOR > 29??
11039 054030 103004      BHIS     105$      ; NO - IAE SHOULD BE ZERO
11040 054032 032737 010000 001432      BIT      #FMT16,RMOFO      ; 18 BIT FORMAT??
11041 054040 001402      BEQ      110$      ; YES!!
11042 054042 005037 001140      105$:      CLR      $GDDAT      ; IAE SHOULD BE ZERO
11043 054046 013737 001344 001142      110$:      MOV      RMER11,$BDDAT      ; GET RECEIVED STATUS
11044 054054 042737 175777 001142      BIC      #^CIAE,$BDDAT
11045 054062 023737 001140 001142      CMP      $GDDAT,$BDDAT      ; IS "IAE" STATUS OK??
11046 054070 001004      BNE      115$      ; NO!!
11047 054072 042737 040000 056412      BIC      #SKI,500$      ; IAE OK - SKI SHOULD BE 0
11048 054100 000412      BR       120$
11049 054102 062716 000004      115$:      ADD      #4,(SP)      ; MOVE SP TO USER'S ERROR CALL
11050 054106 112776 000305 000000      MOV      #305,@(SP)      ; WRITE ERROR NUMBER
11051 054114 162716 000002      SUB      #2,(SP)      ; MOVE SP TO RETURN IF ERROR
11052 054120 004736      JSR      PC,@(SP)+      ; REPORT ERROR AND RETURN
11053 054122 162716 000010      SUB      #10,(SP)      ; MOVE SP TO NO ERROR
11054 054126      120$:
11055
11056      ; REPORT AN ERROR IF "SKI" IS SET AND "IAE" STATUS WAS OK
11057 054126 013737 001372 001142      MOV      RMER21,$BDDAT      ; RECEIVED STATUS
11058 054134 042737 137777 001142      BIC      #^CSKI,$BDDAT
11059 054142 013737 056412 001140      MOV      500$,$GDDAT      ; EXPECTED STATUS
11060 054150 042737 137777 001140      BIC      #^CSKI,$GDDAT
11061 054156 032737 040000 001372      BIT      #SKI,RMER21      ; WAS "SKI" SET??
11062 054164 001417      BEQ      140$      ; NO!!
11063 054166 032737 040000 056412      BIT      #SKI,500$      ; WAS SKI CAUSED BY IAE = 0??
11064 054174 001032      BNE      150$      ; YES - DON'T REPORT SKI
11065 054176 062716 000004      ADD      #4,(SP)      ; MOVE SP TO USER'S ERROR CALL
11066 054202 112776 000306 000000      MOV      #306,@(SP)      ; WRITE ERROR NUMBER
11067 054210 162716 000002      SUB      #2,(SP)      ; MOVE SP TO RETURN IF ERROR
11068 054214 004736      JSR      PC,@(SP)+      ; REPORT ERROR AND RETURN
11069 054216 162716 000010      SUB      #10,(SP)      ; MOVE SP TO NO ERROR
11070 054222 000417      BR       150$
11071
11072 054224      140$:
11073
11074      ; REPORT AN ERROR IF SKI = 0 AND IAE WAS NOT DETECTED
11075 054224 032737 040000 056412      BIT      #SKI,500$      ; SHOULD SKI BE SET??
11076 054232 001413      BEQ      150$      ; NO!!
11077 054234 062716 000004      ADD      #4,(SP)      ; MOVE SP TO USER'S ERROR CALL
11078 054240 112776 000307 000000      MOV      #307,@(SP)      ; WRITE ERROR NUMBER IN CALL
11079 054246 162716 000002      SUB      #2,(SP)      ; MOVE SP TO RETURN IF ERROR
11080 054252 004736      JSR      PC,@(SP)+      ; REPORT ERROR AND RETURN
11081 054254 162716 000010      SUB      #10,(SP)      ; RESTORE SP TO NO ERROR
```

```

11082 054260 000240      NOP
11083 054262      150$:
11084
11085      ;LOOK FOR 'LSC' OR 'LBC' OR 'DVC' IN ERROR REGISTER #2
11086 054262 032737 006200 001372      BIT      #LSC!LBC!DVC,RMER21
11087 054270 001512      BEQ      180$      ;NO ERRORS SET
11088
11089      ;REPORT ANY DEVICE FAULT, I.E., 'DVC' = 1
11090 054272 032737 000200 001372      BIT      #DVC,RMER21      ;IS 'DVC' = 1??
11091 054300 001424      BEQ      160$      ;NO!!
11092 054302 013737 001372 001140      MOV      RMER21,$GDDAT      ;EXPECTED STATUS
11093 054310 042737 000200 001140      BIC      #DVC,$GDDAT
11094 054316 013737 001372 001142      MOV      RMER21,$BDDAT      ;RECEIVED STATUS
11095 054324 062716 000004      ADD      #4,(SP)      ;MOVE SP TO USERS ERROR
11096 054330 112776 000310 000000      MOVB     #310,@(SP)      ;WRITE ERROR NUMBER IN CALL
11097 054336 162716 000002      SUB      #2,(SP)      ;MOVE SP TO RETURN IF ERROR
11098 054342 004736      JSR      PC,@(SP)+      ;REPORT ERROR AND RETURN
11099 054344 162716 000010      SUB      #10,(SP)      ;RESTORE SP TO NO ERROR
11100 054350 000240      NOP
11101 054352      160$:
11102
11103      ;REPORT LOSS OF BIT CLOCK, I.E., 'LBC' = 1, IF 'MOL' = 1
11104 054352 032737 002000 001372      BIT      #LBC,RMER21      ;IS LBC SET??
11105 054360 001430      BEQ      170$      ;NO!!
11106 054362 032737 010000 001342      BIT      #MOL,RMDSI      ;WAS LBC ERROR BY MOL = 0
11107 054370 001424      BEQ      170$      ;YES!!
11108 054372 013737 001372 001140      MOV      RMER21,$GDDAT      ;EXPECTED STATUS
11109 054400 042737 002000 001140      BIC      #LBC,$GDDAT
11110 054406 013737 001372 001142      MOV      RMER21,$BDDAT      ;RECEIVED STATUS
11111 054414 062716 000004      ADD      #4,(SP)      ;MOVE SP TO USER'S ERROR CALL
11112 054420 112776 000311 000000      MOVB     #311,@(SP)      ;WRITE ERROR NUMBER IN CALL
11113 054426 162716 000002      SUB      #2,(SP)      ;MOVE SP TO RETURN IF ERROR
11114 054432 004736      JSR      PC,@(SP)+      ;REPORT ERROR AND RETURN
11115 054434 162716 000010      SUB      #10,(SP)      ;RESTORE SP TO NO ERROR
11116 054440 000240      NOP
11117 054442      170$:
11118
11119      ;REPORT LOS OF SYSTEM CLOCK, I.E., 'LSC' = 1
11120 054442 032737 004000 001372      BIT      #LSC,RMER21      ;IS 'LSC' = 1??
11121 054450 001422      BEQ      180$      ;NO!!
11122 054452 013737 001372 001140      MOV      RMER21,$GDDAT      ;EXPECTED STATUS
11123 054460 042737 004000 001140      BIC      #LSC,$GDDAT
11124 054466 013737 001372 001142      MOV      RMER21,$BDDAT      ;RECEIVED STATUS
11125 054474 062716 000004      ADD      #4,(SP)      ;MOVE SP TO USER'S ERROR CALL
11126 054500 112776 000312 000000      MOVB     #312,@(SP)      ;WRITE ERROR NUMBER
11127 054506 004736      JSR      PC,@(SP)+      ;REPORT ERROR AND RETURN
11128 054510 162716 000010      SUB      #10,(SP)      ;RESTORE SP TO NO ERROR
11129 054514 000240      NOP
11130 054516      180$:
11131
11132      ;LOOK FOR 'UNS' OR 'DTE' OR 'WLE' IN ERROR REGISTER #1
11133 054516 032737 054000 001344      BIT      #UNS!DTE!WLE,RMER11
11134 054524 001527      BEQ      220$      ;NO BITS SET
11135
11136      ;REPORT 'UNS' ERROR IF 'DVC' = 0
11136 054526 032737 040000 001344      BIT      #UNS,RMER11      ;IS 'UNS' SET??
11137 054534 001427      BEQ      190$      ;NO!!

```

```
11138 054536 032737 000200 001372      BIT      #DVC,RMER21      ;WAS 'UNS' CAUSED BY 'DVC'??
11139 054544 001023                BNE      190$              ;YES!!
11140 054546 013737 001344 001140      MOV      RMER11,$GDDAT      ;EXPECTED STATUS
11141 054554 042737 040000 001140      BIC      #UNS,$GDDAT
11142 054562 013737 001344 001142      MOV      RMER11,$BDDAT      ;RECEIVED STATUS
11143 054570 062716 000004                ADD      #4,(SP)          ;MOVE SP TO USERS ERROR CALL
11144 054574 112776 000313 000000      MOV      #313,@(SP)        ;WRITE ERROR NUMBER
11145 054602 162716 000002                SUB      #2,(SP)          ;MOVE SP TO RETURN IF ERROR
11146 054606 004736                JSR      PC,@(SP)+          ;REPORT ERROR AND RETURN
11147 054610 162716 000010                SUB      #10,(SP)         ;RESTORE SP TO NO ERROR
11148 054614                190$:
11149
11150                ;REPORT ANY DRIVE TIMING ERROR, I.E., 'DTE' = 1
11151 054614 032737 010000 001344      BIT      #DTE,RMER11      ;IS DTE SET??
11152 054622 001423                BEQ      200$              ;NO!!
11153 054624 013737 001344 001140      MOV      RMER11,$GDDAT      ;EXPECTED STATUS
11154 054632 042737 010000 001140      BIC      #DTE,$GDDAT
11155 054640 013737 001344 001142      MOV      RMER11,$BDDAT      ;RECEIVED STATUS
11156 054646 062716 000004                ADD      #4,(SP)          ;MOVE SP TO USER'S ERROR CALL
11157 054652 112776 000314 000000      MOV      #314,@(SP)        ;WRITE ERROR NUMBER IN CALL
11158 054660 162716 000002                SUB      #2,(SP)          ;MOVE SP TO RETURN IF ERROR
11159 054664 004736                JSR      PC,@(SP)+          ;REPORT ERROR AND RETURN
11160 054666 162716 000010                SUB      #10,(SP)         ;MOVE SP TO NO ERROR
11161 054672                200$:
11162
11163                ;REPORT AN ERROR IF WRITE LOCK ERROR IS SET. SEE IF DRIVE IS NOT
11164                ;WRITE PROTECTED, OR IF FUNCTION WAS NOT A WRITE
11165 054672 032737 004000 001344      BIT      #WLE,RMER11      ;WAS 'WLE' SET??
11166 054700 001441                BEQ      220$              ;NO!!
11167 054702 013737 001344 001142      MOV      RMER11,$BDDAT      ;RECEIVED STATUS
11168 054710 013737 001344 001140      MOV      RMER11,$GDDAT      ;EXPECTED STATUS
11169 054716 052737 004000 001140      BIS      #WLE,$GDDAT
11170 054724 062716 000004                ADD      #4,(SP)          ;MOVE SP TO USERS ERROR CALL
11171 054730 112776 000315 000000      MOV      #315,@(SP)        ;WRITE ERROR NUMBER IN CALL
11172 054736 032737 004000 001342      BIT      #WRL,RMDS1      ;WAS DRIVE WRITE PROTECTED??
11173 054744 001404                BEQ      205$              ;NO!!
11174 054746 032737 000010 001400      BIT      #BIT3,RMCS10     ;WAS COMMAND A WRITE??
11175 054754 001406                BEQ      210$              ;YES!!
11176 054756 112776 000316 000000 205$: MOV      #316,@(SP)        ;CHANGE ERROR NUMBER
11177 054764 042737 004000 001140      BIC      #WLE,$GDDAT
11178 054772 162716 000002                SUB      #2,(SP)          ;MOVE SP TO RETURN IF ERROR
11179 054776 004736                JSR      PC,@(SP)+          ;REPORT ERROR AND RETURN
11180 055000 162716 000010                SUB      #10,(SP)         ;MOVE SP TO NO ERROR
11181
11182 055004                220$:
11183
11184                ;OMIT DATA ERROR CHECKS IF ANY PREVIOUS ERRORS HAVE BEEN DETECTED
11185 055004 062716 000004                ADD      #4,(SP)          ;MOVE SP TO USER'S ERROR
11186 055010 105776 000000      TSTB      @(SP)          ;WAS ERROR DETECTED??
11187 055014 001404                BEQ      225$              ;NO - DO DATA CHECKS
11188 055016 162716 000004                SUB      #4,(SP)          ;RESTORE SP
11189 055022 000137 056024                JMP      340$          ;SKIP DATA CHECKS
11190 055026 162716 000004 225$: SUB      #4,(SP)          ;RESTORE SP
11191
11192                ;CHECK HEADER ERRORS IF FUNCTION WAS NOT WRITE HEADER AND DATA, AND
11193                ;IF HEADER COMPARE IS NOT INHIBITED
```

```
11194 055032 013737 001400 056414      MOV      RMCS10,510$      ;STRIP AND STORE FUNCTION CODE
11195 055040 042737 177700 056414      BIC      #^CFNCMSK,510$
11196 055046 022737 000063 056414      CMP      #WH!GO,510$      ;WAS FUNCTION WRITE HEADER & DATA??
11197 055054 001512                BEQ      250$      ;YES - SKIP HEADER CHECKS
11198 055056 032737 002000 001362      BIT      #HCI,RMOF1      ;WAS HCI SET??
11199 055064 001106                BNE      250$      ;YES - SKIP HEADER CHECKS
11200
11201                ;SEE IF ANY HEADER ERRORS ARE SET, I.E., 'FER' OR 'HCRC' OR 'HCE'
11202 055066 032737 000620 001344      BIT      #HCRC!FER!HCE,RMER11
11203 055074 001533                BEQ      270$      ;NO ERRORS SET
11204
11205                ;REPORT HEADER CRC ERROR IF SET
11206 055076 032737 000400 001344      BIT      #HCRC,RMER11      ;WAS HCRC SET??
11207 055104 001422                BEQ      230$      ;NO!!
11208 055106 013737 001344 001140      MOV      RMER11,$GDDAT      ;EXPECTED STATUS
11209 055114 042737 000400 001140      BIC      #HCRC,$GDDAT
11210 055122 013737 001344 001142      MOV      RMER11,$BDDAT      ;RECEIVED STATUS
11211 055130 062716 000004                ADD      #4,(SP)      ;MOVE SP TO USERS ERROR
11212 055134 112776 000317 000000      MOV      #317,@(SP)      ;WRITE ERROR NUMBER
11213 055142 162716 000002      SUB      #2,(SP)      ;MOVE SP TO RETURN IF ERROR
11214 055146 004736                JSR      PC,@(SP)+      ;REPORT ERROR AND RETURN
11215 055150 000501                BR       260$
11216 055152                230$:
11217
11218                ;REPORT FORMAT ERROR IF SET
11219 055152 032737 000020 001344      BIT      #FER,RMER11      ;WAS 'FER' SET??
11220 055160 001422                BEQ      240$      ;NO!!
11221 055162 013737 001344 001140      MOV      RMER11,$GDDAT      ;EXPECTED STATUS
11222 055170 042737 000020 001140      BIC      #FER,$GDDAT
11223 055176 013737 001344 001142      MOV      RMER11,$BDDAT      ;RECEIVED STATUS
11224 055204 062716 000004                ADD      #4,(SP)      ;MOVE SP TO USERS ERROR
11225 055210 112776 000320 000000      MOV      #320,@(SP)      ;WRITE ERROR NUMBER
11226 055216 162716 000002      SUB      #2,(SP)      ;MOVE SP TO RETURN IF ERROR
11227 055222 004736                JSR      PC,@(SP)+      ;REPORT ERROR AND RETURN
11228 055224 000453                BR       260$
11229 055226                240$:
11230
11231                ;REPORT HEADER COMPARE ERROR IF SET
11232 055226 032737 000200 001344      BIT      #HCE,RMER11      ;WAS 'HCE' SET??
11233 055234 001453                BEQ      270$      ;NO!!
11234 055236 013737 001344 001140      MOV      RMER11,$GDDAT      ;EXPECTED STATUS
11235 055244 042737 000200 001140      BIC      #HCE,$GDDAT
11236 055252 013737 001344 001142      MOV      RMER11,$BDDAT      ;RECEIVED STATUS
11237 055260 062716 000004                ADD      #4,(SP)      ;MOVE SP TO USER'S ERROR
11238 055264 112776 000321 000000      MOV      #321,@(SP)      ;WRITE ERROR NUMBER
11239 055272 162716 000002      SUB      #2,(SP)      ;MOVE SP TO RETURN IF ERROR
11240 055276 004736                JSR      PC,@(SP)+      ;REPORT ERROR AND RETURN
11241 055300 000425                BR       260$
11242
11243                ;THERE SHOULD BE NO HEADER ERRORS BECAUSE
11244                ;.COMMAND WAS WRITE HEADER AND DATA, OR
11245                ;.HEADER COMPARE INHIBIT WAS SET
11245 055302 032737 000620 001344      250$: BIT      #HCE!FER!HCRC,RMER11
11246 055310 001425                BEQ      270$      ;NO ERRORS WERE SET
11247 055312 013737 001344 001140      MOV      RMER11,$GDDAT      ;EXPECTED STATUS
11248 055320 042737 000620 001140      BIC      #HCE!FER!HCRC,$GDDAT
11249 055326 013737 001344 001142      MOV      RMER11,$BDDAT      ;RECEIVED STATUS
```



```
11250 055334 062716 000004      ADD    #4,(SP)      ;MOVE SP TO USER'S ERROR CALL
11251 055340 112776 000322 000000  MOVB   #322,@(SP)    ;WRITE ERROR NUMBER
11252 055346 162716 000002      SUB    #2,(SP)      ;MOVE SP TO RETURN IF ERROR
11253 055352 004736      JSR    PC,@(SP)+  ;REPORT ERROR AND RETURN
11254 055354 162716 000010      SUB    #10,(SP)     ;MOVE SP TO NO ERROR
11255 055360 000137 056024      JMP     340$      ;OMIT FUPTRHER DATA CHECKS
11256
11257 055364      270$:
11258
11259 ;IF COMMAND WAS A WRITE COMMAND, GO DO WRITE ERROR CHECKS, OTHERWISE
11260 ;DO READ ERROR CHECKS
11261 055364 032737 000010 056414  BIT    #BIT3,510$    ;WAS THIS A WRITE COMMAND?
11262 055372 001002      BNE    275$      ;NO!!
11263 055374 000137 055612      JMP     310$      ;GO DO WRITE STATUS CHECK
11264 055400      275$:
11265
11266 ;REPORT DATA CHECK IF SET
11267 055400 032737 100000 001344  BIT    #DCK,RMER11    ;DATA CHECK ERROR??
11268 055406 001450      BEQ     290$      ;NO!!
11269 055410 013737 001344 001140  MOV     RMER11,$GDDAT  ;EXPECTED STATUS
11270 055416 042737 100000 001140  BIC     #DCK,$GDDAT
11271 055424 013737 001344 001142  MOV     RMER11,$BDDAT  ;RECEIVED STATUS
11272 055432 062716 000004      ADD     #4,(SP)      ;MOVE SP TO USER'S ERROR
11273 055436 112776 000323 000000  MOVB   #323,@(SP)    ;WRITE ERROR NUMBER
11274 055444 032737 004000 001362  BIT    #EC1,RMOFI     ;WAS ECC CORRECTION DISABLED??
11275 055452 001021      BNE     280$      ;YES!!
11276 055454 112776 000324 000000  MOVB   #324,@(SP)    ;CHANGE TO RECOVERABLE ERROR
11277 055462 032737 000100 001344  BIT    #ECH,RMER11    ;IS ERROR RECOVERABLE??
11278 055470 001007      BNE     276$      ;NO !!
11279 ;DO NOT REPORT RECOVERABLE ERROR IF READ COMMAND
11280 055472 032737 000020 056414  BIT    #BIT4,510$    ;WAS THIS A READ COMMAND ??
11281 055500 001406      BEQ     280$      ;NO !!
11282 055502 162716 000004      SUB     #4,(SP)      ;RESTORE SP
11283 055506 000410      BR      290$      ;SKIP ERROR - DATA WILL BE CORRECTED
11284 055510 112776 000325 000000 276$: MOVB   #325,@(SP)    ;CHANGE TO NON RECOVERABLE
11285 055516 162716 000002 280$: SUB     #2,(SP)      ;MOVE SP TO RETURN IF ERROR
11286 055522 004736      JSR     PC,@(SP)+  ;REPORT ERROR AND RETURN
11287 055524 162716 000010      SUB     #10,(SP)     ;RESTORE SP TO NO ERROR
11288
11289 055530      290$:
11290
11291 ;REPORT DATA BUS PARITY ERROR IF SET, I.E., MDPE = 1
11292 055530 032737 000400 001340  BIT    #MDPE,RMCS21   ;PARITY ERROR SET??
11293 055536 001423      BEQ     300$      ;NO!!
11294 055540 013737 001340 001140  MOV     RMCS21,$GDDAT  ;EXPECTED STATUS
11295 055546 042737 000400 001140  BIC     #MDPE,$GDDAT
11296 055554 013737 001340 001142  MOV     RMCS21,$BDDAT  ;RECEIVED STATUS
11297 055562 062716 000004      ADD     #4,(SP)      ;MOVE SP TO USER'S ERROR
11298 055566 112776 000326 000000  MOVB   #326,@(SP)    ;WRITE ERROR NUMBER
11299 055574 162716 000002      SUB     #2,(SP)      ;MOVE SP TO RETURN IF ERROR
11300 055600 004736      JSR     PC,@(SP)+  ;REPORT ERROR AND RETURN
11301 055602 162716 000010      SUB     #10,(SP)     ;MOVE SP TO NO ERROR
11302 055606 000137 056024      300$: JMP     340$      ;SKIP WRITE STATUS CHECK
11303
11304 055612      310$:
11305
```

CZRMDCO RM03/2 FCTNL TST 2
CZRMDC.P11 12-DEC-78 08:24

MACY11 30A(1052) 04-JAN-79 11:23 L 2 PAGE 231
DATA TRANSFER COMMAND STATUS CHECK SUBROUTINE

SEQ 0231

```
11306 ;TEST TO SEE THAT OFFSET MODE WAS RESET; REPORT ERROR IF 'OM' = 1
11307 055612 032737 000001 001342 BIT #OM,RMSI ;IS OFFSET ON??
11308 055620 001423 BEQ 320$ ;NO
11309 055622 013737 001342 001140 MOV RMSI,$GDDAT ;EXPECTED STATUS
11310 055630 042737 000001 001140 BIC #OM,$GDDAT
11311 055636 013737 001342 001142 MOV RMSI,$BDDAT ;RECEIVED STATUS
11312 055644 062716 000004 ADD #4,(SP) ;MOVE SP TO USER'S ERROR CALL
11313 055650 112776 000327 000000 MOVB #327,@(SP) ;WRITE ERROR NUMBER IN CALL
11314 055656 162716 000002 SUB #2,(SP) ;MOVE SP TO RETURN IF ERROR
11315 055662 004736 JSR PC,@(SP)+ ;REPORT ERROR AND RETURN
11316 055664 162716 000010 SUB #10,(SP) ;MOVE SP TO NO ERROR
11317 055670 320$:
11318
11319 ;TEST FOR DATA BUS PARITY ERROR; REPORT ERROR IF 'DPE' = 1
11320 055670 032737 000010 001372 BIT #DPE,RMER21 ;DATA PARITY ERROR??
11321 055676 001423 BEQ 330$ ;NO!!
11322 055700 013737 001372 001140 MOV RMER21,$GDDAT ;EXPECTED STATUS
11323 055706 042737 000010 001140 BIC #DPE,$GDDAT
11324 055714 013737 001372 001142 MOV RMER21,$BDDAT ;RECEIVED STATUS
11325 055722 062716 000004 ADD #4,(SP) ;MOVE SP TO USER'S ERROR CALL
11326 055726 112776 000330 000000 MOVB #330,@(SP) ;WRITE ERROR NUMBER
11327 055734 162716 000002 SUB #2,(SP) ;MOVE SP TO RETURN IF ERROR
11328 055740 004736 JSR PC,@(SP)+ ;REPORT ERROR AND RETURN
11329 055742 162716 000010 SUB #10,(SP) ;MOVE SP TO NO ERROR
11330 055746 330$:
11331
11332 ;TEST FOR WRITE CLOCK FAILURE; REPORT ERROR IF 'WCF' = 1
11333 055746 032737 000040 001344 BIT #WCF,RMER11 ;IS 'WCF' SET??
11334 055754 001423 BEQ 340$ ;NO!!
11335 055756 013737 001344 001140 MOV RMER11,$GDDAT ;EXPECTED STATUS
11336 055764 042737 000040 001140 BIC #WCF,$GDDAT
11337 055772 013737 001344 001142 MOV RMER11,$BDDAT ;RECEIVED STATUS
11338 056000 062716 000004 ADD #4,(SP) ;MOVE SP TO USERS ERROR CALL
11339 056004 112776 000331 000000 MOVB #331,@(SP) ;WRITE ERROR NUMBER
11340 056012 162716 000002 SUB #2,(SP) ;MOVE SP TO RETURN IF ERROR
11341 056016 004736 JSR PC,@(SP)+ ;REPORT ERROR AND RETURN
11342 056020 162716 000010 SUB #10,(SP) ;MOVE SP TO NO ERROR
11343 056024 340$:
11344
11345 ;REPORT 'DATA LATE' ERROR IF 'DLT' = 1
11346 056024 032737 100000 001340 BIT #DLT,RMCS21 ;IS 'DLT' SET??
11347 056032 001423 BEQ 350$ ;NO!!
11348 056034 013737 001340 001140 MOV RMCS21,$GDDAT ;EXPECTED STATUS
11349 056042 042737 100000 001140 BIC #DLT,$GDDAT
11350 056050 013737 001340 001142 MOV RMCS21,$BDDAT ;RECEIVED STATUS
11351 056056 062716 000004 ADD #4,(SP) ;MOVE SP TO USERS ERROR CALL
11352 056062 112776 000332 000000 MOVB #332,@(SP) ;WRITE ERROR NUMBER
11353 056070 162716 000002 SUB #2,(SP) ;MOVE SP TO RETURN IF ERROR
11354 056074 004736 JSR PC,@(SP)+ ;REPORT ERROR AND RETURN
11355 056076 162716 000010 SUB #10,(SP) ;MOVE SP TO NO ERROR
11356 056102 350$:
11357 ;LOOK FOR UNEXPECTED CHANGES IN DRIVE STATUS
11358 056102 013746 001342 MOV RMSI,-(SP) ;STACK DRIVE STATUS
11359 056106 042716 147677 BIC #^C<PIP!MOL!VV>,(SP) ;CLEAR DONT CARES
11360 056112 022726 010100 CMP #MOL!VV,(SP)+ ;IS DRIVE STATUS OK??
11361 056116 001522 BEQ 380$ ;YES!!
```



```
11362
11363 ;REPORT ERROR IF POSITIONING IN PROGRESS AND NO SEEK INCOMPLETE ERROR,
11364 ;I.E. PIP = 1 AND SKI = 0
11365 056120 032737 020000 001342 BIT #PIP,RMSI ;IS 'PIP' SET??
11366 056126 001430 BEQ 360$ ;NO!!
11367 056130 032737 040000 001372 BIT #SKI,RMER2I ;WAS 'SKI' ERROR REPORTED??
11368 056136 001024 BNE 360$ ;YES-DONT REPORT PIP
11369 056140 013737 001342 001140 MOV RMSI,$GDDAT ;EXPECTED STATUS
11370 056146 042737 020000 001140 BIC #PIP,$GDDAT
11371 056154 013737 001342 001142 MOV RMSI,$BDDAT ;RECEIVED STATUS
11372 056162 062716 000004 ADD #4,(SP) ;MOVE SP TO USERS ERROR CALL
11373 056166 112776 000333 000000 MOVB #333,@(SP) ;WRITE ERROR NUMBER
11374 056174 162716 000002 SUB #2,(SP) ;MOVE SP TO RETURN IF ERROR
11375 056200 004736 JSR PC,@(SP)+ ;REPORT ERROR AND RETURN
11376 056202 162716 000010 SUB #10,(SP) ;MOVE SP TO NO ERROR
11377 056206 000240 NOP
11378 056210 360$:
11379
11380 ;REPORT ERROR IF MEDIUM IS NOT ON LINE AND OPI ERROR WAS NOT
11381 ;REPORTED, I.E., MOL = OPI = 0
11382 056210 032737 010000 001342 BIT #MOL,RMSI ;IS MEDIUM ON LINE??
11383 056216 001027 BNE 370$ ;YES!!
11384 056220 032737 020000 001344 BIT #OPI,RMER1I ;WAS OPI ERROR REPORTED??
11385 056226 001023 BNE 370$ ;YES!!
11386 056230 013737 001342 001140 MOV RMSI,$GDDAT ;EXPECTED STATUS
11387 056236 052737 010000 001140 BIS #MOL,$GDDAT
11388 056244 013737 001342 001142 MOV RMSI,$BDDAT ;RECEIVED STATUS
11389 056252 062716 000004 ADD #4,(SP) ;MOVE SP TO USER'S ERROR
11390 056256 112776 000334 000000 MOVB #334,@(SP) ;WRITE ERROR NUMBER
11391 056264 162716 000002 SUB #2,(SP) ;MOVE SP TO RETURN IF ERROR
11392 056270 004736 JSR PC,@(SP)+ ;REPORT ERROR AND RETURN
11393 056272 162716 000010 SUB #10,(SP) ;MOVE SP TO NO ERROR
11394 056276 370$:
11395
11396 ;REPORT ERROR IF VOLUME IS NOT VALID AND 'IVC' ERROR WAS NOT
11397 ;REPORTED, I.E., VV = IVC = 0
11398 056276 032737 000100 001342 BIT #VV,RMSI ;IS VOLUME VALID??
11399 056304 001027 BNE 380$ ;YES!!
11400 056306 032737 010000 001372 BIT #IVC,RMER2I ;WAS IVC ERROR REPORTED??
11401 056314 001033 BNE 390$ ;YES!!
11402 056316 013737 001342 001140 MOV RMSI,$GDDAT ;EXPECTED STATUS
11403 056324 052737 000100 001140 BIS #VV,$GDDAT
11404 056332 013737 001342 001142 MOV RMSI,$BDDAT ;RECEIVED STATUS
11405 056340 062716 000004 ADD #4,(SP) ;MOVE SP TO USERS ERROR CALL
11406 056344 112776 000335 000000 MOVB #335,@(SP) ;WRITE ERROR NUMBER
11407 056352 162716 000002 SUB #2,(SP) ;MOVE SP TO RETURN IF ERROR
11408 056356 004736 JSR PC,@(SP)+ ;REPORT ERROR AND RETURN
11409 056360 162716 000010 SUB #10,(SP) ;MOVE SP TO NO ERROR
11410 056364 380$:
11411
11412 ;AUGMENT THE RETURN ADDRESS IF ANY ERROR WAS FOUND
11413 056364 062716 000004 ADD #4,(SP) ;MOVE SP TO ERROR CALL
11414 056370 105776 000000 TSTB @(SP) ;ANY ERROR??
11415 056374 001403 BEQ 390$ ;NO!!
11416 056376 062716 000004 ADD #4,(SP) ;YES - MOVE SP TO ERROR RETURN
11417 056402 000402 BR 400$
```

CZRMDCO RM03/2 FCTNL TST 2
CZRMDC.P11 12-DEC-78 08:24

MACY11 30A(1052) 04-JAN-79 11:23 N 2
PAGE 233
DATA TRANSFER COMMAND STATUS CHECK SUBROUTINE

SEQ 0233

11418	056404	162716	000004	390\$:	SUB	#4,(SP)	;MOVE SP TO NO ERROR RETURN
11419							
11420	056410	000207		400\$:	RTS	PC	;RETURN TO USER
11421							
11422	056412	000000		500\$:	.WORD		;ERROR FLAGS
11423	056414	000000		510\$:	.WORD		;TEMPORARY STORAGE

```

11424      .SBTTL  STATIC DRIVE STATUS CHECK SUBROUTINE
11425
11426      ;THIS SUBROUTINE LOOKS FOR UNEXPECTED CHANGES IN DRIVE
11427      ;STATUS, SUCH AS THE DRIVE LOSING VOLUME VALID.  THE SUBROUTINE
11428      ;CAN BE USED BY HOUSEKEEPING AND OTHER COMMANDS DURING WHICH THERE
11429      ;SHOULD NOT BE ANY DRIVE ERRORS OR CHANGES IN STATE.
11430
11431      ;THE FOLLOWING CONDITIONS ARE TESTED AND REPORTED AS ERRORS
11432      ;IF TRUE:
11433
11434      ;      .MOL = 0, INDICATES DRIVE WENT OFFLINE, NOTE
11435      ;      THAT MOL IS ASSUMED TO HAVE BEEN SET
11436      ;      .VV = 0, INDICATES THE DRIVE LOST VOLUME VALID
11437      ;      .PIP = 1, INDICATES THAT THE DRIVE IS OFF CYLINDER
11438      ;      .SKI = 1, INDICATES THE DRIVE HAS AN UNEXPECTED SKI ERROR
11439      ;      .DVC = 1, INDICATES AN UNEXPECTED DEVICE FAULT
11440
11441      ;THE SUBROUTINE IS CALLED AFTER STORING STATUS IN THE GET BUFFER.
11442
11443      ;(1)  JSR      PC,STCDRVSTS
11444      ;      BR       ???          RETURN HERE IF NO ERROR
11445      ;      NOP      RETURN HERE TO REPORT AN ERROR
11446      ;      ERROR    ERROR NUMBER DEFINED BY SUB
11447      ;      JSR      PC,@(SP)+    GO BACK TO SUB FOR MORE ERROR CHECKS
11448      ;      ???      RETURN HERE IF NO MORE ERRORS
11449
11450      STCDRVSTS:
11451
11452      ;CLEAR USER'S ERROR CALL
11453      ADD      #4,(SP) ;MOVE SP TO USER'S ERROR CALL
11454      CLR      @ (SP) ;CLEAR ERROR NUMBER
11455      SUB      #4,(SP) ;MOVE SP BACK TO NO ERROR RETURN
11456
11457      ;SEE IF 'MOL' = 'VV' = 1, AND 'PIP' = 0
11458      MOV      RMDSI,-(SP) ;PUT DRIVE STATUS ON STACK
11459      BIC      #^C<PIP!MOL!VV>,(SP)
11460      CMP      #MOL!VV,(SP)+ ;ARE MOL,VV AND PIP O.K.??
11461      BEQ      30$          ;YES!!
11462
11463      ;REPORT AN ERROR IF MOL = 0 AND 'OPI' = 0
11464      BIT      #MOL,RMDSI ;IS MOL ON ??
11465      BNE      10$          ;YES!!
11466      BIT      #OPI,RMER11 ;WAS 'OPI' SET??
11467      BNE      10$          ;YES-DONT REPORT 'MOL' = 0
11468      MOV      RMDSI,$GDDAT ;EXPECTED STATUS
11469      BIS      #MOL,$GDDAT
11470      MOV      RMDSI,$BDDAT ;RECEIVED STATUS
11471      ADD      #4,(SP) ;MOVE SP TO USER'S ERROR CALL
11472      MOVB     #207,@(SP) ;WRITE ERROR NUMBER IN CALL
11473      SUB      #2,(SP) ;MOVE SP TO RETURN FOR ERROR
11474      JSR      PC,@(SP)+ ;REPORT ERROR VIA USER
11475      SUB      #10,(SP) ;MOVE SP BACK TO NO ERROR RETURN

```

```
11475 056536 000240
11476 056540
11477
11478
11479 056540 032737 000100 001342
11480 056546 001030
11481 056550 032737 010000 001372
11482 056556 001024
11483 056560 013737 001342 001140
11484 056566 052737 000100 001342
11485 056574 013737 001342 001142
11486 056602 062716 000004
11487 056606 112776 000210 000000
11488 056614 162716 000002
11489 056620 004736
11490 056622 162716 000010
11491 056626 000240
11492 056630
11493
11494
11495 056630 032737 020000 001342
11496 056636 001430
11497 056640 032737 040000 001372
11498 056646 001024
11499 056650 013737 001342 001140
11500 056656 042737 020000 001140
11501 056664 013737 001342 001142
11502 056672 062716 000004
11503 056676 112776 000211 000000
11504 056704 162716 000002
11505 056710 004736
11506 056712 162716 000010
11507 056716 000240
11508 056720
11509
11510
11511 056720 013746 001372
11512 056724 042726 137577
11513 056730 001460
11514 056732
11515
11516
11517 056732 032737 000200 001372
11518 056740 001424
11519 056742 013737 001372 001140
11520 056750 042737 000200 001140
11521 056756 013737 001372 001142
11522 056764 062716 000004
11523 056770 112776 000212 000000
11524 056776 162716 000002
11525 057002 004736
11526 057004 162716 000010
11527 057010 000240
11528 057012
11529
11530
```

10\$: NOP

;REPORT AN ERROR IF VOLUME VALID IS NOW ZERO AND "IVC" = 0

BIT #VV,RMDS1 ;IS "VV" = 0??

BNE 20\$;NO!!

BIT #IVC,RMER21 ;WAS "IVC" SET??

BNE 20\$;YES-DONT REPORT "VV" = 0

MOV RMDS1,\$GDDAT ;EXPECTED STATUS

BIS #VV,RMDS1

MOV RMDS1,\$BDDAT ;RECEIVED STATUS

ADD #4,(SP) ;MOVE SP TO USER'S ERROR CALL

MOVB #210,@(SP) ;WRITE ERROR NUMBER IN CALL

SUB #2,(SP) ;MOVE SP TO RETURN FOR ERROR

JSR PC,@(SP)+ ;REPORT ERROR VIA USER

SUB #10,(SP) ;MOVE SP BACK TO NO ERROR

20\$: NOP

;REPORT AN ERROR IF DRIVE IS OFF CYLINDER AND "SKI" = 0

BIT #PIP,RMDS1 ;IS DRIVE OFF CYLINDER??

BEQ 30\$;NO!!

BIT #SKI,RMER21 ;WAS "SKI" SET??

BNE 30\$;YES-DONT REPORT "PIP" = 1

MOV RMDS1,\$GDDAT ;EXPECTED STATUS

BIC #PIP,\$GDDAT

MOV RMDS1,\$BDDAT ;RECEIVED STATUS

ADD #4,(SP) ;MOVE SP TO USER'S ERROR CALL

MOVB #211,@(SP) ;WRITE ERROR NUMBER IN USER'S CALL

SUB #2,(SP) ;MOVE SP TO RETURN FOR ERROR

JSR PC,@(SP)+ ;REPORT ERROR VIA USER

SUB #10,(SP) ;MOVE SP TO NO ERROR RETURN

30\$: NOP

;SEE IF "SKI" = "DVC" = 0

MOV RMER21,-(SP) ;PUT ERROR REG 2 ON STACK

BIC #^C<SKI!DVC>,(SP)+

BEQ 60\$;BRANCH IF NO ERROR

40\$: NOP

;REPORT AN ERROR IF THERE IS A DEVICE FAULT

BIT #DVC,RMER21 ;ANY DEVICE FAULT??

BEQ 50\$;NO!!

MOV RMER21,\$GDDAT ;EXPECTED STATUS

BIC #DVC,\$GDDAT

MOV RMER21,\$BDDAT ;RECEIVED STATUS

ADD #4,(SP) ;MOVE SP TO USER'S CALL

MOVB #212,@(SP) ;WRITE NUMBER OF ERROR IN CALL

SUB #2,(SP) ;MOVE SP TO RETURN FOR ERROR

JSR PC,@(SP)+ ;REPORT ERROR VIA USER

SUB #10,(SP) ;MOVE SP BACK TO NO ERROR

50\$: NOP

;REPORT AN ERROR IF "SKI" = 1

CZRMDCO RM03/2 FCTNL TST 2
CZRMDC.P11 12-DEC-78 08:24

MACY11 30A(1052) 04-JAN-79 11:23 PAGE 236
STATIC DRIVE STATUS CHECK SUBROUTINE

SEQ 0756

11531	057012	032737	040000	001372	BIT	#SK1,RMER21	;IS THERE A SEEK INCOMPLETE ERROR
11532	057020	001424			BEQ	60\$	;NO!!
11533	057022	013737	001372	001140	MOV	RMER21,\$GDDAT	;EXPECTED STATUS
11534	057030	042737	040000	001140	BIC	#SK1,\$GDDAT	
11535	057036	013737	001372	001142	MOV	RMER21,\$BDDAT	;RECEIVED STATUS
11536	057044	062716	000004		ADD	#4,(SP)	;MOVE SP TO USER'S ERROR CALL
11537	057050	112776	000213	000000	MOVB	#213,@(SP)	;WRITE ERROR NUMBER IN USER'S ERROR CALL
11538	057056	162716	000002		SUB	#2,(SP)	;MOVE SP TO RETURN FOR ERROR
11539	057062	004736			JSR	PC,@(SP)+	;REPORT ERROR VIA USER
11540	057064	162716	000010		SUB	#10,(SP)	;MOVE SP BACK TO NO ERROR
11541	057070	000240			NOP		
11542	057072						
11543							
11544							
11545	057072	062716	000004		ADD	#4,(SP)	;MOVE SP TO USER'S ERROR CALL
11546	057076	105776	000000		TSTB	@(SP)	;WAS AN ERROR DETECTED??
11547	057102	001403			BEQ	70\$	;NO!!
11548	057104	062716	000004		ADD	#4,(SP)	;YES - MOVE SP TO USER'S ERROR RETURN
11549	057110	000402			BR	80\$	
11550	057112	162716	000004		SUB	#4,(SP)	;NO - MOVE SP TO NO ERROR RETURN
11551	057116	000240			NOP		
11552	057120	000207			RTS	PC	;RETURN TO USER

60\$:

;AUGMENT THE RETURN ADDRESS IF ANY ERROR WAS DETECTED

70\$:

80\$:

```
11553 .SBTTL COMPOSITE ERROR CHECK SUBROUTINE
11554
11555 ;THIS SUBROUTINE CHECKS THE STORED CONTENTS OF RMER1 AND
11556 ;RMER2 AFTER MASKING EACH REGISTER WORD WITH THE USER'S STATUS
11557 ;MASKS AND REPORTS AN ERROR IF ANY BITS ARE LEFT ON AFTER
11558 ;THE MASKS ARE APPLIED.
11559
11560 ;CALL:
11561 ;(1) JSR PC, CMPERRSTS
11562 ;      .WORD MASK FOR ERROR REGISTER 1
11563 ;      .WORD MASK FOR ERROR REGISTER 2
11564 ;      BR ??? RETURN HERE IF NO ERROR
11565 ;      NOP RETURN HERE TO REPORT AN ERROR
11566 ;      ERROR ERROR NUMBER DEFINED BY SUB
11567 ;      JSR PC, @ (SP)+ GO BACK TO SUB FOR MORE ERROR CHECKS
11568 ;      ??? RETURN HERE IF NO MORE ERRORS
11569
11570 ;NOTE: BITS TO BE MASKED SHOULD BE ONE; BITS TO BE TESTED SHOULD
11571 ;BE ZERO
11572
11573 057122 CMPERRSTS:
11574
11575 ;MASK AND STORE THE CONTENTS OF RMER1 AND RMER2
11576 057122 013737 001344 001176 MOV RMER1, $TMP1 ;STORE RMER1 AT TEMP STORAGE
11577 057130 047637 000000 001176 BIC @ (SP), $TMP1 ;MASK RMER1
11578 057136 062716 000002 ADD #2, (SP) ;MOVE SP TO NEXT MASK
11579 057142 013737 001372 001200 MOV RMER2, $TMP2 ;STORE RMER2 AT TEMP STORAGE
11580 057150 047637 000000 001200 BIC @ (SP), $TMP2 ;MASK RMER2
11581
11582
11583 ;CLEAR USER'S ERROR CALL
11584 057156 062716 000006 ADD #6, (SP) ;MOVE SP TO USER'S ERROR CALL
11585 057162 105076 000000 CLRB @ (SP) ;CLEAR ERROR NUMBER
11586 057166 162716 000004 SUB #4, (SP) ;LEAVE SP AT NO ERROR RETURN
11587
11588 ;SEE IF THERE WERE ANY ERRORS IN RMER1, I.E., $TMP1
11589 057172 005737 001176 TST $TMP1 ;ANY ERRORS TO REPORT??
11590 057176 001420 BEQ $$ ;NO !!
11591 057200 013737 001176 001142 MOV $TMP1, $BDDAT ;RECEIVED STATUS FOR TYPEOUT
11592 057206 005037 001140 CLR $GDDAT ;EXPECTED STATUS FOR TYPEOUT
11593 057212 062716 000004 ADD #4, (SP) ;MOVE SP TO USER'S ERROR CALL
11594 057216 112776 000066 000000 MOVB #66, @ (SP) ;CORRECTABLE DATA CHECK ERROR #
11595 057224 162716 000002 SUB #2, (SP) ;MOVE SP TO RETURN FOR ERROR
11596 057230 004736 JSR PC, @ (SP)+ ;REPORT ERROR VIA USER
11597 057232 162716 000010 SUB #10, (SP) ;MOVE SP BACK TO BRANCH
11598 057236 000240 NOP
11599 057240 $$:
11600
11601
11602 ;SEE IF THERE ARE ANY ERRORS TO REPORT IN RMER2 ($TMP2)
11603 057240 005737 001200 TST $TMP2 ;ANY ERRORS IN RMER2?
11604 057244 001420 BEQ 10$ ;NO!!
11605
11606 057246 013737 001200 001142 MOV $TMP2, $BDDAT ;RECEIVED STATUS FOR TYPEOUT
11607 057254 005037 001140 CLR $GDDAT ;EXPECTED STATUS FOR TYPEOUT
11608 057260 062716 000004 ADD #4, (SP) ;MOVE SP TO USER'S ERROR CALL
```


11609	057264	112776	000067	000000	MOVB	#67,@(SP)	:WRITE ERROR NUMBER IN USER'S CALL
11610	057272	162716	000002		SUB	#2,(SP)	:MOVE SP TO RETURN FOR ERROR
11611	057276	004736			JSR	PC,@(SP)+	:REPORT ERROR VIA USER
11612	057300	162716	000010		SUB	#10,(SP)	:MOVE SP TO NO ERROR RETURN
11613	057304	000240			NOP		
11614	057306						
11615							
11616							
11617	057306	062716	000004				
11618	057312	105776	000000		ADD	#4,(SP)	:MOVE SP TO USER'S ERROR CALL
11619	057316	001403			TSTB	@(SP)	:WAS THERE AN ERROR CALLED??
11620	057320	062716	000004		BEQ	20\$	:NO!!
11621	057324	000402			ADD	#4,(SP)	:YES - MOVE SP TO ERROR RETURN
11622	057326	162716	000004		BR	30\$	
11623	057332	000207		20\$:	SUB	#4,(SP)	:MOVE SP TO NO ERROR RETURN
11624				30\$:	RTS	PC	:RETURN TO USER
11625							

```

11626      .SBTTL  STOP AND SHUTDOWN SUBROUTINES
11627
11628 057334      STOP:
11629
11630      ;DROP PRIORITY TO ALLOW CONSOLE INTERRUPT
11631 057334 012746 000140      MOV    #PR3,-(SP)      ;;PUT NEW PS ON STACK
11632 057340 012746 057346      MOV    #64$,-(SP)      ;;PUT NEW PC ON STACK
11633 057344 000002      RTI          ;;POP NEW PC AND PS
11634 057346
11635 057346 000240      64$:      NOP
11636      ;RAISE PRIORITY TO INHIBIT INTERRUPT
11637 057350 012746 000300      MOV    #PR6,-(SP)      ;;PUT NEW PS ON STACK
11638 057354 012746 057362      MOV    #65$,-(SP)      ;;PUT NEW PC ON STACK
11639 057360 000002      RTI          ;;POP NEW PC AND PS
11640 057362
11641
11642 057362 000207      65$:
11643
11644      10$:      RTS      PC          ;CONTINUE
11645
11645 057364 012737 177777 001326 SHUT2: MOV    #-1,CTLFG      ;SET CONTROL-C FLAG      ;;++C
11646 057372      SHUT:
11647 057372 005737 001326      TST     @CTLFG      ;HALT ?
11648 057376 001002      BNE     .+6      ;BRANCH IF YES
11649 057400 000137 007124      JMP     READY      ;CONTINUE
11650 057404 104401 057426      TYPE    ,100$      ;TYPE THE HALT MESSAGE
11651 057410 005737 000042      TST     42      ;RUNNING STANDALONE ??
11652 057414 001402      BEQ     10$      ;YES !!
11653 057416 000137 032766      JMP     $EOP      ;NO - GO TO END OF PASS
11654 057422
11655 057422 000137 005324      10$:      JMP     START      ;GO TO START
11656 057426 042524 052123 053440 100$: .ASCII  @TEST WAS HALTED@<CR><LF><LF>
11657 057434 051501 044040 046101
11658 057442 042524 006504 005012
11659 057450      000
11660      057452      .EVEN

```



```

11661 .SBTTL SAVE AND RESTORE R0-R5 ROUTINES
11662
11663 ;*****
11664 ;*SAVE R0-R5
11665 ;*CALL:
11666 ;* SAVREG
11667 ;*UPON RETURN FROM $SAVREG THE STACK WILL LOOK LIKE:
11668 ;*
11669 ;*TOP---(+16)
11670 ;* +2---(+18)
11671 ;* +4---R5
11672 ;* +6---R4
11673 ;* +8---R3
11674 ;*+10---R2
11675 ;*+12---R1
11676 ;*+14---R0
11677
11678 057452 $SAVREG:
11679 057452 010046 MOV R0,-(SP) ;;PUSH R0 ON STACK
11680 057454 010146 MOV R1,-(SP) ;;PUSH R1 ON STACK
11681 057456 010246 MOV R2,-(SP) ;;PUSH R2 ON STACK
11682 057460 010346 MOV R3,-(SP) ;;PUSH R3 ON STACK
11683 057462 010446 MOV R4,-(SP) ;;PUSH R4 ON STACK
11684 057464 010546 MOV R5,-(SP) ;;PUSH R5 ON STACK
11685 057466 016646 000022 MOV 22(SP),-(SP) ;;SAVE PS OF MAIN FLOW
11686 057472 016646 000022 MOV 22(SP),-(SP) ;;SAVE PC OF MAIN FLOW
11687 057476 016646 000022 MOV 22(SP),-(SP) ;;SAVE PS OF CALL
11688 057502 016646 000022 MOV 22(SP),-(SP) ;;SAVE PC OF CALL
11689 057506 000002 RTI
11690
11691 ;*RESTORE R0-R5
11692 ;*CALL:
11693 ;* RESREG
11694 057510 $RESREG:
11695 057510 012666 000022 MOV (SP)+,22(SP) ;;RESTORE PC OF CALL
11696 057514 012666 000022 MOV (SP)+,22(SP) ;;RESTORE PS OF CALL
11697 057520 012666 000022 MOV (SP)+,22(SP) ;;RESTORE PC OF MAIN FLOW
11698 057524 012666 000022 MOV (SP)+,22(SP) ;;RESTORE PS OF MAIN FLOW
11699 057530 012605 MOV (SP)+,R5 ;;POP STACK INTO R5
11700 057532 012604 MOV (SP)+,R4 ;;POP STACK INTO R4
11701 057534 012603 MOV (SP)+,R3 ;;POP STACK INTO R3
11702 057536 012602 MOV (SP)+,R2 ;;POP STACK INTO R2
11703 057540 012601 MOV (SP)+,R1 ;;POP STACK INTO R1
11704 057542 012600 MOV (SP)+,R0 ;;POP STACK INTO R0
11705 057544 000002 RTI
11706 .SBTTL BINARY TO ASCII AND TYPE ROUTINE
11707
11708 ;*****
11709 ;*THIS ROUTINE IS USED TO CHANGE A 16-BIT BINARY NUMBER TO A 16-BIT
11710 ;*BINARY-ASCII NUMBER AND TYPE IT.
11711 ;*CALL:
11712 ;* MOV NUMBER,-(SP) ;;NUMBER TO BE TYPED
11713 ;* TYPBN ;;TYPE IT
11714
11715 057546 010146 $TYPBN: MOV R1,-(SP) ;;SAVE R1 ON THE STACK
11716 057550 016601 000006 MOV 6(SP),R1 ;;GET THE INPUT NUMBER

```

```
11717 057554 000261          SEC          ;;SET 'C' SO CAN KEEP TRACK OF THE NUMBER OF BITS
11718 057556 112737 000060 057620 1$:  MOVB  #'0,$BIN  ;;SET CHARACTER TO AN ASCII '0'.
11719 057564 006101          ROL  R1      ;;GET THIS BIT
11720 057566 001406          BEQ  2$      ;;DONE?
11721 057570 105537 057620  ADCB  $BIN      ;;NO--SET THE CHARACTER EQUAL TO THIS BIT
11722 057574 104401 057620  TYPE  , $BIN    ;;GO TYPE THIS BIT
11723 057600 000241          CLC          ;;CLEAR 'C' SO CAN KEEP TRACK OF BITS
11724 057602 000765          BR   1$      ;;GO DO THE NEXT BIT
11725 057604 012601          MOV  (SP)+,R1  ;;POP THE STACK INTO R1
11726 057606 016666 000002 000004 2$:  MOV  2(SP),4(SP) ;;ADJUST THE STACK
11727 057614 012616          MOV  (SP)+,(SP)
11728 057616 000002          RTI          ;;RETURN TO USER
11729 057620 000      000  $BIN:  .BYTE  0,0  ;;STORAGE FOR ASCII CHAR. AND TERMINATOR
11730          .SBTTL  CONVERT BINARY TO DECIMAL AND TYPE ROUTINE
11731
11732          ;*****
11733          ;*THIS ROUTINE IS USED TO CHANGE A 16-BIT BINARY NUMBER TO A 5-DIGIT
11734          ;*SIGNED DECIMAL (ASCII) NUMBER AND TYPE IT. DEPENDING ON WHETHER THE
11735          ;*NUMBER IS POSITIVE OR NEGATIVE A SPACE OR A MINUS SIGN WILL BE TYPED
11736          ;*BEFORE THE FIRST DIGIT OF THE NUMBER. LEADING ZEROS WILL ALWAYS BE
11737          ;*REPLACED WITH SPACES.
11738          ;*CALL:
11739          ;*      MOV      NUM,-(SP)      ;;PUT THE BINARY NUMBER ON THE STACK
11740          ;*      TYPDS      ;;GO TO THE ROUTINE
11741
11742          $TYPDS:
11743          MOV  R0,-(SP)      ;;PUSH R0 ON STACK
11744          MOV  R1,-(SP)      ;;PUSH R1 ON STACK
11745          MOV  R2,-(SP)      ;;PUSH R2 ON STACK
11746          MOV  R3,-(SP)      ;;PUSH R3 ON STACK
11747          MOV  R5,-(SP)      ;;PUSH R5 ON STACK
11748          MOV  #20200,-(SP)  ;;SET BLANK SWITCH AND SIGN
11749          MOV  20(SP),R5     ;;GET THE INPUT NUMBER
11750          BPL  1$           ;;BR IF INPUT IS POS.
11751          NEG  R5           ;;MAKE THE BINARY NUMBER POS.
11752          MOVB #'-',1(SP)    ;;MAKE THE ASCII NUMBER NEG.
11753          CLR  R0           ;;ZERO THE CONSTANTS INDEX
11754          MOV  # $DBLK,R3    ;;SETUP THE OUTPUT POINTER
11755          MOVB #'',(R3)+    ;;SET THE FIRST CHARACTER TO A BLANK
11756          CLR  R2           ;;CLEAR THE BCD NUMBER
11757          MOV  $DTBL(R0),R1  ;;GET THE CONSTANT
11758          SUB  R1,R5        ;;FORM THIS BCD DIGIT
11759          BLT  4$           ;;BR IF DONE
11760          INC  R2           ;;INCREASE THE BCD DIGIT BY 1
11761          BR   3$
11762          ADD  R1,R5        ;;ADD BACK THE CONSTANT
11763          TST  R2           ;;CHECK IF BCD DIGIT=0
11764          BNE  5$          ;;FALL THROUGH IF 0
11765          TSTB (SP)        ;;STILL DOING LEADING 0'S?
11766          BMI  7$          ;;BR IF YES
11767          ASLB (SP)        ;;MSD?
11768          BCC  6$          ;;BR IF NO
11769          MOVB 1(SP),-1(R3)  ;;YES--SET THE SIGN
11770          BIS  #'0,R2       ;;MAKE THE BCD DIGIT ASCII
11771          BIS  #' ,R2       ;;MAKE IT A SPACE IF NOT ALREADY A DIGIT
11772          MOVB R2,(R3)+    ;;PUT THIS CHARACTER IN THE OUTPUT BUFFER
```

```
11773 057744 005720          TST      (R0)+      ;;JUST INCREMENTING
11774 057746 020027 000010    CMP      R0,#10      ;;CHECK THE TABLE INDEX
11775 057752 002746          BLT      2$          ;;GO DO THE NEXT DIGIT
11776 057754 003002          BGT      8$          ;;GO TO EXIT
11777 057756 010502          MOV      R5,R2        ;;GET THE LSD
11778 057760 000764          BR       6$          ;;GO CHANGE TO ASCII
11779 057762 105726          8$:  TSTB     (SP)+      ;;WAS THE LSD THE FIRST NON-ZERO?
11780 057764 100003          BPL      9$          ;;BR IF NO
11781 057766 116663 177777 177776 MOVB    -1(SP),-2(R3) ;;YES--SET THE SIGN FOR TYPING
11782 057774 105013          9$:  CLRB     (R3)      ;;SET THE TERMINATOR
11783 057776 012605          MOV      (SP)+,R5      ;;POP STACK INTO R5
11784 060000 012603          MOV      (SP)+,R3      ;;POP STACK INTO R3
11785 060002 012602          MOV      (SP)+,R2      ;;POP STACK INTO R2
11786 060004 012601          MOV      (SP)+,R1      ;;POP STACK INTO R1
11787 060006 012600          MOV      (SP)+,R0      ;;POP STACK INTO R0
11788 060010 104401 060036      TYPE     $DBLK      ;;NOW TYPE THE NUMBER
11789 060014 016666 000002 000004 MOV      2(SP),4(SP) ;;ADJUST THE STACK
11790 060022 012616          MOV      (SP)+,(SP)
11791 060024 000002          RTI                    ;;RETURN TO USER
11792 060026 023420          $DTBL: 10000.
11793 060030 001750          1000.
11794 060032 000144          100.
11795 060034 000012          10.
11796 060036 000004          $DBLK: .BLKW    4
11797                                     .SBTIL  BINARY TO OCTAL (ASCII) AND TYPE
11798
11799 *****
11800 *THIS ROUTINE IS USED TO CHANGE A 16-BIT BINARY NUMBER TO A 6-DIGIT
11801 *OCTAL (ASCII) NUMBER AND TYPE IT.
11802 *$TYPOS---ENTER HERE TO SETUP SUPPRESS ZEROS AND NUMBER OF DIGITS TO TYPE
11803 *CALL:
11804 *      MOV      NUM,-(SP)      ;;NUMBER TO BE TYPED
11805 *      TYPOS     ;;CALL FOR TYPEOUT
11806 *      .BYTE    N              ;;N=1 TO 6 FOR NUMBER OF DIGITS TO TYPE
11807 *      .BYTE    M              ;;M=1 OR 0
11808 *                                     ;;1=TYPE LEADING ZEROS
11809 *                                     ;;0=SUPPRESS LEADING ZEROS
11810 *
11811 *$TYPON---ENTER HERE TO TYPE OUT WITH THE SAME PARAMETERS AS THE LAST
11812 *$TYPOS OR $TYPOC
11813 *CALL:
11814 *      MOV      NUM,-(SP)      ;;NUMBER TO BE TYPED
11815 *      TYPON     ;;CALL FOR TYPEOUT
11816 *
11817 *$TYPOC---ENTER HERE FOR TYPEOUT OF A 16 BIT NUMBER
11818 *CALL:
11819 *      MOV      NUM,-(SP)      ;;NUMBER TO BE TYPED
11820 *      TYPOC     ;;CALL FOR TYPEOUT
11821 *
11822 060046 017646 000000          $TYPOS: MOV      2(SP),-(SP) ;;PICKUP THE MODE
11823 060052 116637 000001 060271 MOVB     1(SP),$OFILL ;;LOAD ZERO FILL SWITCH
11824 060060 112637 060273          MOVB     (SP)+,$OMODE+1 ;;NUMBER OF DIGITS TO TYPE
11825 060064 062716 000002          ADD      #2,(SP) ;;ADJUST RETURN ADDRESS
11826 060070 000406          BR       $TYPON
11827 060072 112737 000001 060271 $TYPOC: MOVB     #1,$OFILL ;;SET THE ZERO FILL SWITCH
11828 060100 112737 000006 060273          MOVB     #6,$OMODE+1 ;;SET FOR SIX(6) DIGITS
```

```
11829 060106 112737 000005 060270 $TYPON: MOVB #5,$SOCNT ;;SET THE ITERATION COUNT
11830 060114 010346 MOV R3,-(SP) ;;SAVE R3
11831 060116 010446 MOV R4,-(SP) ;;SAVE R4
11832 060120 010546 MOV R5,-(SP) ;;SAVE R5
11833 060122 113704 060273 MOVB $OMODE+1,R4 ;;GET THE NUMBER OF DIGITS TO TYPE
11834 060126 005404 NEG R4
11835 060130 062704 000006 ADD #6,R4 ;;SUBTRACT IT FOR MAX. ALLOWED
11836 060134 110437 060272 MOVB R4,$OMODE ;;SAVE IT FOR USE
11837 060140 113704 060271 MOVB $OFILL,R4 ;;GET THE ZERO FILL SWITCH
11838 060144 016605 000012 MOV 12(SP),R5 ;;PICKUP THE INPUT NUMBER
11839 060150 005003 CLR R3 ;;CLEAR THE OUTPUT WORD
11840 060152 006105 1$: ROL R5 ;;ROTATE MSB INTO 'C'
11841 060154 000404 BR 3$ ;;GO DO MSB
11842 060156 006105 2$: ROL R5 ;;FORM THIS DIGIT
11843 060160 006105 ROL R5
11844 060162 006105 ROL R5
11845 060164 010503 MOV R5,R3
11846 060166 006103 3$: ROL R3 ;;GET LSB OF THIS DIGIT
11847 060170 105337 060272 DECB $OMODE ;;TYPE THIS DIGIT?
11848 060174 100016 BPL 7$ ;;BR IF NO
11849 060176 042703 177770 BIC #177770,R3 ;;GET RID OF JUNK
11850 060202 001002 BNE 4$ ;;TEST FOR 0
11851 060204 005704 TST R4 ;;SUPPRESS THIS 0?
11852 060206 001403 BEQ 5$ ;;BR IF YES
11853 060210 005204 4$: INC R4 ;;DON'T SUPPRESS ANYMORE 0'S
11854 060212 052703 000060 BIS #'0,R3 ;;MAKE THIS DIGIT ASCII
11855 060216 052703 000040 5$: BIS #' ,R3 ;;MAKE ASCII IF NOT ALREADY
11856 060222 110337 060266 MOVB R3,8$ ;;SAVE FOR TYPING
11857 060226 104401 060266 TYPE ,8$ ;;GO TYPE THIS DIGIT
11858 060232 105337 060270 7$: DECB $SOCNT ;;COUNT BY 1
11859 060236 003347 BGT 2$ ;;BR IF MORE TO DO
11860 060240 002402 BLT 6$ ;;BR IF DONE
11861 060242 005204 INC R4 ;;INSURE LAST DIGIT ISN'T A BLANK
11862 060244 000744 BR 2$ ;;GO DO THE LAST DIGIT
11863 060246 012605 6$: MOV (SP)+,R5 ;;RESTORE R5
11864 060250 012604 MOV (SP)+,R4 ;;RESTORE R4
11865 060252 012603 MOV (SP)+,R3 ;;RESTORE R3
11866 060254 016666 000002 000004 MOV 2(SP),4(SP) ;;SET THE STACK FOR RETURNING
11867 060262 012616 MOV (SP)+,(SP)
11868 060264 000002 RTI ;;RETURN
11869 060266 000 8$: .BYTE 0 ;;STORAGE FOR ASCII DIGIT
11870 060267 000 .BYTE 0 ;;TERMINATOR FOR TYPE ROUTINE
11871 060270 000 $SOCNT: .BYTE 0 ;;OCTAL DIGIT COUNTER
11872 060271 000 $OFILL: .BYTE 0 ;;ZERO FILL SWITCH
11873 060272 000000 $OMODE: .WORD 0 ;;NUMBER OF DIGITS TO TYPE
11874 .SBTTL TYPE ROUTINE
11875
11876 ;*****
11877 ;*ROUTINE TO TYPE ASCII MESSAGE. MESSAGE MUST TERMINATE WITH A 0 BYTE.
11878 ;*THE ROUTINE WILL INSERT A NUMBER OF NULL CHARACTER AFTER A LINE FEED.
11879 ;*NOTE1: $NULL CONTAINS THE CHARACTER TO BE USED AS THE FILLER CHARACTER.
11880 ;*NOTE2: $FILLS CONTAINS THE NUMBER OF FILLER CHARACTERS REQUIRED.
11881 ;*NOTE3: $FILLC CONTAINS THE CHARACTER TO FILL AFTER.
11882 ;*
11883 ;*CALL:
11884 ;*1) USING A TRAP INSTRUCTION
```

```

11885      ;*      TYPE      ,MESADR      ;;MESADR IS FIRST ADDRESS OF AN ASCIZ STRING
11886      ;*OR
11887      ;*      TYPE
11888      ;*      MESADR
11889      ;*
11890
11891 060274 105737 001173 $TYPE: TSTB $TPFLG      ;;IS THERE A TERMINAL?
11892 060300 100002      BPL 1$      ;;BR IF YES
11893 060302 000000      HALT      ;;HALT HERE IF NO TERMINAL
11894 060304 000430      BR 3$      ;;LEAVE
11895 060306 010046 1$: MOV RO,-(SP)      ;;SAVE RO
11896 060310 017600 000002 MOV @2(SP),RO      ;;GET ADDRESS OF ASCIZ STRING
11897 060314 122737 000001 001242 CMPB #APTENV,$ENV      ;;RUNNING IN APT MODE
11898 060322 001011      BNE 62$      ;;NO,GO CHECK FOR APT CONSOLE
11899 060324 132737 000100 001243 BITB #APTPOOL,$ENV      ;;SPOOL MESSAGE TO APT
11900 060332 001405      BEQ 62$      ;;NO,GO CHECK FOR CONSOLE
11901 060334 010037 060344 MOV RO,61$      ;;SETUP MESSAGE ADDRESS FOR APT
11902 060340 004737 063220 JSR PC,$ATY3      ;;SPOOL MESSAGE TO APT
11903 060344 000000 61$: .WORD 0      ;;MESSAGE ADDRESS
11904 060346 132737 000040 001243 62$: BITB #APTCSUP,$ENV      ;;APT CONSOLE SUPPRESSED
11905 060354 001003      BNE 60$      ;;YES,SKIP TYPE OUT
11906 060356 112046 2$: MOVB (RO)+,-(SP)      ;;PUSH CHARACTER TO BE TYPED ONTO STACK
11907 060360 001005      BNE 4$      ;;BR IF IT ISN'T THE TERMINATOR
11908 060362 005726      TST (SP)+      ;;IF TERMINATOR POP IT OFF THE STACK
11909 060364 012600 60$: MOV (SP)+,RO      ;;RESTORE RO
11910 060366 062716 000002 3$: ADD #2,(SP)      ;;ADJUST RETURN PC
11911 060372 000002      RTI      ;;RETURN
11912 060374 122716 000011 4$: CMPB #HT,(SP)      ;;BRANCH IF <HT>
11913 060400 001430      BEQ 8$      ;;BRANCH IF NOT <CRLF>
11914 060402 122716 000200 CMPB #CRLF,(SP)
11915 060406 001006      BNE 5$      ;;POP <CR><LF> EQUIV
11916 060410 005726      TST (SP)+      ;;TYPE A CR AND LF
11917 060412 104401      TYPE
11918 060414 001217 $CRLF
11919 060416 105037 060552 CLRB $CHARCNT      ;;CLEAR CHARACTER COUNT
11920 060422 000755      BR 2$      ;;GET NEXT CHARACTER
11921 060424 004737 060506 5$: JSR PC,$TYPEC      ;;GO TYPE THIS CHARACTER
11922 060430 123726 001172 6$: CMPB $FILLC,(SP)+      ;;IS IT TIME FOR FILLER CHARS.?
11923 060434 001350      BNE 2$      ;;IF NO GO GET NEXT CHAR.
11924 060436 013746 001170      MOV $NULL,-(SP)      ;;GET # OF FILLER CHARS. NEEDED
11925      ;;AND THE NULL CHAR.
11926 060442 105366 000001 7$: DECB 1(SP)      ;;DOES A NULL NEED TO BE TYPED?
11927 060446 002770      BLT 6$      ;;BR IF NO--GO POP THE NULL OFF OF STACK
11928 060450 004737 060506 JSR PC,$TYPEC      ;;GO TYPE A NULL
11929 060454 105337 060552 DECB $CHARCNT      ;;DO NOT COUNT AS A COUNT
11930 060460 000770      BR 7$      ;;LOOP
11931
11932 ;HORIZONTAL TAB PROCESSOR
11933
11934 060462 112716 000040 8$: MOVB #' ,(SP)      ;;REPLACE TAB WITH SPACE
11935 060466 004737 060506 9$: JSR PC,$TYPEC      ;;TYPE A SPACE
11936 060472 132737 000007 060552 BITB #7,$CHARCNT      ;;BRANCH IF NOT AT
11937 060500 001372      BNE 9$      ;;TAB STOP
11938 060502 005726      TST (SP)+      ;;POP SPACE OFF STACK
11939 060504 000724      BR 2$      ;;GET NEXT CHARACTER
11940 060506 105777 120452 $TYPEC: TSTB @2$TPS      ;;WAIT UNTIL PRINTER IS READY

```

```
11941 060512 100375      BPL      $TYPEC
11942 060514 116677 000002 120444  MOVB  2(SP),@STPB      ;;LOAD CHAR TO BE TYPED INTO DATA REG.
11943 060522 122766 000015 000002  CMPB  #CR,2(SP)      ;;IS CHARACTER A CARRIAGE RETURN?
11944 060530 001003      BNE      1$      ;;BRANCH IF NO
11945 060532 105037 060552  CLRB   $CHARCNT      ;;YES--CLEAR CHARACTER COUNT
11946 060536 000406      BR      $TYPEX      ;;EXIT
11947 060540 122766 000012 000002 1$: CMPB  #LF,2(SP)      ;;IS CHARACTER A LINE FEED?
11948 060546 001402      BEQ      $TYPEX      ;;BRANCH IF YES
11949 060550 105227      INCB   (PC)+      ;;COUNT THE CHARACTER
11950 060552 000000      $CHARCNT: .WORD 0      ;;CHARACTER COUNT STORAGE
11951 060554 000207      $TYPEX: RTS      PC
11952
11953      .SBTTL  SCOPE HANDLER ROUTINE
11954
11955      ;*****
11956      ;*THIS ROUTINE CONTROLS THE LOOPING OF SUBTESTS. IT WILL INCREMENT
11957      ;*AND LOAD THE TEST NUMBER($TSTNM) INTO THE DISPLAY REG.(DISPLAY<7:0>)
11958      ;*AND LOAD THE ERROR FLAG ($ERFLG) INTO DISPLAY<15:08>
11959      ;*THE SWITCH OPTIONS PROVIDED BY THIS ROUTINE ARE:
11960      ;*SW14=1      LOOP ON TEST
11961      ;*SW11=1      INHIBIT ITERATIONS
11962      ;*SW09=1      LOOP ON ERROR
11963      ;*SW08=1      LOOP ON TEST IN SWR<7:0>
11964      ;*CALL
11965      ;*      SCOPE      ;;SCOPE=10T
11966
11967      $SCOPE:
11968      060556 104410      CKSWR      ;;TEST FOR CHANGE IN SOFT-SWR
11969 060560 004737 057334 120362 1$: JSR    PC,STOP      ;;LOOP ON PRESENT TEST?
11970 060564 032777 040000      BIT     #BIT14,@SWR      ;;YES IF SW14=1
11971 060572 001131      BNE      $OVER
11972      ;*****START OF CODE FOR THE XOR TESTER*****
11973 060574 000416      $XTSTR: BR     6$      ;;IF RUNNING ON THE 'XOP' TESTER CHANGE
11974      ;;THIS INSTRUCTION TO A 'NOP' (NOP=240)
11975 060576 013746 000004      MOV      @#ERRVEC,-(SP)      ;;SAVE THE CONTENTS OF THE ERROR VECTOR
11976 060602 012737 060622 000004  MOV      #5$,@#ERRVEC      ;;SET FOR TIMEOUT
11977 060610 005737 177060      TST     @#177060      ;;TIME OUT ON XOR?
11978 060614 012637 000004      MOV      (SP)+,@#ERRVEC      ;;RESTORE THE ERROR VECTOR
11979 060620 000500      BR      $SVLAD      ;;GO TO THE NEXT TEST
11980 060622 022626 5$:      CMP      (SP)+,(SP)+      ;;CLEAR THE STACK AFTER A TIME OUT
11981 060624 012637 000004      MOV      (SP)+,@#ERRVEC      ;;RESTORE THE ERROR VECTOR
11982 060630 000440      BR      7$      ;;LOOP ON THE PRESENT TEST
11983 060632 6$:;*****END OF CODE FOR THE XOR TESTER*****
11984 060632 032777 000400 120314  BIT     #BIT08,@SWR      ;;LOOP ON SPEC. TEST?
11985 060640 001421      BEQ      2$      ;;BR IF NO
11986 060642 005046      CLR      -(SP)      ;;CLEAR A TEMP. LOCATION
11987 060644 117716 120304      MOVB   @SWR,(SP)      ;;PICKUP THE DESIRED TEST NUMBER
11988 060650 001414      BEQ      8$      ;;BRANCH IF BAD TEST NUMBER IN SWR
11989 060652 022716 000035      CMP      #35,(SP)      ;;CHECK THE NUMBER IN THE SWR
11990 060656 002411      BLT      8$      ;;BRANCH IF TEST NUMBER IS OUT OF RANGE
11991 060660 011637 001116      MOV      (SP),$TSTNM      ;;UPDATE THE TEST NUMBER
11992 060664 005316      DEC      (SP)      ;;BACKUP BY ONE
11993 060666 006316      ASL      (SP)      ;;SCALE THE TEST NUMBER AS AN INDEX
11994 060670 062716 061074      ADD      #SW08TBL,(SP)      ;;FORM THE ADDRESS OF TEST POINTER
11995 060674 013637 001122      MOV      @ (SP)+,$LPADR      ;;SET LOOP ADDRESS TO DESIRED TEST
11996 060700 000466      BR      $OVER      ;;GO LOOP ON THE TEST
```



```
11997 060702 005726      8$:   TST      (SP)+      ;;CLEAN THE BAD TEST NUMBER OFF OF THE STACK
11998 060704 105737 001117 2$:   TSTB     $ERFLG      ;;HAS AN ERROR OCCURRED?
11999 060710 001421      BEQ      3$          ;;BR IF NO
12000 060712 123737 001131 001117 CMPB     $ERMAX,$ERFLG  ;;MAX. ERRORS FOR THIS TEST OCCURRED?
12001 060720 101015      BHI      3$          ;;BR IF NO
12002 060722 032777 001000 120224 BIT      #BIT09,$SWR    ;;LOOP ON ERROR?
12003 060730 001404      BEQ      4$          ;;BR IF NO
12004 060732 013737 001124 001122 7$:   MOV     $LPERR,$LPADR  ;;SET LOOP ADDRESS TO LAST SCOPE
12005 060740 000446      BR        $OVER
12006 060742 105037 001117      4$:   CLRB     $ERFLG      ;;ZERO THE ERROR FLAG
12007 060746 005037 001206      CLR      $TIMES      ;;CLEAR THE NUMBER OF ITERATIONS TO MAKE
12008 060752 000415      BR        1$          ;;ESCAPE TO THE NEXT TEST
12009 060754 032777 004000 120172 3$:   BIT      #BIT11,$SWR    ;;INHIBIT ITERATIONS?
12010 060762 001011      BNE      1$          ;;BR IF YES
12011 060764 005737 001230      TST      $PASS      ;;IF FIRST PASS OF PROGRAM
12012 060770 001406      BEQ      1$          ;;      INHIBIT ITERATIONS
12013 060772 005237 001120      INC      $ICNT      ;;INCREMENT ITERATION COUNT
12014 060776 023737 001206 001120 CMP      $TIMES,$ICNT  ;;CHECK THE NUMBER OF ITERATIONS MADE
12015 061004 002024      BGE      $OVER      ;;BR IF MORE ITERATION REQUIRED
12016 061006 012737 000001 001120 1$:   MOV     #1,$ICNT      ;;REINITIALIZE THE ITERATION COUNTER
12017 061014 013737 061072 001206 MOV     $MXCNT,$TIMES  ;;SET NUMBER OF ITERATIONS TO DO
12018 061022 105237 001116      $SVLAD: INCB     $TSTNM      ;;COUNT TEST NUMBERS
12019 061026 113737 001116 001226 MOVB     $TSTNM,$TESTN  ;;SET TEST NUMBER IN APT MAILBOX
12020 061034 011637 001122      MOV      (SP),$LPADR  ;;SAVE SCOPE LOOP ADDRESS
12021 061040 011637 001124      MOV      (SP),$LPERR  ;;SAVE ERROR LOOP ADDRESS
12022 061044 005037 001210      CLR      $ESCAPE  ;;CLEAR THE ESCAPE FROM ERROR ADDRESS
12023 061050 112737 000001 001131 MOVB     #1,$ERMAX  ;;ONLY ALLOW ONE(1) ERROR ON NEXT TEST
12024 061056 013777 001116 120072 $OVER:  MOV     $TSTNM,$DISPLAY  ;;DISPLAY TEST NUMBER
12025 061064 013716 001122      MOV      $LPADR,(SP)  ;;FUDGE RETURN ADDRESS
12026 061070 000002      RTI
12027 061072 000012      $MXCNT: 10.      ;;FIXES PS
12028 061074      $SW08TBL:      ;;MAX. NUMBER OF ITERATIONS
12029 061074 007164      .WORD     TST1+2      ;;STARTING ADDRESS OF TEST 1
12030 061076 007362      .WORD     TST2+2      ;;STARTING ADDRESS OF TEST 2
12031 061100 007546      .WORD     TST3+2      ;;STARTING ADDRESS OF TEST 3
12032 061102 007730      .WORD     TST4+2      ;;STARTING ADDRESS OF TEST 4
12033 061104 010530      .WORD     TST5+2      ;;STARTING ADDRESS OF TEST 5
12034 061106 011330      .WORD     TST6+2      ;;STARTING ADDRESS OF TEST 6
12035 061110 012144      .WORD     TST7+2      ;;STARTING ADDRESS OF TEST 7
12036 061112 012720      .WORD     TST10+2     ;;STARTING ADDRESS OF TEST 10
12037 061114 013640      .WORD     TST11+2     ;;STARTING ADDRESS OF TEST 11
12038 061116 014440      .WORD     TST12+2     ;;STARTING ADDRESS OF TEST 12
12039 061120 015214      .WORD     TST13+2     ;;STARTING ADDRESS OF TEST 13
12040 061122 016132      .WORD     TST14+2     ;;STARTING ADDRESS OF TEST 14
12041 061124 016706      .WORD     TST15+2     ;;STARTING ADDRESS OF TEST 15
12042 061126 017462      .WORD     TST16+2     ;;STARTING ADDRESS OF TEST 16
12043 061130 020236      .WORD     TST17+2     ;;STARTING ADDRESS OF TEST 17
12044 061132 021040      .WORD     TST20+2     ;;STARTING ADDRESS OF TEST 20
12045 061134 021564      .WORD     TST21+2     ;;STARTING ADDRESS OF TEST 21
12046 061136 022310      .WORD     TST22+2     ;;STARTING ADDRESS OF TEST 22
12047 061140 023032      .WORD     TST23+2     ;;STARTING ADDRESS OF TEST 23
12048 061142 023330      .WORD     TST24+2     ;;STARTING ADDRESS OF TEST 24
12049 061144 023626      .WORD     TST25+2     ;;STARTING ADDRESS OF TEST 25
12050 061146 024354      .WORD     TST26+2     ;;STARTING ADDRESS OF TEST 26
12051 061150 025102      .WORD     TST27+2     ;;STARTING ADDRESS OF TEST 27
12052 061152 025630      .WORD     TST30+2     ;;STARTING ADDRESS OF TEST 30
```

```
12053 061154 026522      .WORD TST31+2      ;;STARTING ADDRESS OF TEST 31
12054 061156 027330      .WORD TST32+2      ;;STARTING ADDRESS OF TEST 32
12055 061160 030052      .WORD TST33+2      ;;STARTING ADDRESS OF TEST 33
12056 061162 030574      .WORD TST34+2      ;;STARTING ADDRESS OF TEST 34
12057 061164 031752      .WORD TST35+2      ;;STARTING ADDRESS OF TEST 35
12058                                .SBTTL ERROR HANDLER ROUTINE
12059
12060      ;*****
12061      ;*THIS ROUTINE WILL INCREMENT THE ERROR FLAG AND THE ERROR COUNT,
12062      ;*SAVE THE ERROR ITEM NUMBER AND THE ADDRESS OF THE ERROR CALL
12063      ;*AND GO TO ERRTP ON ERROR
12064      ;*THE SWITCH OPTIONS PROVIDED BY THIS ROUTINE ARE:
12065      ;*SW15=1      HALT ON ERROR
12066      ;*SW13=1      INHIBIT ERROR TYPEOUTS
12067      ;*SW10=1      BELL ON ERROR
12068      ;*SW09=1      LOOP ON ERROR
12069      ;*CALL
12070      ;*      ERROR      N      ;;ERROR=EMT AND N=ERROR ITEM NUMBER
12071
12072      $ERROR:
12073      061166      104410
12074      061170      105237      001117      7$:      CKSWR      ;;TEST FOR CHANGE IN SOFT-SWR
12075      061174      001775      BEQ      7$      ;;SET THE ERROR FLAG
12076      061176      013777      001116      117752      MOV      $TSTNM,$DISPLAY      ;;DON'T LET THE FLAG GO TO ZERO
12077      061204      032777      002000      117742      BIT      #BIT10,$SWR      ;;DISPLAY TEST NUMBER AND ERROR FLAG
12078      061212      001402      BEQ      1$      ;;BELL ON ERROR?
12079      061214      104401      001212      TYPE      $BELL      ;;NO - SKIP
12080      061220      005237      001126      1$:      INC      $ERTTL      ;;RING BELL
12081      061224      011637      001132      MOV      (SP),$ERRPC      ;;COUNT THE NUMBER OF ERRORS
12082      061230      162737      000002      001132      SUB      #2,$ERRPC      ;;GET ADDRESS OF ERROR INSTRUCTION
12083      061236      117737      117670      001130      MOV      @ERRPC,$ITEMB      ;;STRIP AND SAVE THE ERROR ITEM CODE
12084      061244      032777      020000      117702      BIT      #BIT13,$SWR      ;;SKIP TYPEOUT IF SET
12085      061252      001004      BNE      20$      ;;SKIP TYPEOUTS
12086      061254      004737      033176      JSR      PC,ERRTP      ;;GO TO USER ERROR ROUTINE
12087      061260      104401      001217      TYPE      $CRLF
12088      061264
12089      061264      122737      000001      001242      20$:      CMPB      #APTENV,$ENV      ;;RUNNING IN APT MODE
12090      061272      001007      BNE      2$      ;;NO,SKIP APT ERROR REPORT
12091      061274      113737      001130      061306      MOV      $ITEMB,21$      ;;SET ITEM NUMBER AS ERROR NUMBER
12092      061302      004737      063230      JSR      PC,$ATY4      ;;REPORT FATAL ERROR TO APT
12093      061306      000      21$:      .BYTE      0
12094      061307      000      .BYTE      0
12095      061310      000777      22$:      BR      22$      ;;APT ERROR LOOP
12096      061312      005777      117636      2$:      TST      $SWR      ;;HALT ON ERROR
12097      061316      100002      BPL      3$      ;;SKIP IF CONTINUE
12098      061320      000000      HALT      ;;HALT ON ERROR!
12099      061322      104410      CKSWR      ;;TEST FOR CHANGE IN SOFT-SWR
12100      061324      032777      001000      117622      3$:      BIT      #BIT09,$SWR      ;;LOOP ON ERROR SWITCH SET?
12101      061332      001402      BEQ      4$      ;;BR IF NO
12102      061334      013716      001124      MOV      $LPERR,(SP)      ;;FUDGE RETURN FOR LOOPING
12103      061340      005737      001210      4$:      TST      $ESCAPE      ;;CHECK FOR AN ESCAPE ADDRESS
12104      061344      001402      BEQ      5$      ;;BR IF NONE
12105      061346      013716      001210      MOV      $ESCAPE,(SP)      ;;FUDGE RETURN ADDRESS FOR ESCAPE
12106      061352      5$:
12107      061352      022737      033156      000042      CMP      #SENDAD,$#42      ;;ACT-11 AUTO-ACCEPT?
12108      061360      001001      BNE      6$      ;;BRANCH IF NO
```



```
12109 061362 000000          HALT                ;;YES
12110 061364          6$:
12111 061364 000002          RTI                  ;;RETURN
12112          .SBTTL  TTY INPUT ROUTINE
12113
12114          ;*****
12115          .ENABL  LSB
12116 061366 000000  $TKCNT: .WORD 0                ;;NUMBER OF ITEMS IN QUEUE
12117 061370 000000  $TKQIN: .WORD 0                ;;INPUT POINTER
12118 061372 000000  $TKQOUT: .WORD 0               ;;OUTPUT POINTER
12119 061374 000001  $TKQSRT: .BLKB 1              ;;TTY KEYBOARD QUEUE
12120          $TKQEND=.
12121          061375
12122          .EVEN
12123
12124          ;*TK INITIALIZE ROUTINE
12125          ;*THIS ROUTINE WILL INITIALIZE THE TTY KEYBOARD INPUT QUEUE
12126          ;*SETUP THE INTERRUPT VECTOR AND TURN ON THE KEYBOARD INTERRUPT
12127
12128          ;*CALL:
12129          ;*      JSR      PC,$TKINT
12130          ;*      RETURN
12131 061376 005037 061366  $TKINT: CLR      $TKCNT                ;;CLEAR COUNT OF ITEMS IN QUEUE
12132 061402 012737 061374 061370  MOV      # $TKQSRT,$TKQIN    ;;MOVE THE STARTING ADDRESS OF THE
12133 061410 013737 061370 061372  MOV      $TKQIN,$TKQOUT    ;;QUEUE INTO THE INPUT & OUTPUT POINTERS.
12134 061416 012737 061446 000060  MOV      # $TKSRV,@ $TKVEC  ;;INITIALIZE THE KEYBOARD VECTOR
12135 061424 012737 000200 000062  MOV      #200,@ $TKVEC+2    ;;'BR' LEVEL 4
12136 061432 005777 117524          TST      @ $TKB            ;;CLEAR DONE FLAG
12137 061436 012777 000100 117514  MOV      #100,@ $TKS        ;;ENABLE TTY KEYBOARD INTERRUPT
12138 061444 000207          RTS      PC                    ;;RETURN TO CALLER
12139
12140          ;*TK SERVICE ROUTINE
12141          ;*THIS ROUTINE WILL SERVICE THE TTY KEYBOARD INTERRUPT
12142          ;*BY READING THE CHARACTER FROM THE INPUT BUFFER AND PUTTING
12143          ;*IT IN THE QUEUE.
12144          ;*IF THE CHARACTER IS A 'CONTROL-C' (^C) $TKINT IS CALLED AND
12145          ;*UPON RETURN EXIT IS MADE TO THE 'CONTROL-C' RESTART ADDRESS (SHUT2)
12146
12147 061446 117746 117510  $TKSRV: MOVB     @ $TKB, -(SP)        ;;PICKUP THE CHARACTER
12148 061452 042716 177600          BIC      #^C177, (SP)        ;;STRIP THE JUNK
12149 061456 021627 000003          CMP      (SP), #3            ;;IS IT A CONTROL C?
12150 061462 001007          BNE      1$                        ;;BRANCH IF NO
12151 061464 104401 062562          TYPE     , $CNTLC            ;;TYPE A CONTROL-C (^C)
12152 061470 004737 061376          JSR      PC,$TKINT          ;;INIT THE KEYBOARD
12153 061474 005726          TST      (SP)+                    ;;CLEAN UP STACK
12154 061476 000137 057364          JMP      SHUT2              ;;CONTROL C RESTART
12155 061502 021627 000007 1$:          CMP      (SP), #7            ;;IS IT A CONTROL G?
12156 061506 001004          BNE      2$                        ;;BRANCH IF NO
12157 061510 022737 000176 001154  CMP      #SWREG,SWR        ;;IS SOFT-SWR SELECTED?
12158 061516 001500          BEQ      6$                        ;;GO TO SWR CHANGE
12159
12160 061520          2$:
12161 061520 022737 000001 061366  CMP      #1,$TKCNT        ;;IS THE QUEUE FULL?
12162 061526 001004          BNE      3$                        ;;BRANCH IF NO
12163 061530 104401 001212          TYPE     , $BELL            ;;RING THE TTY BELL
12164 061534 005726          TST      (SP)+                    ;;CLEAN CHARACTER OFF OF STACK
```

```
12165 061536 000451          BR      5$          ;;EXIT
12166 061540 021627 000023    3$:  CMP      (SP),#23      ;;IS IT A CONTROL-S?
12167 061544 001021          BNE      32$          ;;BRANCH IF NO
12168 061546 005077 117406    CLR      @STKS          ;;DISABLE TTY KEYBOARD INTERRUPTS
12169 061552 005726          TST      (SP)+          ;;CLEAN CHAR OFF STACK
12170 061554 105777 117400    31$:  TSTB     @STKS          ;;WAIT FOR A CHAR
12171 061560 100375          BPL      31$          ;;LOOP UNTIL ITS THERE
12172 061562 117746 117374    MOVB     @STKB,-(SP)      ;;GET THE CHARACTER
12173 061566 042716 177600    BIC      #^C177,(SP)      ;;MAKE IT 7-BIT ASCII
12174 061572 022627 000021    CMP      (SP)+,#21      ;;IS IT A CONTROL-Q?
12175 061576 001366          BNE      31$          ;;BRANCH IF NO
12176 061600 012777 000100 117352  MOV     #100,@STKS      ;;REENABLE TTY KEYBOARD INTERRUPTS
12177 061606 000002          RTI          ;;RETURN
12178 061610 005237 061366    32$:  INC      $TKCNT          ;;COUNT THIS CHARACTER
12179 061614 021627 000140    CMP      (SP),#140      ;;IS IT UPPER CASE?
12180 061620 002405          BLT      4$          ;;BRANCH IF YES
12181 061622 021627 000175    CMP      (SP),#175      ;;IS IT A SPECIAL CHAR?
12182 061626 003002          BGT      4$          ;;BRANCH IF YES
12183 061630 042716 000040    BIC      #40,(SP)          ;;MAKE IT UPPER CASE
12184 061634 112677 177530    4$:  MOVB     (SP)+,@STKQIN      ;;AND PUT IT IN QUEUE
12185 061640 005237 061370    INC      $TKQIN          ;;UPDATE THE POINTER
12186 061644 023727 061370 061375  CMP     $TKQIN,$$TKQEND      ;;GO OFF THE END?
12187 061652 001003          BNE      5$          ;;BRANCH IF NO
12188 061654 012737 061374 061370  MOV     $$TKQSRT,$TKQIN      ;;RESET THE POINTER
12189 061662 000002    5$:  RTI          ;;RETURN
12190
12191      ;*****
12192      ;*SOFTWARE SWITCH REGISTER CHANGE ROUTINE.
12193      ;*ROUTINE IS ENTERED FROM THE TRAP HANDLER, AND WILL
12194      ;*SERVICE THE TEST FOR CHANGE IN SOFTWARE SWITCH REGISTER TRAP
12195      ;*CALL WHEN OPERATING IN TTY INTERRUPT MODE.
12196 061664 022737 000176 001154  $CKSWR:  CMP     #SWREG,SWR      ;;IS THE SOFT-SWR SELECTED
12197 061672 001124          BNE      15$          ;;EXIT IF NOT
12198 061674 105777 117260    TSTB     @STKS          ;;IS A CHAR WAITING?
12199 061700 100121          BPL      15$          ;;IF NOT, EXIT
12200 061702 117746 117254    MOVB     @STKB,-(SP)      ;;YES
12201 061706 042716 177600    BIC      #^C177,(SP)      ;;MAKE IT 7-BIT ASCII
12202 061712 021627 000007    CMP      (SP),#7          ;;IS IT A CONTROL-G?
12203 061716 001300          BNE      2$          ;;IF NOT, PUT IT IN THE TTY QUEUE
12204          ;;AND EXIT
12205
12206      ;*****
12207      ;*CONTROL IS PASSED TO THIS POINT FROM EITHER THE TTY INTERRUPT SERVICE
12208      ;*ROUTINE OR FROM THE SOFTWARE SWITCH REGISTER TRAP CALL, AS A RESULT OF A
12209      ;*CONTROL-G BEING TYPED, AND THE SOFTWARE SWITCH REGISTER BEING SELECTED.
12210 061720 123727 001150 000001  6$:  CMPB     $AUTOB,#1      ;;ARE WE RUNNING IN AUTO-MODE?
12211 061726 001674          BEQ      2$          ;;BRANCH IF YES
12212 061730 005726          TST      (SP)+          ;;CLEAR CONTROL-G OFF STACK
12213 061732 004737 061376    JSR      PC,$TKINT          ;;FLUSH THE TTY INPUT QUEUE
12214 061736 005077 117216    CLR      @STKS          ;;DISABLE TTY KEYBOARD INTERRUPTS
12215 061742 112737 000001 001151  MOVB     #1,$INTAG          ;;SET INTERRUPT MODE INDICATOR
12216
12217 061750 104401 062574          TYPE     ,$CNTLG          ;;ECHO THE CONTROL-G (^G)
12218 061754 104401 062601    $GTSWR:  TYPE     ,$MSWR          ;;TYPE CURRENT CONTENTS
12219 061760 013746 000176    MOV      SWREG,-(SP)      ;;SAVE SWREG FOR TYPEOUT
12220 061764 104402          TYPOC          ;;GO TYPE--OCTAL ASCII(ALL DIGITS)
```

12221	061766	104401	062612		TYPE	, \$MNEW	:: PROMPT FOR NEW SWR
12222	061772	005046		19\$:	CLR	-(SP)	:: CLEAR COUNTER
12223	061774	005046			CLR	-(SP)	:: THE NEW SWR
12224	061776	105777	117156	7\$:	TSTB	@\$TKS	:: CHAR THERE?
12225	062002	100375			BPL	7\$	:: IF NOT TRY AGAIN
12226							
12227	062004	117746	117152		MOVB	@\$TKB,-(SP)	:: PICK UP CHAR
12228	062010	042716	177600		BIC	#^C177,(SP)	:: MAKE IT 7-BIT ASCII
12229							
12230	062014	021627	000003		CMP	(SP),#3	:: IS IT A CONTROL-C?
12231	062020	001015			BNE	9\$	:: BRANCH IF NOT
12232	062022	104401	062562		TYPE	, \$CNTLC	:: YES, ECHO CONTROL-C (^C)
12233	062026	062706	000006		ADD	#6,SP	:: CLEAN UP STACK
12234	062032	123727	001151	000001	CMPB	\$INTAG,#1	:: REENABLE TTY KEYBOARD INTERRUPTS?
12235	062040	001003			BNE	8\$	:: BRANCH IF NO
12236	062042	012777	000100	117110	MOV	#100,@\$TKS	:: ALLOW TTY KEYBOARD INTERRUPTS
12237	062050	000137	057364	8\$:	JMP	SHUT2	:: CONTROL-C RESTART
12238							
12239							
12240	062054	021627	000025	9\$:	CMP	(SP),#25	:: IS IT A CONTROL-U?
12241	062060	001005			BNE	10\$	:: BRANCH IF NOT
12242	062062	104401	062567		TYPE	, \$CNTLU	:: YES, ECHO CONTROL-U (^U)
12243	062066	062706	000006	20\$:	ADD	#6,SP	:: IGNORE PREVIOUS INPUT
12244	062072	000737			BR	19\$	:: LET'S TRY IT AGAIN
12245							
12246							
12247	062074	021627	000015	10\$:	CMP	(SP),#15	:: IS IT A <CR>?
12248	062100	001022			BNE	16\$	:: BRANCH IF NO
12249	062102	005766	000004		TST	4(SP)	:: YES, IS IT THE FIRST CHAR?
12250	062106	001403			BEQ	11\$	:: BRANCH IF YES
12251	062110	016677	000002	117036	MOV	2(SP),@SWR	:: SAVE NEW SWR
12252	062116	062706	000006	11\$:	ADD	#6,SP	:: CLEAR UP STACK
12253	062122	104401	001217	14\$:	TYPE	, \$CRLF	:: ECHO <CR> AND <LF>
12254	062126	123727	001151	000001	CMPB	\$INTAG,#1	:: RE-ENABLE TTY KBD INTERRUPTS?
12255	062134	001003			BNE	15\$	:: BRANCH IF NOT
12256	062136	012777	000100	117014	MOV	#100,@\$TKS	:: RE-ENABLE TTY KBD INTERRUPTS
12257	062144	000002		15\$:	RTI		:: RETURN
12258	062146	004737	060506	16\$:	JSR	PC,\$TYPEC	:: ECHO CHAR
12259	062152	021627	000060		CMP	(SP),#60	:: CHAR < 0?
12260	062156	002420			BLT	18\$	:: BRANCH IF YES
12261	062160	021627	000067		CMP	(SP),#67	:: CHAR > 7?
12262	062164	003015			BGT	18\$	:: BRANCH IF YES
12263	062166	042726	000060		BIC	#60,(SP)+	:: STRIP-OFF ASCII
12264	062172	005766	000002		TST	2(SP)	:: IS THIS THE FIRST CHAR
12265	062176	001403			BEQ	17\$	:: BRANCH IF YES
12266	062200	006316			ASL	(SP)	:: NO, SHIFT PRESENT
12267	062202	006316			ASL	(SP)	:: CHAR OVER TO MAKE
12268	062204	006316			ASL	(SP)	:: ROOM FOR NEW ONE.
12269	062206	005266	000002	17\$:	INC	2(SP)	:: KEEP COUNT OF CHAR
12270	062212	056616	177776		BIS	-2(SP),(SP)	:: SET IN NEW CHAR
12271	062216	000667			BR	7\$	:: GET THE NEXT ONE
12272	062220	104401	001216	18\$:	TYPE	, \$QUES	:: TYPE ?<CR><LF>
12273	062224	000720			BR	20\$	:: SIMULATE CONTROL-U
12274				.DSABL	LSB		
12275							
12276							

12277					::*****
12278					::THIS ROUTINE WILL INPUT A SINGLE CHARACTER FROM THE TTY
12279					::CALL:
12280					::*
12281					RDCHR
12282					RETURN HERE
12283					::GET A CHARACTER FROM THE QUEUE
12284					::CHARACTER IS ON THE STACK
12285					::WITH PARITY BIT STRIPPED OFF
12286	062226	011646			\$RDCHR: MOV (SP),-(SP)
12287	062230	016666	000004	000002	PUSH DOWN THE PC AND
12288	062236	005066	000004		MOV 4(SP),2(SP)
12289	062242	005046			THE PS
12290	062244	012746	062252		CLR 4(SP)
12291	062250	000002			GET READY FOR A CHARACTER
12292	062252				CLR -(SP)
12293	062252	005737	061366		PUT NEW PS ON STACK
12294	062256	001775			MOV #64\$,-(SP)
12295	062260	005337	061366		PUT NEW PC ON STACK
12296	062264	117766	177102	000004	POP NEW PC AND PS
12297	062272	005237	061372		RTI
12298	062276	023727	061372	061375	64\$: TST STKCNT
12299	062304	001003			WAIT ON A CHARACTER
12300	062306	012737	061374	061372	1\$: BEQ 1\$
12301	062314	000002			DEC STKCNT
12302					DECREMENT THE COUNTER
12303					MOVB @STKQOUT,4(SP)
12304					GET ONE CHARACTER
12305					INC STKQOUT
12306					UPDATE THE POINTER
12307					CMP STKQOUT,#STKQEND
12308					DID IT GO OFF OF THE END?
12309					BNE 2\$
12310					BRANCH IF NO
12311					MOV #STKSRT,STKQOUT
12312					RESET THE POINTER
12313					RTI
12314					RETURN
12315					::*****
12316					::THIS ROUTINE WILL INPUT A STRING FROM THE TTY
12317					::CALL:
12318					::*
12319					RDLIN
12320					RETUPN HERE
12321					::INPUT A STRING FROM THE TTY
12322					::ADDRESS OF FIRST CHARACTER WILL BE ON THE STACK
12323					::TERMINATOR WILL BE A BYTE OF ALL 0'S
12324	062316	010346			\$RDLIN: MOV R3,-(SP)
12325	062320	005046			SAVE R3
12326	062322	012703	062552		CLR -(SP)
12327	062326	022703	062562		CLEAR THE RUBOUT KEY
12328	062332	101456			1\$: MOV #TTYIN,R3
12329	062334	104411			GET ADDRESS
12330	062336	112613			2\$: CMP #TTYIN+8.,R3
12331	062340	122713	000177		BUFFER FULL?
12332	062344	001022			4\$: BLOS 4\$
12333	062346	005716			BR IF YES
12334	062350	001007			GO READ ONE CHARACTER FROM THE TTY
12335	062352	112737	000134	062550	MOV (SP)+,(R3)
12336	062360	104401	062550		GET CHARACTER
12337	062364	012716	177777		10\$: CMPB #177,(R3)
12338	062370	005303			IS IT A RUBOUT
12339	062372	020327	062552		5\$: BNE 5\$
12340	062376	103434			BR IF NO
12341	062400	111337	062550		TST (SP)
12342	062404	104401	062550		IS THIS THE FIRST RUBOUT?
12343	062410	000746			6\$: BNE 6\$
12344	062412	005716			BR IF NO
12345	062414	001406			MOV #'\,9\$
12346	062416	112737	000134	062550	TYPE A BACK SLASH
12347	062424	104401	062550		MOV #-1,(SP)
12348	062430	005016			SET THE RUBOUT KEY
12349					6\$: DEC R3
12350					BACKUP BY ONE
12351					CMP R3,#TTYIN
12352					STACK EMPTY?
12353					4\$: BLO 4\$
12354					BR IF YES
12355					MOV (R3),9\$
12356					SETUP TO TYPEOUT THE DELETED CHAR.
12357					5\$: BR 2\$

```
12333 062432 122713 000025      7$:  CMPB    #25,(R3)      ;;IS CHARACTER A CTRL U?
12334 062436 001003              BNE     8$          ;;BR IF NO
12335 062440 104401 062567      TYPE    ,SCNTLU      ;;TYPE A CONTROL 'U'
12336 062444 000726              BR      1$          ;;GO START OVER
12337 062446 122713 000022      8$:  CMPB    #22,(R3)      ;;IS CHARACTER A '^R'?
12338 062452 001011              BNE     3$          ;;BRANCH IF NO
12339 062454 105013              CLRB    (R3)         ;;CLEAR THE CHARACTER
12340 062456 104401 001217      TYPE    ,SCRLF      ;;TYPE A 'CR' & 'LF'
12341 062462 104401 062552      TYPE    ,STTYIN      ;;TYPE THE INPUT STRING
12342 062466 000717              BR      2$          ;;GO PICKUP ANOTHER CHACTER
12343 062470 104401 001216      4$:  TYPE    ,SQUES      ;;TYPE A '?'
12344 062474 000712              BR      1$          ;;CLEAR THE BUFFER AND LOOP
12345 062476 111337 062550      3$:  MOVB    (R3),9$      ;;ECHO THE CHARACTER
12346 062502 104401 062550      TYPE    ,9$
12347 062506 122723 000015      CMPB    #15,(R3)+      ;;CHECK FOR RETURN
12348 062512 001305              BNE     2$          ;;LOOP IF NOT RETURN
12349 062514 105063 177777      CLRB    -1(R3)        ;;CLEAR RETURN (THE 15)
12350 062520 104401 001220      TYPE    ,SLF         ;;TYPE A LINE FEED
12351 062524 005726              TST     (SP)+        ;;CLEAN RUBOUT KEY FROM THE STACK
12352 062526 012603              MOV     (SP)+,R3      ;;RESTORE R3
12353 062530 011646              MOV     (SP),-(SP)    ;;ADJUST THE STACK AND PUT ADDRESS OF THE
12354 062532 016666 000004 000002 MOV     4(SP),2(SP)  ;; FIRST ASCII CHARACTER ON IT
12355 062540 012766 062552 000004 MOV     #STTYIN,4(SP)
12356 062546 000002              RTI                 ;;RETURN
12357 062550 000          9$:  .BYTE    0              ;;STORAGE FOR ASCII CHAR. TO TYPE
12358 062551 000          .BYTE    0              ;;TERMINATOR
12359 062552 000010      $TTYIN: .BLKB    8.          ;;RESERVE 8 BYTES FOR TTY INPUT
12360 062562 041536 005015 000      $CNTLC: .ASCIZ  /^C/<15><12>  ;;CONTROL 'C'
12361 062567 136 006525 000012      $CNTLU: .ASCIZ  /^U/<15><12>  ;;CONTROL 'U'
12362 062574 043536 005015 000      $CNTLG: .ASCIZ  /^G/<15><12>  ;;CONTROL 'G'
12363 062601 015 051412 051127      $MSWR:  .ASCIZ  <15><12>/SWR = /
12364 062606 036440 000040
12365 062612 020040 042516 020127 $MNEW:  .ASCIZ  / NEW = /
12366 062620 020075 000
12367 062624
12368      .EVEN
12369      .SBTTL  READ AN OCTAL NUMBER FROM THE TTY
12370
12371      ;;*****
12372      ;;THIS ROUTINE WILL READ AN OCTAL (ASCII) NUMBER FROM THE TTY AND
12373      ;;CHANGE IT TO BINARY.
12374      ;;CALL:
12375      ;;*      RDOCT              ;;READ AN OCTAL NUMBER
12376      ;;*      RETURN HERE        ;;LOW ORDER BITS ARE ON TOP OF THE STACK
12377      ;;*                          ;;HIGH ORDER BITS ARE IN $HIOCT
12378 062624 011646      $RDOCT: MOV     (SP),-(SP)      ;;PROVIDE SPACE FOR THE
12379 062626 016666 000004 000002 MOV     4(SP),2(SP)  ;; INPUT NUMBER
12380 062634 010046      MOV     R0,-(SP)      ;;PUSH R0 ON STACK
12381 062636 010146      MOV     R1,-(SP)      ;;PUSH R1 ON STACK
12382 062640 010246      MOV     R2,-(SP)      ;;PUSH R2 ON STACK
12383 062642 104412      1$:  RDLIN      ;;READ AN ASCII LINE
12384 062644 012600      MOV     (SP)+,R0      ;;GET ADDRESS OF 1ST CHARACTER
12385 062646 005001      CLR     R1          ;;CLEAR DATA WORD
12386 062650 005002      CLR     R2
12387 062652 112046      2$:  MOVB    (R0)+,-(SP)    ;;PICKUP THIS CHARACTER
12388 062654 001412      BEQ     3$          ;;IF ZERO GET OUT
```

```
12389 062656 006301      ASL    R1      ;;*2
12390 062660 006102      ROL    R2
12391 062662 006301      ASL    R1      ;;*4
12392 062664 006102      ROL    R2
12393 062666 006301      ASL    R1      ;;*8
12394 062670 006102      ROL    R2
12395 062672 042716 177770 BIC    #^C7,(SP)  ;;STRIP THE ASCII JUNK
12396 062676 062601      ADD    (SP)+,R1  ;;ADD IN THIS DIGIT
12397 062700 000764      BR      2$      ;;LOOP
12398 062702 005726      3$:    TST    (SP)+  ;;CLEAN TERMINATOR FROM STACK
12399 062704 010166 000012 MOV    R1,12(SP)  ;;SAVE THE RESULT
12400 062710 010237 062724 MOV    R2,$HIOCT
12401 062714 012602      MOV    (SP)+,R2  ;;POP STACK INTO R2
12402 062716 012601      MOV    (SP)+,R1  ;;POP STACK INTO R1
12403 062720 012600      MOV    (SP)+,R0  ;;POP STACK INTO R0
12404 062722 000002      RTI      ;;RETURN
12405 062724 000000      $HIOCT: .WORD 0  ;;HIGH ORDER BITS GO HERE
12406
12407      .SBTTL TRAP DECODER
12408
12409      ;;*****
12410      ;;*THIS ROUTINE WILL PICKUP THE LOWER BYTE OF THE 'TRAP' INSTRUCTION
12411      ;;*AND USE IT TO INDEX THROUGH THE TRAP TABLE FOR THE STARTING ADDRESS
12412      ;;*OF THE DESIRED ROUTINE. THEN USING THE ADDRESS OBTAINED IT WILL
12413      ;;*GO TO THAT ROUTINE.
12414 062726 016646 000002      $TRAP: MOV    2(SP),-(SP)  ;;ASSUME THE STATUS OF
12415 062732 042716 000020      BIC    #20,(SP)  ;; THE CALLER--DO NOT ALLOW
12416 062736 012746 062744      MOV    #1$,-(SP)  ;; T-BIT TRAPS
12417 062742 000002      RTI      ;;SET THE NEW STATUS
12418 062744 010046      1$:    MOV    R0,-(SP)  ;;SAVE R0
12419 062746 016600 000002      MOV    2(SP),R0  ;;GET TRAP ADDRESS
12420 062752 005740      TST    -(R0)  ;;BACKUP BY 2
12421 062754 1110STRUCTION.
12437
12438
12439      : ROUTINE
12440      : -----
12440 063000 062766      $TRPAD: .WORD $TRAP2
12441 063002 060274      $TYPE  ;;CALL=TYPE  TRAP+1(104401) TTY TYPEOUT ROUTINE
12442 063004 060072      $TYPOC  ;;CALL=TYPOC  TRAP+2(104402) TYPE OCTAL NUMBER (WITH LEADING ZEROS)
12443 063006 060046      $TYPOS  ;;CALL=TYPOS  TRAP+3(104403) TYPE OCTAL NUMBER (NO LEADING ZEROS)
12444 063010 060106      $TYPON  ;;CALL=TYPON  TRAP+4(104404) TYPE OCTAL NUMBER (AS PER LAST CALL)
```


12445	063012	057622			\$TYPDS	::CALL=TYPDS	TRAP+5(104405)	TYPE DECIMAL NUMBER (WITH SIGN)
12446	063014	057546			\$TYPBN	::CALL=TYPBN	TRAP+6(104406)	TYPE BINARY (ASCII) NUMBER
12447								
12448	063016	061754			\$GTSWR	::CALL=GTSWR	TRAP+7(104407)	GET SOFT-SWR SETTING
12449								
12450	063020	061664			\$CKSWR	::CALL=CKSWR	TRAP+10(104410)	TEST FOR CHANGE IN SOFT-SWR
12451	063022	062226			\$RDCHR	::CALL=RDCHR	TRAP+11(104411)	TTY TYPEIN CHARACTER ROUTINE
12452	063024	062316			\$RDLIN	::CALL=RDLIN	TRAP+12(104412)	TTY TYPEIN STRING ROUTINE
12453	063026	062624			\$RDOCT	::CALL=RDOCT	TRAP+13(104413)	READ AN OCTAL NUMBER FROM TTY
12454	063030	057452			\$SAVREG	::CALL=SAVREG	TRAP+14(104414)	SAVE R0-R5 ROUTINE
12455	063032	057510			\$RESREG	::CALL=RESREG	TRAP+15(104415)	RESTORE R0-R5 ROUTINE

.SBTTL POWER DOWN AND UP ROUTINES

```
*****
:POWER DOWN ROUTINE
$PWRDN: MOV    $ILLUP, @PWRVEC ;;SET FOR FAST UP
        MOV    #340, @PWRVEC+2 ;;PRIO:7
        MOV    R0, -(SP)      ;;PUSH R0 ON STACK
        MOV    R1, -(SP)      ;;PUSH R1 ON STACK
        MOV    R2, -(SP)      ;;PUSH R2 ON STACK
        MOV    R3, -(SP)      ;;PUSH R3 ON STACK
        MOV    R4, -(SP)      ;;PUSH R4 ON STACK
        MOV    R5, -(SP)      ;;PUSH R5 ON STACK
        MOV    @SWR, -(SP)    ;;PUSH @SWR ON STACK
        MOV    SP, $SAVR6    ;;SAVE SP
        MOV    $PWRUP, @PWRVEC ;;SET UP VECTOR
        HALT
        BR      -2           ;;HANG UP
```

```
*****
:POWER UP ROUTINE
$PWRUP: MOV    $ILLUP, @PWRVEC ;;SET FOR FAST DOWN
        MOV    $SAVR6, SP    ;;GET SP
        CLR    $SAVR6       ;;WAIT LOOP FOR THE TTY
        1$: INC    $SAVR6    ;;WAIT FOR THE INC
        BNE    1$           ;;OF WORD
        MOV    (SP)+, @SWR   ;;POP STACK INTO @SWR
        MOV    (SP)+, R5     ;;POP STACK INTO R5
        MOV    (SP)+, R4     ;;POP STACK INTO R4
        MOV    (SP)+, R3     ;;POP STACK INTO R3
        MOV    (SP)+, R2     ;;POP STACK INTO R2
        MOV    (SP)+, R1     ;;POP STACK INTO R1
        MOV    (SP)+, R0     ;;POP STACK INTO R0
        MOV    $PWRDN, @PWRVEC ;;SET UP THE POWER DOWN VECTOR
        MOV    #340, @PWRVEC+2 ;;PRIO:7
        TYPE    $POWER      ;;REPORT THE POWER FAILURE
        $PWRMG: .WORD    $POWER ;;POWER FAIL MESSAGE POINTER
        RTI
        $ILLUP: HALT        ;;THE POWER UP SEQUENCE WAS STARTED
        BR      -2           ;; BEFORE THE POWER DOWN WAS COMPLETE
        $SAVR6: 0           ;;PUT THE SP HERE
        $POWER: .ASCIIZ <15><12>'POWER'
        .EVEN
.SBTTL APT COMMUNICATIONS ROUTINE
```

```
12501 *****
12502 063212 112737 000001 063456 $ATY1: MOVB #1,$FFLG ;;TO REPORT FATAL ERROR
12503 063220 112737 000001 063454 $ATY3: MOVB #1,$MFLG ;;TO TYPE A MESSAGE
12504 063226 000403 BR $ATYC
12505 063230 112737 000001 063456 $ATY4: MOVB #1,$FFLG ;;TO ONLY REPORT FATAL ERROR
12506 063236 $ATYC:
12507 063236 010046 MOV RO,-(SP) ;;PUSH RO ON STACK
12508 063240 010146 MOV R1,-(SP) ;;PUSH R1 ON STACK
12509 063242 105737 063454 TSTB $MFLG ;;SHOULD TYPE A MESSAGE?
12510 063246 001450 BEQ 5$ ;;IF NOT: BR
12511 063250 122737 000001 001242 CMPB #APTENV,$ENV ;;OPERATING UNDER APT?
12512 063256 001031 BNE 3$ ;;IF NOT: BR
12513 063260 132737 000100 001243 BITB #APTSPOOL,$ENVM ;;SHOULD SPOOL MESSAGES?
12514 063266 001425 BEQ 3$ ;;IF NOT: BR
12515 063270 017600 000004 MOV #4(SP),RO ;;GET MESSAGE ADDR.
12516 063274 062766 000002 000004 ADD #2,4(SP) ;;BUMP RETURN ADDR.
12517 063302 005737 001222 1$: TST $MSGTYPE ;;SEE IF DONE W/ LAST XMISSION?
12518 063306 001375 BNE 1$ ;;IF NOT: WAIT
12519 063310 010037 001236 MOV RO,$MSGAD ;;PUT ADDR IN MAILBOX
12520 063314 105720 2$: TSTB (RO)+ ;;FIND END OF MESSAGE
12521 063316 001376 BNE 2$
12522 063320 163700 001236 SUB $MSGAD,RO ;;SUB START OF MESSAGE
12523 063324 006200 ASR RO ;;GET MESSAGE LGTH IN WORDS
12524 063326 010037 001240 MOV RO,$MSGGLT ;;PUT LENGTH IN MAILBOX
12525 063332 012737 000004 001222 MOV #4,$MSGTYPE ;;TELL APT TO TAKE MSG.
12526 063340 000413 BR 5$
12527 063342 017637 000004 063366 3$: MOV #4(SP),4$ ;;PUT MSG ADDR IN JSR LINKAGE
12528 063350 062766 000002 000004 ADD #2,4(SP) ;;BUMP RETURN ADDRESS
12529 063356 013746 177776 MOV 177776,-(SP) ;;PUSH 177776 ON STACK
12530 063362 004737 060274 JSR PC,$TYPE ;;CALL TYPE MACRO
12531 063366 000000 4$: .WORD 0
12532 063370 5$:
12533 063370 105737 063456 10$: TSTB $FFLG ;;SHOULD REPORT FATAL ERROR?
12534 063374 001416 BEQ 12$ ;;IF NOT: BR
12535 063376 005737 001242 TST $ENV ;;RUNNING UNDER APT?
12536 063402 001413 BEQ 12$ ;;IF NOT: BR
12537 063404 005737 001222 11$: TST $MSGTYPE ;;FINISHED LAST MESSAGE?
12538 063410 001375 BNE 11$ ;;IF NOT: WAIT
12539 063412 017637 000004 001224 MOV #4(SP),$FATAL ;;GET ERROR #
12540 063420 062766 000002 000004 ADD #2,4(SP) ;;BUMP RETURN ADDR.
12541 063426 005237 001222 INC $MSGTYPE ;;TELL APT TO TAKE ERROR
12542 063432 105037 063456 12$: CLRB $FFLG ;;CLEAR FATAL FLAG
12543 063436 105037 063455 CLRB $LFLG ;;CLEAR LOG FLAG
12544 063442 105037 063454 CLRB $MFLG ;;CLEAR MESSAGE FLAG
12545 063446 012601 MOV (SP)+,R1 ;;POP STACK INTO R1
12546 063450 012600 MOV (SP)+,RO ;;POP STACK INTO RO
12547 063452 000207 RTS PC ;;RETURN
12548 063454 000 $MFLG: .BYTE 0 ;;MESSG. FLAG
12549 063455 000 $LFLG: .BYTE 0 ;;LOG FLAG
12550 063456 000 $FFLG: .BYTE 0 ;;FATAL FLAG
12551 063460 .EVEN
12552 000200 APTSIZE=200
12553 000001 APTENV=001
12554 000100 APTSPOOL=100
12555 000040 APTCSUP=040
12556
```


CZRMDCO RM03/2 FCTNL TST 2
CZRMDC.P11 12-DEC-78 08:24

MACY11 30A(1052) 04-JAN-79 11:23^{K 4} PAGE 256
APT COMMUNICATIONS ROUTINE

SEQ 0256

12557

.NLIST BEX

.SBTTL CONSOLE MESSAGES

063460				SCTMSG:	
063460	005015	040503	047116	.ASCII	<CR><LF>@CANNOT RECOVER THE BAD SECTOR FILES FROM LAST @<CR><LF>
063542	051124	041501	020113	.ASCII	@TRACK FOR THIS DEVICE@
063570	051			CLSPRN:	.ASCII @)@
063571	075	000		EQUALS:	.ASCII @=@
063573	015	025012	000	PROMPT:	.ASCII <CR><LF>@*@
063577	077	000		QSTMRK:	.ASCII @?@
063601				HELPQST:	
063601	015	006412	052012	.ASCII	<CR><LF><CR><LF>/THIS PROGRAM SHOULD BE HALTED BY TYPE ^C./
063656	005015	044124	020105	.ASCII	<CR><LF>/THE PROGRAM WILL BE HALTED AT END OF PASS/<CR><LF><CR>
063734	005015	054524	042520	.ASCII	<CR><LF>@TYPE HELP TEXT (Y OR N)??@
063770				UBUSQST:	
063770	005015	044103	047101	.ASCII	<CR><LF>@CHANGE RM03 UNIBUS ADDRESS OR VECTOR ADDRESS (Y OR N)<CR> ??@
064067	015	052412	042523	CNSL00:	.ASCII <CR><LF>@USE SAME DEVICES (Y OR N) ??@
064126	005015	046522	031460	CNSL01:	.ASCII <CR><LF>@RM03 BUS ADDRESS (@
064153	015	042412	052116	CNSL02:	.ASCII <CR><LF>@ENTRY NOT IN I/O PAGE@
064202	005015	042101	051104		.ASCII <CR><LF>@ADDRESS MUST BE >160000@
064234	005015	046522	031460	CNSL03:	.ASCII <CR><LF>@RM03 VECTOR ADDRESS (@
064264	005015	047105	051124	CNSL04:	.ASCII <CR><LF>@ENTRY OUT OF RANGE@
064310	005015	042101	051104		.ASCII <CR><LF>@ADDRESS MUST BE <1000@
064340	005015	046522	031460	CNSL05:	.ASCII <CR><LF>@RM03 INTERRUPT PRIORITY (@
064374	005015	047105	051124	CNSL06:	.ASCII <CR><LF>@ENTRY OUT OF RANGE@
064421				CNSL07:	
064421	015	052012	050131	.ASCII	<CR><LF>@TYPE (A) TO TEST ALL DEVICES, OR TYPE DEVICE@
064477	040	052516	041115	.ASCII	@ NUMBER(S)@
064511	015	052012	051105	.ASCII	<CR><LF>@TERMINATE INPUT WITH CARRIAGE RETURN@
064560	005015	044103	047101	XDPMG:	.ASCII <CR><LF>/CHANGE XXDP PACK,CLEAR LOC 40/
064617	015	051012	051505		.ASCII <CR><LF>/RESTART THE PROGRAM/
064645	015	047012	052117	NOTEX:	.ASCII <CR><LF>/NOT EXIST DRIVE /

064672

.EVEN

.SBTTL FUNCTION CODE TABLE

;THE FUNCTION CODE TABLE IS USED TO DEFINE STATUS CONDITIONS FOR
;EACH FUNCTION CODE. BIT USAGE IS AS FOLLOWS:

; ATA - BIT 15 IS SET IN THE ENTRY FOR A GIVEN FUNCTION CODE
;IF ATA SHOULD BE SET WHEN THE FUNCTION CODE IS EXECUTED, OTHERWISE,
;BIT 15 IS ZERO, INDICATING THAT ATA SHOULD NOT NORMALLY BE SET.
;NOTE THAT ATA MAY BE SET WHEN A COMMAND IS EXECUTED EVEN THOUGH
;IT IS NOT EXPECTED AS A RESULT OF THE COMMAND.

; WCE - BIT 14 IS SET IN THE ENTRY FOR A GIVEN FUNCTION CODE
;IF WRITE CHECK ERRORS ARE ENABLED AS A FUNCTION OF THE COMMAND.

; OPI - BIT 13 IS SET IN THE ENTRY FOR A GIVEN FUNCTION CODE
;IF OPI ERRORS ARE ENABLED DURING THE EXECUTION OF THAT COMMAND.

; IVC - BIT 12 IS SET IN THE ENTRY FOR A GIVEN FUNCTION CODE
;IF IVC ERRORS ARE ENABLED DURING THE EXECUTION OF THAT COMMAND.

; WLE - BIT 11 IS SET IN THE ENTRY FOR A GIVEN FUNCTION CODE
;IF WRITE ERRORS ARE ENABLED DURING THE EXECUTION OF THAT COMMAND.
;THE WRITE ERRORS WHICH ARE ENABLED ARE 'WLE', 'WCF', 'DPE', 'UPE'.

; IAE - BIT 10 IS SET IN THE ENTRY FOR A GIVEN FUNCTION CODE
;IF INVALID ADDRESS ERROR IS ENABLED FOR THAT COMMAND.

; AOE - BIT 09 IS SET IN THE ENTRY FOR A GIVEN FUNCTION CODE
;IF READ AND WRITE ERRORS ARE ENABLED DURING THE EXECUTION OF THE
;COMMAND. THE ERRORS ENABLED BY THIS BIT ARE 'TRE', 'DLT', 'NEM',
;'MXF', 'LBT', AND 'AOE'.

; BIT 08 IS NOT USED.

; HCE - BIT 07 IS SET IN THE ENTRY FOR A GIVEN FUNCTION CODE
;IF HEADER ERRORS ARE ENABLED DURING THE EXECUTION OF THAT COMMAND.
;HEADER ERRORS INCLUDE 'HCRC', 'HCE', 'FER', AND 'BSE'.

; ECH - BIT 06 IS SET IN THE ENTRY FOR A GIVEN FUNCTION CODE
;IF DATA FIELD ERRORS ARE ENABLED DURING THE EXECUTION OF THAT
;COMMAND. THESE ERRORS INCLUDE 'MDPE', 'DCK', AND 'ECH'.

; BIT 05 IS NOT USED.

; BIT 04 IS NOT USED.

; BIT 03 IS NOT USED.

; BIT 02 IS NOT USED.

; BIT 01 IS NOT USED.

; ILF - BIT 00 IS SET IF THE FUNCTION CODE IS ILLEGAL.

064672

FNCDTB:

;FUNCTION CODE TABLE

064672	020000	.WORD	OPI	:NOP
064674	130001	.WORD	OPI:ATA:ILF:IVC	:ILLEGAL FUNCTION (2)
064676	132000	.WORD	ATA:OPI:IVC:IAE	:SEEK
064700	130000	.WORD	ATA:OPI:IVC	:RECALIBRATE
064702	020000	.WORD	OPI	:DRIVE CLEAR
064704	030000	.WORD	OPI:IVC	:RELEASE
064706	130000	.WORD	OPI:ATA:IVC	:OFFSET
064710	130000	.WORD	OPI:ATA:IVC	:RETURN TO CENTERLINE
064712	020000	.WORD	OPI	:READ IN PRESET
064714	020000	.WORD	OPI	:PACK ACKNOWLEDGE
064716	130001	.WORD	OPI:ATA:ILF:IVC	:ILLEGAL FUNCTION (24)
064720	130001	.WORD	OPI:ATA:ILF:IVC	:ILLEGAL FUNCTION (26)
064722	132000	.WORD	ATA:OPI:IVC:IAE	:SEARCH
064724	130001	.WORD	OPI:ATA:ILF:IVC	:ILLEGAL FUNCTION (32)
064726	130001	.WORD	OPI:ATA:ILF:IVC	:ILLEGAL FUNCTION (34)
064730	130001	.WORD	OPI:ATA:ILF:IVC	:ILLEGAL FUNCTION (36)
064732	130001	.WORD	OPI:ATA:ILF:IVC	:ILLEGAL FUNCTION (40)
064734	130001	.WORD	OPI:ATA:ILF:IVC	:ILLEGAL FUNCTION (42)
064736	130001	.WORD	OPI:ATA:ILF:IVC	:ILLEGAL FUNCTION (44)
064740	130001	.WORD	OPI:ATA:ILF:IVC	:ILLEGAL FUNCTION (46)
064742	073300	.WORD	WCE:OPI:IVC:IAE:AOE:HLE:ECH	:WRITE CHECK DATA
064744	073300	.WORD	WCE:OPI:IVC:IAE:AOE:HCE:ECH	:WRITE CHECK HEADER AND DATA
064746	130001	.WORD	OPI:ATA:ILF:IVC	:ILLEGAL FUNCTION (54)
064750	130001	.WORD	OPI:ATA:ILF:IVC	:ILLEGAL FUNCTION (56)
064752	037200	.WORD	OPI:IVC:WLE:IAE:AOE:HCE	:WRITE DATA
064754	037000	.WORD	OPI:IVC:WLE:IAE:AOE	:WRITE HEADER AND DATA
064756	130001	.WORD	OPI:ATA:ILF:IVC	:ILLEGAL FUNCTION (64)
064760	130001	.WORD	OPI:ATA:ILF:IVC	:ILLEGAL FUNCTION (66)
064762	033300	.WORD	OPI:IVC:IAE:AOE:HCF:ECH	:READ DATA
064764	033300	.WORD	OPI:IVC:IAE:AOE:HCE:ECH	:READ HEADER AND DATA
064766	130001	.WORD	OPI:ATA:ILF:IVC	:ILLEGAL FUNCTION (74)
064770	130001	.WORD	OPI:ATA:ILF:IVC	:ILLEGAL FUNCTION (76)

CZRMDCO RM03/2 FCTNL TST 2
CZRMDC.P11 12-DEC-78 08:24

MACY11 30A(1052) 04-JAN-79 11:23 PAGE 260
ATTENTION (ATA) TABLE

SEQ 0260

.SBTTL ATTENTION (ATA) TABLE

064772 001
064773 002
064774 004
064775 010
064776 020
064777 040
065000 100
065001 200

ATNTBL: .BYTE 1.
.BYTE 2.
.BYTE 4.
.BYTE 8.
.BYTE 16.
.BYTE 32.
.BYTE 64.
.BYTE 128.

.SBTTL DATA PATTERN TABLE

065002		RGDTPT:	
065002		MIXED:	
065002	000000	.WORD	0.
065004	000001	.WORD	1.
065006	000003	.WORD	3.
065010	000007	.WORD	7.
065012	000017	.WORD	15.
065014	000037	.WORD	31.
065016	000077	.WORD	63.
065020	000177	.WORD	127.
065022	000377	.WORD	255.
065024	000777	.WORD	511.
065026	001777	.WORD	1023.
065030	003777	.WORD	2047.
065032	007777	.WORD	4095.
065034	017777	.WORD	8191.
065036	037777	.WORD	16383.
065040	077777	.WORD	32767.
065042	177777	ONES:	.WORD 65535.
065044	177777		.WORD 65535.
065046	077777		.WORD 32767.
065050	037777		.WORD 16383.
065052	017777		.WORD 8191.
065054	007777		.WORD 4095.
065056	003777		.WORD 2047.
065060	001777		.WORD 1023.
065062	000777		.WORD 511.
065064	000377		.WORD 255.
065066	000177		.WORD 127.
065070	000077		.WORD 63.
065072	000037		.WORD 31.
065074	000017		.WORD 15.
065076	000007		.WORD 7.
065100	000003		.WORD 3.
065102	000001		.WORD 1.
065104	000000	ZEROS:	.WORD 0.
065106	000000		.WORD 0.
065110	000001		.WORD 1.
065112	000002		.WORD 2.
065114	000004		.WORD 4.
065116	000010		.WORD 8.
065120	000020		.WORD 16.
065122	000040		.WORD 32.
065124	000100		.WORD 64.
065126	000200		.WORD 128.
065130	000400		.WORD 256.
065132	001000		.WORD 512.
065134	002000		.WORD 1024.
065136	004000		.WORD 2048.
065140	010000		.WORD 4096.
065142	020000		.WORD 8192.
065144	040000		.WORD 16384.
065146	100000		.WORD 32768.
065150	100000		.WORD 32768.

065152	040000	.WORD	16384.
065154	020000	.WORD	8192.
065156	010000	.WORD	4096.
065160	004000	.WORD	2048.
065162	002000	.WORD	1024.
065164	001000	.WORD	512.
065166	000400	.WORD	256.
065170	000200	.WORD	128.
065172	000100	.WORD	64.
065174	000040	.WORD	32.
065176	000020	.WORD	16.
065200	000010	.WORD	8.
065202	000004	.WORD	4.
065204	000002	.WORD	2.
065206	000001	.WORD	1.
065210	000000	.WORD	0.
065212	177777	.WORD	65535.
065214	177776	.WORD	65534.
065216	177774	.WORD	65532.
065220	177770	.WORD	65528.
065222	177760	.WORD	65520.
065224	177740	.WORD	65504.
065226	177700	.WORD	65472.
065230	177600	.WORD	65408.
065232	177400	.WORD	65280.
065234	177000	.WORD	65024.
065236	176000	.WORD	64512.
065240	174000	.WORD	63488.
065242	170000	.WORD	61440.
065244	160000	.WORD	57344.
065246	140000	.WORD	49152.
065250	100000	.WORD	32768.
065252	000000	.WORD	0.
065254	000000	.WORD	0.
065256	100000	.WORD	32768.
065260	140000	.WORD	49152.
065262	160000	.WORD	57344.
065264	170000	.WORD	61440.
065266	174000	.WORD	63488.
065270	176000	.WORD	64512.
065272	177000	.WORD	65024.
065274	177400	.WORD	65280.
065276	177600	.WORD	65408.
065300	177700	.WORD	65472.
065302	177740	.WORD	65504.
065304	177760	.WORD	65520.
065306	177770	.WORD	65528.
065310	177774	.WORD	65532.
065312	177776	.WORD	65534.
065314	177777	.WORD	65535.
065316	125252	EARLY: .WORD	43690.
065320	152525	.WORD	43690./2
065322	125252	.WORD	43690.
065324	177777	.WORD	65535.
065326	177776	.WORD	65534.
065330	177775	.WORD	65533.

CZRMDCO RM03/2 FCTNL TST 2
CZRMDC.P11 12-DEC-78 08:24

MACY11 30A(1052) 04-JAN-79 11:23 E 5
DATA PATTERN TABLE PAGE 263

SEQ 0263

065332	177773	.WORD	65531.
065334	177767	.WORD	65527.
065336	177757	.WORD	65519.
065340	177737	.WORD	65503.
065342	177677	.WORD	65471.
065344	177577	.WORD	65407.
065346	177377	.WORD	65279.
065350	176777	.WORD	65023.
065352	175777	.WORD	64511.
065354	173777	.WORD	63487.
065356	167777	.WORD	61439.
065360	157777	.WORD	57343.
065362	137777	.WORD	49151.
065364	077777	.WORD	32767.
065366	077777	.WORD	32767.
065370	137777	.WORD	49151.
065372	157777	.WORD	57343.
065374	167777	.WORD	61439.
065376	173777	.WORD	63487.
065400	175777	.WORD	64511.
065402	176777	.WORD	65023.
065404	177377	.WORD	65279.
065406	177577	.WORD	65407.
065410	177677	.WORD	65471.
065412	177737	.WORD	65503.
065414	177757	.WORD	65519.
065416	177767	.WORD	65527.
065420	177773	.WORD	65531.
065422	177775	.WORD	65533.
065424	177776	.WORD	65534.
065426	177777	.WORD	65535.
065430			

ENRGDT:

.SBTTL ERROR MESSAGE TABLE

065430	072024	000000		EMT1:	.WORD	EMS1,0
065434	072073	072110	000000	EMT2:	.WORD	EMS2,EMS3,0
065442	072073	072153	000000	EMT3:	.WORD	EMS2,EMS4,0
065450	072216	072246	000000	EMT4:	.WORD	EMS5,EMS6,0
065456	072216	072360	000000	EMT5:	.WORD	EMS5,EMS10,0
065464	077053	074241	000000	EMT6:	.WORD	EMS167,EMS64,0
065472	075007	077100	000000	EMT7:	.WORD	EMS110,EMS170,0
065500	072313	000000		EMT10:	.WORD	EMS7,0
065504	072360	000000		EMT11:	.WORD	EMS10,0
065510	072422	072433	000000	EMT12:	.WORD	EMS11,EMS12,0
065516	072474	072505	072516	EMT13:	.WORD	EMS13,EMS14,EMS15,EMS16,0
065530	072570	074241	000000	EMT14:	.WORD	EMS17,EMS64,0
065536	072422	072653	000000	EMT15:	.WORD	EMS11,EMS21,0
065544	072422	072676	073025	EMT16:	.WORD	EMS11,EMS22,EMS27,0
065554	072422	072712	073036	EMT17:	.WORD	EMS11,EMS23,EMS30,0
065564	072422	072740	073036	EMT20:	.WORD	EMS11,EMS24,EMS30,0
065574	072422	072767	073025	EMT21:	.WORD	EMS11,EMS25,EMS27,0
065604	072422	073004	073025	EMT22:	.WORD	EMS11,EMS26,EMS27,0
065614	072422	073046	073036	EMT23:	.WORD	EMS11,EMS31,EMS30,0
065624	072422	073075	073036	EMT24:	.WORD	EMS11,EMS32,EMS30,0
065634	072422	073124	073036	EMT25:	.WORD	EMS11,EMS33,EMS30,0
065644	072422	073152	073036	EMT26:	.WORD	EMS11,EMS34,EMS30,0
065654	072422	073223	073036	EMT27:	.WORD	EMS11,EMS35,EMS30,0
065664	072422	073252	073036	EMT30:	.WORD	EMS11,EMS36,EMS30,0
065674	072422	073301	073036	EMT31:	.WORD	EMS11,EMS37,EMS30,0
065704	072422	073327	073036	EMT32:	.WORD	EMS11,EMS40,EMS30,0
065714	072422	073356	073036	EMT33:	.WORD	EMS11,EMS41,EMS30,0
065724	072422	073404	073036	EMT34:	.WORD	EMS11,EMS42,EMS30,0
065734	072422	073433	073036	EMT35:	.WORD	EMS11,EMS43,EMS30,0
065744	072422	073462	073036	EMT36:	.WORD	EMS11,EMS44,EMS30,0
065754	072422	073535	073036	EMT37:	.WORD	EMS11,EMS45,EMS30,0
065764	074325	072630	000000	EMT40:	.WORD	EMS66,EMS20,0
065772	074513	076221	074521	EMT41:	.WORD	EMS75,EMS141,EMS76,0
066002	076312	076322	074447	EMT42:	.WORD	EMS144,EMS145,EMS72,EMS76,0
066014	073627	073745	074521	EMT43:	.WORD	EMS47,EMS53,EMS76,0
066024	074552	073745	074521	EMT44:	.WORD	EMS77,EMS53,EMS76,0
066034	074600	073745	074521	EMT45:	.WORD	EMS100,EMS53,EMS76,0
066044	074626	073745	074521	EMT46:	.WORD	EMS101,EMS53,EMS76,0
066054	074257	074241	000000	EMT47:	.WORD	EMS65,EMS64,0
066062	072474	072516	074213	EMT50:	.WORD	EMS13,EMS15,EMS63,0
066072	072422	073600	073036	EMT51:	.WORD	EMS11,EMS46,EMS30,EMS67,0
066104	073627	073745	074375	EMT52:	.WORD	EMS47,EMS53,EMS67,EMS115,EMS140,EMS141,0
066122	073627	073745	074375	EMT53:	.WORD	EMS47,EMS53,EMS67,EMS115,EMS141,EMS164,0
066140	073656	073745	074375	EMT54:	.WORD	EMS50,EMS53,EMS67,0
066150	076247	076264	073745	EMT55:	.WORD	EMS142,EMS143,EMS53,EMS67,0
066162	073705	074447	074375	EMT56:	.WORD	EMS51,EMS72,EMS67,EMS115,EMS50,EMS70,0
066200	077053	074457	074375	EMT57:	.WORD	EMS167,EMS73,EMS67,0
066210	074030	074375	075207	EMT60:	.WORD	EMS56,EMS67,EMS115,EMS150,EMS152,EMS70,0
066226	074434	074030	074375	EMT61:	.WORD	EMS71,EMS56,EMS67,EMS115,EMS150,EMS152,EMS72,0
066246	076200	074375	075207	EMT62:	.WORD	EMS140,EMS67,EMS115,EMS47,EMS70,0
066262	000000			EMT63:	.WORD	
066264	076405	076450	074422	EMT64:	.WORD	EMS150,EMS152,EMS70,EMS115,EMS56,EMS73,EMS67,0
066304	073733	077500	077661	EMT65:	.WORD	EMS52,EMS205,EMS214,EMS206,EMS115,EMS51,EMS72,0
066324	077012	074703	074447	EMT66:	.WORD	EMS165,EMS103,EMS72,EMS124,0

066336	077012	074703	074447	EMT67:	.WORD	EMS165,EMS103,EMS72,EMS171,0
066350	073600	072630	076705	EMT70:	.WORD	EMS46,EMS20,EMS163,0
066360	074434	074626	076705	EMT71:	.WORD	EMS71,EMS101,EMS163,0
066370	073627	074447	076705	EMT72:	.WORD	EMS47,EMS72,EMS163,EMS115,EMS140,EMS141,0
066406	073627	074447	076705	EMT73:	.WORD	EMS47,EMS72,EMS163,EMS115,EMS141,EMS72,0
066424	074030	073745	076705	EMT74:	.WORD	EMS56,EMS53,EMS163,0
066434	074434	074030	076705	EMT75:	.WORD	EMS71,EMS56,EMS163,EMS115,EMS150,EMS152,EMS72,0
066454	073656	073745	076705	EMT76:	.WORD	EMS50,EMS53,EMS163,0
066464	076247	076264	073745	EMT77:	.WORD	EMS142,EMS143,EMS53,EMS163,0
066476	074513	076221	076705	EMT100:	.WORD	EMS75,EMS141,EMS163,EMS115,EMS47,EMS70,0
066514	074513	076405	076705	EMT101:	.WORD	EMS75,EMS150,EMS163,EMS115,EMS56,EMS73,0
066532	077053	074457	076705	EMT102:	.WORD	EMS167,EMS73,EMS163,0
066542	076370	076424	074474	EMT103:	.WORD	EMS147,EMS151,EMS74,EMS163,0
066554	073705	074474	076705	EMT104:	.WORD	EMS51,EMS74,EMS163,EMS115,EMS50,EMS70,0
066572	077012	074600	076705	EMT105:	.WORD	EMS165,EMS100,EMS163,0
066602	077012	074552	076705	EMT106:	.WORD	EMS165,EMS77,EMS163,0
066612	076312	076322	073745	EMT107:	.WORD	EMS144,EMS145,EMS53,EMS163,EMS115,EMS143,EMS70,0
066632	075007	075047	075214	EMT110:	.WORD	EMS110,EMS112,EMS116,EMS111,0
066644	075133	072153	000000	EMT111:	.WORD	EMS113,EMS4,0
066652	075133	072110	000000	EMT112:	.WORD	EMS113,EMS3,0
066660	075007	075207	075214	EMT113:	.WORD	EMS110,EMS115,EMS116,EMS117,EMS114,0
066674	075133	075266	000000	EMT114:	.WORD	EMS113,EMS120,0
066702	075303	075743	075767	EMT115:	.WORD	EMS121,EMS132,EMS133,0
066712	075346	075743	075767	EMT116:	.WORD	EMS122,EMS132,EMS133,0
066722	075403	075743	075767	EMT117:	.WORD	EMS123,EMS132,EMS133,0
066732	075446	075743	075767	EMT120:	.WORD	EMS124,EMS132,EMS133,0
066742	075500	075743	075767	EMT121:	.WORD	EMS125,EMS132,EMS133,0
066752	075543	075743	075767	EMT122:	.WORD	EMS126,EMS132,EMS133,0
066762	076143	075743	075767	EMT123:	.WORD	EMS137,EMS132,EMS133,0
066772	075645	075743	075767	EMT124:	.WORD	EMS130,EMS132,EMS133,0
067002	075703	075743	075767	EMT125:	.WORD	EMS131,EMS132,EMS133,0
067012	075303	075743	076012	EMT126:	.WORD	EMS121,EMS132,EMS134,EMS123,0
067024	075346	075743	076012	EMT127:	.WORD	EMS122,EMS132,EMS134,EMS123,0
067036	075403	075743	076012	EMT130:	.WORD	EMS123,EMS132,EMS134,EMS123,0
067050	075446	075743	076012	EMT131:	.WORD	EMS124,EMS132,EMS134,EMS123,0
067062	075500	075743	076012	EMT132:	.WORD	EMS125,EMS132,EMS134,EMS123,0
067074	075543	075743	076012	EMT133:	.WORD	EMS126,EMS132,EMS134,EMS123,0
067106	076143	075743	076012	EMT134:	.WORD	EMS137,EMS132,EMS134,EMS123,0
067120	075645	075743	076012	EMT135:	.WORD	EMS130,EMS132,EMS134,EMS123,0
067132	075703	075743	076012	EMT136:	.WORD	EMS131,EMS132,EMS134,EMS123,0
067144	075303	075743	076054	EMT137:	.WORD	EMS121,EMS132,EMS135,0
067154	075403	075743	076054	EMT140:	.WORD	EMS121,EMS132,EMS135,0
067164	075303	075743	076116	EMT141:	.WORD	EMS121,EMS132,EMS136,0
067174	076143	075743	076116	EMT142:	.WORD	EMS137,EMS132,EMS136,0
067204	075446	075743	076116	EMT143:	.WORD	EMS124,EMS132,EMS136,0
067214	075500	075743	076116	EMT144:	.WORD	EMS125,EMS132,EMS136,0
067224	075543	075743	076116	EMT145:	.WORD	EMS126,EMS132,EMS136,0
067234	075703	075743	076116	EMT146:	.WORD	EMS131,EMS132,EMS136,0
067244	076652	075743	076116	EMT147:	.WORD	EMS162,EMS132,EMS136,0
067254	075645	075743	076116	EMT150:	.WORD	EMS130,EMS132,EMS136,0
067264	076200	075207	076221	EMT151:	.WORD	EMS140,EMS115,EMS141,EMS70,0
067276	076247	075207	076264	EMT152:	.WORD	EMS142,EMS115,EMS143,EMS72,0
067310	076312	076322	076351	EMT153:	.WORD	EMS144,EMS145,EMS146,EMS115,EMS143,EMS72,0
067326	076312	076322	072630	EMT154:	.WORD	EMS144,EMS145,EMS20,EMS115,EMS143,EMS70,0
067344	076405	076450	076516	EMT155:	.WORD	EMS150,EMS152,EMS154,EMS153,0
067356	076370	076424	076516	EMT156:	.WORD	EMS147,EMS151,EMS154,EMS155,0

067370	076370	076424	076552	EMT157: .WORD	EMS147,EMS151,EMS156,EMS157,0
067402	076622	076552	076605	EMT160: .WORD	EMS161,EMS156,EMS160,0
067412	072767	073025	076552	EMT161: .WORD	EMS25,EMS27,EMS156,EMS160,0
067424	073004	073025	076552	EMT162: .WORD	EMS26,EMS27,EMS156,EMS160,0
067436	073627	076705	076200	EMT163: .WORD	EMS47,EMS163,EMS140,0
067446	073627	072630	000000	EMT164: .WORD	EMS47,EMS20,0
067454	074030	072630	000000	EMT165: .WORD	EMS56,EMS20,0
067462	073600	072630	000000	EMT166: .WORD	EMS46,EMS20,0
067470	100201	072630	000000	EMT167: .WORD	EMS224,EMS20,0
067476	077053	076516	077026	EMT170: .WORD	EMS167,EMS154,EMS166,0
067506	077053	076516	076570	EMT171: .WORD	EMS167,EMS154,EMS157,0
067516	077053	076516	076532	EMT172: .WORD	EMS167,EMS154,EMS155,0
067526	077127	075743	075767	EMT173: .WORD	EMS171,EMS132,EMS133,0
067536	077127	075743	076012	EMT174: .WORD	EMS171,EMS132,EMS134,EMS123,0
067550	075133	077302	000000	EMT175: .WORD	EMS113,EMS177,0
067556	077324	077341	000000	EMT176: .WORD	EMS200,EMS201,0
067564	077437	076221	073036	EMT177: .WORD	EMS203,EMS141,EMS30,EMS202,0
067576	077437	073705	073036	EMT200: .WORD	EMS203,EMS51,EMS30,EMS202,0
067610	077437	077452	073036	EMT201: .WORD	EMS203,EMS204,EMS30,EMS202,0
067622	077437	073656	073036	EMT202: .WORD	EMS203,EMS50,EMS30,EMS202,0
067634	077437	076264	073036	EMT203: .WORD	EMS203,EMS143,EMS30,EMS202,0
067646	076405	074474	077407	EMT204: .WORD	EMS150,EMS74,EMS202,EMS115,EMS152,EMS72,0
067664	073656	074703	074447	EMT205: .WORD	EMS50,EMS103,EMS72,0
067674	074712	074457	077407	EMT206: .WORD	EMS104,EMS73,EMS202,0
067704	074513	076221	075207	EMT207: .WORD	EMS75,EMS141,EMS115,EMS140,0
067716	074513	076405	000000	EMT210: .WORD	EMS75,EMS150,0
067724	073705	074447	075207	EMT211: .WORD	EMS51,EMS72,EMS115,EMS50,EMS70,0
067740	076247	073745	075207	EMT212: .WORD	EMS142,EMS53,EMS115,EMS143,EMS72,0
067754	073656	074703	073745	EMT213: .WORD	EMS50,EMS103,EMS53,0
067764	073733	077500	077026	EMT214: .WORD	EMS52,EMS205,EMS166,EMS206,EMS115,EMS51,EMS72,0
070004	073733	075244	074030	EMT215: .WORD	EMS52,EMS117,EMS56,EMS163,0
070016	074030	073036	074241	EMT216: .WORD	EMS56,EMS30,EMS64,0
070026	073600	073036	074241	EMT217: .WORD	EMS46,EMS30,EMS64,0
070036	073046	073036	074241	EMT220: .WORD	EMS31,EMS30,EMS64,0
070046	073627	073036	074241	EMT221: .WORD	EMS47,EMS30,EMS64,0
070056	073733	075244	074552	EMT222: .WORD	EMS52,EMS117,EMS77,0
070066	073733	075244	074213	EMT223: .WORD	EMS52,EMS117,EMS63,0
070076	000000			EMT224: .WORD	
070100	000000			EMT225: .WORD	
070102	000000			EMT226: .WORD	
070104	000000			EMT227: .WORD	
070106	000000			EMT230: .WORD	
070110	000000			EMT231: .WORD	
070112	000000			EMT232: .WORD	
070114	000000			EMT233: .WORD	
070116	000000			EMT234: .WORD	
070120	000000			EMT235: .WORD	
070122	000000			EMT236: .WORD	
070124	000000			EMT237: .WORD	
070126	000000			EMT240: .WORD	
070130	000000			EMT241: .WORD	
070132	000000			EMT242: .WORD	
070134	000000			EMT243: .WORD	
070136	000000			EMT244: .WORD	
070140	000000			EMT245: .WORD	
070142	077053	075743	077537	EMT246: .WORD	EMS167,EMS132,EMS207,0

Line	Code	Code	Code	Code	Code	Code
070152	077053	075743	077564	EMT247:	.WORD	EMS167,EMS132,EMS210,EMS125,0
070164	077053	077575	077564	EMT250:	.WORD	EMS167,EMS211,EMS210,EMS207,EMS206,0
070200	077613	077636	000000	EMT251:	.WORD	EMS212,EMS213,0
070206	077012	077613	000000	EMT252:	.WORD	EMS165,EMS212,0
070214	076370	076424	076552	EMT253:	.WORD	EMS147,EMS151,EMS156,EMS210,EMS26,EMS27,0
070232	077437	074626	073036	EMT254:	.WORD	EMS203,EMS101,EMS30,0
070242	077437	077053	073036	EMT255:	.WORD	EMS203,EMS167,EMS30,0
070252	077437	074600	073036	EMT256:	.WORD	EMS203,EMS100,EMS30,0
070262	072422	073600	073036	EMT257:	.WORD	EMS11,EMS46,EMS30,EMS102,0
070274	073733	075244	074030	EMT260:	.WORD	EMS52,EMS117,EMS56,EMS102,0
070306	073733	077500	100003	EMT261:	.WORD	EMS52,EMS205,EMS220,EMS206,EMS115,EMS51,EMS72,0
070326	074712	074457	077407	EMT262:	.WORD	EMS104,EMS73,EMS202,0
070336	073656	073745	074654	EMT263:	.WORD	EMS50,EMS53,EMS102,0
070346	074030	073745	074654	EMT264:	.WORD	EMS56,EMS53,EMS102,EMS115,EMS150,EMS152,EMS70,0
070366	074434	074030	074654	EMT265:	.WORD	EMS71,EMS56,EMS102,EMS115,EMS150,EMS152,EMS72,0
070406	076247	076264	073745	EMT266:	.WORD	EMS142,EMS143,EMS53,EMS102,0
070420	073656	076351	075207	EMT267:	.WORD	EMS50,EMS146,EMS115,EMS52,EMS117,EMS46,0
070436	073627	073745	074654	EMT270:	.WORD	EMS47,EMS53,EMS102,EMS115,EMS140,0
070452	073627	073745	074654	EMT271:	.WORD	EMS47,EMS53,EMS102,EMS115,EMS141,EMS72,0
070470	074513	076221	074654	EMT272:	.WORD	EMS75,EMS141,EMS102,EMS115,EMS47,EMS73,0
070506	073705	074474	074654	EMT273:	.WORD	EMS51,EMS74,EMS102,EMS115,EMS50,EMS70,0
070524	074213	073745	074105	EMT274:	.WORD	EMS63,EMS53,EMS57,EMS115,EMS41,EMS146,0
070542	075214	073745	073356	EMT275:	.WORD	EMS116,EMS53,EMS41,EMS57,0
070554	073627	073745	074105	EMT276:	.WORD	EMS47,EMS53,EMS57,EMS115,EMS140,0
070570	073627	073745	074105	EMT277:	.WORD	EMS47,EMS53,EMS57,EMS115,EMS141,EMS72,0
070606	074030	073745	074105	EMT300:	.WORD	EMS56,EMS53,EMS57,EMS115,EMS150,EMS152,EMS70,0
070626	074434	074030	073745	EMT301:	.WORD	EMS71,EMS56,EMS53,EMS57,EMS115,EMS150,EMS152,EMS72,0
070650	077012	074600	074703	EMT302:	.WORD	EMS165,EMS100,EMS103,EMS57,0
070662	077012	074626	074703	EMT303:	.WORD	EMS165,EMS101,EMS103,EMS57,0
070674	077012	074552	074703	EMT304:	.WORD	EMS165,EMS77,EMS103,EMS57,0
070706	073600	073036	074241	EMT305:	.WORD	EMS46,EMS30,EMS64,EMS57,0
070720	073656	073745	074105	EMT306:	.WORD	EMS50,EMS53,EMS57,0
070730	073656	076351	075207	EMT307:	.WORD	EMS50,EMS146,EMS115,EMS52,EMS117,EMS46,EMS57,0
070750	076247	076264	073745	EMT310:	.WORD	EMS142,EMS143,EMS53,EMS57,0
070762	074712	074703	073745	EMT311:	.WORD	EMS104,EMS103,EMS53,EMS57,0
070774	074741	074703	073745	EMT312:	.WORD	EMS105,EMS103,EMS53,EMS57,0
071006	076312	076322	074703	EMT313:	.WORD	EMS144,EMS145,EMS103,EMS57,EMS115,EMS143,EMS70,0
071026	073404	074703	073745	EMT314:	.WORD	EMS42,EMS103,EMS53,EMS57,0
071040	073046	074703	073745	EMT315:	.WORD	EMS31,EMS103,EMS53,EMS57,0
071052	074434	073046	074703	EMT316:	.WORD	EMS71,EMS31,EMS103,EMS57,0
071064	073433	074703	074105	EMT317:	.WORD	EMS43,EMS103,EMS57,0
071074	073535	074703	074105	EMT320:	.WORD	EMS45,EMS103,EMS57,0
071104	073462	074703	074105	EMT321:	.WORD	EMS44,EMS103,EMS57,0
071114	074770	072630	000000	EMT322:	.WORD	EMS106,EMS20,0
071122	073252	074703	074105	EMT323:	.WORD	EMS36,EMS103,EMS57,0
071132	077202	073252	074703	EMT324:	.WORD	EMS173,EMS36,EMS103,EMS57,0
071144	077162	073252	074703	EMT325:	.WORD	EMS172,EMS36,EMS103,EMS57,0
071156	072474	077217	072516	EMT326:	.WORD	EMS13,EMS174,EMS15,EMS35,EMS53,EMS175,0
071174	076370	076424	074474	EMT327:	.WORD	EMS147,EMS151,EMS74,EMS175,0
071206	074325	073745	077225	EMT330:	.WORD	EMS66,EMS53,EMS175,0
071216	073124	074703	073745	EMT331:	.WORD	EMS33,EMS103,EMS53,EMS175,0
071230	073327	074703	073745	EMT332:	.WORD	EMS40,EMS103,EMS53,EMS57,0
071242	073705	074474	074105	EMT333:	.WORD	EMS51,EMS74,EMS57,EMS115,EMS50,EMS70,0
071260	074513	076221	074105	EMT334:	.WORD	EMS75,EMS141,EMS57,EMS115,EMS47,EMS73,0
071276	074513	076405	076450	EMT335:	.WORD	EMS75,EMS150,EMS152,EMS57,EMS115,EMS56,EMS73,0
071316	074133	074146	074175	EMT336:	.WORD	EMS60,EMS61,EMS62,0

CZRMDCO RM03/2 FCTNL TST 2
CZRMDC.P11 12-DEC-78 08:24

MACY11 30A(1052) 04-JAN-79 11:23 J 5
PAGE 268
ERROR MESSAGE TABLE

SEQ 0268

071326	075214	075244	073152	EMT337: .WORD	EMS116,EMS117,EMS34,0
071336	073152	073745	073757	EMT340: .WORD	EMS34,EMS53,EMS54,EMS111,0
071350	074001	073152	000000	EMT341: .WORD	EMS55,EMS34,0
071356	073733	075244	074030	EMT342: .WORD	EMS52,EMS117,EMS56,EMS57,0
071370	073733	075244	073535	EMT343: .WORD	EMS52,EMS117,EMS45,EMS57,0
071402	073733	075244	073462	EMT344: .WORD	EMS52,EMS117,EMS44,EMS57,0
071414	073733	075244	100023	EMT345: .WORD	EMS52,EMS117,EMS221,0
071424	074770	072630	075207	EMT346: .WORD	EMS106,EMS20,EMS115,EMS223,EMS72,0
071440	073733	077500	100073	EMT347: .WORD	EMS52,EMS205,EMS222,EMS206,0
071452	074513	076405	074654	EMT350: .WORD	EMS75,EMS150,EMS102,EMS115,EMS56,EMS73,0
071470	077053	074457	074654	EMT351: .WORD	EMS167,EMS73,EMS102,0
071500	077677	000000		EMT352: .WORD	EMS215,0
071504	077750	077437	077720	EMT353: .WORD	EMS217,EMS203,EMS216,0
071514	100023	072630	000000	EMT354: .WORD	EMS221,EMS20,0

071522	100253	101067	101146	ENT1:	.WORD	EH1,STSH1,STSH2,STSH4,0
071534	101067	101146	101277	ENT2:	.WORD	STSH1,STSH2,STSH4,0
071544	100272	000000		ENT110:	.WORD	EH110,0
071550	100301	000000		ENT111:	.WORD	EH111,0
071554	100320	000000		ENT114:	.WORD	EH114,0
071560	100347	101067	101146	ENT223:	.WORD	EH223,STSH1,STSH2,STSH4,0
071572	100375	101067	101146	ENT256:	.WORD	EH256,STSH1,STSH2,STSH4,0
071604	100452	101067	101146	ENT336:	.WORD	EH336,STSH1,STSH2,STSH4,0
071616	100511	101067	101146	ENT337:	.WORD	EH337,STSH1,STSH2,STSH4,0
071630	100650	101067	101146	ENT344:	.WORD	EH344,STSH1,STSH2,STSH4,0
071642	101010	000000		ENT353:	.WORD	EH353,0

071646	101340	101434	101452	EDT11: .WORD	ED1,STSD1,STSD2,STSD4
071656	101434	101452	101504	EDT2: .WORD	STSD1,STSD2,STSD4
071664	101346			EDT110: .WORD	ED110
071666	101352			EDT111: .WORD	ED111
071670	101360			EDT114: .WORD	ED114
071672	101370	101434	101452	EDT223: .WORD	ED223,STSD1,STSD2,STSD4
071702	101400	101434	101452	EDT336: .WORD	ED336,STSD1,STSD2,STSD4
071712	101412	101434	101452	EDT337: .WORD	ED337,STSD1,STSD2,STSD4
071722	101412	101434	101452	EDT344: .WORD	ED337,STSD1,STSD2,STSD4,0
071734	101424			EDT353: .WORD	ED353

071736	101517	101535	101535	EFT1:	.WORD	EF111,STSF,STSF,STSF
071746	101535	101535	101535	EFT2:	.WORD	STSF,STSF,STSF
071754	101516			EFT110:	.WORD	EF110
071756	101517			EFT111:	.WORD	EF111
071760	101521			EFT114:	.WORD	EF114
071762	101521	101535	101535	EFT223:	.WORD	EF114,STSF,STSF,STSF
071772	101524	101535	101535	EFT336:	.WORD	EF336,STSF,STSF,STSF
072002	101524	101535	101535	EFT337:	.WORD	EF336,STSF,STSF,STSF
072012	101524	101535	101535	EFT344:	.WORD	EF336,STSF,STSF,STSF
072022	101521			EFT353:	.WORD	EF114

.SBTTL ERROR MESSAGE STRINGS

072024	051127	047117	020107	EMS1:	.ASCIZ	@WRONG UNIT SELECTED (RMCS2, BITS 0-2) @
072073	104	053105	041511	EMS2:	.ASCIZ	@DEVICE WENT @
072110	047125	053101	044501	EMS3:	.ASCIZ	@UNAVAILABLE 'DVA' (RMCS1, BIT 11) @
072153	116	047117	054105	EMS4:	.ASCIZ	@NONEXISTENT 'NED' (RMCS2, BIT 12) @
072216	047503	046515	047101	EMS5:	.ASCIZ	@COMMAND NOT COMPLETED, @
072246	047503	052116	047522	EMS6:	.ASCIZ	@CONTROLLER NOT READY (RMCS1, BIT 7) @
072313	104	044522	042526	EMS7:	.ASCIZ	@DRIVE NOT READY 'DRY' (RMDS, BIT 7) @
072360	047507	047040	052117	EMS10:	.ASCIZ	@GO NOT RESET 'GO' (RMCS1, BIT 0) @
072422	047111	040526	044514	EMS11:	.ASCIZ	@INVALID @
072433	106	047125	052103	EMS12:	.ASCIZ	@FUNCTION CODE (RMCS1, BITS 1-5) @
072474	040515	051523	052502	EMS13:	.ASCIZ	@MASSBUS @
072505	103	047117	051124	EMS14:	.ASCIZ	@CONTROL @
072516	052502	020123	040520	EMS15:	.ASCIZ	@BUS PARITY ERROR @
072540	046442	050103	021105	EMS16:	.ASCIZ	@'MCPE' (RMCS1, BIT 13) @
072570	051124	047101	043123	EMS17:	.ASCIZ	@TRANSFER ERROR (RMCS1, BIT 14) @
072630	044123	052517	042114	EMS20:	.ASCIZ	@SHOULD NOT BE SET @
072653	127	051117	020104	EMS21:	.ASCIZ	@WORD COUNT (RMWC) @
072676	052502	020123	051050	EMS22:	.ASCIZ	@BUS (RMB) @
072712	046042	052102	020042	EMS23:	.ASCIZ	@'LBT' (RMDS, BIT 10) @
072740	040442	042517	020042	EMS24:	.ASCIZ	@'AOE' (RMER1, BIT 09) @
072767	104	051511	020113	EMS25:	.ASCIZ	@DISK (RMDA) @
073004	054503	044514	042116	EMS26:	.ASCIZ	@CYLINDER (RMDC) @
073025	101	042104	042522	EMS27:	.ASCIZ	@ADDRESS @
073036	052123	052101	051525	EMS30:	.ASCIZ	@STATUS @
073046	053442	042514	020042	EMS31:	.ASCIZ	@'WLE' (RMER1, BIT 11) @
073075	042	050125	021105	EMS32:	.ASCIZ	@'UPE' (RMCS2, BIT 13) @
073124	053442	043103	020042	EMS33:	.ASCIZ	@'WCF' (RMER1, BIT 5) @
073152	051127	052111	020105	EMS34:	.ASCIZ	@WRITE CHECK ERROR-'WCE' (RMCS2, BIT 14) @
073223	042	042115	042520	EMS35:	.ASCIZ	@'MDPE' (RMCS2, BIT 8) @
073252	042042	045503	020042	EMS36:	.ASCIZ	@'DCK' (RMER1, BIT 15) @
073301	042	041505	021110	EMS37:	.ASCIZ	@'ECH' (RMER1, BIT 6) @
073327	042	046104	021124	EMS40:	.ASCIZ	@'DLT' (RMCS2, BIT 15) @
073356	046442	043130	020042	EMS41:	.ASCIZ	@'MXF' (RMCS2, BIT 9) @
073404	042042	042524	020042	EMS42:	.ASCIZ	@'DTE' (RMER1, BIT 12) @
073433	042	041510	041522	EMS43:	.ASCIZ	@'HCRC' (RMER1, BIT 8) @
073462	042510	042101	051105	EMS44:	.ASCIZ	@HEADER COMPARE ERROR 'HCE' (RMER1, BIT 7) @
073535	106	051117	040515	EMS45:	.ASCIZ	@FORMAT ERROR 'FER' (RMER1, BIT 4) @
073600	044442	042501	020042	EMS46:	.ASCIZ	@'IAE' (RMER1, BIT 10) @
073627	042	050117	021111	EMS47:	.ASCIZ	@'OPI' (RMER1, BIT 13) @
073656	051442	044513	020042	EMS50:	.ASCIZ	@'SKI' (RMER2, BIT 14) @
073705	042	044520	021120	EMS51:	.ASCIZ	@'PIP' (RMDS, BIT 13) @
073733	124	042510	051040	EMS52:	.ASCIZ	@THE RMO3 @
073745	104	052105	041505	EMS53:	.ASCIZ	@DETECTED @
073757	101	020124	047101	EMS54:	.ASCIZ	@AT AN UNEXPECTED @
074001	111	041516	051117	EMS55:	.ASCIZ	@INCORRECT DATA DURING @
074030	047111	040526	044514	EMS56:	.ASCIZ	@INVALID COMMAND ERROR 'IVC' (RMER2, BIT 12) @
074105	104	051125	047111	EMS57:	.ASCIZ	@DURING DATA TRANSFER @
074133	104	052101	020101	EMS60:	.ASCIZ	@DATA READ @
074146	047504	051505	047040	EMS61:	.ASCIZ	@DOES NOT COMPARE WITH @
074175	104	052101	020101	EMS62:	.ASCIZ	@DATA WRITTEN @
074213	042	040520	021122	EMS63:	.ASCIZ	@'PAR' (RMER1, BIT 3) @
074241	111	020123	047111	EMS64:	.ASCIZ	@IS INCORRECT @
074257	103	046517	047520	EMS65:	.ASCIZ	@COMPOSITE ERROR 'ERR' (RMDS, BIT 14) @
074325	104	052101	020101	EMS66:	.ASCIZ	@DATA PARITY ERROR 'DPE' (RMER2, BIT 3) @

074375	104	051125	047111	EMS67:	.ASCIZ	@DURING SEEK COMMAND @
074422	051511	051040	051505	EMS70:	.ASCIZ	@IS RESET @
074434	051105	047522	042516	EMS71:	.ASCIZ	@ERRONEOUS @
074447	111	020123	042523	EMS72:	.ASCIZ	@IS SET @
074457	104	042111	047040	EMS73:	.ASCIZ	@DID NOT SET @
074474	044504	020104	047516	EMS74:	.ASCIZ	@DID NOT RESET @
074513	114	051517	020124	EMS75:	.ASCIZ	@LOST @
074521	104	051125	047111	EMS76:	.ASCIZ	@DURING PACK ACK COMMAND @
074552	051042	051115	020042	EMS77:	.ASCIZ	@'RMR' (RMER1, BIT 2) @
074600	044442	051114	020042	EMS100:	.ASCIZ	@'ILR' (RMER1, BIT 1) @
074626	044442	043114	020042	EMS101:	.ASCIZ	@'ILF' (RMER1, BIT 0) @
074654	052504	044522	043516	EMS102:	.ASCIZ	@DURING SEARCH COMMAND @
074703	105	051122	051117	EMS103:	.ASCIZ	@ERROR @
074712	046042	041502	020042	EMS104:	.ASCIZ	@'LBC' (RMER2, BIT 10) @
074741	042	051514	021103	EMS105:	.ASCIZ	@'LSC' (RMER2, BIT 11) @
074770	042510	042101	051105	EMS106:	.ASCIZ	@HEADER ERRORS @
075007	102	051525	052040	EMS110:	.ASCIZ	@BUS TIMEOUT (04 TRAP) @
075036	042101	051104	051505	EMS111:	.ASCIZ	@ADDRESS @
075047	127	042510	020116	EMS112:	.ASCIZ	@WHEN READING/WRITING RM REGISTERS @
075111	101	020124	044124		.ASCIZ	@AT THE FOLLOWING @
075133	124	042510	051440	EMS113:	.ASCIZ	@THE SELECTED DEVICE IS @
075163	116	047117	054105	EMS114:	.ASCIZ	@NONEXISTENT DEVICE @
075207	040	006455	000012	EMS115:	.ASCIZ	@ -@<CR><LF>
075214	044124	020105	040515	EMS116:	.ASCIZ	@THE MASSBUS CONTROLLER @
075244	040506	046111	042105	EMS117:	.ASCIZ	@FAILED TO DETECT @
075266	047516	020124	047101	EMS120:	.ASCIZ	@NOT AN RM03 @
075303	103	047117	051124	EMS121:	.ASCIZ	@CONTROL STATUS REGISTER 1, RMCS1, @
075346	052502	020123	042101	EMS122:	.ASCIZ	@BUS ADDRESS REGISTER, RMBA, @
075403	103	047117	051124	EMS123:	.ASCIZ	@CONTROL STATUS REGISTER 2, RMCS2, @
075446	051105	047522	020122	EMS124:	.ASCIZ	@ERROR REGISTER 1, RMER1, @
075500	052101	042524	052116	EMS125:	.ASCIZ	@ATTENTION SUMMARY REGISTER, RMAS, @
075543	115	044501	052116	EMS126:	.ASCIZ	@MAINTENANCE REGISTER #1, RMMR #1, @
075606	041505	020103	047520	EMS127:	.ASCIZ	@ECC POSITION REGISTER, RMEC1, @
075645	105	041503	050040	EMS130:	.ASCIZ	@ECC PATTERN REGISTER, RMEC2, @
075703	115	044501	052116	EMS131:	.ASCIZ	@MAINTENANCE REGISTER 2, RMMR2, @
075743	116	052117	044440	EMS132:	.ASCIZ	@NOT INITIALIZED BY @
075767	125	044516	052502	EMS133:	.ASCIZ	@UNIBUS INITIALIZE @
076012	047503	052116	047522	EMS134:	.ASCIZ	@CONTROLLER CLEAR, I.E. BIT 5 OF @
076054	044122	030461	042440	EMS135:	.ASCIZ	@RH11 ERROR CLEAR (RMCS1, BIT 14) @
076116	051104	053111	020105	EMS136:	.ASCIZ	@DRIVE CLEAR COMMAND @
076143	104	044522	042526	EMS137:	.ASCIZ	@DRIVE STATUS REGISTER, RMDS @
076200	042515	044504	046525	EMS140:	.ASCIZ	@MEDIUM OFF LINE @
076221	042	047515	021114	EMS141:	.ASCIZ	@'MOL' (RMDS, BIT 12) @
076247	104	044522	042526	EMS142:	.ASCIZ	@DRIVE FAULT @
076264	042042	041526	020042	EMS143:	.ASCIZ	@'DVC' (RMER2, BIT 7) @
076312	047125	040523	042506	EMS144:	.ASCIZ	@UNSAFE @
076322	052442	051516	020042	EMS145:	.ASCIZ	@'UNS' (RMER1, BIT 14) @
076351	123	047510	046125	EMS146:	.ASCIZ	@SHOULD BE SET @
076370	043117	051506	052105	EMS147:	.ASCIZ	@OFFSET MODE @
076405	040	047526	052514	EMS150:	.ASCIZ	@ VOLUME VALID @
076424	047442	021115	024040	EMS151:	.ASCIZ	@'OM' (RMDS, BIT 0) @
076450	053042	021126	024040	EMS152:	.ASCIZ	@'VV' (RMDS, BIT 6) @
076474	040520	045503	040440	EMS153:	.ASCIZ	@PACK ACK COMMAND @
076516	047516	020124	042523	EMS154:	.ASCIZ	@NOT SET BY @
076532	043117	051506	052105	EMS155:	.ASCIZ	@OFFSET COMMAND @
076552	047516	020124	042522	EMS156:	.ASCIZ	@NOT RESET BY @

076570	052122	020103	047503	EMS157:	.ASCIZ	@RTIC COMMAND @
076605	122	050111	041440	EMS160:	.ASCIZ	@RIP COMMAND @
076622	043117	051506	052105	EMS161:	.ASCIZ	@OFFSET REGISTER (RMOF) @
076652	051105	047522	020122	EMS162:	.ASCIZ	@ERROR REGISTER #2, RMER2, @
076705	104	051125	047111	EMS163:	.ASCIZ	@DURING RECALIBRATE @
076731	111	020123	047111	EMS164:	.ASCIZ	@IS INTERMITTENT OR DRIVE DIDNT DROP ON @
077000	054503	044514	042116		.ASCIZ	@CYLINDER @
077012	047125	054105	042520	EMS165:	.ASCIZ	@UNEXPECTED @
077026	042522	040503	044514	EMS166:	.ASCIZ	@RECALIBRATE COMMAND @
077053	042	052101	021101	EMS167:	.ASCIZ	@'ATA' (RMD5, BIT15) @
077100	044127	047105	051040	EMS170:	.ASCIZ	@WHEN READING REGISTER @
077127	105	051122	051117	EMS171:	.ASCIZ	@ERROR REGISTER #2, RMER2, @
077162	047516	051116	041505	EMS172:	.ASCIZ	@NONRECOVERABLE @
077202	042522	047503	042526	EMS173:	.ASCIZ	@RECOVERABLE @
077217	104	052101	020101	EMS174:	.ASCIZ	@DATA @
077225	104	051125	047111	EMS175:	.ASCIZ	@DURING WRITE COMMAND @
077253	042	050117	021105	EMS176:	.ASCIZ	@'OPE' (RMER2, BIT 13) @
077302	047111	053440	044522	EMS177:	.ASCIZ	@IN WRITE PROTECT @
077324	040503	020116	047516	EMS200:	.ASCIZ	@CAN NOT SET @
077341	104	040511	047107	EMS201:	.ASCIZ	@DIAGNOSTIC MODE 'DMD' (RMMR1, BIT 0) @
077407	104	051125	047111	EMS202:	.ASCIZ	@DURING DIAGNOSTIC MODE @
077437	111	041516	051117	EMS203:	.ASCIZ	@INCORRECT @
077452	053442	046122	020042	EMS204:	.ASCIZ	@'WRL' (RMD5, BIT 11) @
077500	054105	041505	052125	EMS205:	.ASCIZ	@EXECUTED @
077512	044527	044124	041440	EMS206:	.ASCIZ	@WITH COMP ERROR SET @
077537	042	047507	020042	EMS207:	.ASCIZ	@'GO' (RMCS1, BIT 0) @
077564	051127	052111	047111	EMS210:	.ASCIZ	@WRITING @
077575	127	051501	051040	EMS211:	.ASCIZ	@WAS RESET BY @
077613	120	047522	051107	EMS212:	.ASCIZ	@PROGRAM INTERRUPT @
077636	040527	020123	047516	EMS213:	.ASCIZ	@WAS NOT GENERATED @
077661	123	042505	020113	EMS214:	.ASCIZ	@SEEK COMMAND @
077677	120	047522	051107	EMS215:	.ASCIZ	@PROGRAM TIMEOUT @
077720	052504	044522	043516	EMS216:	.ASCIZ	@DURING LOOK AHEAD TEST @
077750	047514	045517	040440	EMS217:	.ASCIZ	@LOOK AHEAD REGISTER,RMLA, @
100003	123	040505	041522	EMS220:	.ASCIZ	@SEARCH COMMAND @
100023	102	042101	051440	EMS221:	.ASCIZ	@BAD SECTOR ERROR 'BSE' (RMER2, BIT 15) @
100073	101	042040	052101	EMS222:	.ASCIZ	@A DATA TRANSFER COMMAND @
100124	042510	042101	051105	EMS223:	.ASCIZ	@HEADER COMPARE INHIBIT 'HCI' (RMOF, BIT 10) @
100201	116	047117	054105	EMS224:	.ASCIZ	@NONEXISTENT MEMORY 'NEM' (RMCS2, BIT 11) @

100253	105	050130	052103	EH1:	.ASC1Z	@EXPCTD	RECEVD@	
100272	052502	040523	051104	EH110:	.ASC1Z	@BUSADR@		
100301	040	046522	051503	EH111:	.ASC1Z	@ RMCS2	RMCS1@	
100320	042522	042503	042126	EH114:	.ASC1Z	@RECEVD	SNGPRT	DULPRT@
100347	105	050130	052103	EH223:	.ASC1Z	@EXPCTD	RECEVD	DATA@
100375	105	050130	052103	EH256:	.ASC1Z	@EXPCTD	RECEVD	RGSTR@<CR><LF>
100424	052123	052101	051525		.ASC1Z	@STATUS	STATUS	INDEX@
100452	042107	042101	051522	EH336:	.ASC1Z	@GDADRS	GDDATA	BDADRS BDDATA@
100511	122	041515	031123	EH337:	.ASC1Z	@RMCS2	STATUS	FAILING DATA@<CR><LF>
100551	137	057537	057537		.ASC1Z	@		@<CR><LF>
100611	105	050130	052103		.ASC1Z	@EXPCTD	RECEVD	--BIT--ADRESS@
100650	046522	051105	020061	EH344:	.ASC1Z	@RMER1	STATUS	HEADER FAILING@<CR><LF>
100711	137	057537	057537		.ASC1Z	@	WORD	BIT@<CR><LF>
100750	054105	041520	042124		.ASC1Z	@EXPCTD	RECEVD	NUMBER POSITION@
101010	054105	041520	042124	EH353:	.ASC1Z	@EXPCTD	RECEVD@<CR><LF>	
101030	041474	037122	046074		.ASC1Z	@<CR><LF>	RMLA	RMLA RMOF @
101067	040	046522	051503	STSH1:	.ASC1Z	@ RMCS1	RMCS2	RMDS RMER1 RMER2@
101134	020040	051040	040515		.ASC1Z	@	RMA@<CR><LF>	
101146	051040	053515	020103	STSH2:	.ASC1Z	@ RMWC	RMBA	RMDA RMOF RMD@
101213	040	020040	051040		.ASC1Z	@	RMEC1	RMEC2@<CR><LF>
101237	040	046522	040504	STSH3:	.ASC1Z	@ RMDA	RMDC	RMOF RMLA@<CR><LF>
101277	040	046522	051115	STSH4:	.ASC1Z	@ RMMR1	RMMR2	RMDT RMSN@<CR><LF>

CZRMDCO RM03/2 FCTNL TST 2
CZRMDC.P11 12-DEC-78 08:24

MACY11 30A(1052) 04-JAN-79 11:23 E 6
PAGE 276
ERROR MESSAGE STRINGS

SEQ 0276

	101340			.EVEN		
101340	001140	001142	000000	ED1:	.WORD	\$GDDAT,\$BDDAT,0
101346	001276	000000		ED110:	.WORD	\$BASE,0
101352	001174	001176	000000	ED111:	.WORD	\$TMP0,\$TMP1,0
101360	001356	001176	001200	ED114:	.WORD	RMDT1,\$TMP1,\$TMP2,0
101370	001140	001142	001174	ED223:	.WORD	\$GDDAT,\$BDDAT,\$TMP0,0
101400	001134	001140	001136	ED336:	.WORD	\$GDADR,\$GDDAT,\$BDADR,\$BDDAT,0
101412	001140	001142	001174	ED337:	.WORD	\$GDDAT,\$BDDAT,\$TMP0,\$TMP1,0
101424	001140	001142	001432	ED353:	.WORD	\$GDDAT,\$BDDAT,RMOFO,0
101434	001330	001340	001342	STSD1:	.WORD	RMCS11,RMCS21,RMDS1,RMER11,RMER21,RMAS1,0
101452	001332	001334	001336	STSD2:	.WORD	RMWC1,RMBA1,RMDA1,RMOF1,RMDC1,RMEC11
101466	001376	000000			.WORD	RMEC21,0
101472	001336	001364	001362	STSD3:	.WORD	RMDA1,RMDC1,RMOF1,RMLA1,0
101504	001354	001370	001356	STSD4:	.WORD	RMMR11,RMMR21,RMDT1,RMSN1,0

CZRMDCO RM03/2 FCTNL TST 2
CZRMDC.P11 12-DEC-78 08:24

MACY11 30A(1052) 04-JAN-79 11:23 F 6
PAGE 277
ERROR MESSAGE STRINGS

SEQ 0277

101516	000			EF110:	.BYTE	0
101517	000	000		EF111:	.BYTE	0,0
101521	000	000	000	EF114:	.BYTE	0,0,0
101524	000	000	000	EF336:	.BYTE	0,0,0,0
101530	000	000	000	EF337:	.BYTE	0,0,0,0,0
101535	000	000	000	STSF:	.BYTE	0,0,0,0,0,0,0

CZRMDCO RM03/2 FCTNL TST 2
CZRMDC.P11 12-DEC-78 08:24

MACY11 30A(1052) 04-JAN-79 11:23 ^{G 6} PAGE 278
ERROR MESSAGE STRINGS

SEQ 0278

101544 000402
102550 177777
102552 177777
102554 000402
103560 177777
103562 177777

.EVEN
MFGFIL: .BLKW 258.
.WORD -1
.WORD -1
USRFIL: .BLKW 258.
.WORD -1
.WORD -1
.EVEN

103564
103564 000402
104570 000402BUFFER:
BUFONE: .BLKW 258.
BUFTWO: .BLKW 258.103564 103564
103564 005015

.HELP: = BUFFER

```
103566 046011 051511 020124 .ASCII <CR><LF>
103606 057411 057537 057537 .ASCII <CR><LF>
103626 030524 041411 047117 .ASCII <CR><LF>
103661 124 004462 042504 .ASCII <CR><LF>
103713 124 004463 051104 .ASCII <CR><LF>
103737 124 004464 047506 .ASCII <CR><LF>
103765 124 004465 047506 .ASCII <CR><LF>
104013 124 004466 042532 .ASCII <CR><LF>
104036 033524 043011 051117 .ASCII <CR><LF>
104072 030524 004460 047506 .ASCII <CR><LF>
104137 124 030461 043011 .ASCII <CR><LF>
104165 124 031061 043011 .ASCII <CR><LF>
104221 124 031461 043011 .ASCII <CR><LF>
104266 030524 004464 047506 .ASCII <CR><LF>
104323 124 032461 043011 .ASCII <CR><LF>
104361 124 033061 043011 .ASCII <CR><LF>
104422 030524 004467 047506 .ASCII <CR><LF>
104456 031124 004460 047506 .ASCII <CR><LF>
104516 031124 004461 047506 .ASCII <CR><LF>
104555 124 031062 043011 .ASCII <CR><LF>
104611 124 031462 043011 .ASCII <CR><LF>
104641 124 032062 043011 .ASCII <CR><LF>
104672 031124 004465 047506 .ASCII <CR><LF>
104735 124 033062 043011 .ASCII <CR><LF>
104777 124 033462 043011 .ASCII <CR><LF>
105044 031524 004460 047506 .ASCII <CR><LF>
105072 031524 004461 053111 .ASCII <CR><LF>
105117 124 031063 043011 .ASCII <CR><LF>
105153 124 031463 043011 .ASCII <CR><LF>
105207 124 032063 043011 .ASCII <CR><LF>
105252 031524 004465 047506 .ASCII <CR><LF>
105316 005015 .ASCII <CR><LF>
105320 047411 042520 040522 .ASCII <CR><LF>
105356 057411 057537 057537 .ASCII <CR><LF>
105414 005015 .ASCII <CR><LF>
105416 053523 052111 044103 .ASCII <CR><LF>
105434 026455 026455 026455 .ASCII <CR><LF>
105472 020040 032461 004411 .ASCII <CR><LF>
105517 040 030440 004464 .ASCII <CR><LF>
105543 040 030440 004463 .ASCII <CR><LF>
105601 040 030440 004462 .ASCII <CR><LF>
105611 040 030440 004461 .ASCII <CR><LF>
105643 040 030440 004460 .ASCII <CR><LF>
105670 020040 034440 004411 .ASCII <CR><LF>
105715 040 020040 004470 .ASCII <CR><LF>
```

```
CAUTION: PARTS 2 AND 3 OF THE FUNCTIONAL TEST LEAVE @<CR><LF>
BAD HEADERS ON THE PACK SO BE SURE TO FORMAT THE PACKS@<CR><LF>
WHEN DONE.@<CR><LF>
LIST OF TESTS@<CR><LF>
@<CR><LF>
CONTROLLER ACCESS TEST@<CR><LF>
DEVICE AVAILABLE TEST@<CR><LF>
DRIVE TYPE TEST@<CR><LF>
FORMAT ZEROS - 18@<CR><LF>
FORMAT ZEROS - 16@<CR><LF>
ZERO FILL TEST@<CR><LF>
FORMAT CHECK ZEROS - 16@<CR><LF>
FORMAT CHECK ZEROS W/ WCE ERROR@<CR><LF>
FORMAT ONES - 16@<CR><LF>
FORMAT CHECK ONES - 16@<CR><LF>
FORMAT CHECK ONES W/ WCE ERROR@<CR><LF>
FORMAT MULTIPLE SECTORS@<CR><LF>
FORMAT W/ HEAD SWITCHING@<CR><LF>
FORMAT W/ MID TRANSFER SEEK@<CR><LF>
FORMAT W/ IMPLIED SEEK@<CR><LF>
FORMAT EACH SECTOR ADDRESS@<CR><LF>
FORMAT EACH TRACK ADDRESS@<CR><LF>
FORMAT PRIME CYLINDERS@<CR><LF>
FORMAT LAST SECTOR@<CR><LF>
FORMAT W/ AOE ERROR@<CR><LF>
FORMAT INVALID SECTOR ADDRESS@<CR><LF>
FORMAT INVALID TRACK ADDRESS@<CR><LF>
FORMAT INVALID CYLINDER ADDRESS@<CR><LF>
FORMAT AT OFFSET@<CR><LF>
IVC FORMAT TEST@<CR><LF>
FORMAT ERROR TEST - 18@<CR><LF>
FORMAT ERROR TEST - 16@<CR><LF>
FORMAT HCE, FIRST HEADER WORD@<CR><LF>
FORMAT HCE, SECOND HEADER WORD@<CR><LF>
OPERATIONAL SWITCH SETTINGS@<CR><LF>
@<CR><LF>
-----@<CR><LF>
SWITCH USE@<CR><LF>
-----@<CR><LF>
@ 15 HALT ON ERROR@<CR><LF>
@ 14 LOOP ON TEST@<CR><LF>
@ 13 INHIBIT ERROR TYPEOUTS@<CR><LF>
@<CR><LF>
@ 12 INHIBIT ITERATIONS@<CR><LF>
@ 11 BELL ON ERROR@<CR><LF>
@ 10 LOOP ON ERROR@<CR><LF>
@ 9 LOOP ON TEST IN SWR<7:0>@<CR><LF>
@ 8
```


CZRMDCO RM03/2 FCTNL TST 2
CZRMDC.P11 12-DEC-78 08:24

MACY11 30A(1052) 04-JAN-79 11:23 PAGE 280
ERROR MESSAGE STRINGS

SEQ 0280

105755	040	020040	004467	.ASCII	a	7	TN128a<CR><LF>
105772	020040	033040	004411	.ASCII	a	6	TN64a<CR><LF>
106006	020040	032440	004411	.ASCII	a	5	TN32a<CR><LF>
106022	020040	032040	004411	.ASCII	a	4	TN16a<CR><LF>
106036	020040	031440	004411	.ASCII	a	3	TN8a<CR><LF>
106051	040	020040	004462	.ASCII	a	2	TN4a<CR><LF>
106064	020040	030440	004411	.ASCII	a	1	TN2a<CR><LF>
106077	040	020040	004460	.ASCII	a	0	TN1a<CR><LF>
106112	005015			.ASCII	<CR><LF>		
106114	005015	000		.ASCII	<CR><LF>		
	000001			.END			

10329#

[illegible]

CZRMDCO RM03/2 FCTNL TST 2
CZRMDC.P11 12-DEC-78 08:24

K 6
MACY11 30A(1052) 04-JAN-79 11:23 PAGE 283
CROSS REFERENCE TABLE -- USER SYMBOLS

SEQ 0282

ARGS = 000004

3672#	3709#	3741#	3748#	3755#	3784#	3791#	3798#	3807#	3840#	3877#	3909#	3916#
3923#	3952#	3959#	3966#	3975#	4008#	4045#	4078#	4085#	4092#	4122#	4129#	4136#
4145#	4178#	4215#	4247#	4254#	4261#	4289#	4296#	4303#	4338#	4375#	4407#	4414#
4421#	4452#	4463#	4526#	4563#	4595#	4602#	4609#	4638#	4645#	4652#	4661#	4694#
4731#	4763#	4770#	4777#	4805#	4812#	4819#	4854#	4891#	4923#	4930#	4937#	4968#
4979#	5042#	5079#	5111#	5118#	5125#	5153#	5160#	5167#	5201#	5238#	5270#	5277#
5284#	5312#	5319#	5326#	5360#	5397#	5429#	5436#	5443#	5471#	5478#	5485#	5519#
5558#	5591#	5598#	5605#	5633#	5640#	5647#	5684#	5722#	5729#	5736#	5765#	5772#
5779#	5788#	5829#	5867#	5874#	5881#	5910#	5917#	5924#	5933#	5974#	6012#	6019#
6026#	6055#	6062#	6069#	6078#	6107#	6155#	6162#	6169#	6191#	6237#	6244#	6251#
6286#	6324#	6331#	6338#	6347#	6378#	6385#	6392#	6433#	6471#	6478#	6485#	6494#
6525#	6532#	6539#	6580#	6618#	6625#	6632#	6641#	6672#	6679#	6686#	6726#	6776#
6783#	6790#	6838#	6845#	6852#	6861#	6901#	6952#	6966#	6975#	7006#	7020#	7054#
7092#	7099#	7106#	7136#	7147#	7158#	7192#	7230#	7237#	7244#	7274#	7285#	7296#
7331#	7378#	7385#	7392#	7421#	7436#	7451#	7471#	7489#	7516#	7567#	7614#	7621#
7628#	7657#	7668#	7686#	7711#								

ASNDA 001500
ASNDC 001476
ASWREG= 000000
ATA = 100000
ATESTN= 000000
ATNMSK= 000377
ATNTBL 064772
AUNIT = 000000
AUSWR = 000000
AVECT1= 120254
AVECT2= 000000
A16 = 000400
A17 = 001000
BACK = 000000

1487#	8464*	8493	8539*	8540	8542*	8543*	8544	8546*	8591			
1486#	8463*	8492	8547*	8548	8550*	8590						
1363	1376											
1011#	9326	9327	9329	10061	10062	10097	10100	10592	10593	10632	10635	12557

1363	1367		
1048#	10789		
3469	3487	12557#	
1363	1370		
1363	1377		
1252#	1363	1402	
1363	1403		

3672#	3677	3709#	3713	3741#	3745	3748#	3752	3755#	3759	3784#	3788	3791#
3795	3798#	3802	3807#	3813	3840#	3845	3877#	3881	3909#	3913	3916#	3920
3923#	3927	3952#	3956	3959#	3963	3966#	3970	3975#	3981	4008#	4013	4045#
4049	4078#	4082	4085#	4089	4092#	4096	4122#	4126	4129#	4133	4136#	4140
4145#	4151	4178#	4183	4215#	4219	4247#	4251	4254#	4258	4261#	4265	4289#
4293	4296#	4300	4303#	4307	4338#	4343	4375#	4379	4407#	4411	4414#	4418
4421#	4425	4452#	4456	4463#	4467	4526#	4531	4563#	4567	4595#	4599	4602#
4606	4609#	4613	4638#	4642	4645#	4649	4652#	4656	4661#	4667	4694#	4699
4731#	4735	4763#	4767	4770#	4774	4777#	4781	4805#	4809	4812#	4816	4819#
4823	4854#	4859	4891#	4895	4923#	4927	4930#	4934	4937#	4941	4968#	4972
4979#	4983	5042#	5047	5079#	5083	5111#	5115	5118#	5122	5125#	5129	5153#
5157	5160#	5164	5167#	5171	5201#	5206	5238#	5242	5270#	5274	5277#	5281
5284#	5288	5312#	5316	5319#	5323	5326#	5330	5360#	5365	5397#	5401	5429#
5433	5436#	5440	5443#	5447	5471#	5475	5478#	5482	5485#	5489	5519#	5524
5558#	5562	5591#	5595	5598#	5602	5605#	5609	5633#	5637	5640#	5644	5647#
5651	5684#	5689	5722#	5726	5729#	5733	5736#	5740	5765#	5769	5772#	5776
5779#	5783	5788#	5794	5829#	5834	5867#	5871	5874#	5878	5881#	5885	5910#
5914	5917#	5921	5924#	5928	5933#	5939	5974#	5979	6012#	6016	6019#	6023
6026#	6030	6055#	6059	6062#	6066	6069#	6073	6078#	6084	6107#	6112	6155#
6159	6162#	6166	6169#	6173	6191#	6196	6237#	6241	6244#	6248	6251#	6255
6286#	6291	6324#	6328	6331#	6335	6338#	6342	6347#	6352	6378#	6382	6385#
6389	6392#	6396	6433#	6438	6471#	6475	6478#	6482	6485#	6489	6494#	6499
6525#	6529	6532#	6536	6539#	6543	6580#	6585	6618#	6622	6625#	6629	6632#
6636	6641#	6646	6672#	6676	6679#	6683	6686#	6690	6726#	6731	6776#	6780
6783#	6787	6790#	6794	6838#	6842	6845#	6849	6852#	6856	6861#	6867	6901#
6906	6952#	6956	6966#	6970	6975#	6980	7006#	7010	7020#	7024	7054#	7059
7092#	7096	7099#	7103	7106#	7110	7136#	7140	7147#	7151	7158#	7162	7192#

SEQ 0283

[illegible]

```

CC      = 004000
CH      = 002000
CHRCNT 033741
CKSWR   = 104410
CLEAN   = ***** U
CLKADR  001502
CLKVCT  001504
CLR      = 000040
CLRSTS  046776
CLSPRN  063570
CMNSTA  006772
CMPBUF  037064
CMPERR  057122
CNSLOO  064067
CNSLO1  064126
CNSLO2  064153
CNSLO3  064234
CNSLO4  064264
CNSLO5  064340
CNSLO6  064374
CNSLO7  064421
CNTCLR  046660
CONT     = 000100
CR       = 000015
CRLF    = 000200
CTLFG   001326
CYLSK   = 001777
DBCK     = 100000
DBEN     = 040000
DBL      = 002000
DCK      = 100000
DDISP    = 177570
DEBL     = 020000
DEVSEL   045206
DISPLA   001156
DISPRE   000174
DLT      = 100000
DMD      = 000001
DPE      = 000010
DPEMI    = 040000
DPELO    = 020000
DPR      = 000400
DRQ      = 004000
DRVCLR   = 000010
DRVSTS   052214
DRY      = 000200
DSWR     = 177570
DTASTS   053016

```

5005	5747	5790	5892	5935	6037	6080	6120	6204	6357	6504	6651	6815
6863	6985	7118	7256	7403	7462	7481	7639	7678	12557#			
1127#												
1128#												
7851*	7869*	7875*	7876	7879*	7883	7888*	7899*	7947#				
11968	12073	12099	12450#									
7465	12557											
1488#	8964*	8966	8970*	8972	8997							
1489#	8965*	8971*										
1218#	3318	10158										
8035	10194#											
3389	3405	3426	12557#									
3341	3476#											
3807	3975	4145	4661	5788	5933	6078	6861	8693#				
11573#												
3351	12557#											
3386	12557#											
3395	12557#											
3400	12557#											
3411	12557#											
3421	12557#											
3432	12557#											
3445	12557#											
3576	3620	8015	10150#									
1091#												
842#	3459	7867	11656	11943	11953	12557						
843#	3295	11914	11953									
1418#	3515*	11645*	11647									
1118#	8631											
1064#												
1065#												
1235#												
1025#	1042	8369	8701	9657	9677	11267	11270					
849#	1335	3259										
1066#												
8002	9860#											
1335#	3259*	3267*	12024*	12076*								
1262#	3267											
1207#	9501	11346	11349									
1078#	1097#	6910										
1150#	8370	8376	9163	9443	9939	10478	10899	11320	11323			
1231#												
1232#												
1018#	10100	10297	10298	10764								
1104#												
962#	8223	10752										
8241	10743#											
1019#	9130	9226	9229	9230	10100	10297	10298	10764				
848#	1334	3258										
3748	3791	3916	3959	4085	4129	4254	4296	4414	4463	4602	4645	4770
4812	4930	4979	5118	5160	5277	5319	5436	5478	5598	5640	5729	5772
5874	5917	6019	6062	6162	6244	6331	6385	6478	6532	6625	6679	6783
6845	7099	7147</										

CZRMDCO RM03/2 FCTNL TST 2
CZRMDC.P11 12-DEC-78 08:24

MACY11 30A(1052) 04-JAN-79 11:23 N 6
CROSS REFERENCE TABLE -- USER SYMBOLS

SEQ 0285

DVA = 004000	947#	3324	3595	8853	8926	9091	9094	9885	10203	10751	10752	11512	11517
DVC = 000200	1149#	10032	10287	10539	10577	10580	10713	11086	11090	11093	11138		
EARLY = 065316	11520												
EBL = 020000	12557#												
ECM = 000100	1084#												
ECI = 004000	1034#	1042	8369	8703	9640	9655	9673	9679	11277	12557			
ECRC = 001000	1112#	8705	9675	11274									
EDT1 071646	1088#												
	1523	1530	1537	1544	1551	1558	1572	1579	1586	1593	1600	1607	1614
	1621	1628	1635	1642	1649	1656	1663	1670	1677	1684	1691	1698	1705
	1712	1719	1726	1733	1740	1747	1754	1761	1768	1775	1782	1789	1796
	1803	1810	1818	1825	1832	1839	1846	1854	1862	1870	1884	1891	1898
	1905	1912	1919	1926	1934	1941	1948	1955	1962	1969	1976	1983	1990
	1997	2004	2011	2018	2060	2067	2074	2081	2088	2095	2102	2109	2116
	2123	2130	2137	2144	2151	2158	2165	2172	2179	2186	2193	2200	2207
	2214	2221	2228	2235	2242	2249	2256	2263	2270	2277	2284	2291	2298
	2305	2312	2319	2334	2341	2348	2355	2369	2376	2383	2390	2397	2404
	2411	2418	2425	2432	2439	2446	2453	2460	2467	2474	2481	2488	2495
	2516	2523	2530	2537	2544	2684	2691	2698	2719	2726	2733	2747	2754
	2761	2768	2775	2782	2789	2796	2804	2811	2819	2826	2833	2841	2849
	2857	2866	2874	2882	2889	2896	2903	2910	2917	2924	2931	2938	2945
	2952	2959	2966	2973	2980	2987	2994	3001	3008	3015	3022	3029	3036
	3043	3050	3057	3064	3071	3078	3113	3120	3134	3141	3148	3155	3162
	3183	12557#											
EDT110 071664	2025	12557#											
EDT111 071666	2032	2039	12557#										
EDT114 071670	2053	12557#											
EDT2 071656	2502	2509	2705	2712	12557#								
EDT223 071672	2551	2740	12557#										
EDT336 071702	2327	3085	3099	3106	12557#								
EDT337 071712	3092	12557#											
EDT344 071722	3127	12557#											
EDT353 071734	3176	12557#											
ED1 101340	12557#												
ED110 101346	12557#												
ED111 101352	12557#												
ED114 101360	12557#												
ED223 101370	12557#												
ED336 101400	12557#												
ED337 101412	12557#												
ED353 101424	12557#												
EECC = 000020	1093#												
EFT1 071736	1524	1531	1538	1545	1552	1559	1573	1580	1587	1594	1601	1608	1615
	1622	1629	1636	1643	1650	1657	1664	1671	1678	1685	1692	1699	1706
	1713	1720	1727	1734	1741	1748	1755	1762	1769	1776	1783	1790	1797
	1804	1811	1819	1826	1833	1840	1847	1855	1863	1871	1885	1892	1899
	1906	1913	1920	1927	1935	1942	1949	1956	1963	1970	1977	1984	1991
	1998	2005	2012	2019	2061	2068	2075	2082	2089	2096	2103	2110	2117
	2124	2131	2138	2145	2152	2159	2166	2173	2180	2187	2194	2201	2208
	2215	2222	2229	2236	2243	2250	2257	2264	2271	2278	2285	2292	2299
	2306	2313	2320	2335	2342	2349	2356	2370	2377	2384	2391	2398	2405
	2412	2419	2426	2433	2440	2447	2454	2461	2468	2475	2482	2489	2496
	2517	2524	2531	2538	2545	2685	2692	2699	2720	2727	2734	2748	2755
	2762	2769	2776	2783	2790	2797	2805	2812	2820	2827	2834	2842	2850
	2858	2867	2875	2883	2890	2897	2904	2911	2918	2925	2932	2939	2946
	2953	2960	2967	2974	2981	2988	2995	3002	3009	3016	3023	3030	3037

		3044	3051	3058	3065	3072	3079	3114	3121	3135	3142	3149	3156	3163
EF1110	071754	3184	12557#											
EF1111	071756	2026	12557#											
EF1114	071760	2033	2040	12557#										
EF12	071746	2054	12557#											
EF1223	071762	2503	2510	2706	2713	12557#								
EF1336	071772	2552	2741	12557#										
EF1337	072002	2328	3086	3100	3107	12557#								
EF1344	072012	3093	12557#											
EF1353	072022	3128	12557#											
EF110	101516	3177	12557#											
EF111	101517	12557#												
EF114	101521	12557#												
EF336	101524	12557#												
EF337	101530	12557#												
EHT1	071522	1522	1529	1536	1543	1550	1557	1571	1578	1585	1592	1599	1606	1613
		1620	1627	1634	1641	1648	1655	1662	1669	1676	1683	1690	1697	1704
		1711	1718	1725	1732	1739	1746	1753	1760	1767	1774	1781	1788	1795
		1802	1809	1817	1824	1831	1838	1845	1853	1861	1869	1883	1890	1897
		1904	1911	1918	1925	1933	1940	1947	1954	1961	1968	1975	1982	1989
		1996	2003	2010	2017	2059	2066	2073	2080	2087	2094	2101	2108	2115
		2122	2129	2136	2143	2150	2157	2164	2171	2178	2185	2192	2199	2206
		2213	2220	2227	2234	2241	2248	2255	2262	2269	2276	2283	2290	2297
		2304	2311	2318	2333	2340	2347	2354	2368	2375	2382	2389	2396	2403
		2410	2417	2424	2431	2438	2445	2452	2459	2466	2473	2480	2487	2494
		2515	2522	2529	2536	2543	2683	2690	2697	2718	2725	2732	2746	2753
		2760	2767	2774	2781	2788	2795	2803	2810	2818	2825	2832	2840	2848
		2856	2865	2873	2881	2888	2895	2902	2909	2916	2923	2930	2937	2944
		2951	2958	2965	2972	2979	2986	2993	3000	3007	3014	3021	3028	3035
		3042	3049	3056	3063	3070	3077	3112	3119	3133	3140	3147	3154	3161
		3182	12557#											
EHT110	071544	2024	12557#											
EHT111	071550	2031	2038	12557#										
EHT114	071554	2052	12557#											
EHT2	071534	2501	2508	2704	2711	12557#								
EHT223	071560	2550	12557#											
EHT256	071572	2739	12557#											
EHT336	071604	2326	3084	3098	3105	12557#								
EHT337	071616	3091	125											

CZRMDCO RM03/2 FCTNL TST 2
CZRMDC.P11 12-DEC-78 08:24

C 7
MACY11 30A(1052) 04-JAN-79 11:23 PAGE 288
CROSS REFERENCE TABLE -- USER SYMBOLS

SEQ 0287

EMS102	074654	12557#
EMS103	074703	12557#
EMS104	074712	12557#
EMS105	074741	12557#
EMS106	074770	12557#
EMS11	072422	12557#
EMS110	075007	12557#
EMS111	075036	12557#
EMS112	075047	12557#
EMS113	075133	12557#
EMS114	075163	12557#
EMS115	075207	12557#
EMS116	075214	12557#
EMS117	075244	12557#
EMS12	072433	12557#
EMS120	075266	12557#
EMS121	075303	12557#
EMS122	075346	12557#
EMS123	075403	12557#
EMS124	075446	12557#
EMS125	075500	12557#
EMS126	075543	12557#
EMS127	075606	12557#
EMS13	072474	12557#
EMS130	075645	12557#
EMS131	075703	12557#
EMS132	075743	12557#
EMS133	075767	12557#
EMS134	076012	12557#
EMS135	076054	12557#
EMS136	076116	12557#
EMS137	076143	12557#
EMS14	072505	12557#
EMS140	076200	12557#
EMS141	076221	12557#
EMS142	076247	12557#
EMS143	076264	12557#
EMS144	076312	12557#
EMS145	076322	12557#
EMS146	076351	12557#
EMS147	076370	12557#
EMS15	072516	12557#
EMS150	076405	12557#
EMS151	076424	12557#
EMS152	076450	12557#
EMS153	076474	12557#
EMS154	076516	12557#
EMS155	076532	12557#
EMS156	076552	12557#
EMS157	076570	12557#
EMS16	072540	12557#
EMS160	076605	12557#
EMS161	076622	12557#
EMS162	076652	12557#
EMS163	076705	12557#
EMS164	076731	12557#

CZRMDCO RM03/2 FCTNL TST 2
CZRMDC.P11 12-DEC-78 08:24

MACY11 30A(1052) 04-JAN-79 11:23 PAGE 289
CROSS REFERENCE TABLE -- USER SYMBOLS

0 7

SEQ 0288

EMS165	077012	12557#
EMS166	077026	12557#
EMS167	077053	12557#
EMS17	072570	12557#
EMS170	077100	12557#
EMS171	077127	12557#
EMS172	077162	12557#
EMS173	077202	12557#
EMS174	077217	12557#
EMS175	077225	12557#
EMS176	077253	12557#
EMS177	077302	12557#
EMS2	072073	12557#
EMS20	072630	12557#
EMS200	077324	12557#
EMS201	077341	12557#
EMS202	077407	12557#
EMS203	077437	12557#
EMS204	077452	12557#
EMS205	077500	12557#
EMS206	077512	12557#
EMS207	077537	12557#
EMS21	072653	12557#
EMS210	077564	12557#
EMS211	077575	12557#
EMS212	077613	12557#
EMS213	077636	12557#
EMS214	077661	12557#
EMS215	077677	12557#
EMS216	077720	12557#
EMS217	077750	12557#
EMS22	072676	12557#
EMS220	100003	12557#
EMS221	100023	12557#
EMS222	100073	12557#
EMS223	100124	12557#
EMS224	100201	12557#
EMS23	072712	12557#
EMS24	072740	12557#
EMS25	072767	12557#
EMS26	073004	12557#
EMS27	073025	12557#
EMS3	072110	12557#
EMS30	073036	12557#
EMS31	073046	12557#
EMS32	073075	12557#
EMS33	073124	12557#
EMS34	073152	12557#
EMS35	073223	12557#
EMS36	073252	12557#
EMS37	073301	12557#
EMS4	072153	12557#
EMS40	073327	12557#
EMS41	073356	12557#
EMS42	073404	12557#
EMS43	073433	12557#

CZRMDCO RM03/2 FCTNL TST 2
CZRMDC.P11 12-DEC-78 08:24

MACY11 30A(1052) 04-JAN-79 11:23 E 7
PAGE 290
CROSS REFERENCE TABLE -- USER SYMBOLS

SEQ 0289

EMS44	073462	12557#	
EMS45	073535	12557#	
EMS46	073600	12557#	
EMS47	073627	12557#	
EMS5	072216	12557#	
EMS50	073656	12557#	
EMS51	073705	12557#	
EMS52	073733	12557#	
EMS53	073745	12557#	
EMS54	073757	12557#	
EMS55	074001	12557#	
EMS56	074030	12557#	
EMS57	074105	12557#	
EMS6	072246	12557#	
EMS60	074133	12557#	
EMS61	074146	12557#	
EMS62	074175	12557#	
EMS63	074213	12557#	
EMS64	074241	12557#	
EMS65	074257	12557#	
EMS66	074325	12557#	
EMS67	074375	12557#	
EMS7	072313	12557#	
EMS70	074422	12557#	
EMS71	074434	12557#	
EMS72	074447	12557#	
EMS73	074457	12557#	
EMS74	074474	12557#	
EMS75	074513	12557#	
EMS76	074521	12557#	
EMS77	074552	12557#	
EMTVEC=	000030	937#	3242* 3243*
EMT1	065430	1521	12557#
EMT10	065500	1570	12557#
EMT100	066476	1967	12557#
EMT101	066514	1974	12557#
EMT102	066532	1981	12557#
EMT103	066542	1988	12557#
EMT104	066554	1995	12557#
EMT105	066572	2002	12557#
EMT106	066602	2009	12557#
EMT107	066612	2016	12557#
EMT11	065504	1577	12557#
EMT110	066632	2023	12557#
EMT111	066644	2030	12557#
EMT112	066652	2037	12557#
EMT113	066660	2044	12557#
EMT114	066674	2051	12557#
EMT115	066702	2058	12557#
EMT116	066712	2065	12557#
EMT117	066722	2072	12557#
EMT12	065510	1584	12557#
EMT120	066732	2079	12557#
EMT121	066742	2086	12557#
EMT122	066752	2093	12557#
EMT123	066762	2100	12557#

CZRMDCO RM03/2 FCTNL TST 2
CZRMDC.P11 12-DEC-78 08:24

MACY11 30A(1052) 04-JAN-79 11:23 F 7 PAGE 291
CROSS REFERENCE TABLE -- USER SYMBOLS

SEQ 0290

EMT124	066772	2107	12557#
EMT125	067002	2114	12557#
EMT126	067012	2121	12557#
EMT127	067024	2128	12557#
EMT13	065516	1591	12557#
EMT130	067036	2135	12557#
EMT131	067050	2142	12557#
EMT132	067062	2149	12557#
EMT133	067074	2156	12557#
EMT134	067106	2163	12557#
EMT135	067120	2170	12557#
EMT136	067132	2177	12557#
EMT137	067144	2184	12557#
EMT14	065530	1598	12557#
EMT140	067154	2191	12557#
EMT141	067164	2198	12557#
EMT142	067174	2205	12557#
EMT143	067204	2212	12557#
EMT144	067214	2219	12557#
EMT145	067224	2226	12557#
EMT146	067234	2233	12557#
EMT147	067244	2240	12557#
EMT15	065536	1605	12557#
EMT150	067254	2247	12557#
EMT151	067264	2254	12557#
EMT152	067276	2261	12557#
EMT153	067310	2268	12557#
EMT154	067326	2275	12557#
EMT155	067344	2282	12557#
EMT156	067356	2289	12557#
EMT157	067370	2296	12557#
EMT16	065544	1612	12557#
EMT160	067402	2303	12557#
EMT161	067412	2310	12557#
EMT162	067424	2317	12557#
EMT163	067436	12557#	
EMT164	067446	2332	12557#
EMT165	067454	2339	12557#
EMT166	067462	2346	12557#
EMT167	067470	2353	12557#
EMT17	065554	1619	12557#
EMT170	067476	12557#	
EMT171	067506	2367	12557#
EMT172	067516	2374	12557#
EMT173	067526	2381	12557#
EMT174	067536	2388	12557#
EMT175	067550	2395	12557#
EMT176	067556	2402	12557#
EMT177	067564	2409	12557#
EMT2	065434	1528	12557#
EMT20	065564	1626	12557#
EMT200	067576	2416	12557#
EMT201	067610	2423	12557#
EMT202	067622	2430	12557#
EMT203	067634	2437	12557#
EMT204	067646	2444	12557#

CZRMDCO RM03/2 FCTNL TST 2
CZRMDC.P11 12-DEC-78 08:24

MACY11 30A(1052) 04-JAN-79 11:23 ^{6 7}PAGE 292
CROSS REFERENCE TABLE -- USER SYMBOLS

SEQ 0291

EMT205	067664	2451	12557#
EMT206	067674	2458	12557#
EMT207	067704	2465	12557#
EMT21	065574	1633	12557#
EMT210	067716	2472	12557#
EMT211	067724	2479	12557#
EMT212	067740	2486	12557#
EMT213	067754	2493	12557#
EMT214	067764	2500	12557#
EMT215	070004	2507	12557#
EMT216	070016	2514	12557#
EMT217	070026	2521	12557#
EMT22	065604	1640	12557#
EMT220	070036	2528	12557#
EMT221	070046	2535	12557#
EMT222	070056	2542	12557#
EMT223	070066	2549	12557#
EMT224	070076	12557#	
EMT225	070100	12557#	
EMT226	070102	12557#	
EMT227	070104	12557#	
EMT23	065614	1647	12557#
EMT230	070106	12557#	
EMT231	070110	12557#	
EMT232	070112	12557#	
EMT233	070114	12557#	
EMT234	070116	12557#	
EMT235	070120	12557#	
EMT236	070122	12557#	
EMT237	070124	12557#	
EMT24	065624	1654	12557#
EMT240	070126	12557#	
EMT241	070130	12557#	
EMT242	070132	12557#	
EMT243	070134	12557#	
EMT244	070136	12557#	
EMT245	070140	12557#	
EMT246	070142	2682	12557#
EMT247	070152	2689	12557#
EMT25	065634	1661	12557#
EMT250	070164	2696	12557#
EMT251	070200	2703	12557#
EMT252	070206	2710	12557#
EMT253	070214	2717	12557#
EMT254	070232	2724	12557#
EMT255	070242	2731	12557#
EMT256	070252	2738	12557#
EMT257	070262	2745	12557#
EMT26	065644	1668	12557#
EMT260	070274	2752	12557#
EMT261	070306	2759	12557#
EMT262	070326	2766	12557#
EMT263	070336	2773	12557#
EMT264	070346	2780	12557#
EMT265	070366	2787	12557#
EMT266	070406	2794	12557#

CZRMDCO RM03/2 FCTNL TST 2
CZRMDC.P11 12-DEC-78 08:24

MACY11 30A(1052) 04-JAN-79 11:23 H 7
PAGE 293
CROSS REFERENCE TABLE -- USER SYMBOLS

SEQ 0292

EMT267	070420	2802	12557#
EMT27	065654	1675	12557#
EMT270	070436	2809	12557#
EMT271	070452	2817	12557#
EMT272	070470	2824	12557#
EMT273	070506	2831	12557#
EMT274	070524	2839	12557#
EMT275	070542	2847	12557#
EMT276	070554	2855	12557#
EMT277	070570	2864	12557#
EMT3	065442	1535	12557#
EMT30	065664	1682	12557#
EMT300	070606	2872	12557#
EMT301	070626	2880	12557#
EMT302	070650	2887	12557#
EMT303	070662	2894	12557#
EMT304	070674	2901	12557#
EMT305	070706	2908	12557#
EMT306	070720	2915	12557#
EMT307	070730	2922	12557#
EMT31	065674	1689	12557#
EMT310	070750	2929	12557#
EMT311	070762	2936	12557#
EMT312	070774	2943	12557#
EMT313	071006	2950	12557#
EMT314	071026	2957	12557#
EMT315	071040	2964	12557#
EMT316	071052	2971	12557#
EMT317	071064	2978	12557#
EMT32	065704	1696	12557#
EMT320	071074	2985	12557#
EMT321	071104	2992	12557#
EMT322	071114	2999	12557#
EMT323	071122	3006	12557#
EMT324	071132	3013	12557#
EMT325	071144	3020	12557#
EMT326	071156	3027	12557#
EMT327	071174	3034	12557#
EMT33	065714	1703	12557#
EMT330	071206	3041	12557#
EMT331	071216	3048	12557#
EMT332	071230	3055	12557#
EMT333	071242	3062	12557#
EMT334	071260	3069	12557#
EMT335	071276	3076	12557#
EMT336	071316	2325	3083 12557#
EMT337	071326	3090	12557#
EMT34	065724	1710	12557#
EMT340	071336	3097	12557#
EMT341	071350	3104	12557#
EMT342	071356	3111	12557#
EMT343	071370	3118	12557#
EMT344	071402	3125	12557#
EMT345	071414	3132	12557#
EMT346	071424	3139	12557#
EMT347	071440	3146	12557#

MACY11 30A(1052) 04-JAN-79 11:23 PAGE 294
CROSS REFERENCE TABLE -- USER SYMBOLS

17

EMT35	065734	1717	12557#
EMT350	071452	3153	12557#
EMT351	071470	3160	12557#
EMT352	071500	3167	12557#
EMT353	071504	3174	12557#
EMT354	071514	3181	12557#
EMT36	065744	1724	12557#
EMT37	065754	1731	12557#
EMT4	065450	1542	12557#
EMT40	065764	1738	12557#
EMT41	065772	1745	12557#
EMT42	066002	1752	12557#
EMT43	066014	1759	12557#
EMT44	066024	1766	12557#
EMT45	066034	1773	12557#
EMT46	066044	1780	12557#
EMT47	066054	1787	12557#
EMT5	065456	1549	12557#
EMT50	066062	1794	12557#
EMT51	066072	1801	12557#
EMT52	066104	1808	12557#
EMT53	066122	1816	12557#
EMT54	066140	1823	12557#
EMT55	066150	1830	12557#
EMT56	066162	1837	12557#
EMT57	066200	1844	12557#
EMT6	065464	1556	12557#
EMT60	066210	1852	12557#
EMT61	066226	1860	12557#
EMT62	066246	1868	12557#
EMT63	066262	12557#	
EMT64	066264	1882	12557#
EMT65	066304	1889	12557#
EMT66	066324	1896	12557#
EMT67	066336	1903	12557#
EMT7	065472	1563	12557#
EMT70	066350	1910	12557#
EMT71	066360	1917	12557#
EMT72	066370	1924	12557#
EMT73	066406	1932	12557#
EMT74	066424	1939	12557#
EMT75	066434	1946	12557#
EMT76	066454	1953	12557#
EMT77	066464	1960	12557#
ENRGDT	065430	12557#	
EQUALS	063571	12557#	
ERR =	040000	1012#	9272
ERRNMB	033734	7831*	7832*
ERRTYP	033176	7810#	12086
ERRVEC=	000004	930#	3256
		3583	3584*
		8917	8918
		8992	8993
		10154	10155*
		7817	7949#
		7825	7950#
			9274
			7835
			9290
			7847
			9324
			7852
			7944#
			3536
			3537
			3538*
			3539*
			3550*
			3551*
			3555*
			3556*
			3582
			3257*
			3268*
			3538*
			3539*
			3550*
			3551*
			3555*
			3556*
			3582
			3585*
			3589*
			3590*
			3601*
			3602*
			8844
			8845
			8849*
			8850*
			8881*
			8882*
			8922*
			8923*
			8948*
			8949*
			8960
			8961
			8962*
			8963*
			8969*
			8977*
			8978*
			8994*
			8995*
			9019*
			9020*
			9867
			9868
			9871*
			9872*
			9905*
			9906*
			10153
			10156*
			10167*
			10168*
			11975
			11976*
			11978*
			11981*
ERTY00	033742		
ERTY01	033750		

ERTY02 033760 7834 7952#
ERTY03 033767 7840 7954#
ERTY04 033775 7936 7956#
ESRC = 004000 1086#
FER = 000020 1036#
FIND = 000001 11245 11248

3672#	3674#	3709#	3710	3741#	3742	3748#	3749	3755#	3756	3784#	3785	3791#	
3792	3798#	3799	3807#	3810	3840#	3842#	3877#	3878	3909#	3910	3916#	3917	
3923#	3924	3952#	3953	3959#	3960	3966#	3967	3975#	3978	4008#	4010#	4045#	
4046	4078#	4079	4085#	4086	4092#	4093	4122#	4123	4129#	4130	4136#	4137	
4145#	4148	4178#	4180#	4215#	4216	4247#	4248	4254#	4255	4261#	4262	4289#	
4290	4296#	4297	4303#	4304	4338#	4340#	4375#	4376	4407#	4408	4414#	4415	
4421#	4422	4452#	4453	4463#	4464	4526#	4528#	4563#	4564	4595#	4596	4602#	
4603	4609#	4610	4638#	4639	4645#	4646	4652#	4653	4661#	4664	4694#	4696#	
4731#	4732	4763#	4764	4770#	4771	4777#	4778	4805#	4806	4812#	4813	4819#	
4820	4854#	4856#	4891#	4892	4923#	4924	4930#	4931	4937#	4938	4968#	4969	
4979#	4980	5042#	5044#	5079#	5080	5111#	5112	5118#	5119	5125#	5126	5153#	
5154	5160#	5161	5167#	5168	5201#	5203#	5238#	5239	5270#	5271	5277#	5278	
5284#	5285	5312#	5313	5319#	5320	5326#	5327	5360#	5362#	5397#	5398	5429#	
5430	5436#	5437	5443#	5444	5471#	5472	5478#	5479	5485#	5486	5519#	5521#	
5558#	5559	5591#	5592	5598#	5599	5605#	5606	5633#	5634	5640#	5641	5647#	
5648	5684#	5686#	5722#	5723	5729#	5730	5736#	5737	5765#	5766	5772#	5773	
5779#	5780	5788#	5791	5829#	5831#	5867#	5868	5874#	5875	5881#	5882	5910#	
5911	5917#	5918	5924#	5925	5933#	5936	5974#	5976#	6012#	6013	6019#	6020	
6026#	6027	6055#	6056	6062#	6063	6069#	6070	6078#	6081	6107#	6109#	6155#	
6156	6162#	6163	6169#	6170	6191#	6193#	6237#	6238	6244#	6245	6251#	6252	
6286#	6288#	6324#	6325	6331#	6332	6338#	6339	6347#	6349#	6378#	6379	6385#	
6386	6392#	6393	6433#	6435#	6471#	6472	6478#	6479	6485#	6486	6494#	6496#	
6525#	6526	6532#	6533	6539#	6540	6580#	6582#	6618#	6619	6625#	6626	6632#	
6633	6641#	6643#	6672#	6673	6679#	6680	6686#	6687	6726#	6728#	6776#	6777	
6783#	6784	6790#	6791	6838#	6839	6845#	6846	6852#	6853	6861#	6864	6901#	
6903#	6952#	6953	6966#	6967	6975#	6977#	7006#	7007	7020#	7021	7054#	7056#	
7092#	7093	7099#	7100	7106#	7107	7136#	7137	7147#	7148	7158#	7159	7192#	
7194#	7230#	7231	7237#	7238	7244#	7245	7274#	7275	7285#	7286	7296#	7297	
7331#	7333#	7378#	7379	7385#	7386	7392#	7393	7421#	7422	7436#	7437	7451#	
7452	7471#	7472	7489#	7490	7516#	7518#	7567#	7569#	7614#	7615	7621#	7622	
7628#	7629	7657#	7658	7668#	7669	7686#	7687	7711#	7713#				
1111#	3830	3998	4168	4328	4516	4684	4844	5032	5191	5350	5509	5674	
5819	5964	6118	6202	6423	6570	6716	6891	7116	7182	7321	7430	7510	
7557	7706	8205	8634	8636	8707	9964	11040						
FMT16 = 010000	9318	12557#											
FNCDTB 064672	954#	10751	11195										
FNCMSK= 000077	952#	9217											
F0 = 000002	951#	9217											
F1 = 000004	950#	9217	9791										
F2 = 000010	949#	9217											
F3 = 000020	948#	9217											
F4 = 000040													
GENBUF 036620	3668	3836	4004	4174	4334	4522	4690	4850	5038	5197	5356	5515	5680
	5825	5970	6282	6429	6576	6722	6897	7050	7188	7327	7514	7563	7710
	8618#												
GET 037516	3629	3701	3733	3776	3869	3901	3944	4037	4070	4114	4207	4239	4281
	4367	4399	4444	4484	4555	4587	4630	4723	4755	4797	4883	4915	4960
	4999	5071	5103	5145	5230	5262	5304	5389	5421	5463	5550	5583	5625
	5714	5757	5859	5902	6004	6047	6147	6229	6316	6370	6463	6517	6610
	6664	6768	6830	6944	6998	7084	7128	7222	7266	7370	7413	7606	7649
	8028	8052	8079	8102	8128	8232	8265	8301	8335	8835#			

SEQ 0295

[illegible]

SEQ 0296

[illegible]

RMASO	=	001416	1460#												
RMBA	=	000004	1245#	3544*	3545	3721	3889	4058	4227	4387	4575	4743	4903	5091	5250
			5409	5571	5699	5844	5989	6127	6211	6301	6448	6595	6753	6818	6929
			7069	7207	7355	7528	7591	7722	8213						
RMBAE	=	000050	1248#												
RMBAI		001334	1428#	4478	4993	9718	9720	10214	12557						
RMBAO		001404	1455#	3664*	3766*	3832*	3934*	4000*	4104*	4170*	4330*	4518*	4620*	4686*	4846*
			5034*	5193*	5352*	5511*	5676*	5747*	5821*	5892*	5966*	6037*	6120*	6204*	6278*
			6357*	6425*	6504*	6572*	6651*	6718*	6815*	6872*	6893*	6985*	7046*	7118*	7184*
			7256*	7323*	7403*	7512*	7559*	7639*	7708*	8206*	8624	8711	9714	9717	
RMCC	=	000036	1170#												
RMCC1		001366	1441#												
RMCCO		001436	1468#												
RMCS1	=	000000	1159#	1243#	3323	3541*	3587	3686	3722	3854	3890	4022	4059	4192	4228
			4352	4388	4540	4576	4708	4744	4868	4904	5056	5092	5215	5251	5374
			5410	5535	5572	5700	5845	5990	6129	6212	6302	6449	6596	6740	6754
			6803	6819	6930	7070	7208	7356	7529	7592	7724	8063	8112	8214	8852
			8925	9004	9878										
RMCS11		001330	1426#	9091	9093	9095	9112	9114	9117	9128	9132	9134	9146	9148	9150
			9239	9241	9252	9295	9701	10201	10750	10883	10885	10887	10906	12557	
RMCS10		001400	1453#	3665*	3681*	3718*	3765*	3833*	3849*	3886*	3933*	4001*	4017*	4055*	4103*
			4171*	4187*	4224*	4271*	4331*	4347*	4384*	4434*	4519*	4535*	4572*	4619*	4687*
			4703*	4740*	4787*	4847*	4863*	4900*	4950*	5035*	5051*	5088*	5135*	5194*	5210*
			5247*	5294*	5353*	5369*	5406*	5453*	5512*	5530*	5568*	5615*	5677*	5693*	5746*
			5822*	5838*	5891*	5967*	5983*	6036*	6121*	6205*	6279*	6295*	6356*	6426*	6442*
			6503*	6573*	6589*	6650*	6719*	6735*	6750*	6798*	6814*	6894*	6921*	6984*	7047*
			7063*	7117*	7185*	7201*	7255*	7324*	7349*	7402*	7513*	7522*	7560*	7585*	7638*
			7709*	7717*	8062*	8111*	8223*	8256*	8290*	8324*	8470	8628	9216	9732	11174
			11194												
RMCS2	=	000010	1246#	3318*	3319*	3320	3546*	3547	3588	8851	8924	9877*	9879	10158*	10160*
RMCS21		001340	1430#	4461	4469	4471	4977	4985	4987	9073	9098	9100	9101	9287	9358
			9459	9502	9517	9532	9643	9715	10223	10920	10922	10924	11292	11294	11296
			11346	11348	11350	12557									
RMCS20		001410	1457#												
RMCS3	=	000052	1249#												
RMDA	=	000006	1160#	3683	3851	4019	4189	4349	4537	4705	4865	5053	5212	5371	5532
			5695	5840	5985	6124	6207	6297	6444	6591	6737	6800	6925	7065	7203
			7351	7524	7587	7719	8209								
RMDA1		001336	1429#	9814	12557										
RMDAO		001406	1456#	3661*	3829*	3997*	4167*	4327*	4515*	4683*	4843*	5031*	5190*	5349*	5508*
			5673*	5678	5798*	5799	5818*	5823	5943*	5944	5963*	6117*	6201*	6275*	6280
			6402*	6403	6422*	6427	6549*	6550	6569*	6715*	6720	6890*	6895	7043*	7181*
			7320*	7556*	8202*	8383*	8384	8386	8404	8412*	8464	8591*	8627	9740	9741
			9960	9962	9966	11034	11036	11038							
RMDB	=	000022	1247#	3548*	3549	4482	4997	8800							
RMDB1		001352	1435#	4489	5004										
RMDBO		001422	1462#												
RMDC	=	000034	1169#	3684	3852	4020	4190	4350	4538	4706	4866	5054	5213	5372	5533
			5696	5841	5986	6125	6208	6298	6445	6592	6738	6801	6926	7066	7204
			7352	7525	7588	7720	8210								
RMDC1		001364	1440#	9826	12557										
RMDCO		001434	1467#	3660*	3828*	3996*	4166*	4326*	4514*	4682*	4842*	5030*	5189*	5348*	5507*
			5528	5529*	5567*	5672*	5817*	5962*	5968	6088*	6089	6116*	6200*	6274*	6421*
			6568*	6574	6695*	6696	6714*	6889*	7042*	7180*	7319*	7555*	8203*	8463	8590*
			8626	9742	9957	11031									
RMDS	=	000012	1161#	8050	8100										

1431#	8059	8109	8254	8287	8361	9130	9226	9228	9273	9290	9324	9328
9384	9411	9546	9771	9996	10051	10060	10067	10071	10073	10082	10086	10088
10097	10099	10101	10111	10115	10117	10296	10337	10339	10341	10351	10353	10355
10515	10553	10591	10600	10604	10606	10616	10620	10621	10632	10634	10636	10648
10650	10652	10663	10667	10669	10762	10945	10947	10976	11106	11172	11307	11309
11311	11358	11365	11369	11371	11382	11386	11388	11398	11402	11404	11457	11463
11467	11469	11479	11483	11484*	11485	11495	11499	11501	12557			

1458#												
1166#	3626											
1437#	3628*	3633	3635	3637	3639	12557						
1464#												
1173#												
1444#	8712	12557										
1471#												
1174#	8795											
1445#	8733	8794	10264	10828	12557							
1472#												
1162#	9169											
1432#	7145	7153	7154	7283	7291	7292	7434	7442	7443	7469	7477	7478
7666	7674	7675	8368	8701	8703	9161	9176	9178	9268	9344	9371	9414
9429	9472	9549	9575	9590	9605	9658	9677	9680	9768	9783	9798	9809
9937	9944	9971	10045	10048	10069	10241	10365	10369	10371	10372	10383	10385
10386	10397	10399	10400	10411	10413	10414	10425	10427	10428	10471	10476	10480
10482	10492	10494	10496	10508	10510	10512	10525	10527	10529	10602	10679	10683
10685	10687	10697	10699	10701	10711	10715	10717	10775	10897	10901	10903	10940
10942	10944	10985	10988	10990	10992	11002	11004	11006	11016	11018	11020	11043
11133	11136	11140	11142	11151	11153	11155	11165	11167	11168	11202	11206	11208
11210	11219	11221	11223	11232	11234	11236	11245	11247	11249	11267	11269	11271
11277	11333	11335	11337	11384	11465	11576	12557					

1459#	9165											
1172#												
1443#	6959	6961	6962	7013	7015	7016	7449	7458	7459	8370	8375	9163
9270	9388	9444	9620	9939	9990	9993	10004	10032	10035	10084	10113	10286
10478	10539	10546	10548	10550	10563	10565	10567	10577	10579	10581	10618	10665
10713	10837	10899	10968	10971	10973	11057	11061	11086	11090	11092	11094	11104
11108	11110	11120	11122	11124	11138	11320	11322	11324	11367	11400	11481	11497
11511	11517	11519	11521	11531	11533	11535	11579	12557				

1470#												
1164#												
1434#	12557											
1461#												
1165#	6911	6924										
1436#	10251	10803	12557									
1463#	6910*	6922*										
1171#												
1442#	10273	10815	12557									
1469#												
1168#	3685	3853	4021	4191	4351	4539	4707	4867	5055	5214	5373	5534
5697	5842	5987	6126	6209	6299	6446	6593	6739	6802	6927	7067	7205

1439#	8705	8707	9565	9675	11198	11274	12557						
1466#	3662*	3830*	3998*	4168*	4328*	4516*	4684*	4844*	5032*	5191*	5350*	5509*	
5674*	5819*	5964*	6118*	6202*	6276*	6423*	6570*	6716*	6869	6871*	6891*	7044*	
7116*	7182*	7251*	7321*	7510*	7557*	7706*	8205*	8631*	8964*	11040	12557		

[illegible]

1438#	12557											
1465#												
1244#	3542*	3543	3720	3888	4057	4226	4386	4574	4742	4902	5090	5249
5408	5570	5698	5843	5988	6128	6210	6300	6447	6594	6752	6817	6928
7068	7206	7354	7527	7590	7723	8211						
1427#	8750	9699	9711	9729	9793	12557						
1454#	3663*	3831*	3999*	4054*	4102*	4169*	4329*	4517*	4685*	4845*	5033*	5192*
5351*	5510*	5675*	5820*	5965*	6119*	6203*	6277*	6424*	6571*	6717*	6892*	7045*
7183*	7322*	7511*	7558*	7707*	8204*	8466	8625	8751	9712	9730		

1183#	10274	10816										
1123#	10274	10816										
1124#	10274	10816										
965#												
1007#												
7811	12454#											
1002#												
998#												
1001#												
1000#												
999#												
1195#	9116	9133	9149	10202								
12557#												
1058#												
1056#												
1055#												
1054#												
1053#												
1052#												
971#	9292	9693										
3755	3798	3923	3966	4092	4136	4261	4303	4421	4609	4652	4777	4819
4937	5125	5167	5284	5326	5443	5485	5605	5647	5736	5779	5881	5924
6026	6069	6169	6251	6338	6392	6485	6539	6632	6686	6790	6852	6966

[illegible]

1106	3633	3637	3641									
835	3238	3531	3571	3615	3653	3821	3989	4159	4319	4507	4675	4835
5023	5182	5341	5500	5665	5810	5955	6100	6185	6267	6414	6561	6707
6882	7035	7173	7311	7547								

[illegible]

CZRMDCO RM03/2 FCTNL TST 2
CZRMDC.P11 12-DEC-78 08:24

MACY11 30A(1052) 04-JAN-79 11:23 PAGE 302
CROSS REFERENCE TABLE -- USER SYMBOLS

SEQ 0301

STSH3	101237	12557#												
STSH4	101277	12557#												
SWR	001154	1334#	3236	3258*	3260	3266*	3273*	3287	3508	7812	11970	11984	11987	12002
		12059	12077	12084	12096	12100	12157	12196	12251*	12468	12481*			
SWREG	000176	1263#	3266	3287	3508	12157	12196	12219						
SW0	= 000001	899#												
SW00	= 000001	889#	899											
SW01	= 000002	888#	898											
SW02	= 000004	887#	897											
SW03	= 000010	886#	896											
SW04	= 000020	885#	895											
SW05	= 000040	884#	894											
SW06	= 000100	883#	893											
SW07	= 000200	882#	892											
SW08	= 000400	881#	891											
SW09	= 001000	880#	890											
SW1	= 000002	898#												
SW10	= 002000	879#												
SW11	= 004000	878#												
SW12	= 010000	877#												
SW13	= 020000	876#	7812											
SW14	= 040000	875#												
SW15	= 100000	874#												
SW2	= 000004	897#												
SW3	= 000010	896#												
SW4	= 000020	895#												
SW5	= 000040	894#												
SW6	= 000100	893#												
SW7	= 000200	892#												
SW8	= 000400	891#												
SW9	= 001000	890#												
TADMSK	= 003400	1006#												
TAG	= 020000	1125#												
TAGADR	= 001114	1306#	1313											
TAP	= 040000	1102#												
TA1	= 000400	997#												
TA2	= 001000	996#												
TA4	= 002000	995#												
TBITVE	= 000014	932#												
TIMOUT	040326	3697	3732	3775	3865	3900	3943	4033	4069	4113	4203	4238	4280	4363
		4398	4443	4551	4586	4629	4719	4754	4796	4879	4914	4959	5067	5102
		5144	5226	5261	5303	5385	5420	5462	5546	5582	5624	5713	5756	5858
		5901	6003	6046	6146	6228	6315	6369	6462	6516	6609	6663	6767	6829
		6943	6997	7083	7127	7221	7265	7369	7412	7537	7605	7648	7732	8122
		8300	8334	8988#										
TKVEC	= 000060	939#	12134*	12135*										
TPVEC	= 000064	940#												
TRAPVE	= 000034	938#	3244*	3245*										
TRE	= 040000	1196#	9116	9133	9149	9294	9296	9701						
TRTVEC	= 000014	933#												
TST	= 010000	1126#	10275	10817										
TSTNMB	033732	7823*	7824*	7826	7943#									
TSTPRP	034000	3672	3840	4008	4178	4338	4526	4694	4854	5042	5201	5360	5519	5684
		5829	5974	6107	6191	6286	6347	6433	6494	6580	6641	6726	6901	6975
		7054	7192	7331	7516	7567	7711	7991#						
TSTQUE	001450	1478#	3480	3481*	3521	3533	3573	3617	3655	3823	3991	4161	4321	4509

		4677	4837	5025	5184	5343	5502	5607	5812	5957	6102	6187	6269	6416
		6563	6709	6884	7037	7175	7313	7549	7739	7741*	7745*	9874	10159	10226
		10787												
TST1	007162	3526#	12029											
TST10	012716	4316#	12036											
TST11	013636	4504#	12037											
TST12	014436	4672#	12038											
TST13	015212	4832#	12039											
TST14	016130	5020#	12040											
TST15	016704	5179#	12041											
TST16	017460	5338#	12042											
TST17	020234	5497#	12043											
TST2	007360	3568#	12030											
TST20	021036	5662#	12044											
TST21	021562	5807#	12045											
TST22	022306	5952#	12046											
TST23	023030	6097#	12047											
TST24	023326	6182#	12048											
TST25	023624	6264#	12049											
TST26	024352	6411#	12050											
TST27	025100	6558#	12051											
TST3	007544	3612#	12031											
TST30	025626	6704#	12052											
TST31	026520	6879#	12053											
TST32	027326	7032#	12054											
TST33	030050	7170#	12055											
TST34	030572	7308#	12056											
TST35	031750	7544#	12057											
TST4	007726	3650#	12032											
TST5	010526	3818#	12033											
TST6	011326	3986#	12034											
TST7	012142	4156#	12035											
TYPBN =	104406	7933	12446#											
TYPDS =	104405	7773	7780	7927	12445#									
TYPE =	104401	3281	3301	3329	3351	3354	3360	3365	3368	3371	3375	3378	3386	3389
		3395	3400	3405	3411	3421	3426	3432	3445	3446	3449	3455	3458	3465
		7767	7774	7781	7816	7817	7825	7834	7840	7849	7887	7893	7897	7910
		7916	7918	7936	7938	11650	11722	11788	11857	11917	12079	12087	12151	12163
		12217	12218	12221	12232	12242	12253	12272	12320	12326	12331	12335	12340	12341
		12343	12346	12350	12441#	12490								
		3388	7930	12220	12442#									
TYPOC =	104402													
TYPOM =	104404	12444#												
TYPOS =	104403	3331	3402	342										

[illegible]

CZRMDCO RM03/2 FCTNL TST 2
CZRMDC.P11 12-DEC-78 08:24

MACY11 30A(1052) 04-JAN-79 11:23 PAGE 305
CROSS REFERENCE TABLE -- USER SYMBOLS

SEQ 0304

SCNTLG	062574	12217	12362#											
SCNTLU	062567	12242	12335	12361#										
SCPUOP	001250	1378#												
SCRLF	001217	1353#	7781	7816	7849	7887	7897	7910	7918	7938	11918	11953	12087	12112
		12253	12340	12360										
SDBLK	060036	11754	11788	11796#										
SDDW0	001306	1408#												
SDDW1	001310	1409#												
SDDW2	001312	1410#												
SDDW3	001314	1411#												
SDDW4	001316	1412#												
SDDW5	001320	1413#												
SDDW6	001322	1414#												
SDDW7	001324	1415#												
SDEVCT	001232	1369#												
SDEVH	001300	1405#	3313*	3314*	3326*	3444*	3453*	3471*	3472	3479				
SDOAGN	033166	7763	7784	7790#										
SDTBL	060026	11757	11792#											
SENDAD	033156	1272	3279	7786#	12107									
SENDCT	033022	3248	7765#											
SENULL	033172	7793#												
SENV	001242	1374#	3285	3306	3506	11897	12089	12511	12535					
SENVH	001243	1375#	3271	3311	11899	11904	12513							
SEOP	032766	3561	7755#	11653										
SEOPCT	033014	3248*	7762#	7766										
SEOSP	032732	3604	3644	7737#										
SERFLG	001117	1317#	11958	11998	12000	12006*	12028	12074*	12112					
SERMAX	001131	1323#	3251*	12000	12023*	12028								
SERROR	061166	3242	12072#											
SERRPC	001132	1324#	7841	12081*	12082*	12083	12112							
SERRTB	001564	1517#	7856											
SERTTL	001126	1321#	7778	7782*	12080*	12112								
SESCAP	001210	1350#	3250*	12022*	12103	12105	12112							
SETABL	001242	1373#												
SETEND	001326	1305	1416#											
SFATAL	001224	1366#	12539*											
SFFLG	063456	12502*	12505*	12533	12542*	12550#								
SFILLC	001172	1342#	11922	11953										
SFILLS	001171	1341#	11953											
SGDADR	001134	1325#	4477*	4492	4992*	5007	8760*	12557						
SGDDAT	001140	1327#	4469*	4470*	4490*	4491*	4496	4985*	4986*	5005*	5006*	5012	6962*	6963*
		7016*	7017*	7154*	7155*	7292*	7293*	7443*	7444*	7459*	7460*	7478*	7479*	7675*
		7676*	8758*	9075*	9076*	9077	9093*	9094*	9100*	9102*	9114*	9115*	9116*	9132*
		9133*	9148*	9149*	9176*	9177*	9230*	9243*	9254*	9255	9267*	9272*	9275	9286*
		9294*	9297	9323*	9326*	9327*	9330	9342*	9343*	9346	9353*	9705*	9711*	9712*
		9713*	9714*	9717*	9718	9765*	9770*	9773	9782*	9795*	9800	9811*	9812*	9813*
		9815	9824*	9825*	9827	9943*	9955*	9968*	9973	9992*	10006*	10007*	10034*	10047*
		10071*	10072*	10086*	10099*	10100*	10115*	10116*	10203*	10204	10213*	10229*	10231	10240*
		10253*	10254	10263*	10275*	10276	10285*	10298*	10299	10339*	10340*	10353*	10354*	10372*
		10373*	10386*	10387*	10400*	10401*	10414*	10415*	10428*	10429*	10480*	10481*	10494*	10495*
		10510*	10511*	10527*	10528*	10548*	10549*	10565*	10566*	10579*	10580*	10604*	10605*	10620*
		10622*	10634*	10635*	10650*	10651*	10667*	10668*	10685*	10686*	10699*	10700*	10715*	10716*
		10752*	10753	10764*	10765	10774*	10805*	10806	10817*	10818	10826*	10885*	10886*	10901*
		10902*	10922*	10923*	10942*	10943*	10971*	10972*	10990*	10991*	11004*	11005*	11018*	11019*
		11029*	11042*	11045	11059*	11060*	11092*	11093*	11108*	11109*	11122*	11123*	11140*	11141*
		11153*	11154*	11168*	11169*	11177*	11208*	11209*	11221*	11222*	11234*	11235*	11247*	11248*

		11269*	11270*	11294*	11295*	11309*	11310*	11322*	11323*	11335*	11336*	11348*	11349*	11369*
		11370*	11386*	11387*	11402*	11403*	11467*	11468*	11483*	11499*	11500*	11519*	11520*	11533*
		11534*	11592*	11607*	12557									
\$GET42	033146	7783#												
\$GTSWR	061754	12218#	12448											
\$HD =	000001	811	812											
\$HIBTS	001100	1300#												
\$HIOCT	062724	12400*	12405#											
\$ICNT	001120	1318#	12013*	12014	12016*	12027								
\$ILLUP	063174	12460	12476	12493#										
\$INTAG	001151	1332#	12215*	12234	12254	12367								
\$ITEMB	001130	1322#	7832	12083*	12091	12112								
\$LF	001220	1354#	11953	12112	12350	12360								
\$LFLG	063455	12543*	12549#											
\$LPADR	001122	1319#	3252*	3528*	11995*	12004*	12020*	12025	12027					
\$LPERR	001124	1320#	3253*	3529*	12004	12021*	12027	12102						
\$MADR1	001254	1391#												
\$MADR2	001260	1395#												
\$MADR3	001264	1398#												
\$MADR4	001270	1401#												
\$MAIL	001222	1301	1305	1364#	3270	3285	3506	3534	3574	3618	3656	3824	3992	4162
		4322	4510	4678	4838	5026	5185	5344	5503	5668	5813	5958	6103	6188
		6270	6417	6564	6710	6885	7038	7176	7314	7550	11897	12019	12089	
\$MAMS1	001252	1385#												
\$MAMS2	001256	1393#												
\$MAMS3	001262	1396#												
\$MAMS4	001266	1399#												
\$MBADR	001102	1301#												
\$MFLG	063454	12503*	12509	12544*	12548#									
\$MNEW	062612	12221	12365#											
\$MSGAD	001236	1371#	12519*	12522										
\$MSGLG	001240	1372#	12524*											
\$MSGTY	001222	1365#	12517	12525*	12537	12541*								
\$MSWR	062601	12218	12363#											
\$MTYP1	001253	1386#												
\$MTYP2	001257	1394#												
\$MTYP3	001263	1397#												
\$MTYP4	001267	1400#												
\$MXCNT	061072	12017	12027#											
\$NULL	001170	1340#	11924	11953										
\$NWTST=	000001	3523#	3525	3564#	3566	3608#	3610	3647#	3815#	3983#	4153#	4313#	4501#	4669#
		4829#	5017#	5176#	5335#	5494#	5659#	5804#	5949#	6094#	6179#	6261#	6408#	6555#

```

$RDOCT 062624
$RDSZ = 000010
$RESRE 057510
$RTNAD 033170
$RZA = ***** U
$SAVRE 057452
$SAVR6 063200
$SCOPE 060556
$SETUP= 000137

```

```

$STUP = 177777
$SVLAD 061022
$SVPC = 000200
$SWR = 167400

```

```
SSWREG 001244
SSWRMK= 000000
SSW08T 061074
STESTN 001226
```

STIMES	001206
STKB	001162
STKCNT	061366
STKINT	061376
STKQEN=	061375
STKQIN	061370
STKQOU	061372
STKQSR	061374
STKS	001160
STKSRV	061446
STMPO	001174

STMP1 001176

```
STMP2    001200
STMP3    001202
STMP4    001204
STN      = 000036
```

STPB 001166
STPFLG 001173

12378#	12453											
12301#												
11694#	12455											
7792#												
12456												
11678#	12454											
12469*	12477	12478*	12479*	12495#								
3240	11967#											
1254#	3239	3240	3242	3244	3246	3248	3249	3250	3252	3279	3282	3503
7757	11968	12073	12099	12107	12155	12160	12161	12191	12367			
1254#												
11979	12018#											
1270#	1275											
800#	811	816	817	818	819	820	821	822	823	1349	1350	1351
3249	3250	3252	3253	3534	3574	3618	3656	3824	3992	4162	4322	4510
4678	4838	5026	5185	5344	5503	5668	5813	5958	6103	6188	6270	6417
6564	6710	6885	7038	7176	7314	7550	7752	7758	7785	7791	7793	11959
11960	11961	11962	11963	11970	11982	11984	11985	11998	11999	12000	12007	12008
12009	12021	12024	12027	12064	12065	12066	12067	12068	12077	12084	12096	12100
12112	12492											
1376#	3273											
823	824	11963	11964	11988								
11994	12028#											
1367#	3534*	3574*	3618*	3656*	3824*	3992*	4162*	4322*	4510*	4678*	4838*	5026*
5185*	5344*	5503*	5668*	5813*	5958*	6103*	6188*	6270*	6417*	6564*	6710*	6885*
7038*	7176*	7314*	7550*	7824	12019*							
1349#	3249*	7758*	12007*	12014	12017*	12027						
1337#	12115	12136	12147	12172	12200	12227						
12116#	12131*	12161	12178*	12292	12294*							
3343	3516	12131#	12152	12213								
12120#	12186	12297										
12117#	12132*	12133	12184*	12185*	12186	12188*						
12118#	12133*	12295	12296*	12297	12299*							
12119#	12132	12188	12299									
1336#	12115	12137*	12168*	12170	12176*	12198	12214*	12224	12236*	12256*		
12134	12147#											
1344#	3588*	3591	3666*	3834*	4002*	4172*	4332*	4520*	4688*	4848*	5036*	5195*
5354*	5513*	5678*	5823*	5968*	6280*	6427*	6574*	6720*	6895*	7048*	7186*	7325*
7461*	7480*	7561*	7677*	8655	8762*	8851*	8924*	9879*	9880	12557		
1345#	3353*	3354	3355	3358	3367*	3368	3369	3377*	3378	3381	3391*	3393
3397	3398*	3399*	3401	3407*	3409	3413	3414*	3415*	3416*	3417*	3418*	3419*
3420*	3422	3428*	3430	3435*	3436*	3437*	3438*	3439*	3440	3448*	3449	3450
3457*	3458	3459	3461	3463	3467	3587*	3595	3641*	3667*	3835*	4003*	4173*

STPS	001164	1338#	11940	11953															
STRAP	062726	3244	12414#																
STRAP2	062766	12429#	12440																
STRP =	000016	12433#	12442#	12443#	12444#	12445#	12446#	12447#	12448	12449#	12450	12451#	12452#	12453#					
		12454#	12455#	12456#															
STRPAD	063000	12423	12440#																
STSTM	001104	1302#																	
STSTM#	001116	1316#	7757*	11958	11991*	12018*	12019	12024	12028	12076	12112								
STTYIN	062552	12310	12311	12323	12341	12355	12359#												
STYPBN	057546	11715#	12446																
STYPDS	057622	11742#	12445																
STYPE	060274	11891#	12433	12441	12530														
STYPEC	060506	11921	11928	11935	11940#	11941	12258												
STYPEX	060554	11946	11948	11951#															
STYPOC	060072	11827#	12442																
STYPON	060106	11826	11829#	12444															
STYPOS	060046	11822#	12443																
SUNIT	001234	1370#	3521*	7818	9075														
SUNITM	001110	1304#																	
SUSWR	001246	1377#																	
SVECT1	001272	1402#	3398	3413*	3414	3440*													
SVECT2	001274	1403#																	
SXTSTR	060574	11973#																	
SSGET4=	000000	7785#																	
SSSW08=	000036	12028#	12029	12030#	12031#	12032#	12033#	12034#	12035#	12036#	12037#	12038#	12039#	12040#					
		12041#	12042#	12043#	12044#	12045#	12046#	12047#	12048#	12049#	12050#	12051#	12052#	12053#					
		12054#	12055#	12056#	12057#	12058#													
		11823*	11827*	11837	11872#														
		11970	12086																
		1257#	1261#	1270	1271#	1273#	1275#	1280#	1283#	1289	1290#	1292#	1294#	1306					
		1313#	1355	1478#	1494#	1499#	3237	3252	3253	7770#	7793	7794#	11648	11660#					
		11796#	11953	12027	12028	12112	12115	12119#	12120	12121#	12359#	12360	12367#	12472					
		12494	12551#	12557#															
		12503	12506																
		1289#	1294																

.SASTA= ***** U
.SX = 001100

. ABS. 106117 000

ERRORS DETECTED: 0

DSKZ:CZRMDC,DSKZ:CZRMDC.SEQ/SOL/CRF/DOC/NL:MC:MD:CND:TOC/LI:ME=DSKZ:CZRMDC.P11
RUN-TIME: 70 66 3 SECONDS
RUN-TIME RATIO: 633/140=4.5
(CORE USED: 33K (65 PAGES))

DOCUMENT PAGES: 307