d	A	g	Ħ	t	a	ı	

The RZ26B Fixed Disk Drive in the VAXstation 4000

EK-RZ26B-IN. A01

October 1992

This documentation package contains the following information for the RZ26B fixed disk drive:

- Illustration of the RZ26B drive
- SCSI ID settings
- Verifying the installation
- Drive specifications

Your VAXstation 4000 Options Installation Guide explains how to install disk drives in your system. You will need this document to set the correct SCSI address for the RZ26B disk.

Insert this document into your *VAXstation 4000 Options Installation Guide* (in the fixed disk drives chapter) for future reference.

	Compatibility	
The RZ26B Model 90.	can be installed <i>only</i> in the Model 60 and	

© Digital Equipment Corporation 1992. All rights reserved. The following are trademarks of Digital Equipment Corporation: TURBOchannel, VAXstation, and the Digital logo.

S2109

The RZ26B Fixed Disk Drive

Preparing Your System

Use the instructions in the VAXstation 4000 Options Installation Guide to:

- · Shut down your system
- Remove the system unit cover
- Prevent static discharge by touching the "Touch Me First" label on the power supply

Setting the SCSI ID


Before you begin installation of your RZ26B drive, enter the SHOW CONFIG command to find the current SCSI IDs of your devices. In the following example, SCSI IDs 0 and 5 are being used:

>>>SHOW CONFIG

DEVNBR	DEVNAM	INFO
10	SCSI	OK 0RZ24 5TZK10

Make a note of the SCSI IDs of your devices.

Refer to Figure 1 to choose a SCSI setting for your drive. Digital recommends SCSI settings 0, 1, 2, and 3 for fixed disk drives. Each device must have a unique SCSI ID. Never set two or more devices to the same SCSI ID; the system will not be able to communicate with the devices.






Figure 1 SCSI Settings on the RZ26B Fixed Disk Drive

Installing the Drive

Follow the instructions in the VAXstation 4000 Options Installation Guide to install this drive.

The RZ26B Fixed Disk Drive

Verifying the Installation

Enter the SHOW CONFIG command to verify that your installation was successful.

>>>SHOW	CONFIG			
DEVNBR	DEVNAM	INFO		
10	SCSI	OK 0RZ24	2RZ26B	 5TZK10

In this example the RZ26B drive was set to SCSI ID number 2.

RZ26B Fixed Disk Drive Specifications

Capacity

Table 1 provides the capacity specifications for the RZ26B fixed disk drive.

Table 1 RZ26B Fixed Disk Drive Storage Specifications

	- -	
Formatted Storage Capaci	ty	
Per drive	1.05 GB	
Per surface	80.9 MB	
Bytes per block	512	
Blocks per track	56 to 96	
Blocks per drive	50,860	
Spare cylinders	69	
Buffer size	256K	

RZ26B Fixed Disk Drive Specifications

Performance

Table 2 provides performance specifications for the RZ26B fixed disk drive.

Table 2 RZ26B Performance Specifications

Performance Variable	Operating Conditions
Data transfer rate to/from media	2.6 MB/sec to 4 MB/sec
Data transfer rate to/from buffer	2.5 MB (asynchronous) to 5 MB (synchronous)
Seek time track to track	2.5 msec
Seek time average	10.5 msec
Seek time maximum (full stroke)	22 msec
Average latency	5.56 msec
Rotational speed	5400 rpm
Start time	14 ms (nominal) 20 MS (maximum)
Stop time	20 ms (maximum)
Interleave	1:1

RZ26B Fixed Disk Drive Specifications

Operating Conditions

Table 3 provides the operating conditions for the RZ26B fixed disk drive.

Table 3 RZ26B Drive Operating Conditions

Environmental Variable	Operating Conditions		
Ambient temperature	5°C to 50°C (41°F to 122°F)		
Relative humidity	8% to 80%		
Altitude	-1000 ft to 10,000 ft above sea level		
Maximum wet bulb	28°C		
Heat dissipation	12.1 W (on idle)		
Temperature gradient	12° C per hour		

Nonoperating Conditions

Table 4 provides the nonoperating conditions for the RZ26B fixed disk drive.

Table 4 RZ26B Drive Nonoperating Conditions

Environmental Variable	Nonoperating Conditions	
Ambient temperature	-40°C to 65°C (-40°F to 149°F)	
Relative humidity	5% to 90%	
Altitude	-305 M (-1000 ft) to 15,240 M (50,000 ft) above sea level	
Maximum wet bulb	28°C	
Temperature gradient	30° C per hour	