

IDENTIFICATION

Product Code: MAINDEC-12-D9CA-D

Product Name: PDP-12 Operating Procedure

Date Created: December 1, 1969

Author: Harold Long

1. ABSTRACT

Due to console switch and control differences between Family-of-Eight and PDP-12 computers, the following generalized instructions are given to insure proper loading and starting of punched paper tape programs supplied by DEC for the PDP-12.

2. REQUIREMENTS

2.1 Equipment

- a) Any PDP-12 computer with necessary options for each particular program.
- b) An ASR-33 teletype or equivalent.

2.2 Preliminary Programs

- a) RIM - Formatted tapes require only that the rim loader be in core and operating.
- b) BINARY - Formatted tapes require that the binary loader be in core and operating.

3. LOADING PROCEDURES

3.1 Rim Loader

The Rim Loader is a minimum-logic program designed to load basic processor and memory diagnostics. It is toggled in from the console in the following manner:

- a) Set the MODE switch to 8 MODE.
- b) Set the IF switches to the desired memory bank (usually 000).
- c) Depress I/O preset.
- d) Place the address of the first instruction in the left switches (7756).
- e) Place the first instruction in the right switches (6032).
- f) Depress FILL; this loads the instruction at the specified address, and also places that address in the MA register.
- g) Depress FILL STEP; this reloads the instruction at the specified address, and increments the MA.
- h) Place the second, and succeeding, instructions in the right switches, depressing fill step after each instruction.
- i) When completed, the MA should equal 7776.

RIM LOADER
(LOW SPEED)

ADDR	CONT
7756	6032
7757	6031
7760	5357
7761	6036
7762	7106
7763	7006
7764	7510
7765	5357
7766	7006
7767	6031
7770	5367
7771	6034
7772	7420
7773	3776
7774	3376
7775	5356

3.2 Binary Loader

The Binary Loader is a rim-formatted program designed to increase loading speed by 50% over the rim loader. It is loaded using the rim loader in the following manner.

- a) Set the MODE switch to 8 mode.
- b) Set the IF switches to the desired memory bank in which the rim loader resides (usually 000).
- c) Depress I/O preset.
- d) Set the teletype reader switch to free.
- e) Open the teletype reader and insert the program tape such that the directional arrows are visible and pointing in the direction of tape travel with the leader punches over the sensing fingers.
- f) Close the reader and set the reader switch to start.
- g) Get the teletype front panel switch to on line.
- h) Set the left switches to 7756.
- i) Insure that the computer is set to 8 mode.
- j) Depress start LS.
- k) The program tape will read in; when the data transfer is completed, as indicated by the trailer code passing over the reader, momentarily depress stop.
- l) The Binary Loader is now in core.

3.3 Rim-Formatted Paper Tapes

The procedure is identical to loading the Binary Loader, section 3.2.