

MAINDEC-11-D3B-

NEW NUMBER = DZTCB

TC2 = TC11 Test 2

## ABSTRACT

TC2 = TC11 Test 2 is part 2 of a five program package used to test the TC11 DECTape control. TC2 uses the maintenance bit feature of the TC11 control to check the TC11 control without depending on DECTape transport movement. Prior to actual use of the maintenance bit feature, correct operation of the interrupt circuits is checked, and the maintenance bit itself is checked.

## REQUIREMENTS

PDP-11

ASR33-35 Teletype

TC11 DECTape Control and at least one TU56 Dual Transport

STORAGE = 0 = 17400

LOADING = Absolute Loader

EXECUTION TIME = 1, Normal pass = 4 min,  
2, Single iteration pass = 5 sec,

Printout will occur

STARTING PROCEDURE = Start at 200  
Restart at 1000

PRINTOUTS = Yes

SWITCH REGISTER OPTIONS = Yes

SW15 = HALT ON ERROR

SW14 = ENTER SCOPE MODE

SW13 = INHIBIT ERROR PRINTOUT

SW11 = INHIBIT ITERATION

SW10 = HALT AT END OF TEST

SW 9 = SELECT TEST SPECIFIED BY SW7 = SW0

SW 7 = SW0 = NUMBER OF TEST SELECTED